



Sample acknowledgement

样品承认书

Project name项目名称:	P1018
Product name产品名称:	P1018_3IN1_ANT
Material number物料料号:	K5330000156LA
Material Description 物料描述:	FPC 0.12mm thick GPS/WIFI/BT antenna, black Shangyuan P1018_ three-in-one antenna FPC
Supplier Product Model 供应产品型号:	P1018_3IN1_ANT
TP FW mass production version TP FW量产版本	
Reminders提醒注意事项:	Each of the above information needs to be complete and accurate, and it needs to be consistent with the material information in the order BOM. 以上每项信息需要填写完整准确无误, 需要与下单BOM中的物料信息保持一致性。

Supplier signature (with company seal)

供应商签署 (加盖公司章)

☒ ROHS material ROHS物料		☐ Non-ROHS materials非ROHS物料		
Department 部门	☐ Producer制作人	☐ Engineering Department 工程部	☐ Design Department 设计部	☐ Quality department质量部
Signatory 签署者				
Signing date 签署日期				
Supplier information 供应商信息				
Supplier name供应商名称:	Sunnyway Technology Co., Ltd			
Supplier address供应商地址:	Building 4, No. 99, Lane 215, Gaoguang Road, Qingpu District, Shanghai			
Supplier to contact 供应商收件人-联系方式	Ma Ronglai-15921558333			
Recipient email address 收件人邮箱地址:	maronglai@sunnyway-iot.com			
Note注意: 1. Supplier information must be filled in correctly 供应商信息填写必须正确 2. Company seal required 必须加盖公司印章				

Customer review and signature 客户审核签署

Recognition state 承认状态	☐ Official recognition 正式承认		☐ Conditional recognition 条件承认		☐ Provisional limited recognition 临时限量承认					
	☐ Conditional recognition 条件承认 Conditions to be met需满足条件: _____									
	☐ Provisional limited recognition 临时限量承认 Limited Procurement限量采购 _____K									
Reviewed and signed by the Department (with the seal of recognition) 部门审核签署 (加盖承认章)										
Department 部门	☐ ID	☐ MD	☐ HW	☐ HWtest	☐ Packing	☐ NPI	☐ PM	☐ SPM	☐ PQM	☐ SQE
Signatory 签署者										
Signing date 签署日期										
Check item 检查项	Appearance / Workmanship 外观/工艺	Material / size / specification 材质/尺寸/规格		Specification/el ectrical performance 规格/电性能	Material / size / specification 材质/尺寸/规格	Process assembly/produ ction yield 工艺装配/生产 良率	Specificatio ns/customer needs 规格/客需	FW Version FW版本	Appearance / reliability 外观/可靠性	Appearance/man ufacturer yield/drawing specification 外观/厂商良率/ 图纸规范
Note注意: Before signing, the material information description, specification, drawing, dimension report, electrical performance test report, reliability test report, packaging specification and other information shall be carefully reviewed 签署前需要认真审核物料信息描述、规格书、图纸、尺寸报告、电性能测试报告、可靠性测试报告、包装规范等信息										


表单编码: QR-PQM-04-02

版本: C

修订日期: 2023年10月16日

TOP

BOTTOM



0.1mm PI stiffening plate

Technical Requirements

1. Shipping packaging requirements: (Micro-membrane packaging)

2. The surface of the copper foil is coated with black matte; the ink should be evenly distributed.

3. The thickness of the gold plating is 0.5u", and it has passed the salt spray test for 24 hours.

4. The dimensions marked with "*" are key dimensions.

5. Use 3M94711SE for the back adhesive.

6. The base material is PI with a thickness of 0.5 mil.

7. The thickness of the copper foil is 0.5 oz.

8. The unmarked fillet radius is 0.2, and the process edge is 0.2mm.

9. The unmarked tolerances are in accordance with the general tolerance table.

10. The product complies with RoHS 2.0 and REACH standards.



Copper foil area

gold plating

Glue

Shanghai Shangyuan Communication Technology Co., Ltd.

Ltd.



PART NAME: 3IN1 ANT P1018

DATE: 2025.09.11

PART NO: SH253081B75-1S1

DRAWN: shaoping

RF: hefang

Tel:

PM: wanglai

Tel: 15921558333

MATERIAL:

CHECKED: yujiang

FINISHING:

APPROVED:

UNIT:mm

COLOR: Black

SCALE:1:1

REV:



A

B

C


D

E



1. Project information

Machine information




Note: The customer finally verified that the antenna performance prototype was retained in our company for at least one year, which is convenient for analysis and solution to abnormal situations in antenna mass production. Ensure antenna shipment quality.

2. Test fixtures

Purpose: To test the passive parameters of the antenna as accurately as possible.

How to make: The prototyping mechanism is made of a 50 ohm coaxial cable, one end is connected to the test point at the back of the matching circuit of the prototype motherboard (the front of the RF test hole), and the other end is connected to the SMA connector. The schematic diagram is as follows:

3. Matching circuits



Element	Value
E1	NC
E2	0Ω
E3	NC
E4	0Ω
E5	NC

Note: No correction for the matching circuit.


4. S11 test

1. S11 Test Method Description

Test Equipment: Network Analyzer (E5071C)

Test method: A 50 ohm CABLE cable is derived from the instrument test port, and the SMA connector of the prototype is connected after calibration using the calibrator to record the return loss and standing wave ratio corresponding to the relevant frequency point.


The test diagram is as follows:



Test the schematic

4.2 S11 parameter

Three in one antenna S11



5 Darkroom test data

Test system: Shielded darkroom

Test environment: temperature $22^{\circ}\text{C}\pm 3^{\circ}\text{C}$, humidity
 $50\%\pm 15\%$
















Test equipment: When testing passive data, use the
Network Analyzer Agilent E5062C When testing
active data, the Comprehensive Tester Agilent 8960
/CMW500/E4438C is used

5.1 Passive test data

Three in one antenna efficiency

Fre/Mhz	Gain (dBi)	Effi/dB	Effi/%	Fre/Mhz	Gain (dBi)	Effi/dB	Effi/%
1170	-0.07	-4.9	32.36	2400	-0.38	-3.45	45.19
1171	-0.18	-4.97	31.84	2410	-0.68	-3.76	42.07
1172	-0.13	-5.04	31.33	2420	-0.31	-3.38	45.92
1173	-0.1	-5.11	30.83	2430	-0.04	-3.7	42.66
1174	-0.09	-5.18	30.34	2440	0.64	-3.27	47.1
1175	-0.13	-5.27	29.72	2450	0.91	-3.56	44.06
1176	-0.15	-5.33	29.31	2460	1.14	-3.27	47.1
1177	-0.17	-5.38	28.97	2470	1.06	-3.5	44.67
1178	-0.17	-5.43	28.64	2480	1.07	-3.33	46.45
1179	-0.12	-5.45	28.51	2490	1.1	-3.56	44.06
1180	-0.05	-5.47	28.38	2500	1.51	-3.36	46.13
				5150	4.06	-3.22	47.64
				5200	3.84	-2.97	50.47
1550	0.43	-4.81	33.04	5250	3.89	-2.98	50.35
1555	1.03	-4.38	36.48	5300	3.54	-2.85	51.88
1560	1.33	-4.02	39.63	5350	3.54	-2.81	52.36
1565	1.47	-3.95	40.27	5400	3.61	-2.59	55.08
1570	1.5	-3.73	42.36	5450	3.6	-2.85	51.88
1575	1.75	-3.52	44.46	5500	3.67	-2.62	54.7
1580	1.88	-3.32	46.56	5550	3.92	-2.87	51.64
1585	1.86	-3.33	46.45	5600	3.94	-2.91	51.17
1590	1.81	-3.19	47.97	5650	3.47	-3.19	47.97
1595	2.2	-3	50.12	5700	3.1	-3.37	46.03
1600	2.44	-2.8	52.48	5750	2.66	-3.73	42.36
1605	2.46	-3	50.12	5800	1.55	-4.1	38.9
1610	2.5	-2.93	50.93	5850	1.89	-4.16	38.37

Three in one antenna 3D Pattern




5.1 Active test data (Turn off the screen)


frequency (MHz)	channel	OTA (dB)	
		TRP	TIS
WIFI 11a (54M)	36	10.42	
	149	10.49	
	165	10.33	-72.53
WIFI 11b (11M)	1	17.4	
	6	17.59	
	11	17.19	-85.81
WIFI 11g	1	14.69	
	6	14.82	
	11	13.44	-72.61
WIFI 11n	1	12.64	
	6	12.76	
	11	12.44	-68.79

frequency (MHz)	channel	OTA (dB)
		tracking sensitivity
GPS	1575.42	-145.36


6 Environmental treatment.



Increase the conductive sponge and motherboard grounding




The horn is grounded to the motherboard through a conductive cloth



1. The bracket needs to be modified by digging holes in the mold, and the channel steel plate needs to be grounded to the copper leakage point of the motherboard through a conductive cloth

2. The main board next to the motor has a small copper leakage area, and it is recommended to increase the grounding area with the auxiliary board




The magnetic head is grounded through a conductive cloth

6 Environmental treatment.



Grounding of power button to shield interference



Grounding of power button to shield interference

