



User manual

Self-powered Wireless Switch

1.Product description



2.Product technical parameters

2.1Receiver Specifications

Working voltage	no need battery	Maximum current	wireless remote control
working Frequency	433.92MHz	size	49*49*24mm 80*43*27.4mm


2.2.switch specifications

working voltage	no need battery	working mode	wireless remote control
working frequency	433.92MHz	working temperature	-10°C ~ +70°C
Standby power consumption	0uA	size	86*86*16.5mm
Transmitting power	<10mW	Emission distance	200M(outdoor) 30M(indoor)

The transmission distance is affected by the wall barrier and may be different from the actual measured value


3.Product installation

The wireless switch panel can be placed at will, or it can be fixed in the position you choose. Fix it with double-sided stickers: As shown in the figure, stick one side of the double-sided sticker to the back of the switch, and stick the other side to the place you choose. Before fixing, please test the remote control effect of the panel and select a convenient position with good performance.




The receiver can be fixed with double-sided adhesive tape and wired according to the schematic diagram below. There is no need to distinguish between the neutral wire and the live wire, but the input and output cannot be connected reversely. (Note: Please do not install it in a metal container, otherwise the working distance will be shortened.)


The wiring for 1 way control



The wiring for 2 way control



The wiring for 3way control



Warning: please disconnect the power supply before wiring, and do not operate with power on. S1 and S2 can only be connected to the two ends of a single fire wall switch and cannot be connected to strong electricity. They can be left unconnected unless necessary.

4.Learning settings

The set has been paired at the factory. If you need to make changes, please refer to the following steps

Pairing method 1 (self-locking)

Press and hold the receiver button for 3 seconds. When the blue indicator light comes on, press the remote control switch and the indicator light flashes to indicate successful pairing.

Pairing Method 2 (Interlocking)

Attention: Interlocking pairing requires two switches. Press and hold the receiver button for 6 seconds. When the blue indicator light comes on, pressing the first switch only turns on the light, and pressing the second switch only turns off the light. Pairing is complete.

Clear code

Press and hold the receiver button for 10 seconds, and the blue indicator light will flash rapidly three times, indicating successful code clearing.

5.Cautions

- 1) The load power cannot exceed the rated power of the product.
- 2) Please avoid interference sources such as metal masks, large electronic devices, and electromagnetic fields to prevent the product from shortening its working distance or malfunctioning.
- 3) Please do not disassemble the product without authorization, otherwise you will not be able to enjoy warranty services.

FCC Warning Statement

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference. (2) This device must accept any interference received, including interference that may cause undesired operation. NOTE: This device and its antenna(s) must not be co-located or operation in conjunction with any other antenna or transmitter. The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.