产品介绍

感谢使用本产品。本产品适配器和移动电源两种工作模式，采用美国进口芯片的解决方案，同时支持5台设备充电，体积小巧，方便携带。电芯采用高品质锂离子电芯，在安全，效率，兼容性等方面均有杰出表现。



基本参数

型号:K02-分拆式旅行充　　容量:10000mAh(37.0Wh)
尺寸:83*89*29MM　　重量:约258g

四合一旅行充状态:

输入:AC100-240V 50/60Hz 0.3A 或 Type-C:PD 20W

输出:Type-C:5V/3A,9V/2.2A,12V/1.5A(PD20W)　无线充:15W(Max)

USB1(彩色):5V/3A,4.5V/5A,9V/2A,12V/1.5A (22.5W Max) USB2(黑色):5V/2.1A

分离后旅行充状态:(充电器)

输入:AC100-240V 50/60Hz 0.3A　AC Charger:5V/2A

输出:Type-C:5V/2A (10W)

分离后旅行充状态:(移动电源)

输入:Type-C:5V/3A,9V/2.2A,12V/1.5A (PD20W)

输出:Type-C:5V/3A,9V/2.2A,12V/1.5A (PD20W)　无线充:15W(Max)

USB1(彩色):5V/3A,4.5V/5A,9V/2A,12V/1.5A (22.5W Max) USB2(黑色):5V/2.1A

产品特点

安全：多重保护，包括雷击保护，短路保护，过流保护，过压保护，过温保护和欠压保护等；独立电池仓设计，保护电芯可靠工作；外壳采用V0防火耐高温材料打造，安全可靠。

高效：支持100-240V AC输入，满足六级能效。

兼容：内置智能识别芯片，可以兼容市面上主流智能手机/平板以及其他可用Type-C及USB-A接口和无线充供电的数码设备。

快充：本产品在移动电源模式下具有USB数据线插入侦测功能，当仅有一个输出接口（C口或者绿色A口）插入数据线时，输出支持5V, 9V, 12V快充；无线充需按键启动，兼容5W, 7. 5W, 10W, 15W；两个接口或多口同时使用时，输出支持5V/3A MAX。如需使用快充模式，请确保其他任意留空。*墙充状态不支持快充。

范围：可满足5000m的高海拔场合使用。

产品一分为二：

充电器模式：支持市面上主流的5V智能设备，安全可靠。

移动电源模式：支持市面上主流的5V，9V, 12V智能设备。

充电

用本产品连接电源或者其他Type-C口适配器，均可实现对本产品进行充电。充电时，显示状态和电量对应关系如下：

数码管显示0，产品需充电，数字从0-99闪烁，一直到100常亮表示电量充满。

放电

用数据线连接本产品与数码产品，可实现对数码产品进行充电。带有无线充电设备需按一次按键后，放置本产品无线线圈发射区域进行充电。

放电时，显示状态和电量关系如下：

启动本产品放电，前10秒数码管常亮"PD和((•))"，表示检测。正常充电后，"PD和((•))"会灭；在使用无线充电时，((•))一直常亮。当出现PD字符，则代表产品在快充状态。

电量显示：随着本产品放电，电量从100至0递减，直至关机。

小电流放电功能：在产品充电状态下，长按3秒进入小电流模式，可以给蓝牙耳机，手环等小电流设备持续充电。每次进入小电流模式工作时间为2小时，之后自动退出模式。

注意事项

- 在为本产品充电或使用本产品为其他设备充电时，请自行选择适配的数据线。
- 对本产品充电过程中，应确保有人在场，外出或者长时间离开时请拔除电源。
- 本产品充满电或本产品对其他设备充满电后，请及时拔除电源和连接线，避免长时间处于连接状态产生损耗。
- 如本产品按键后无电量显示，可能处于保护状态，可连接到外部充电器尝试恢复。
- 长时间不用本产品时，请保持电量在25-50%范围，存放于阴凉干燥环境，避免于满电或无电状态下长期保存。

注意事项

▲不要将移动电源放入水中或用湿布进行清洁！

▲远离火源　易燃易爆液体、气体或爆炸品存放

▲不要随意扔掷、敲打或剧烈摇晃！

▲请在常规温度（-10℃~45℃）使用，高温和低温都会对其造成影响！

▲切勿高温灼烧电芯！

▲不能在低温环境下长时间使用！

▲不要长期暴露在阳光和潮湿、雨水环境之中或在此类环境中使用！

▲不经常使用最好每月都对其充电和放电一次！

▲请使用适当的充电器或适配器，如果有任何畸形或腐蚀，请停止使用！

▲使用不当可能导致产品损坏并可能伤害您！

▲保持远离孩子！

K02分拆式旅行充保修说明

本产品售后服务严格依据《中华人民共和国消费者权益保护法》《中华人民共和国产品质量法》实行售后三包服务，服务内容如下：

在三包有效期内，您可以依照本规定免费享受退货，换货，维修的服务；维修，退货，换货应当提供凭证办理。

本产品出现《产品性能故障表》所列性能故障的情况，经检测确定后，可以免费享受如下服务：由用户承担物流费用。

服务类型	服务政策
退货	自签收次日起7天内产品质量原因退货
换货	自签收次日起15天内产品质量原因换货
维修	自签收次日起1年内产品质量原因维修

产品性能故障表

名称	性能故障
K02分拆式旅行充	1.因结构或材料因素造成的外壳裂损 2.插头松动，无法插入插座 3.充电性能故障

非保修条例

1.未经授权的维修，误用，碰撞，疏忽，滥用，进液，事故，改动，不正确的使用本产品；

2.已超过三包有效期；

3.因不可抗力造成的损坏；

4.不符合《产品性能故障表》所列性能故障的情况；

5.因人为原因导致本产品产生《产品性能故障表》所列性能故障。

产品中有害物质的名称及含量

部件名称	有害物质					
	铅（Pb）	汞（Hg）	镉（Cd）	六价铬（Cr）	多溴联苯（PBB）	多溴二苯醚（PBDE）
印刷电路组件	X	○	○	○	○	○
电池组	○	○	○	○	○	○
外壳	○	○	○	○	○	○
垫片及泡棉等小结构件	○	○	○	○	○	○

本表格依据SJ/T11364的规定编制。

○:表示该有害物质在该部件所有均质材料中含量均在GB/T26572规定的限量要求以下。

x:表示该有害物质至少在该部件的某一均质材料中含量超出GB/T26572规定的限量要求。

Introdction

Thank you for using this product.This product supports two work modes as adapter and power bank.Using the chip imported from America,It is pocket size and can charge five devices at the same time.The quality of lithium-ion cell is high with excellent performance in safety,efficiency and compatibility.



Basic Parameters

Model:K02-Detachable　　Capacity:10000mAh(37.0Wh)
Size:83*89*29MM　　Net Weight:258g

4 in 1 Charging Status:

Input:AC100-240V 50/60Hz 0.3A or Type-C:PD 20W

Output:Type-C:5V/3A,9V/2.2A,12V/1.5A(PD20W)　Wireless:15W(Max)

USB1(colour):5V/3A,4.5V/5A,9V/2A,12V/1.5A (22.5W Max) USB2:5V/2.1A

State after separation:(Charger)

Input:AC100-240V 50/60Hz 0.3A　AC Charger:5V/2A

Output:Type-C:5V/2A (10W)

State after separation:(Power bank)

Input:Type-C:5V/3A,9V/2.2A,12V/1.5A (PD20W)

Output:Type-C:5V/3A,9V/2.2A,12V/1.5A(PD20W)　Wireless:15W(Max)

USB1(colour):5V/3A,4.5V/5A,9V/2A,12V/1.5A (22.5W Max) USB2:5V/2.1A

Features

Safety:Multiple protections,including thunder-strike protection, short circuit protection.over-voltage protection,overtemperature protection and under-voltage protection;the battery bunker is designed to be independent to protect the operation of cell;the shell is made of safe and reliable V0 material,which is fire-resistant and high-temperature resistant.

High-efficiency:Support 100-240V AC input to meet level-VI energy efficiency.

Compatibility:Built in intelligent chip,compatible with popular mobile phonetablet pc electronic equipments with Type-C or USB-A connection.

Fast Charging:Products with function of USB cable connection detect under charging mode, supporting 5V,9V,12V fast charging when USB cable connects to the only output (Cport or Green A port);Press the key to start wireless charging,compatible with 5W, 7.5W,10W,15W;Max output is 5V/3A when more than two ports working at the same time;Using only one output to ensure fast charging.Caution:fast charging function closed when using wall charging;

Range:Available in 5km High altitude environment.

Split Type design:

Charging mode:Supporting major digital equipment with 5V voltage,safe and reliable;

Portable charging mode:Supporting major digital equipments with 5V,9V,12V,voltage;

Input charging:Connect to power supply or Type-C adaptor to fulfill input charging;below LED display shows power volume; "0" flashing shows input charging needed, "100" flashing

shows input charging over; "0-99" flashing shows ongoing input;

Output charging

Connect this unit to digital equipments with USB cable for output charging;Press the key to start wireless output charging,place those equipments onto wireless loop;

PD Lights and ((•)) turn on 10 seconds shows system detection running, ((•)) is on when charging, PD lights and ((•)) turn off when charging ends;

PD lights on mean at Fast Charging.

Please stop charging when White light flashes as it shows Metal debris detected;

Power volume display: power volume shows from 99 to 0 while output charging up to auto shutdown;

Small current output charge function: Charging Bluetooth headset, Smart Bracelet and other small current equipment

Press on/ff key 3 seconds switch to Low current mode.

Each process sustains 2 hours then to auto stop;

Caution:

- Please apply suitable cables for charging;
- Make sure the user is present while charging, remove the connection when leaving;
- Remove the connection when the equipments fully charged, avoid power volume loss;
- Connect power supply to reset power bank when it is under protection mode (no power volume shows after pressing the start button)
- Keep the power volume in the level of 25-50 if long time not using, save it in dry place, avoid full power/zero power storage;

Warnings

▲Do not place charger into water or clean with wet cloth!

▲Keep charger safe distance from fire, Inflammable and explosive liquid & gas!

▲Do not drop, hit and shake violently!

▲Use it under -10 upto 45 degree centigrate temperature condition, both high temp.& low temp. affect the charger!

▲Do not burn the battery!

▲Avoid long time using under low temp. condition!

▲Avoid exposing to sunlight, humid & rainning weather!

▲Charge or discharge it at least one time in a month if Infrequently used!

▲Select suitable power charger or adaptor, stop using by any sign of Battery corrosion or deformation!

▲Improper use might harm the product or user!

▲Keep safe distance from Child!

K02-分拆式旅行充

快速指南

分拆式四合一旅行充

4 in 1 Detachable & Multipurpose PD Charger

Charger+Power Bank+Wireless Charger 15W+Wall Charger

FCC Statement

This device complies with part 18 of the FCC Rules. Operation is Subject To the following two conditions:

(1) This device may not cause harmful interference, and (2) this devicemust accept any interference received, including interference that may cause undesired operation. Changes or modifications not explicitly approved by the partyresponsible for compliance could void the user's authority tooperate this equipment.

Note: this equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 18 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and canradiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference toradio or television reception, which can be determined by turning the equipment off and on, the user is encouraged totry to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

- Consult the dealer or an experienced radio/TV technician for help.

The equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. During the operation of device a distance of 15 cm surrounding the device and 20 cm above the top surface of the device must be respected.

This device complies with Part 18 of the FCC Rules. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Increase the separation between the equipment and any other radio device.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.