说 明 书
USER MANUAL
取扱説明書

Zwide®

无线领夹麦克风
Wireless Lavalier Microphone
ワイヤレスピンマイク

Model No.

M1



M1 RX　　TX*1

M1 Plus



M1 Plus RX　　TX*2

Product Introduction

Thank you for choosing Zwide products. In order to know more abut our products, please read this User Manual carefully before using. Have a good using experience.

This product is an intelligent noise reduction wireless microphone, which can provide professional recording output, plug and play, no APP required. Multiple uses: network broadcast, Vlog shooting, interview recording, video teaching and other scenarios.

The products consists of two parts, Mic TX and Mic RX.

Connecting Cables



Camera Cable　　USB-C Cable

3.5mm TRRS Cable　　Lightning Cable

ID Diagram of RX



① Monitor Earphone Port	⑤ Connect Indicator 2 (Only for M1 Plus)
② Audio Output Port	⑥ Mic Clip
③ Connect Indicator	⑦ Power Key
④ Power Indicator	⑧ USB-C Port

ID Diagram of TX



① Built-in Mic	⑤ ENC Indicator	⑨ Power Key
② External Mic Port	⑥ Mic Clip	⑩ ENC Key
③ Connect Indicator	⑦ Volume +	⑪ Mute Key
④ Power Indicator	⑧ Volume -	⑫ USB-C Port

Operating Instruction

RX :

I : Power Key function :
1. Hold the key 3s to power on/off. When the product powered on, press the key twice to enter connecting state.(Please operate simultaneously with the TX)
2. Factory reset without connecting by pressing key 6 times (This feature is forbidden in Non-abnormal condition)

II : USB-C Port : For 5V charging.

III : Monitor Earphone Port : Insert the CTIA earphone to monitor the voice from TX.

IV : Audio output port : Connect camera, mobile phone or computer .

V : Description of Indicators :
1.Power Indicator : The indicator will light up when the product power on; It will blinks rapidly at low power and blinks slowly during charging ; The indicator will keep on when power full.
2.Connect Indicator 1(②) : The indicator will blinks when the product disconnected and keep on if it connect successfully.

VI : The TX is automatically connect with the RX and it will save the sequence after the first connect.

TX :

I : Power Key function :
1. Hold the key 3s to power on/off. When the product powered on, press the key twice to enter connecting state.(Please operate simultaneously with the RX)
2. Factory reset without connecting by pressing key 6 times (This feature is forbidden in Non-abnormal condition)

II : ENC key function : Press ENC Key to switch noise reduction function on/off.

III: Mute Key : Press the key to mute/unmute the sound from the TX, the Connect Indicator will turn off/on.

IV: Volume + / - : Press to adjust recording sound level.

V : USB-C Port: For 5V charging.

VI : External Mic Port : For external microphone input.

VII : Description of Indicators :
1.Power Indicator : The indicator will light up when the product power on; It will blinks rapidly at low power and blinks slowly during charging; The indicator will keep on when power full.
2.Connect Indicator : The indicator will blinks when the product disconnected and keep on if it connect successfully. It will off if mute the Mic.
3.ENC Indicator : The indicator will turn on/off when the noise reduction function on/off.

VIII : The TX is automatically connect with the RX and it will save the sequence after the first connect.

Operating Instruction

接收器：

一：开机键功能：
1.长按3秒开/关机，开机状态下连续按2次配对。
（此功能同步发射器）
2.未连接设备情况下，连按开机键6次恢复出厂设置。
（此功能非特殊情况禁止使用）

二：USB-C接口：用于5V充电。

三：监听耳机：插入CTIA耳机用于监听发射器讲话。

四：音频输出耳机：连接相机、手机、电脑等接口。

五：指示灯状态说明：

1.电源灯：开机时蓝灯长亮，低电时快速闪烁。充电时电源灯慢闪，充满长亮。

2.配对灯1：未配对时蓝灯慢闪，配对成功蓝灯长亮。

3.配对灯2：未配对时蓝灯慢闪，配对成功蓝灯长亮。

六：第一次配对后，后面再开机发射跟接收自动配对并且发射端默认第一次配对顺序。

发射器：

一：开机键功能：
1.长按3秒开/关机，开机状态下连续按2次配对。
（此功能同步接收器）
2.未连接设备情况下，连按开机键6次恢复出厂设置。
（此功能非特殊情况禁止使用）

二：ENC键功能：短按ENC键降噪功能开/关。

三：禁麦键：短按一下禁止发射器声音传输，同时配对蓝灯关闭，再短按恢复声音传输功能，配对蓝灯长亮。

四：音量+/-键：短按控制录音声音大小。

五：USB-C接口：用于5V充电。

六：外接麦克风接口：用于外接麦克风输入。

七：指示灯状态说明：

电源灯：开机时蓝灯长亮，低电时快速闪烁。充电时电源灯慢闪，充满长亮。

配对灯：未配对蓝灯慢闪，配对成功蓝灯长亮。禁麦后蓝灯关闭。

ENC灯：降噪打开时蓝灯常亮，降噪关闭后蓝灯灭。

八：第一次配对后，后面再开机发射跟接收自动配对。

NOTE:The RX of M1(1to1) contains 2 indicators;
The RX of M1 Plus(1to2) contains 3 indicators.



NOTE: Take video on the device after the Mic RX connected with the device is successfully Please disconnect the cable from the device if you want to play the video with audio in the device directly.

注明：M1(1拖1)接收器有两个指示灯，M1 Plus(1拖2)接收器有三个指示灯。



注明：无线麦克风与设备连接成功后，打开相机录制视频。录制视频完成后，如需在本设备播放视频需断开连接线，设备才会有声音输出。

The Basic Parameters

The basic specs of Wireless Lavalier Mcorphone

Working Frequency	2.4GHz	Recording Sampling Frequency	48kbps	Transmission Distance	The barrier- free distance is about 15m
Wireless Version	V5.3	Transmission Delay	20ms	Frequency Response Range	20Hz-20kHz
Charging Time	~1.1h	Working Time	~8h	Charging Voltage	DC 5V

Packing List

M1 Configuration

(1) Mic RX*1
(2) Mic TX *1
(3) USB-C Charging Cable*1
(4) Camera Cable *1
(5) Windscreen*1
(6) Wired Microphone*1
(7) Monitor Earphone*1
(8) Carrying Pouch*1
(9) User Manual & Warranty Card*1
(10) Qualified Certificate*1
(11) USB-C Cable*1
(12) Lightning Cable*1
(13) 3.5mm TRRS Cable *1

M1 Plus Configuration

(1) Mic RX*1
(2) Mic TX *2
(3) USB-C Charging Cable*1
(4) Camera Cable *1
(5) Windscreen*2
(6) Wired Microphone*2
(7) Monitor Earphone*1
(8) Carrying Pouch*1
(9) User Manual & Warranty Card*1
(10) Qualified Certificate*1
(11) USB-C Cable*1
(12) Lightning Cable*1
(13) 3.5mm TRRS Cable *1

NOTE:Our products are constantly innovative and subject to change without prior notice.

基本参数

领夹麦基本规格参数

频率范围	2.4GHz	语音采样频率	48kbps	传输距离	无障碍距离75米左右
蓝牙版本	V5.3	传输延迟	20ms	频响范围	20Hz-20kHz
充电时间	约1.1h	工作时间	约8h	充电电压	DC 5V

包装清单

M1 配置

(1) 麦克风接收端x1
(2) 麦克风发射端x1
(3) USB-C充电线x1
(4) 相机连接线x1
(5) 防风罩x1
(6) 有线麦克风x1
(7) 监听耳机x1
(8) 收纳(袋/盒)x1
(9) 说明书&保修卡x1
(10) 合格证x1
(11) USB-C 连接线 x1
(12) Lightning 连接线 x1
(13) 3.5mm TRRS 连接线 x1

M1 Plus配置

(1) 麦克风接收端x1
(2) 麦克风发射端x2
(3) USB-C充电线x1
(4) 相机连接线x1
(5) 防风罩x2
(6) 有线麦克风x2
(7) 监听耳机x1
(8) 收纳(袋/盒)x1
(9) 说明书&保修卡x1
(10) 合格证x1
(11) USB-C 连接线 x1
(12) Lightning 连接线 x1
(13) 3.5mm TRRS 连接线 x1

▲ 安卓版套装　◆ 苹果版套装　● 豪华版套装

注：本公司产品不断创新，如有更改恕不另行通知。

ワイヤレスピンマイク

型番：M1 Plus

取扱説明書

このたびは、弊社のワイヤレスマイクをお買い上げいただき、誠にありがとうございます。 正しくご使用いただくために、必ずこの取扱説明書をお読みになり、末長くご愛用くださいますようお願い申し上げます。

製品概要

- 弊社のスマートワイヤレスピンマイクは、高品質の録音効果、小型・軽量化により、屋外における映画、ドラマのロケ取材や緊急報道などの制作現場における音声の収音に最適です。
- 本機は送信機×2、受信機×1、付属品などと組み合わせて使用するワイヤレスピンマイクです。



M1Plus 受信機



送信機×1　　送信機×2

受信機 RX



① イヤホーン接続口	⑤ ペアリング指示ランプ 2	
② オーディオ出力ポート	⑥ マイククリップ	
③ ペアリング指示ランプ 1	⑦ 電源ボタン	
④ 電源指示ランプ	⑧ USB-C ポート	

送信機 TX



① 内蔵マイク	⑤ ノイズリ低減指示ランプ	⑨ 電源ボタン
② 外付けマイク接続口	⑥ マイククリップ	⑩ ENCボタン
③ ペアリング指示ランプ 1	⑦ ボリューム+ボタン	⑪ 消音ボタン
④ 電源指示ランプ	⑧ ボリューム-ボタン	⑫ USB-C ポート

使用前の準備

セットアップ

- 電源ボタンを３秒間押し続け、送信機と受信機の電源を入れます。
- 送信機と受信機の電源を入れると自動的にペアリングされ、音声の送信を開始します。送信機の内蔵マイクで収音します。
- 送信機には互換性のある外部マイクを接続することができます。外部マイク接続時、送信機の内蔵マイクから外部マイクへ自動的に音声入力を切り替えます。

受信機

- 電源ボタン
電源ボタンを3秒間押し続けると、電源が入ります。使用中に電源ボタンを3秒間押し続けると、電源が切れます。
充電モード時に電源ボタンを1回短く押すと、電源が入ります。
- USB-Cポート
付属のUSBケーブルで充電する際に使用します。
- イヤホン入力
イヤホンを接続して、音声を監視することができます。
- USB-Cポート
外部機器を接続する(カメラ、スマホ、ノートパソコンなど)
- ペアリングボタン
送信機1、2と受信機の電源を入れると、通常は自動的にペアリングされます。
送信機1、2と受信機は、同時にペアリングする必要があります。

LEDランプがゆっくりとした点滅=充電中
青色に点灯=充電完成

送信機

- 電源ボタン
電源ボタンを３秒間押し続けると、電源が入ります。使用中に電源ボタンを3秒間押し続けると、電源が切れます。
- 内蔵マイク
外部マイクが接続されていない場合、送信機は自動的に内蔵マイクを使用します。内蔵マイクは特に人の声を良く収音できるように設計されています。
- ペアリングの状態
LEDランプは全部青色に点灯＝受信機とペアリングされ、受信機にデータを送信しています。
LEDランプ１がゆっくりとした点滅＝受信機に接続されていないか、送信機が通信範囲外になっています。
ランプ３が消灯=音声の送信を停止、消音ボタンを一回押すと音声の送信を開始します。
- バッテリーの状態
LEDランプが特に速い点滅＝バッテリー残量が10%以下です。

LEDランプがゆっくりとした点滅=充電中
青色に点灯=充電完成
- USB-Cポート
付属のUSBケーブルで充電する際に使用します。
- ENCボタン
ボタンを短く押すと低減機能OPEN/OFF

- マイク入力
外部マイクを接続することができます。
- ボリューム+/-ボタン
短く押すと、音声の音量を制御できます。

付属品



ケーブルの接続方法

カメラに使用する場合
カメラMicポート、カメラ用ケーブル、オーディオ出力ポート(受信機)

3.5mmイヤホン接続口
3.5mmイヤホン接続口、3.5mm TRRSケーブル、オーディオ出力ポート(受信機)



iPhone
Lightning ケーブル×1、オーディオ出力ポート (受信機)



USB-C
USB-C ケーブル×1、オーディオ出力ポート (受信機)



注意事項

内蔵マイクがデバイスに正常に接続されたら、ビデオを録画します。 ビデオを録画した後、このデバイスでビデオを再生したい場合は、ケーブルを使用機器から取外してください。

製品仕様

送受信周波数	2.4GHz	録音周波数	48kbps	転送距離	バリアフリー距離 約75m
Wireless バージョン	V5.3	伝送遅延	20ms	周波数特性	20Hz-20kHz
充電時間	約1.1h	バッテリー持続使用可能時間	約8h	充電電圧	DC 5V

セット内容

(1) 受信機 ×1
(2) 送信機 ×2
(3) USB-C充電ケーブル ×1
(4) カメラ用ケーブル ×1
(5) ファーウインドシールド ×2
(6) 外付けマイク ×2
(7) 監視イヤホン ×1
(8) 収納袋 ×1
(9) 取扱説明書と保証書 x1
(10) 合格書 x1
(11) USB-C ケーブル ×1
(12) Lightning ケーブル x1
(13) 3.5mm TRRS ケーブル x1

保修卡

保修范围：如有产品故障，凭厂商授权服务中心的检测证明，享受15日包换，365日免费维修服务!

Warranty Card

Warranty scope:In case of product failure, you can get a replacement within 15 days and free repair service for 365 days, with inspection report issued by authorized service center.

保証書

【1年日本国内保証付き】保証期間に正常な使用状態でご使用の場合に限り品質を保証しております。万一保証期間で故障がありました場合は、お買い上げの販売店へお問い合わせください。
保証書は再発行いたしませんので、大切に保管してください。

Zwide

产品型号 Model No. 型　番	
购买日期 Date of Purchase お買い上げ日	
订单号 Order No. ご注文番号	
经销商 Dealer 販売店名	
客户姓名 Customer Name お名前	
联系电话 Contact No. 電　話	
联系地址 Contact Address ご住所	
维修记录 Maintenance Record 修理記録	

Zwide®

深圳市智纬科技有限公司
SHENZHEN ZHIWEI TECHNOLOGY CO., LTD

Zwide is a trademark of SHENZHEN ZHIWEI TECHNOLOGY CO., LTD
Copyright ©2022 Zwide All Rights Reserved.
Zwide 是深圳市智纬科技有限公司的商标
Copyright ©2022 智纬科技 版权所有
Made in China 中国制造

The Apple logo, iPhone, iPad and Lightning are trademarks of Apple Inc., registered in the U.S. and other countries.
The trademark of "iPhone" is used in Japan with a license from Aiphone K.K.

Android is trademark of Google LLC, registered in the U.S. and other countries.

USB-C and USB Type-C are registered trademarks of USB Implementers Forum.
All other company names, product names and logos are the trademarks or registered trademarks of their respective owners.

FCC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
-- Reorient or relocate the receiving antenna.
-- Increase the separation between the equipment and receiver.
-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
-- Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.
Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

IC STATEMENT
This device complies with Industry Canada's licence-exempt RSSs. Operation is subject to the following two conditions:
(1) This device may not cause interference; and
(2) This device must accept any interference, including interference that may cause undesired operation of the device.

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes :
(1) l'appareil ne doit pas produire de brouillage, et
(2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

RF Exposure Information
The device has been evaluated to meet general RF exposure requirement.
The device can be used in portable exposure condition without restriction.

RoHS

SUBSCRIBE FOR MORE INFO
关注Zwide智纬及时获取最新资讯
http://www.zwide.com

地址：广东省深圳市龙华区龙华街道油松社区利金城工业园3号厂房3层东侧分隔体、6#厂房四楼、五楼

Address: 4th ~ 5th Floor , Bld 6 and East side of 3rd Floor Bld 3, LiJinCheng Industrial Park, Yousong Community, Longhua Street, Longhua District, Shenzhen, China 518109