Copyright by i.Tech Dynamic Limited. All Rights Reserved.

Project : i.Tech 3000 / User manual
Drawing : 2D Rendering / Scale 1:1
From : Design Team / Eddie Lau / To : All / Date : 20140205v1

68

58

File Name / Part no.	
Artwork Purpose	Sampling no. ( ) / FEP / PP / MP / CR
Checked by Design Team	
Checked by Product Marketing Team	
Checked by Marketing Team	
Checked by R & D Team	
Checked by QA Team	
Approval by	
Remarks	

User Manual Content Page / 說明書內頁	
Paper	書紙
K	單色印刷

MyVoice 3000

i.Tech Bluetooth Headset

www.itechdynamic.com

Quick Start Guide







Caution:

This device complies with Part 15 of the FCC Rules / Industry Canada licence-exempt RSS standard(s). Operation is subject to the following two conditions: (1) this device may nc cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.
Change or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.
This equipment has been tested and found to comply with the limits for a Class B digital device,pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and usd in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference wl not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more c the following measures:
—Reorint or relocate the receiving antenna.
—Increase the separation between the equipment and receiver.
—Connect the equipment into an outlet on a circuit different from that to wlicc the receiver is connected.
—Consult the dealer or an experienced radio/TV technician for help.

NCC認證碼：CCAF14LP0140T0

「經型式認證合格之低功率射頻電機，非經許可，公司、商號或使用者均不得擅自變更頻率，加大功率或變更原設計之特性及功能。」

「低功率射頻電機之使用不得影響飛航安全及干擾合法通信；經發現有干擾現象時，應立即停用，並改善至無干擾時方得繼續使用。前項合法通信，指依電信法規定作業之無線電通信。低功率射頻電機須忍受合法通信或工業、科學及醫療用電波輻射性電機設備之干擾。」

Version 1.1

All features, functionality and other product specifications, as well as the information contained in this guide, are based upon the latest available information and believed to be accurate at the time of printing. i.Tech reserves the right to change or modify any information or specifications without notice or obligation. The latest version of this guide can be obtained from www.itechdynamic.com. The images in this guide are for reference only.

i.Tech™ The Stylized i.Tech logos are registered trademarks. Bluetooth®

Disposal of the packaging and this product in accordance with the latest ecordance.
Printed in China

EN 1. About your MyVoice 3000

a. **Multi-function Button (MFB)**
- **Power On / Off**
- **Pair with mobile phone**
- **Answer / End a call**

b. **Status Indicator**
c. **USB Charging Socket**
d. **Volume Control**

2. Charging Your Headset

The headset comes with a built-in rechargeable battery. Prior to using the headset for the first time, it is recommended to fully charge the battery.
Insert the charger's plug into the headset's USB charging socket and plug the mains charger to an AC wall outlet or plug to the PC/notebook.
Use only the supplied charger / USB charging cable to charge the headset.

Headset Status	Status Indicator Light
Charging (OFF MODE)	Solid red
Fully charged (OFF MODE)	Solid blue
Low battery	Flash red with short beep sound
Charging (STANDBY MODE)*	Solid red
Fully charged (STANDBY MODE)*	Solid blue

2 hours are required to fully charge the headset.

* Warning: It is recommended not to use the headset while it is connected to the charger.

3. Pairing Your Headset with a Bluetooth Device

1) Ensure the headset is off.
2) To activate the pairing mode, press and hold the headset's MFB for 8 seconds without releasing your finger until its status indicator flashes blue and red alternately.
3) Activate your mobile phone's Bluetooth, search Bluetooth devices, select "MyVoice 3000" and enter the pass code "0000". When the pairing is completed, the headset's status indicator will turn blue for 2 seconds and return a short beep with voice prompt "Your phone is connected."

4. Basic Operation

Function	Button	Alert Tone	Status Indicator
Power on	Press and hold the MFB for 3 seconds	Remaining talk time: > 3.75 hours: "Battery high" 0.75 - 3.75 hours: "Battery medium" < 0.75 hours: "Battery low"	Flash blue light 3 times
When you turn on your headset for the first time, the headset proceeds into pairing mode, i.e. the status indicator flashes blue and red alternately, you can immediately pair it with your mobile phone.			
Power off	Press & hold the MFB for 5 seconds	--	Flash red light for 2 times

Function	Button	Alert Tone	Status Indicator
Incoming call	--	Ringtone through the earphone	--
Answer / End a call	Press the MFB once	--	--
Reject a call	Press and hold the MFB for 3 seconds	Short beep	--
Voice Dial*	Press and hold the MFB for 3 seconds	--	--
last number redial	Double press MFB	--	--

* The voice dialing function only supports with voice recognition enabled mobile phones.

Multi-point allows simultaneous pairing of the headset with 2 mobile phones, to pair 2 mobile phones:
1. pair your headset with the 1st mobile phone as normal and then switch off
2. repeat the pairing procedure for the 2nd mobile phone
3. re-connect the 1st mobile phone with the headset via the phone menu

i.Tech Bluetooth headset is designed to work with Bluetooth devices. Due to large variability between different Bluetooth devices from different manufacturers, interoperability between the headset and all Bluetooth-enabled products is not guaranteed.

5. Smart Battery Check

Power Off Mode: Press the MFB once
Standby Mode: Press and hold both Volume buttons while not on a call.

Voice Prompt	Status Indicator	Talk Time
Battery High	Solid blue for 3 seconds	More than 3.75 hours
Battery Medium	Flash blue light 3 times	Between 0.75 and 3.75 hours
Battery Low	Flash red light 3 times	Less than 0.75 hour

繁中 1. 關於您的 MyVoice 3000

a. 多功能按鈕（MFB）
- 開機 / 關機
- 與行動電話配對
- 接聽 / 結束來電

b. 指示燈
c. USB 充電插座
d. 音量控制

2. 耳機充電

耳機內置可再充電電池。在第一次使用耳機前，建議先為耳機完全充電。
將充電器插頭插入耳機的USB充電插座，然後將充電器連接至交流電源插座或個人電腦／手提電腦之中。
請僅使用隨附的充電器 / USB 充電線，為耳機充電。

耳機狀態	狀態指示燈光
充電中（關機模式）	紅色
完全充電（關機模式）	藍色
低電量	閃動紅色及短哨聲
充電中（待機模式）*	紅色
完全充電（待機模式）*	藍色

需要 2 小時的時間，才能將耳機充滿電量。
* 警告：請勿在耳機連接至充電器時使用耳機。

3. 將耳机與藍牙行動電話配對

1) 確保耳機已關閉。
2) 如要啟動配對模式，請按住耳機的MFB鍵 8 秒鐘，直至狀態指示燈交替閃動藍色和紅色。
3) 啟動手機的藍牙功能，搜索藍牙裝置，選擇 "MyVoice 3000"，然後輸入密碼 "0000"。當配對完成後，耳機的狀態指示燈會快速閃動藍色 2 秒，並會聽到一下具哨聲及語音提示 "Your Phone is connected"。

4. 基本操作

功能	按鈕	警報聲	狀態指示燈
開機	長按MFB 3 秒	剩餘通話時間：>3.75 小時：「Battery high」；0.75 - 3.75 小時：「Battery medium」；<0.75 小時：「Battery low」	藍燈閃爍 3 次
首次啟動耳機時，耳機會自動進入配對模式（狀態指示燈交替閃爍藍、紅燈），此時可立即將耳機與手機進行連線。			
關機	長按MFB 3 秒	--	紅燈閃爍 2 次

功能	按鈕	警報聲	狀態指示燈
來電	--	耳機發出鈴聲	--
接聽／結束來電	按一下 MFB	--	--
拒絕來電	按住 MFB 一次	--	--
已錯號電	長按MFB 3 秒	短嗶聲	--
重撥最後號碼	按 MFB 兩次	--	--
音量調節*	長按 MFB 3 秒	--	--

* 音量調節功能僅支援配備語音調節功能之手機型號。

Multi-point 技術讓您可同時將兩部流動電話配接。
配接程序：
1. 把你的耳機首第一部電話配接，然後關閉
2. 為第二部電話重複配接程序
3. 使用電話功能表，把第一部電話與耳機重新配接。

i.Tech 藍牙耳機是專門設計與藍牙裝置相配使用。由於不同製造商提供的裝置多的藍牙配置，因此無法完全保證耳機可與可與啟用藍牙的產品之間能互通。

5. 簡便電量檢查

關機模式: 按 MFB 一次
待機模式: 在未通話時同時長按兩個音量按鍵。

語音提示	狀態指示燈	通配時間
Battery High	顯示藍燈約 3 秒鐘	高於 3.75 小時
Battery Medium	閃爍藍燈 3 次	0.75-3.75小時之間
Battery Low	閃爍紅燈 3 次	低於 0.75 小時

簡中 1.关于您的 MyVoice 3000

a. 多功能按钮（MFB）
- 开机 / 关机
- 与行动电话配对
- 接听 / 结束来电

b. 状态指示灯
c. USB 充电插孔
d. 音量控制器

2. 耳机充电

耳机随附内建式充电电池。第一次使用耳机之前，建议您将电池充饱电量。
将充电器的插头插入 USB 充电插槽，并将主充电器插入 AC 墙壁插座或插入个人计算机 / 笔记型计算机。
请仅使用随附的充电器 / USB充电线，为耳机充电。

耳机状态	状态指示灯光
充电中（关闭模式）	红光
已充饱电（关闭模式）	蓝光
低电量	闪红光，而且发出短哨声
充电中（待机模式）*	红光
已充饱电（待机模式）*	蓝光

需要 2 小时的时间，才能将耳机充饱电量。
* 警告：请勿在耳机连接至充电器时使用耳机。

3. 将耳机与蓝牙行动电话配对

1）确保耳机关闭。
如果要启动配对模式，请按住耳机的 MFB 按钮 8 秒钟，直至状态指示灯交替地闪烁蓝光和红光。
3）启动手机的蓝牙功能，搜索蓝牙装置，选择 "MyVoice 3000"，然后输入密码 " 0000 "。当配对完成时，耳机的状态指示灯会快速闪烁蓝光 2 秒，并可听到一声长响及语音提示 "Your phone is connected"。

4. 基本操作

功能	按钮	警报声	状态指示灯
开机	按住 MFB 约 3 秒钟	剩余通话时间：>3.75 小时：「Battery high」；0.75 - 3.75 小时：「Battery medium」；<0.75 小时：「Battery low」	闪烁蓝灯 3 次
当您首次开启耳机时，耳机会自动进入配对模式（即状态指示灯会交替闪烁蓝灯和红灯），此时可以立即将耳机与手机进行配对。			
关机	按住 MFB 约 3 秒钟	--	红灯闪烁 3次

功能	按钮	警报声	状态指示灯
来电	--	耳机发出铃声	--
接听／结束来电	按一下 MFB	--	--
拒绝来电	按住 MFB 约 3 秒钟	短哨呼声	--
最后号码重拨	按 MFB 两次	--	--
音量调节*	按住 MFB 约 3 秒钟	--	--

* 音量级号功能仅支持配备语音调节功能之手机型号。

多点连接允许耳机同时和两台手机配对。
配对程序：
1. 按照正常方式将耳机和第一台手机配对，然后关闭
2. 对第二台手机重复配对步骤
3. 通过手机菜单重新连接第一台手机和耳机。

i.Tech 蓝牙耳机是专门设计与蓝牙装置相配使用。由于不同制造商提供种类繁多的蓝牙装置，因此无法保证耳机可与启用蓝牙的产品之间能互通。

5. 简便电量检查

关机模式: 按 MFB 一次
待机模式: 在未通话时同时长按两个音量按键。

语音提示	状态指示灯	通话时间
Battery High	显示蓝灯约 3 秒钟	高於 3.75 小时
Battery Medium	闪烁蓝灯 3 次	0.75-3.75小时之间
Battery Low	闪烁红灯 3 次	低於 0.75 小时

العربية 1. حول بك 3000 MyVoice

a. زر متعدد الوظائف (MFB)
- تشغيل / إيقاف
- إقران السماعة بالهاتف المحمول
- الرد على / إنهاء المكالمة

b. مؤشر الحالة
c. مقبس شحن USB
d. التحكم في مستوى الصوت

2. شحن سماعة الرأس

سماعة الرأس مزودة ببطارية مضمنة قابلة لإعادة الشحن. يوصى بشحن بطارية السماعة بصورة كاملة قبل استخدامها لأول مرة.
الموجود USB قم بإدخال قابس الشحن في مقبس شحن بالسماعة، ثم قم بتوصيل قابس الشحن الرئيسي بمأخذ أو قم بتوصيله بالكمبيوتر AC جداري للتيار المتردد الشخصي/ الكمبيوتر المحمول.
المرفق لشحن USB استخدم فقط الشاحن / كبل شحن السماعة.

حالة سماعة الرأس	مصباح مؤشر الحالة
الشحن في (وضع إيقاف)	أحمر ثابت
شحنة بالكامل في (وضع إيقاف)	ضوء أزرق طويل
بطارية منخفضة	وميض أحمر مع صافرة قصيرة متكررة كل دقيقة
الشحن في (وضع استعداد)*	أحمر ثابت
شحنة بالكامل (وضع استعداد)*	ضوء أزرق طويل

يستلزم الأمر 2 ساعات لشحن سماعة الرأس بشكل تام.
* تحذير: لا تستخدم سماعة الرأس بينما الكرن متصلة بالشاحن

3. مزاوجة سماعة الرأس بهاتف محمول يدعم تقنية Bluetooth

1) تأكد من أن سماعة الرأس في وضع إيقاف التشغيل وإلغاء القفل.
2) لتنشيط وضع المزاوجة، اضغط مع الاستمرار على الزر متعدد الوظائف (MFB) بسماعة الرأس لمدة 8 ثوان.
سيومض مؤشر الحالة باللونين الأزرق والأحمر بالتناوب.
3) قم بتنشيط خاصية Bluetooth بهاتفك المحمول، والبحث عن أجهزة Bluetooth وتحديد "MyVoice 3000" وإدخال رمز المرور " 0000 " عند اكتمال المزاوجة، سيومض مؤشر الحالة بسماعة الرأس 2 مرات بشكل مربع ويمكنك سماع إشارة صوتية طويلة

4 . التشغيل الأساسي

الوظيفة	الزر	نغماتكتيه	مؤشرالحالة
التشغيل	اضغط مع الاستمرار على الزر متعدد الوظائف لمدة 3 ثوان	--	--
إيقاف التشغيل	اضغط مع الاستمرار على الزر متعدد الوظائف لمدة 5 ثوان	--	--
مكالمة واردة	--	--	--

الوظيفة	الزر	نغماتكتيه	مؤشرالحالة
الرد على مكالمة / إنهاء مكالمة	اضغط على الزر متعدد الوظائف مرة واحدة	--	--
رفض مكالمة واردة	اضغط مع الاستمرار على الزر متعدد الوظائف لمدة 2 ثوان	إشارة صوتية قصيرة	--
إعادة الاتصال برقم الاتصال به	اضغط مرتين على الزر متعدد الوظائف لمدة 2 ثوان	--	--
الاتصال بقرة الصوت	اضغط مع الاستمرار على الزر متعدد الوظائف لمدة 2 ثوان	--	--

يمكنك تشغيل وظيفة الاتصال بقرة الصوت فقط من قبل بعض وظيفة الصوت على قرة الصوتية أو الوظائف المحددة.

متعدد النقاط يسمح بإقران السماعة بجهازي هاتف محمول في نفس الوقت، كالقرن وجهازي هاتف محمول:

1. الزن السماعة بالجهاز الأول كالمعتاد ثم أوقف التشغيل
2. أعد عملية الإقران للجهاز الثاني
3. أعد الاتصال بالهاتف المحمول الأول من خلال قائمة الهاتف إذا تطلب الأمر

5. التحقق من مستوى طاقة البطارية

في وضع إيقاف: اضغط على الزر متعدد الوظائف مرة واحدة
في وضع الاستعداد: اضغط على زري رفع مستوى الصوت لمدة 2 ثانية

نغمة التنبيه	مؤشر الحالة	زمن المحدث المقابل
Battery High	ضوء أزرق لمدة 3 ثانية	أكثر من 3.75 ساعة
Battery Medium	يومض باللون الأزرق 3 مرات	بين 0.75 و 3.75 ساعة
Battery Low	يومض باللون أحمر 3 مرات	أقل من 0.75 ساعة