

Name		Description
Auth mode	Mode	Select a authentication mode (Face only , Face or card , Face and PIN , Card and face , Card an PIN , Card only)
	Bypass	Allows unregistered users to access
	Touch start	Starts recognition by touching the screen
	Recog threshold	Adjusts match threshold (permitted value range: 90 — 100)
		 Increasing the value increases FRR (false rejection rate) whereas decreasing the value increases FAR (false acceptance rate).
	Recog distance	Select the distance from where the face detection starts (2M , 1.4M , 0.9M)
	Enroll sensitivity	Determines how strict the device is about facial orientation during enrollment. It can be set to high (Sensitive), medium (Common), or low (Insensitive).
	Recog sensitivity	Determines how strict the device is about facial orientation during recognition. It can be set to high (Sensitive), medium (Common), or low (Insensitive).
	Enroll liveness	Prevents enrolling with fake faces, such as photos or mannequins by checking for liveness
	Recog liveness	Prevents authentication with fake faces, such as photos or mannequins by checking for liveness
	Liveness threshold	Determines how strict the device is at detecting fake faces during enrollment and recognition.
		 A higher threshold means the system requires a stronger sign of liveness (e.g., blinking, head movement). This reduces false positives (accepting a fake face) but might also increase false negatives (rejecting a real person).
	1:1 Recog threshold	Determines how strict the device is at matching a face to a single user.

Name		Description
Auth option	No mask reject	Select the action to take when a mask is not detected (Not used, Warning message, Access deny)
	Mask reject	Select the action to take when a mask is detected (Not used, Warning message, Access deny)
	No helmet reject	Select the action to take when a helmet is not detected (Not used, Warning message, Access deny)
	Face image log	Select whether to show face image on event log
T&A	Use T&A	Select whether to use T&A
	T&A value	Select T&A type (None, In, Out, Leave, Return)
	Use T&A time	Select whether to use T&A time
		 - If Use T&A time is enabled, you can set specific times for clocking in and out in In time and Out time fields that appear below. The device will automatically clock users in or out when they authenticate during the set times. - You can use either Use T&A or Use T&A time depending on your attendance tracking needs. If you want to track attendance without specific clock-in/out times, enable Use T&A. If you want to automate clocking in/out at specific times, enable Use T&A time and set the desired times. You cannot enable both options at the same time.
Admin password	In time	Set the time for clocking in
	Out time	Set the time for clocking out
	Use admin password	Select whether to use admin password
	Password	Enter admin password

Name		Description
Card	Use CSN	Select whether to use card serial number
	CSN order	Select CSN order on card reading (MSB, LSB)
	Use HID Secure ID	Available only when HID card module is detected
	Use face TOC	Select whether to use TOC (Template on Card) for face recognition
Wiegand	Output type	Select Wiegand output type (Wiegand, Card, ID)

A.5. Log

Name		Description
Log info	Total used	Shows the used space for logs in percent
	Total count	Shows the total count of logs
Log list		Shows the list of logs
Log search		Searches logs by date, time, event type, log info, user ID, and additional data
Delete all logs		Deletes all logs

Appendix B: Legal Information

B.1. Disclaimer

The words of which the initial letter is capitalized have meanings defined under the following conditions. The following definitions shall have the same meaning regardless of whether they appear in singular or in plural.

For the purposes of this Disclaimer:

- **Company** (referred to as either "the Company", "We", "Us" or "Our" in this Disclaimer) refers to CMITech Co. Ltd.
- **You** means the individual accessing the Product, or the company, or other legal entity on behalf of which such individual is accessing or using the Product, as applicable.
- **Product** means the electronic device provided by the Company named FACE CAMERA and its manual.

The information contained on the Product is for general information purposes only. The Company assumes no responsibility for errors or omissions in the contents of the Product. In no event shall the Company be liable for any special, direct, indirect, consequential, or incidental damages or any damages whatsoever, whether in an action of contract, negligence or other tort, arising out of or in connection with the use of the Product or the contents of the Product. The Company reserves the right to make additions, deletions, or modifications to the contents on the Product at any time without prior notice.

The Product may contain links to external websites that are not provided or maintained by or in any way affiliated with the Company. Please note that the Company does not guarantee the accuracy, relevance, timeliness, or completeness of any information on these external websites.

The information given by the Product is for general guidance on matters of interest only. Even if the Company takes every precaution to insure that the content of the Product is both current and accurate, errors can occur. Plus, given the changing nature of laws, rules and regulations, there may be delays, omissions or inaccuracies in the information contained on the Product. The Company is not responsible for any errors or omissions, or for the results obtained from the use of this information.

All information in the Product is provided "as is", with no guarantee of completeness, accuracy, timeliness or of the results obtained from the use of this information, and without warranty of any kind, express or implied, including, but not limited to warranties of performance, merchantability and fitness for a particular purpose. The Company will not be liable to You or anyone else for any decision made or action taken in reliance on the information given by the Product or for any consequential, special or similar damages, even if advised of the possibility of such damages.

B.2. Copyright Notice

All rights reserved. This documentation is copyrighted by CMITech Co., Ltd. No part of this guide may be reproduced, transmitted, or transcribed without the expressed written permission from CMITech Co., Ltd. All other product names, trademarks, or registered trademarks are property of their respective owners.

We reserve the right to make any alterations which may be required due to technical improvement. For the most current information, contact your CMITech representative.

Appendix C: Regulatory Information

C.1. FCC compliance statement

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

This equipment has been tested and found to comply with the limits for a Class A digital device pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable

Note: This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

Changes or modifications to this product not authorized by CMITech could void the electromagnetic compatibility (EMC) and wireless compliance and negate your authority to operate the product.

This product has demonstrated EMC compliance under conditions that included the use of compliant peripheral devices and shielded cables between system components. It is important that you use compliant peripheral devices and shielded cables between system components to reduce the possibility of causing interference to radios, television sets, and other electronic devices.

The antenna(s) used for this transmitter must not be co-located or operating in conjunction with any other antenna or transmitter, except in accordance with FCC multi-transmitter product procedures.

A minimum separation distance of 20cm must be maintained between the antenna and the person for this appliance to satisfy the RF exposure requirements.

C.2. EU Declaration of Conformity (CE)

This product is CE marked according to the provisions of the RED (Radio Equipment Directive) Directive (2014/53/EU). CMITech Co., Ltd. hereby declares that this product is in compliance with the essential requirements and other relevant provisions of Directive 2014/53/EU. This device is a class 1 radio device according to the directive. For more information, contact us using the following contact information.

CMITech Company, Ltd.

- Website: <https://www.cmi-tech.com/>
- Address: 4th Floor, #417 - 419, 136, LS-ro, Dongan-gu, Anyang-si, Gyeonggi-do, 14118, Republic of Korea
- Tel: +82-70-8633-8278 / Fax: +82-31-624-4490

Appendix D: Contact Information

CMITech Company, Ltd.

4th Floor, #417 - 419, 136, LS-ro, Dongan-gu, Anyang-si, Gyeonggi-do, 14118, Republic of Korea

Tel: +82-70-8633-8277

CMITech America, Inc.

2033 Gateway Place, Suite 500
San Jose, CA 95110 USA

Tel: (1) 408 573-6930

sales@cmi-tech.com or service@cmi-tech.com