



In-Wall Dimmer

In-Wall Dimmer is a Zigbee switch device controls on, off and, dim of any type of adjustable bulb. It supports a variety of installation for wiring connection, such as 3-wire, 2-wire connection. Within the network, it works as a repeater to increase network reliability.

What's included?



Familiarize yourself with your Dimmer



Description of terminals:
L=Power input for live
N=Power input for neutral
OUT=Output for load
COM=Common pin for all external switches
S1=Internal switch 1 control for load
S2=Internal switch 2 for remote other Zigbee device

Installation wiring diagram

⚠ Safety warning

Failure to follow the recommendations may be dangerous or cause a violation of the law. The manufacturer accepts no responsibility for any damage resulting from not following any instructions in this guide.
1. Read the manual closely. The manufacturer assumes no liability for any off-lying installation.
2. A licensed electrician with knowledge and understanding of electrical systems and safety should conduct the installation.
3. The installation distance of the product is 20CM from human body.



⚠ Avvertenza di sicurezza

La mancata osservanza delle raccomandazioni può essere pericolosa o causare una violazione della legge. Il produttore, il trasportatore, l'installatore o l'utente non sono responsabili per danni o lesioni dovuti al mancato rispetto delle istruzioni. Leggere attentamente il manuale di istruzioni.
1. Leggere attentamente il manuale di istruzioni. Il produttore non si assume alcuna responsabilità per qualsiasi installazione errata.
2. Completare l'installazione con competenza e in una comprensione dei sistemi elettrici e della sicurezza dell'installazione.
3. La distanza di installazione del prodotto è di 20 cm dal corpo umano.



⚠ Alerte de sécurité

Le non respect des recommandations peut être dangereux ou causer une violation de la loi. Le fabricant, l'importateur, le distributeur ou l'utilisateur ne sont pas responsables des dommages ou des blessures résultant du non respect des instructions de ce guide.
1. Lire attentivement le manuel d'installation. Le fabricant n'assume aucune responsabilité en cas d'installation erronée.
2. L'installation électrique doit être effectuée par un électricien qualifié et avec une compréhension des systèmes électriques et de la sécurité de l'installation.
3. La distance de l'installation du produit est de 20 cm du corps humain.



⚠ Advertencia de seguridad

El no cumplimiento de las recomendaciones puede ser peligroso o causar una violación de la ley. El fabricante, el importador, el distribuidor o el usuario no son responsables de los daños o lesiones resultantes de no seguir las instrucciones de este guía.
1. Lea el manual de instalación. El fabricante no asume ninguna responsabilidad en caso de una instalación incorrecta.
2. Las instalaciones eléctricas deben completarse con competencia y comprensión de los sistemas eléctricos y la seguridad de la instalación.
3. La distancia de instalación del producto debe de 20 cm del cuerpo humano.




a) 3-Wire connection (With Neutral)


1. Without Bypass The minimum load is 5 watts
2. With Bypass The minimum load is 3 watts



b) 2-Wire connection (Without Neutral)



c) SPOT connection (work with/without Neutral)



Quick start

Download APP

1. Android phone download "Smart Life" from Google play store.
2. iPhone download "Smart Life" from Apple App Store.



Adding In-Wall Dimmer into a Zigbee network

1. Power the Dimmer, LED will blink slowly. If LED is solid or OFF, please try a factory reset.
2. Set your Zigbee gateway to "add subdevice" according to Figure 1.
3. Double-click the Action Button on your In-Wall Dimmer indicated by a LED blink. If you are successful, LED will blink. Otherwise, LED will blink slowly, in which case you need to repeat the process from step 2.

Remove In-Wall Dimmer from network

1. Make sure the In-Wall Dimmer is connected to the power supply.

supply.
2. Press the Action Button 5 times quickly. If this is successful, the LED on In-Wall Dimmer will be blue, eventually blink slowly.
However, if the In-Wall Dimmer is still in the APP to remove the widget from the APP, please follow step 3.
3. Press the "Disconnect" button on the web page of the device in Smart Life APP according to Figure 2.
Note: These operation will delete the configuration value.

Factory Reset

1. Make sure the In-Wall Dimmer has been connected to the power supply.
2. Press and hold the Action Button for 20 seconds. The LED on In-Wall Dimmer will blink (intermittently) fast and will be lit solidly for 2 seconds after the factory reset.
3. Double-click the Action Button on your In-Wall Dimmer indicated by a LED blink. If you are successful, LED will blink. Otherwise, LED will blink slowly, in which case you need to repeat the process from step 2.

Restore the default configuration settings include load type



Figure 1

Advanced Functions

Identify external switch type

In-Wall Dimmer works with some type of wall switch, including momentary switch, SPST, SPDT, and trailing edge. Or the In-Wall Dimmer is used in the network and if it doesn't control the load, you need to identify its type with the APP.
1. Select the correct switch type on the device web page of the Smart Life APP.
2. If you can't identify the switch type, you can follow:
2.1. Select the switch type on the device web page of the Smart Life APP.
2.2. If the switch type is not the same as the device web page, you can click the "Identify" button on the device web page of the Smart Life APP. Then, the device will identify the switch type and the device will be lit solidly for 2 seconds after the factory reset.

Identify load type

In-Wall Dimmer can control on, off and dim of multiple types of loads in different stages, including LED lighting, CFL, incandescent, dimmable CFL, and fans. And it can turn on/off non-dimmable CFL, LED.

Figure 2

Waste Electrical and Electronic Equipment (WEEE)

Information for the user

At the end of useful life, the product must be disposed of separately from other waste. For more detailed information about disposal, contact the supplier that provided you with the product or question or contact the dedicated sector of the waste Parson Technologies Co., Ltd.

Informazione per gli utenti

Al termine dell'utilizzo, il prodotto deve essere smaltito separatamente dai rifiuti. Per maggiori informazioni sulla raccolta differenziata, contattare il fornitore del prodotto o il settore dedicato alla gestione dei rifiuti Parson Technologies Co., Ltd.

Information for users

At the end of useful life, the product must be disposed of separately from other waste. For more detailed information about disposal, contact the supplier that provided you with the product or question or contact the dedicated sector of the waste Parson Technologies Co., Ltd.

Benutzerinformation bezüglich

Am Ende des Lebenszyklus des Produkts muss das Produkt nicht über den allgemeinen Hausmüll entsorgt werden. Bitte kontaktieren Sie



Information for the user

At the end of useful life, the product must be disposed of separately from other waste. For more detailed information about disposal, contact the supplier that provided you with the product or question or contact the dedicated sector of the waste Parson Technologies Co., Ltd.

Información para el usuario

Al final de la vida útil, el producto debe ser eliminado de forma adecuada. Para obtener más información sobre la eliminación, póngase en contacto con el proveedor de donde se compró el producto o con el departamento de residuos de Parson Technologies Co., Ltd.

Informação para o usuário

Após o fim da vida útil do produto, ele deve ser descartado separadamente dos outros resíduos. Para obter mais informações sobre a eliminação, contate o fornecedor do produto ou o departamento de resíduos da Parson Technologies Co., Ltd.

Información para el usuario

Al final de la vida útil, el producto debe ser eliminado de forma adecuada. Para obtener más información sobre la eliminación, póngase en contacto con el proveedor de donde se compró el producto o con el departamento de residuos de Parson Technologies Co., Ltd.

