


AIPHONE

GT SYSTEM


Entrance station (modular type)
Entrance station (all-in-one type)
Guard station

OPERATION MANUAL


Entrance station
(modular type)



Entrance station
(all-in-one type)



Guard station



Thank you for selecting Aiphone for your communication needs. Please read this manual carefully before installation, and keep this in a safe place for future reference.

Please note that images and illustrations depicted in this manual may differ from the actual product.

PRECAUTIONS



Prohibited



Do not dismantle unit



Keep unit away from water



Be sure to follow the instruction

WARNING

(Negligence could result in death or serious injury.)

-  1. Do not dismantle or alter the unit. Fire or electric shock could result.
-  2. Do not put any metal and flammable material into the unit through the openings. Fire, electric shock, or unit trouble could result.
-  3. Keep the unit away from water or any other liquid. Fire or electric shock could result.
-  4. During an electrical storm, do not touch the unit. Electric shock could result.
-  5. If there is any smoke, unusual odor, or abnormal sound, or if you drop or damage the unit, turn off the system power breaker immediately. Fire or electric shock could result.
-  6. Do not use power supply with a voltage other than specified. Fire or electric shock could result.
-  7. Do not use the unit in/under following locations/conditions. If not observed, it may result in noises or malfunctions.
 - Where use of the unit is prohibited, such as in a hospital
 - Near an electric medical equipment (e.g. operating rooms, ICU, or CCU)
 - Near automatic control equipment such as auto doors or fire-alarm boxes
 - In the area within 15cm from a cardiac pacemaker

CAUTION

(Negligence could result in injury to people or damage to property.)

-  1. Do not put anything on or cover the unit with cloth, etc. Fire or unit trouble could result.
-  2. Do not apply high pressure on the screen. If fractured, injury could result.
-  3. If the LCD is punctured, do not touch the liquid crystal inside. Inflammation could result. If contact should occur, flush or rinse area with water thoroughly and consult your doctor.
-  4. Be sure to perform a call test with the handset on the hook. If you operate the hook switch with the handset on your ear, a sudden call etc. may arrive causing damage to your ear.
-  5. Do not place your ear near the speaker during use. An unexpected loud sound could cause hearing damage.
-  6. When cleaning the wall with a high-pressure water sprayer, be careful not to spray on the entrance station. If not observed, it may result in fire or electric shock.

General Precautions

1. Keep the unit more than 1 m (3.3') away from radio or TV set.
2. Keep more than 20 cm (7-7/8") away from other radio equipment, for example floor heating controller, wireless router or cordless telephone, etc. It may cause unwanted noise and video distortion.
3. Talk within 30 cm (12") from this unit. If you are too far away, it may be difficult to hear audio.
4. When installing and using this unit, protect subject's privacy, portrait rights, etc. on your own responsibility.
5. As to other manufacturer's devices (such as sensor, detectors, door releases) used with this system, comply with the Specifications and Warranty conditions that the manufacturers or vendors present.
6. Avoid using this unit in places under direct sunlight. If it is unavoidable, block out light during use.
7. When putting a hearing aid into T-mode and approaching the unit, the intercom system may be affected by radio frequency interference etc., depending on the installation environment.
8. Please receive and retain all configuration data from the supplier. If you lose the configuration data, there are cases where maintenance and after-sales service calls may incur additional setup fees.
10. The area to be monitored by the sensor should be free of obstacles such as ornamental plants.

Notice

- We will under no conditions be liable for any damages or losses resulting from this product's contents or specifications.
- We will under no conditions be liable for damage occurring due to the inability to communicate due to malfunctions, problems, or operational errors in this product.
- The unit is inoperative during power failure.
- This system is not intended for life support or crime prevention. It is just a supplementary means of conveying information. Aiphone will under no conditions be liable for loss of life or property which occurs while the system is being operated.
- In areas where broadcasting station antennas are close by, this system may be affected by radio frequency interference.
- Please note the LCD panel, though manufactured with very high precision techniques, inevitably will have a very small portion of its image elements always lit or not lit at all. This is not considered a unit malfunction.
- The unit may get slightly warm, but this is not a malfunction.
- During communication, if you speak before the other person has finished talking, your voice may not come through clearly. Conversation will proceed smoothly if you speak when the other person has finished talking.
- The entrance station is intended to be mounted on a wall only. It cannot be used on a desktop.
- Available functions and services are limited according to the specifications of the installed system.
- If you speak in a fixed tone, the noise-cut function may judge it to be a noise and cut the transmission, but this is not a malfunction.
- Using a mobile phone or professional-use radio equipment such as walkie-talkie close to the system may cause a malfunction.
- Warm-color lighting shining on the camera may change the tint of the image on the screen.
- The outline of video images displayed may differ from that of the actual person(s) or background, but this is not a malfunction.
- When the unit's screen is illuminated with strong light, the image looks white or silhouetted. But this is not a unit trouble.
- When outside temperature lowers sharply after rainfall, etc., the inside of the camera may fog up slightly, causing a blurry images, but this is not a malfunction. Normal operation will be restored when moisture evaporates.
- When using a fluorescent light that shines around the camera, the screen colors may variously change (color rolling), but it is not a malfunction.
- If the entrance station freezes during winter time, the picture may become difficult to see or the buttons of the entrance station may not operate.

Table of Contents

PRECAUTIONS.....	2
-------------------------	----------

READ THIS BEFORE USING THE STATIONS

1 SYSTEM CONFIGURATION.....	4
2 NOTES ABOUT USING THIS MANUAL	5

ENTRANCE STATION

1 PART NAMES AND FUNCTIONS.....	6
1-1 Entrance station (modular type).....	6
1-2 Entrance station (all-in-one type).....	7
1-3 Indicators.....	8
2 OPERATIONS.....	9
2-1 Calling a resident/tenant or guard station	9
Calling with the call switch module.....	9
Calling with the name scrolling module	9
Calling with the 10 key module	10
Calling with the all-in-one type entrance station (GT-DMB-LVN/GT-DMB-N).....	12
2-2 Door release	16
2-3 Other	16

GUARD STATION

1 PART NAMES AND FUNCTIONS.....	17
1-1 Operation panel.....	17
1-2 Indicators.....	18
1-3 LCD (display)	19
1-4 Button operations.....	20
2 RECEIVING A CALL	22
2-1 Receiving a call.....	22
3 CALLING (from a tenant building)	23
3-1 How to search for a unit to call (from a tenant building)	23
3-2 Calling a unit (residential/tenant station) or guard station	24
3-3 Calling an entrance station.....	29
4 CALLING (from a main building)	31
4-1 How to select a unit to call (from a main building)	31
4-2 Calling a room (residential/tenant station) or guard station	32
4-3 Calling an entrance station.....	37
5 OPERATIONS DURING COMMUNICATION	39
5-1 Transferring a call	39
5-2 Door release	39
5-3 Operating an optional device	40
5-4 Viewing and adjusting video at an entrance station	41
6 MONITORING	43

7 OTHER OPERATIONS.....	45
7-1 Checking for missed calls and calling back.....	45
7-2 Receiving an emergency call	46
8 SETTING.....	48
8-1 Adjusting display brightness and volumes.....	48
8-2 Switching to reception mode	50
8-3 Switching to program mode.....	51
9 UPDATING RESIDENT INFORMATION	52

FOR PROPER USE OF THIS STATION

1 TECHNICAL PRECAUTIONS.....	53
2 SPECIFICATIONS.....	54
3 SOFTWARE LICENSE.....	56
4 REGULATIONS	57
5 WARRANTY.....	58

READ THIS BEFORE USING THE STATIONS

1 SYSTEM CONFIGURATION

The GT system consists of up to 8 main buildings and 24 tenant buildings.

Main building:

A control section that functions as a main entrance, guard station, security center, administration office, etc. A main building includes no residential/tenant stations. You can call up all of the residential/tenant stations and guard stations from an entrance station or guard station in the same system (site).


* A station that is not programmed cannot be called.

* Modular type entrance stations cannot be installed in a main building. Only all-in-one type can be used.

Tenant building:

A section of collective housing. A tenant building includes residential/tenant stations, entrance stations and guard stations. You can call up all of the residential/tenant stations and guard stations from an entrance station in the same tenant building. However, you cannot call stations in another tenant building.

Example : A system (site) consisting of 1 main and 3 tenant buildings



Coverage of calling, communication and monitoring

The following table shows the coverage of calling, communication, and monitoring from a tenant building and a main building.

NOTE: Performance depends on the settings. If you cannot call even when ✓ is indicated, its setting is not configured.

				Incoming call									
				Same tenant building			Other tenant buildings			Same main building		Other main buildings	
													
				Entrance st.	Guard st.	Residential/tenant st.	Entrance st.	Guard st.	Residential/tenant st.	Entrance st.	Guard st.	Entrance st.	Guard st.
Outgoing call		Entrance st.	Calling/communication	-	✓	✓	-	-	-	-	-	-	-
		Guard st.	Calling/communication	✓	✓	✓	-	-	-	✓	✓	✓	✓
			Monitoring	✓	-	-	-	-	-	-	-	-	-
		Entrance st.	Calling/communication	-	✓	✓	-	✓	✓	-	✓	-	✓
		Guard st.	Calling/communication	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
			Monitoring	✓	-	-	✓	-	-	✓	-	✓	-

✓ : Possible — : Impossible

About the term "building" and "section":

The term "section" is used on the setting screens of entrance stations and guard stations instead of "building".
"Section" and "building" have the same meaning in this manual.

Setting screen of guard station

e.g.

CALLING METHOD	
NAME / SEARCH	
SECT LIST + UNIT #	
GROUP NUMBER	
SECT # + UNIT #	

Standby screen of guard station

e.g.

BUILDING #	
01	
UNIT #	
1	

2 NOTES ABOUT USING THIS MANUAL


This manual describes how to use the entrance stations and guard stations. The use of them differs depending on the building/section (main or tenant) where they belong. This manual uses the following icons to separate descriptions for the main and tenant buildings.

Icon	Meaning
	Main building/section
	Tenant building/section


ENTRANCE STATION

1 PART NAMES AND FUNCTIONS

1-1 Entrance station (modular type)



[Combination examples]




1-2 Entrance station (all-in-one type)

All-in-one entrance station

GT-DMB-N

(NFC capable)



All-in-one entrance station


GT-DMB-LVN

(VIGIK and NFC capable, Hearing aid compatible)

Each part and indicator are the same as **GT-DMB-N** except as shown below (VIGIK).




VIGIK (available in France)




1-3 Indicators

Entrance station (modular type)



Entrance station (all-in-one type)



Indication patterns

Status \ Indicator	1 IN USE LED (orange) 	2 Call indicator 	3 Talk indicator 	4 Door release indicator 	5 Display
Standby	Off	Off	Off	Off	WELCOME ^{(*)3}
System in use	Lit 	Off	Off	Off	IN USE
Call	Off	Lit 	Off	Off ^{(*)1}	CALLING SMITH ^{(*)3}
Communication	Off	Off	Lit 	Off ^{(*)2}	IN COMMUNICATION
Releasing a door	Off	Off ^{(*)1}	Off ^{(*)2}	Lit 	DOOR OPEN
Monitoring	Off	Off	Off	Off	WELCOME
Communication is on hold	Lit 	Off	Off	Off	ON HOLD

(*)1: Lit when door release is activated during call.

(*)2: Lit when door release is activated during communication.

(*)3: The display differs depending on the settings.

2 OPERATIONS




: Main building/section




: Tenant building/section

2-1 Calling a resident/tenant or guard station

Calling with the call switch module



1 Press the call button for the unit to be called.



The call indicator will light up and you will hear a call tone.

* Audio guidance will be heard depending on the settings.



When the call is answered

Communication starts and the talk indicator lights up.

* Audio guidance will be heard depending on the settings.




When the door is released

The door release indicator lights up.

* Audio guidance will be heard depending on the settings.




Calling with the name scrolling module



■ Searching for a unit by scrolling the list


1 In standby mode, press Δ and ∇ to display the target unit # and resident name.



* Depending on the settings, only the resident name may be displayed.

* The list is displayed in order of either unit # or resident name.

2 Press $\odot$.



The call indicator will light up and you will hear a call tone.

* Audio guidance will be heard depending on the settings.



When the call is answered

Communication starts and the talk indicator lights up.

* Audio guidance will be heard depending on the settings.




When the door is released

The door release indicator lights up.

* Audio guidance will be heard depending on the settings.




Calling with the 10 key module



■ Searching for a unit by entering the unit

- 1 In standby mode, enter the numbers using [0] to [9] on the 10-key to display the target unit # and resident name.



101
SMITH

- 2 When the target unit # and resident name is displayed, press .

The call indicator will light up and you will hear a call tone.

- * Audio guidance will be heard depending on the settings.



- * If there is no relevant unit #, "NO ENTRY" is displayed.

NO ENTRY

- * When the residential/tenant station that has been called is in use, the IN USE LED lights up to indicate that the residential/tenant station cannot be called.
(In an expanded system, there may be a case that a residential/tenant station cannot be called even if the IN USE LED is off.)

When the call is answered

Communication starts and the talk indicator lights up.

- * Audio guidance will be heard depending on the settings.




When the door is released

The door release indicator lights up.

- * Audio guidance will be heard depending on the settings.



■ Searching for a unit by entering resident name



- 1 In standby mode, press on the 10-key.

- 2 When "ENTER A LETTER" is displayed, enter a letter using the 10-key to display the target unit # and resident name.

The number and resident name for the unit whose initial corresponds to the entered letter will be displayed.

(e.g.) Enter "S".

101
SMITH


- * Pressing or searches for the next unit # and resident name.
- * Depending on the settings, only the resident name may be displayed.
- * When the unit # is set to not be displayed, a letter can be entered without pressing .
- * If there is no relevant resident name, "NO ENTRY" is displayed.

NO ENTRY: S

NOTES:

- Pressing or for approximately 2 seconds will display resident names in succession.
- If both unit # 111 and 1111 exist, the resident name for unit 111 will be displayed when 1, 1, 1 is entered, and the resident name for unit 1111 will be displayed if 1 is entered one more time.
- Stations can be set to display in order by unit #. (The order starts with the lowest digit from 0 to 9 and then the order goes by letter.) In cases where unit # such as A101, A201, A901, A1001, and B101 exist, the order starts with the lowest digit and goes in the order A101, A201, A901, B101, A1001.

3 When the target unit # or resident name is displayed, press .



The call indicator will light up and you will hear a call tone.

* Audio guidance will be heard depending on the settings.



When the call is answered

Communication starts and the talk indicator lights up.

* Audio guidance will be heard depending on the settings.



When the door is released

The door release indicator lights up.

* Audio guidance will be heard depending on the settings.




Calling with the all-in-one type entrance station GT-DMB-LVN/GT-DMB-N

The following diagram shows the screen transitions starting from the standby screen. One of the standby screens shown below is preset to this station. Find the standby screen of this station from **A** to **E** below and confirm the transition from it, and refer to the designated page for the calling operation.

NOTE:

If "NO ENTRY" is displayed on the screen, press (X).

Standby screen




A Confirming the target unit in the quick list




Unit # and resident names frequently called are preset to be displayed in the quick list.

* Up to 4 units can be displayed.



- 1 In standby mode, press and to display the target unit, or 10-key to change the standby screen.



The "UNIT LIST" screen **B** or "ENTER UNIT #" screen **C** is displayed.

- 2 Follow the operating procedure of either **B** or **C** depending on the displayed screen.


* **C** is available in a tenant building/section only.

B Searching for a unit in the unit list



HOW TO CALL	
1. SELECT UNIT	
2. CALL	
NUMBER	ALPHA

- 1 In standby mode, press and or 10-key to display the target unit # and resident name.



UNIT LIST	
101	
SMITH	
CALL	
	CANCEL

The 10-key can be used to enter unit #, or by pressing on the 10-key, then the 10-key can be used to enter letters (resident name).

- * Depending on the settings, only the resident name may be displayed.
- * The list is displayed in order of either unit # or resident name.
- * If you have entered a wrong number, press to return to standby mode.

- 2 When the target unit is displayed, press .

The target unit is called.

* Refer to "When the target unit is successfully called" at the end of **(2-1)** for details.

C Entering unit




NOTE: Entering unit # can only be performed on this screen.
Entering resident name is not possible.

HOW TO CALL	
1. ENTER UNIT #	
2. CALL	

- ◆ When the target unit number is numerals only

- 1 In standby mode, enter numbers using [0] to [9] on the 10-key to display the target unit #.

* The 10-key can be used even after pressing or .



* Depending on the system, only the resident name may be displayed.

* If you have entered a wrong number, press to return to standby mode.

- 2 When the target unit # is displayed, press .


The target unit is called.

* Refer to "When the target unit is successfully called" at the end of **(2-1)** for details.

- ◆ When the target unit number is alphanumeric

- 1 In standby mode, press on the 10-key.


* The 10-key can be used even after pressing or .



- 2 Enter letters using the 10-key to display the target unit #.

* Refer to the next page for how to enter letters.

- 3 When the target unit # is displayed, press .



The target unit is called.

* Refer to "When the target unit is successfully called" at the end of **(2-1)** for details.

How to enter letters

(e.g.) Entering "CATHY"

1. To enter "C", press **ABC 2** three times.
2. Press **▽** once. (*1)
3. To enter "A", press **ABC 2** once.
4. To enter "T", press **TUV 8** once.
5. To enter "H", press **HIJ 4** twice.
6. To enter "Y", press **WXYZ 9** three times.

(*1): This step is needed for entering different letters with the same key sequentially.

To enter a special character

- , : Press **[0]** once.
- : Press **[0]** twice.
- . : Press **[0]** three times.
- / : Press **[0]** four times.
- Space : Press **[0]** five times.
- Æ : Press **[0]** six times.
- Ø : Press **[0]** seven times.
- Å : Press **[0]** eight times.


* If you have entered a wrong letter, press **[X]** to return to standby mode.

D Searching for a building in the building list and entering unit



HOW TO CALL	
1. BUILDING LIST	▲ ▼
2. SELECT	▲
3. ENTER UNIT #	■
4. CALL	▲

- 1 In standby mode, press **▲** and **▼** to display the target building number and name.




- 2 When the target building is displayed, press **▲**.

- 3 Enter numbers or letters using the 10-key to display the target unit #.

* For entering numbers or letters, follow steps 1 and 2 of

- C** - ◆ "When the target unit number is numerals only"
- or ◆ "When the target unit number is alphanumeric".



- 4 When the target unit # is displayed, press **▲**.

The target unit is called.

* Refer to "When the target unit is successfully called" at the end of (2-1) for details.

E Entering a building # and unit




HOW TO CALL	
1. ENTER BLDG#	
2. SELECT	
3. ENTER UNIT #	
4. CALL	

1 In standby mode, enter numbers or letters using the 10-key to display the target building.

* For entering numbers or letters, follow steps 1 and 2 of

C - ◆ "When the target unit number is numerals only"
or ◆ "When the target unit number is alphanumeric".




2 When the target building number is displayed, press .

3 Enter numbers or letters using the 10-key to display the target unit #.

* For entering numbers or letters, follow steps 1 and 2 of

C - ◆ "When the target unit number is numerals only"
or ◆ "When the target unit number is alphanumeric".



4 When the target unit # is displayed, press .

The target unit is called.

* Refer to "When the target unit is successfully called" at the end of **2-1** for details.

When the target unit is successfully called

The call indicator will light up and you will hear a call tone.



* Audio guidance will be heard depending on the settings.

When the call is answered

Communication starts and the talk indicator lights up.



* Audio guidance will be heard depending on the settings.

When the door is released

The door release indicator lights up.



* Audio guidance will be heard depending on the settings.

NOTES:

- If "DENIED" is displayed or returns to standby mode, the entered unit #/resident name is not registered.
- Enter the target unit # exactly. Otherwise, "DENIED" is displayed or returns to standby mode.
- If both unit # 111 and 1111 exist, the resident name for unit 111 will be displayed when 1, 1, 1 is entered, and the resident name for unit 1111 will be displayed if 1 is entered one more time.
- Stations can be set to be displayed in order by unit #. (The order starts with the lowest digit from 0 to 9 and then the order goes by letter.) In cases where unit # such as A101, A201, A901, A1001, and B101 exist, the order starts with the lowest digit and goes in the order A101, A201, A901, B101, A1001.


2-2 Door release



■ Door release by using the access code

* The access code is preset by the system installer or administrator.


1 In standby mode, enter [#] and then the access code (4 to 6 digits) using [0] to [9] on the 10-key.



(e.g.)

When the access code is "4567", enter "#", "4", "5", "6", "7".

The door is released.



- The door release indicator lights up.
- Audio guidance will be heard depending on the settings.




- * If there is no relevant number, "DENIED" is displayed.
- * Door release is enabled even while the IN USE LED is lit.

■ Door release by an NFC-compliant IC card, etc.


A card incorporated with an NFC tag can be used to release a door. To use, the ID of the NFC tag must be registered as a door release code.

1 Pass an NFC-compliant IC card over the NFC reader.



- * Put the card within 10 mm of the NFC reader. Otherwise, the code may not be read correctly.

The door is released.



- The door release indicator lights up.
- Audio guidance will be heard depending on the settings.



- * Door release is enabled even while the IN USE LED is lit.

NOTE: Do not overlap IC cards when passing them over the NFC reader. The code may not be read correctly.

2-3 Other




- * Calling from an entrance station is disabled while the IN USE LED is lit. Wait until the IN USE LED turns off.


NOTE: For a multi building system with lift control, if you unlock from a room and terminate call at the same time, the entrance station may not unlock properly.

1 PART NAMES AND FUNCTIONS

1-1 Operation panel



1-2 Indicators



Indication patterns

Status	Indicator	⑥ Status LED (orange)
Standby		Off
Standby (Call tone volume: off)		Long interval flashing (0.5 sec.) → (5.5 sec.)
Standby (Reception mode: on)		Slow flashing (0.5 sec.) → (2.5 sec.)
This station is in use by another station (this station is inoperable)		Off
Being called by an entrance station		Fast flashing (0.5 sec.) → (0.5 sec.)
Being called by a door station		Normal flashing (1 sec.) → (1 sec.)
Being called by a door bell		Fast flashing (0.5 sec.) → (1 sec.)
Monitoring an entrance station		Lit
Communicating with an entrance station		Lit
Calling another guard station or residential/tenant station (including in reception mode)		Fast flashing (0.5 sec.) → (0.5 sec.)
Sounding an emergency alarm		Fast flashing (0.5 sec.) → (0.5 sec.)
A new list of missed calls from residential/tenant stations has arrived		Slow flashing (0.5 sec.) → (2.5 sec.)
Error indication		Off (An error message is displayed.)
Communication is on hold		Off


1-3 LCD (display)

The following are samples of typical screens and icons.

In standby mode

* When nothing is displayed (black) on the screen, the screen below can be displayed by pressing

any key other than , 0-9, , , ,  or lifting the handset.



Status display icons

The following icons are displayed here depending on the status of this station.

Icon	The status when the icon appears
	Appears when this station is in reception mode.
	Appears while searching for a unit.
	Appears while the number or letter entry screen is displayed.
	Appears while receiving a call.
	Appears when a record of missed calls is displayed.
	Appears while in communication.
	Appears while transferring.
	Appears while this station is in communication with a residential/tenant station after transferring a call from an entrance station to the residential/tenant station.
	Appears when a record of emergency calls is displayed.
	Appears while monitoring.
	Appears while a wide video at the entrance or a video at the door station is displayed.
	Appears while a zoom video at the entrance station is displayed.
	Appears when the setting screen is displayed.

NAME SEARCH screen


The screen for searching for a unit by its name.

List page number

When the list of units or setting items consists of two or more pages, the current page number is shown here.

Information display

Displays the unit # or resident name of selected station, operation method, etc.



List of units


The list of units you searched for is shown here by their unit # and resident names. Nothing appears in the list when no corresponding unit is detected.

NOTE: The above display example may differ from the actual one.

1-4 Button operations


■ Multi-function buttons and icons

The functions to be performed by the multi-function buttons are displayed by icons just above the buttons.



Icons and their functions

Icons and their functions for each multi-function button are as follows.




	Icon	Function
①		Determines the choice.
		Turns the entrance light on (when light is installed in common area).
		Adjusts brightness.
		Turns off the emergency alarm.
②		Calls the selected unit.
		Transfers a call from entrance station to residential/tenant station.
		Adjusts call tone volume.
		Turns off overlay.
		Calls the preset entrance station directly.
		Deletes the selected item.

	Icon	Function
③	ABC	Changes the 10-key to the letter entry mode.
	123	Changes the 10-key to the number entry mode.
		Displays the search item list.
		Adjusts receive volume.
④		Restores the previous screen.
		Displays the setting screen.
		Cancels the choice.

■ How to enter numbers and letters by using the 10-key (0 to 9, *, #)

Use the 10-key in the number or letter entry mode.

The number and letter entry modes can be switched by pressing  (ABC/123).



How to enter letters

(e.g.) Entering "CATHY"

1. To enter "C", press  three times.
2. Press  once. (*1)
3. To enter "A", press  once.
4. To enter "T", press  once.
5. To enter "H", press  twice.
6. To enter "Y", press  three times.

(*1): This step is needed for entering different letters with the same key sequentially.

To enter a special character

- , : Press  once.
- : Press  twice.
- . : Press  three times.
- / : Press  four times.
- Space : Press  five times.
- Æ : Press  six times.
- Ø : Press  seven times.
- Å : Press  eight times.

* If you have entered a wrong letter, press  to return to standby mode.

2 RECEIVING A CALL




: Main building/section



: Tenant building/section

2-1 Receiving a call




When receiving a call, the call tone sounds and the number and name of the caller (station) are displayed in the screen.

The caller can be confirmed on the display.

A call from a residential/tenant station or another guard station

The unit # and station name



A call from an entrance station with a camera


The number and entrance name



The video at the entrance

A call from an entrance station without a camera

The number and entrance name



A call from a door station




The video at the door station

NOTE: When receiving a call from a door bell, nothing is displayed on the screen and answering is not possible.

Answering a call

To answer a call

1 Press  or lift handset.




OR



2 Begin communication with the caller.

* Lift handset at any time for privacy.

* While communicating with the caller, unlock the door or use the other features by pressing the following buttons.



To end communication

Press  or hang up handset.

Communication ends automatically after 3 minutes.

* Communication with a residential/tenant station in hands-free mode ends automatically after 1 minute in hands-free mode.

3 CALLING (from a tenant building)



3-1 How to search for a unit to call (from a tenant building)


The following methods are available in standby mode to search for a unit (residential/tenant station) or guard station to call.

- A** Searching by number
- B** Searching by name
- C** Using the search item list

* When nothing is displayed (black) on the screen, press any key other than *****, 0-9, **VIDEO CALL**, **LIST**, **IT SETTING**, **📶** or lift handset to enter standby mode.

* An entrance station can be searched for by using method **C** only.

Standby mode



- Searching by number (**UNIT BY NUMBER**) (→ 3-2)
- Searching by name (**UNIT BY NAME**) (→ 3-2)
- Searching a guard station from the guard station list (**GUARD STATION**) (→ 3-2)
- Searching an entrance station from the entrance station list (**ENTRANCE**) (→ 3-3)

Coverage of calling from a guard station in a tenant building

NOTE: Performance depends on the settings. If you cannot call even when ✓ is indicated, its setting is not configured.


				Incoming call							
				Same tenant building			Other tenant buildings			Main building	
											
Outgoing call	Tenant building	Guard st.	Calling/communication	Entrance st.	Guard st.	Residential/tenant st.	Entrance st.	Guard st.	Residential/tenant st.	Entrance st.	Guard st.
				✓	✓	✓	-	-	-	✓	✓

✓ : Possible — : Impossible

3-2 Calling a unit (residential/tenant station) or guard station



A Searching for a unit by number

- In standby mode, enter numbers using [0] to [9] on the 10-key to display the target unit # and resident name.



- * The list is displayed in order of unit #.
- * This station is not displayed.

- Select the target unit by pressing




- * Press  or  to turn the page of the list.

- Press  (),  or lift handset.

When the call is answered

Communication starts and " " is displayed.

- To end communication, press  or hang up handset.

NOTES:


- Communication will end automatically after approximately 3 minutes. Communication with a residential/tenant station in hands-free mode ends automatically after 1 minute in hands-free mode.
- If both unit # 111 and 1111 exist, the resident name for unit 111 will be displayed when 1, 1, 1 is entered, and the resident name for unit 1111 will be displayed if 1 is entered one more time.
- Stations can be set to be displayed in order by unit #. (The order starts with the lowest digit from 0 to 9 and then the order goes by letter.) In cases where unit # such as A101, A201, A901, A1001, and B101 exist, the order starts with the lowest digit and goes in the order A101, A201, A901, B101, A1001.

B Searching for a unit by name

- 1 In standby mode, press  or .

The search screen is displayed.

- 2 Select the target unit by pressing  or .



Unit # and resident names are displayed in alphabetical or numerical order.


* The arranging method differs depending on the setting.

- * Press  or  to turn the page of the list.
- * The list is displayed in order of either unit # or name.
- * This station is not displayed.

- 3 Press  (),  or lift handset.

When the call is answered

Communication starts and " " is displayed.

- 4 To end communication, press  or hang up handset.


NOTES:

- Communication will end automatically after approximately 3 minutes. Communication with a residential/tenant station in hands-free mode ends automatically after 1 minute in hands-free mode.
- Stations can be set to be displayed in order by unit #. (The order starts with the lowest digit from 0 to 9 and then the order goes by letter.) In cases where unit # such as A101, A201, A901, A1001, and B101 exist, the order starts with the lowest digit and goes in the order A101, A201, A901, B101, A1001.

C Searching for a unit by using the search item list




Press  ().

The search item list is displayed.



◆ Searching for a unit by unit


1 Select "UNIT BY NUMBER" by pressing  or



2 Press  () or  .

The "NUMBER SEARCH" screen is displayed.

3 Enter numbers using [0] to [9] on the 10-key to display the target unit # and resident name.



Unit # whose initial number matches the entered number are displayed in the list.

- * The list is displayed in order of unit #.
- * This station is not displayed.

4 Select the target unit by pressing



- * Press  or  to turn the page of the list.

5 Press  (),  or lift handset.


When the call is answered

Communication starts and "  " is displayed.

6 To end communication, press  or hang up handset.

◆ Searching for a unit by resident name


- 1** Select "UNIT BY NAME" by pressing  or .



- 2** Press  () or .

The "NAME SEARCH" screen is displayed.

- 3** Enter an alphabetical character using [0] to [9] on the 10-key to display the target resident name.




The unit # and resident names whose initial letter matches the entered letter are displayed in the list.
(e.g.) When "A" is entered, 301A, 1003ABC, ABC, etc. are displayed in the list.

* The arranging method differs depending on the setting.

- * The list is displayed in order of name.
- * This station is not displayed.

- 4** Select the target unit by pressing  or .



- * Press  or  to turn the page of the list.

- 5** Press  (),  or lift handset.


When the call is answered

Communication starts and " " is displayed.

- 6** To end communication, press  or hang up handset.

◆ Searching for a guard station from the guard station list


1 Select "GUARD STATION" by pressing  or



2 Press  () or .

The guard station list is displayed.

3 Select the target guard station by pressing  or




Guard station numbers and names are displayed in alphabetical or numerical order.
* The arranging method differs depending on the setting.

- * Press  or  to turn the page of the list.
- * The list is displayed in order of either station number or name.
- * This station is not displayed.

4 Press  (),  or lift handset.

When the call is answered

Communication starts and "  " is displayed.

5 To end communication, press  or hang up handset.

◆ Searching for an entrance station

(→ 3-3)


NOTES:

- Communication will end automatically after approximately 3 minutes. Communication with a residential/tenant station in hands-free mode ends automatically after 1 minute in hands-free mode.
- If both unit # 111 and 1111 exist, the resident name for unit 111 will be displayed when 1, 1, 1 is entered, and the resident name for unit 1111 will be displayed if 1 is entered one more time.
- Stations can be set to be displayed in order by unit #. (The order starts with the lowest digit from 0 to 9 and then the order goes by letter.) In cases where unit # such as A101, A201, A901, A1001, and B101 exist, the order starts with the lowest digit and goes in the order A101, A201, A901, B101, A1001.


3-3 Calling an entrance station

1 Press ().

The search item list is displayed.




2 Select "ENTRANCE" by pressing or .



3 Press () or .

The entrance station list is displayed.

4 Select the target entrance station by pressing or .



Entrance station numbers and names are displayed in alphabetical or numerical order.
* The arranging method differs depending on the setting.

* Press  or  to turn the page of the list.

* The list is displayed in order of either station number or name.

5 Press (), or lift handset.

Communication starts and "" is displayed.

6 To end communication, press or hang up handset.

◆ Direct calling an entrance station (only when is displayed in standby mode)

1 When is displayed, press ().

The preset entrance station is called, and then communication is enabled.

2 Talk hands-free or lift the handset.

3 To end communication, press or hang up handset.

NOTE: Communication will end automatically after approximately 3 minutes.

- ◆ Transferring video image taken by an entrance station camera or surveillance camera to a residential/tenant station (only when  is displayed in standby mode)

1 Press  (.

2 Select a residential/tenant station by one of the following methods **A** - **C**.

A Press  () and then  or  to select the target residential/tenant station.

B ① Enter a number by using the 10-key to display the list of residential/tenant stations that include the number.

② Press  or  to select the target residential/tenant station.


③ Press  () or .

C ① Press  and enter a letter by using the 10-key to display the list of residential/tenant stations that include the letter.

② Press  or  to select the target residential/tenant station.

③ Press  () or .

3 Press  (.

4 When the resident/tenant station answers and accepts the visitor, press  or hang up handset.

* Step 2 differs depending on the settings.

4 CALLING (from a main building)



4-1 How to select a unit to call (from a main building)

The following methods are available in standby mode to select a room (residential/tenant station) or guard station to call.

A Searching by number

- B**
- ① Searching for a unit in the list
 - ② Entering unit #
 - ③ Searching for a building in the list + entering unit #
 - ④ Entering a building # + unit #

* Any of ① to ④ are available by default.


C Using the search item list

* When nothing is displayed (black) on the screen, press any key other than , 0-9, , , , or lift handset to enter standby mode.

* To return to the standby screen, press .

* An entrance station can be searched for by using the method **C** only.

Standby mode



- Searching for a building in the list + entering unit # or Entering a building # + unit # (→ 4-2)
- Searching a guard station from the guard station list (**GUARD STATION**) (→ 4-2)
- Searching an entrance station from the entrance station list (**ENTRANCE**) (→ 4-3)

Coverage of calling from a guard station in a main building

NOTE: Performance depends on the settings. If you cannot call even when ✓ is indicated, its setting is not configured.


			Incoming call					
			Tenant building			Same main building		Other main buildings
			Entrance st.	Guard st.	Residential/tenant st.	Entrance st.	Guard st.	Entrance st. Guard st.
Outgoing call	Main building	Guard st. Calling/communication	✓	✓	✓	✓	✓	✓

✓ : Possible

4-2 Calling a room (residential/tenant station) or guard station


A Searching for a unit by number

- 1 In standby mode, enter numbers using [0] to [9] on the 10-key to display the target unit # and name.



- * The list is displayed in order of unit #.
- * This station is not displayed.

- 2 Select the target unit by pressing or .



- * Press or to turn the page of the list.

- 3 Press (), or lift handset.

When the call is answered

Communication starts and " " is displayed.

- 4 To end communication, press or hang up handset.

NOTES:


- Communication will end automatically after approximately 3 minutes. Communication with a residential/tenant station in hands-free mode ends automatically after 1 minute in hands-free mode.
- If both unit # 111 and 1111 exist, the resident name for unit 111 will be displayed when 1, 1, 1 is entered, and the resident name for unit 1111 will be displayed if 1 is entered one more time.
- Stations can be set to display in order by unit #. (The order starts with the lowest digit from 0 to 9 and then the order goes by letter.) In cases where unit # such as A101, A201, A901, A1001, and B101 exist, the order starts with the lowest digit and goes in the order A101, A201, A901, B101, A1001.

B-① Searching for a unit in the list

- 1 In standby mode, press  or .

The unit list is displayed.

- 2 Select the target unit, by pressing  or .




- * Press  or  to turn the page of the list.
- * The list is displayed in order of either unit # or name.
- * This station is not displayed.

- 3 Press  (),  or lift handset.

When the call is answered

Communication starts and " " is displayed.

- * Audio guidance will be heard depending on the settings.

- 4 To end communication, press  or hang up handset.

NOTE: Communication will end automatically after approximately 3 minutes. Communication with a residential/tenant station in hands-free mode ends automatically after 1 minute in hands-free mode.

B-② Entering unit

- 1 In standby mode, press  or .


"UNIT #" screen is displayed.

- 2 [When the target unit number is numerals only]
Enter the unit # using [0] to [9] on the 10-key.

[When the target unit number is alphanumeric]

- ① Press  (ABC).
- ② Enter the resident name using [0] to [9] on the 10-key.


* How to enter letters (→P. 21).



- 3 Press  (),  or lift handset.

When the call is answered

Communication starts and " " is displayed.

- 4 To end communication, press  or hang up handset.

NOTES:


- Communication will end automatically after approximately 3 minutes. Communication with a residential/tenant station in hands-free mode ends automatically after 1 minute in hands-free mode.
- If both unit # 111 and 1111 exist, the resident name for unit 111 will be displayed when 1, 1, 1 is entered, and the resident name for unit 1111 will be displayed if 1 is entered one more time.
- Stations can be set to display in order by unit #. (The order starts with the lowest digit from 0 to 9 and then the order goes by letter.) In cases where unit # such as A101, A201, A901, A1001, and B101 exist, the order starts with the lowest digit and goes in the order A101, A201, A901, B101, A1001.

B-③ Searching for a building in the list + entering unit

- 1 In standby mode, press  or .

The building list is displayed.

- 2 Select the target building by pressing  or .



* Press  or  to turn the page of the list.

* The list is displayed in order of either building number or name.


- 3 Press  () or .

"UNIT #" is displayed.

- 4 [When the target unit number is numerals only]
Enter the unit # using [0] to [9] on the 10-key.

[When the target unit number is alphanumeric]

- ① Press  (ABC).
② Enter the resident name using [0] to [9] on the 10-key.
* How to enter letters (→P. 21).



- 5 Press  (),  or lift handset.

When the call is answered

Communication starts and "  " is displayed.

- 6 To end communication, press  or hang up handset.

B-④ Entering a building # + unit


- 1 In standby mode, press  or .

"BUILDING #" screen is displayed.

- 2 [When the target building number is numerals only]
Enter the building number using [0] to [9] on the 10-key.

[When the target building number is alphanumeric]

- ① Press  (ABC).
② Enter the building name using [0] to [9] on the 10-key.
* How to enter letters (→P. 21).




- 3 Press  () or .

"UNIT #" is displayed.

- 4 [When the target unit number is numerals only]
Enter the unit # using [0] to [9] on the 10-key.

[When the target unit number is alphanumeric]

- ① Press  (ABC).
② Enter the resident name using [0] to [9] on the 10-key.
* How to enter letters (→P. 21).



- 5 Press  (),  or lift handset.

When the call is answered

Communication starts and "  " is displayed.

- 6 To end communication, press  or hang up handset.


C Searching for a unit by using the search item list

◆ Searching for a building in the list + entering unit

1 Press (LIST).

The search item list is displayed.

2 Select "BUILDING" by pressing or .



3 Press (LIGHT) or .

The building list is displayed.


4 Follow steps 2 to 6 of **B-③**.

◆ Entering a building # + unit

1 Press (LIST).

The search item list is displayed.

2 Select "BUILDING" by pressing or .



3 Press (LIGHT) or .

"BUILDING #" screen is displayed.

4 Follow steps 2 to 6 of **B-④**.

NOTES:


- Communication will end automatically after approximately 3 minutes. Communication with a residential/tenant station in hands-free mode ends automatically after 1 minute in hands-free mode.
- If both unit # 111 and 1111 exist, the resident name for unit 111 will be displayed when 1, 1, 1 is entered, and the resident name for unit 1111 will be displayed if 1 is entered one more time.
- Stations can be set to display in order by unit #. (The order starts with the lowest digit from 0 to 9 and then the order goes by letter.) In cases where unit # such as A101, A201, A901, A1001, and B101 exist, the order starts with the lowest digit and goes in the order A101, A201, A901, B101, A1001.

◆ Searching for a guard station from the guard station list

1 Press (≡).

The search item list is displayed.


2 Select "GUARD STATION" by pressing or .



3 Press (☉) or .

The building list is displayed.

4 Select the target building by pressing or .




Building numbers and names are displayed in alphabetical or numerical order.
* The arranging method differs depending on the setting.

- * Press  or  to turn the page of the list.
- * The list is displayed in order of either building number or name.

5 Press (☉) or .

The guard station list is displayed.

6 Select the target guard station by pressing or .



Guard station numbers and names are displayed in alphabetical or numerical order.
* The arranging method differs depending on the setting.

- * Press  or  to turn the page of the list.
- * The list is displayed in order of either station number or name.
- * This station is not displayed.

7 Press (☎), , or lift handset.

When the call is answered

Communication starts and "☎" is displayed.

8 To end communication, press or hang up handset.


NOTES:

- Communication will end automatically after approximately 3 minutes. Communication with a residential/tenant station in hands-free mode ends automatically after 1 minute in hands-free mode.
- If both unit # 111 and 1111 exist, the resident name for unit 111 will be displayed when 1, 1, 1 is entered, and the resident name for unit 1111 will be displayed if 1 is entered one more time.
- Stations can be set to display in order by unit #. (The order starts with the lowest digit from 0 to 9 and then the order goes by letter.) In cases where unit # such as A101, A201, A901, A1001, and B101 exist, the order starts with the lowest digit and goes in the order A101, A201, A901, B101, A1001.


4-3 Calling an entrance station

1 Press (≡).

The search item list is displayed.




2 Select "ENTRANCE" by pressing or .



3 Press (☉) or .

The building list is displayed.

4 Select the target building by pressing or .




Building numbers and names are displayed in alphabetical or numerical order.
* The arranging method differs depending on the setting.

- * Press  or  to turn the page of the list.
- * The list is displayed in order of either building number or name.

5 Press (☉) or .

The entrance station list is displayed.

6 Select the target entrance station.



Entrance station numbers and names are displayed in alphabetical or numerical order.
* The arranging method differs depending on the setting.

- * Press  or  to turn the page of the list.
- * The list is displayed in order of either station number or name.

7 Press (☎), or lift handset.

When the call is answered

Communication starts and "☎" is displayed.

- * Audio guidance will be heard depending on the settings.

8 To end communication, press or hang up handset.


NOTE: Communication will end automatically after approximately 3 minutes.

◆ **Direct calling an entrance station**
(only when is displayed in standby mode)

1 When  is displayed, press  (.

The preset entrance station is called, and then communication is enabled.

2 Talk hands-free or lift the handset.

3 To end communication, press  or hang up handset.

◆ **Transferring video image taken by an entrance station camera or surveillance camera to a residential/tenant station**
(only when is displayed in standby mode)

1 Press  (.

2 Select a residential/tenant station by one of the following methods **A** - **C**.

A Press  () and then  or  to select the target residential/tenant station.

B ① Enter a number by using the 10-key to display the list of residential/tenant stations that include the number.

② Press  or  to select the target residential/tenant station.


③ Press  () or .

C ① Press  and enter a letter by using the 10-key to display the list of residential/tenant stations that include the letter.

② Press  or  to select the target residential/tenant station.

③ Press  () or .

3 Press  (.

4 When the resident/tenant station answers and accepts the visitor, press  or hang up handset.

* Step 2 differs depending on the settings.

5 OPERATIONS DURING COMMUNICATION




5-1 Transferring a call

A call from an entrance station can be transferred to a residential/tenant station via a guard station

- 1 After the guard station is called from an entrance station, press  or lift handset to answer the call.

The number and name of calling entrance station




- 2 Press  (LIST) or enter the unit # by using [0] to [9] on the 10-key.

The list of residential/tenant stations is displayed.


- 3 Select the target residential/tenant station, then press  (VIDEO CALL).


The call is transferred to the residential/tenant station.

* "ON HOLD" is displayed on the entrance station and no sound is heard at the entrance station.

- 4 When the residential/tenant station answers and accepts the visitor, press  or hang up handset to establish communication between the entrance station and the residential/tenant station.

* When there is no answer from the residential/tenant station,

hang up handset and pick it up again, or press  and

then  to communicate with the entrance station.

* Step 2 differs depending on the settings.


Reference:

Reception mode (→ 8-2)

When there is a call from an entrance station to a residential/tenant station, it is first transferred to the guard station, so a call tone sounds and the video at the entrance station is displayed on the guard station.

5-2 Door release

- 1 While receiving a call or communicating with an entrance station, press .



Door release is activated at the entrance station.



* Audio guidance will be heard depending on the settings.

NOTES:


- For an all-in-one type entrance station:
The door lock is released for the preset time. If the preset release time is "0", it can be released while the button is pressed and held.
- For a modular type entrance station:
If the VR1 dial (inside the cover) is set to "M (Momentary)", it can be released while the button is pressed and held.
- Depending on the electric door release system that you use, door release may be active only while the door release button is pressed.

CAUTION:

Be sure to confirm the visitor securely before releasing the door if the entrance station has no camera.

5-3**Operating an optional device**

You can operate an optional device such as a light on this station.

1 Press .

The optional device turns on.

NOTES:

- A signal is sent to the device installed in the site. Please refer to the specifications of the device.
- If no optional device is installed, nothing happens when the button is pressed.


5-4 Viewing and adjusting video at an entrance station

You can view video at the target station when receiving a call from or communicating with an entrance station with a camera, or monitoring it. The video can be adjusted as desired by using the following functions.

* These functions are not available for a door station.

Switching Zoom/Wide

The display mode can be switched between zoom and wide by each press of .



Wide



Zoom




NOTES:

- The preset position of zoom image depends on the setting.
- When the display mode switches from wide to zoom, the zoom image is displayed at the preset position.
- Depending on the properties of the camera, the wide image may appear more distorted than the zoom image but this is not a malfunction.
- The image range of the zoom mode and wide mode differs. The edge of wide image will not be displayed with the zoom mode.

Pan & Tilt

When a zoom image is displayed, pressing , , , or , moves the image as shown below.




NOTES:

- At night, the object image may be blurred and less-visible when moving the image from right to left or up and down because illumination to the object is reduced. The same applies to a moving object.
- The pan & tilt function is not available for a video door station (JO-DV).

Adjusting screen view

If the video on the screen is difficult to see, you can adjust the screen view.

1 Press  when the video is difficult to see.



The backlight or night sensitivity is automatically adjusted.

- * The discrimination between day and night is performed automatically by this station.
- * The adjustment result may vary depending on the setting.

<Day>

<Night>



[Before adjustment]



[Before adjustment]



[After adjustment]



[After adjustment]

To restore the screen view before adjustment

Press  again.

The icon is cleared and the screen view before adjustment is restored.

NOTES:

- Pressing  at night may make visitors' faces easier to see, but may also make moving objects more difficult to see.
- The screen view adjusting function is not available for a video door station (JO-DV).

6 MONITORING


You can monitor an entrance station or door station.

- * When monitoring an entrance station or door station with a camera, you can view the video at the station and hear the sound.
- * The monitoring function is not available for an entrance station or door station without a camera.

Monitoring from a tenant building


- * For monitoring a door station, start from step 5.

1 In standby mode, press (LIST).



The search item list is displayed.


2 Select "ENTRANCE" by pressing or .



3 Press (LIGHT) or .

The entrance station list is displayed.

4 Select the target entrance station by pressing or .




Entrance station numbers and names are displayed in alphabetical or numerical order.
* The arranging method differs depending on the setting.

- * Press  or  to turn the page of the list.
- * The list is displayed in order of either station number or name.

5 Press .


The sound at the station is heard, and the video is displayed on the screen.



- * While monitoring, you can switch zoom/wide, pan & tilt, and adjust the screen view. (→ 5-4)

6 [To communicate with the station]

Press  or lift handset.



Communication with the station starts and " " is displayed.

- * Until this step, the monitored stations cannot hear any sound from the guard station.

7 To end monitoring or communication,

Press  or hang up handset.

NOTES:

- Monitoring ends automatically after about 30 seconds.
- Only entrance stations that can be selected by the guard station can be monitored.
- When no door station is installed, pressing  has no effect on the display.


Monitoring from a main building




* For monitoring a door station, start from step 7.

1 In standby mode, press (LIST).

The search item list is displayed.




2 Select "ENTRANCE" by pressing or .



3 Press (LIGHT) or .

The building list is displayed.

4 Select the target building.




Building numbers and names are displayed in alphabetical or numerical order.
* The arranging method differs depending on the setting.

- * Press or to turn the page of the list.
- * The list is displayed in order of either building number or name.

5 Press (LIGHT) or .

The entrance station list is displayed.

6 Select the target entrance station.




Entrance station numbers and names are displayed in alphabetical or numerical order.
* The arranging method differs depending on the setting.

- * Press or to turn the page of the list.
- * The list is displayed in order of either station number or name.

7 Press .


The sound at the station is heard, and the video is displayed on the screen.



- * While monitoring, you can switch zoom/wide, pan & tilt, and adjust the screen view. (→ 5-4)

8 [To communicate with the station]

Press or lift handset.



Communication with the entrance station side starts and "TALK" is displayed.

- * Until this step, the monitored stations cannot hear any sound from the guard station.

9 To end monitoring or communication,

Press or hang up handset.

NOTES:


- Monitoring ends automatically after about 30 seconds.
- Only entrance stations that can be selected by the guard station can be monitored.
- When no door station is installed, pressing has no effect on the display.

7 OTHER OPERATIONS




7-1 Checking for missed calls and calling back

If this station fails to respond to a call from a residential/tenant station, "MISSED CALLS" flashes continuously on the display in standby mode, and the status LED on the unit flashes. Check the missed calls and call back if necessary.



1 To check for missed calls, press in standby mode.



A record of missed calls is displayed.



When there are two or more missed calls, they are listed in reverse chronological order.

* On a guard station in a main section, building #, building names, and unit # are displayed.

2 To call back, select the target unit by pressing



Selected unit # and name

* On a guard station in a main section, the building #, building name, and unit # of the selected unit are displayed.

* Press or to turn the page of the list.

* Depending on the settings, only the unit # may be displayed.

3 Press (), or lift handset.

When the call is answered

Communication starts and "" is displayed.

4 To end communication,

press or hang up handset.

NOTES:


- The guard station can hold up to 20 missed calls.
- A record of answered calls is not kept.
- While a record of missed calls are displayed, this station cannot enter program mode.

7-2 Receiving an emergency call


When an emergency alarm switch is locked (or when a wire disconnection occurs), an alarm sounds and an "EMERGENCY" screen is displayed on this station. Check for the unit that sent the emergency call, and take the necessary action.

The unit # and name of the unit that sent the emergency call

* On a guard station in a main section, the building #, building name, and unit # are displayed.



1 To stop the alarm sound, press (🔊).




The alarm stops and a record of emergency calls is displayed.

- * On a guard station in a main section, building #, building names, and unit # are displayed.
- * When linked with multiple guard stations, stopping the alarm on any guard station will stop the alarm of all the guard stations.

2 To communicate with the unit, press (📞),

 or lift handset.



- * When there are two or more emergency calls, select one by pressing  or , then press  (📞), , or lift handset.

- * Press  or  to turn the page of the list.
- * The list is displayed in chronological order.


When the call is answered

Communication starts and "📞" is displayed.

3 To end communication, press or hang up handset.


To delete an emergency call from the list.

Select the target call by pressing  or , then press  (🗑️).



NOTE: While a record of emergency calls are displayed, this station cannot enter program mode.

◆ To display a record of emergency calls



Flashes when there is one or more unchecked emergency calls.

1 Press In standby mode.

A record of emergency calls is displayed.

To call a room that sent the emergency call

Select the target record by pressing  or , and then press  (),  or lift handset.

NOTE: The emergency alarm keeps flashing until the target record is deleted from the list. To delete it, select it on the list and

then press  ().

⚠ The residential/tenant station keeps sounding the alarm until the emergency alarm switch is restored at the room. In such case, the record of emergency calls cannot be deleted with the guard station. Unless the alarm is restored at the room, no call can be made from the guard station to the room. Please make sure the alarm is restored at the room.

NOTES:

- If an emergency call is already active on this station and this station is in communication, another guard station cannot interrupt. (An in-use tone will be heard from handset or speaker of the guard station.)
- The emergency alarm is given priority even when the system is in use. (Alarms can be activated at the same time for up to 5 units. This excludes GT-2C-L and GT-2C.)
- Emergency calls can be made while the system is in use.
- With the GT-2C-L and GT-2C, it is possible to transfer to a guard station even when there is a security alarm, depending on the settings.
- Even when the call tone volume is set to mute on the guard station, an alarm goes off at the maximum volume.


8 SETTING



8-1 Adjusting display brightness and volumes


Adjusting brightness of the display

- 1** In standby mode, press .




The SETTINGS screen is displayed.

- 2** Select "BRIGHTNESS" by pressing or .



- 3** Adjust the brightness by pressing or .



Adjustment can be made in 10 levels.

To return to the previous screen

Press ().

◆ To adjust brightness of the display while being called or in communication

- 1** While being called or in communication, press .

- 2** Press ().

- 3** Adjust the brightness by pressing or .


Adjusting the call tone volume

You can adjust the call tone volume at this station.


- 1** In standby mode, press .

The SETTINGS screen is displayed.

- 2** Select "TONE VOLUME" by pressing or .



- 3** Adjust the volume by pressing or .



Adjustment can be made in 4 levels.
("Mute" is available.)

* If set to "mute", the status LED will flash with long intervals. (→ **1-2**)

To return to the previous screen

Press ().

◆ To adjust the call tone volume while being called or in communication

- 1** While being called or in communication, press .

- 2** Press ().

- 3** Adjust the volume by pressing or .


Adjusting the receive volume

You can adjust the speaker volume of this station.


- 1 In standby mode, press .

The SETTINGS screen is displayed.

- 2 Select "RECEIVE VOLUME" by pressing  or



- 3 Adjust the volume by pressing  or .



Adjustment can be made in 3 levels.

To return to the previous screen

Press  ().

◆ To adjust the receive volume while being called or in communication

- 1 While being called or in communication,

press .

- 2 Press  ().

- 3 Adjust the volume by pressing  or .


8-2 Switching to reception mode

* This section describes the reception mode and how to configure it. Refer to steps 2 to 3 of "**5-1 Transferring a call**" for the operating procedure.


◆ What is reception mode?

In reception mode, all of the calls from entrance stations to residential/tenant stations are first transferred to guard stations. You can transfer the calls to residential/tenant stations after confirming they are not unwanted calls to the target residents.

[Normal mode]



[Reception mode]



NOTES:

- In a main building:
Calls from an entrance station are transferred to all guard stations in the building. The call tone sounds on all guard stations at the same time.
- In a tenant building:
Calls from an entrance station are transferred to all guard stations in the tenant building that are linked to the corresponding residential/tenant station. The call tone sounds on all guard stations at the same time.
- A call to a residential/tenant station that is not linked to a guard station will result in a call to the residential/tenant station directly.


◆ Switching this station between normal mode and reception mode

1 In standby mode, press .

The SETTINGS screen is displayed.


2 Select "ADVANCED SETTINGS"

by pressing or .




3 Select "RECEPTION MODE"

by pressing or .



4 Press () or .

5 Change reception mode to "ON" or "OFF" by pressing or .



ON: Reception mode is active.
OFF: Normal mode is active.

6 Press () or .

* When this station is in reception mode, the status LED will flash slowly. (→ **1-2**)

To return to the previous screen

Press ().

8-3 Switching to program mode

*** This operation is for Administrators and Managers only**

Entering a passcode is needed to switch this station into program mode. Ask the system installer for the passcode.


* A registered NFC-compliant IC card can be used instead of a passcode.

- 1 In standby mode, press  (or pass an registered NFC-compliant IC card over the NFC reader).**

The SETTINGS screen is displayed.


- 2 Select "ADVANCED SETTINGS"**

by pressing  or .



- 3 Select "PROGRAM MODE"**

by pressing  or .



- 4 Press  (◎) or .**

The passcode entry screen is displayed.

- 5 Enter the passcode.**

* Refer to the **GT SYSTEM SETTING MANUAL/Standard & Expanded System** for details about the settings.

NOTE: An NFC card can be used with either "Admin" or "Manager" authority. (→ **GT SYSTEM SETTING MANUAL/Standard & Expanded System**)

9 UPDATING RESIDENT INFORMATION

Refer to the **GT SYSTEM/SETTING MANUAL**.

- For single building system (→ **GT SYSTEM SETTING MANUAL/Standard & Expanded System**)
- For multi building system (→ **GT SYSTEM SETTING MANUAL/Multi Building System**)

When using an Android device

(→ **GT SYSTEM SETTING MANUAL/Aiphone GT Setup Tool for Android**)

Android is a trademark of Google Inc. in the United States and/or other countries.

FOR PROPER USE OF THIS STATION

1 TECHNICAL PRECAUTIONS

[For guard station only]

- The video image may distort when door release is activated. This is not a station malfunction.
- If a zoom/wide, pan/tilt, door release operation or brightness adjustment is performed during communication with the entrance station, noise will be produced at the entrance station. This is not a malfunction.

[General]

- If there is a system malfunction, contact a qualified technician for service.

• Cleaning:

Clean the units with a soft cloth dampened with a neutral household cleanser. Do not use any abrasive cleaner or cloth.

CAUTION: Do not use chemicals such as thinner or benzine. In addition, do not use a scrub brush, sandpaper, etc. Otherwise the unit surface could be damaged or discolored.

2 SPECIFICATIONS

◆ Entrance station (modular type)

Camera module (GT-VB)

Power source	Supplied from GT-VBC
Ambient temperature	- 10°C - +60°C (+14°F - +140°F)
Material	Self-extinguishing PC+ABS resin
Dimensions	108 (W) x 93 (H) x 55 (D) mm 4-1/4" (W) x 3-11/16" (H) x 2-3/16" (D)
Mass	Approx. 130g (0.29 lbs.)

Camera module panel (GT-VP)

Material	Zinc die cast
Color	Metallic beige
Dimensions	110 (W) x 95 (H) x 8 (D) mm 4-5/16" (W) x 3-3/4" (H) x 5/16" (D)
Mass	Approx. 150g (0.34 lbs.)

Audio module (GT-DB/GT-DB-V/GT-DB-VN)

Power source	Supplied from GT-BC
Ambient temperature	- 10°C - +60°C (+14°F - +140°F)
Material	Self-extinguishing ABS resin
Dimensions	108 (W) x 93 (H) x 53.4 (D) mm 4-1/4" (W) x 3-11/16" (H) x 2-1/8" (D)
Mass	GT-DB, GT-DB-V: Approx. 210g (0.47 lbs.) GT-DB-VN: Approx. 220g (0.49 lbs.)

Audio panel (GT-DBP)

Material	Zinc die cast
Color	Metallic beige
Dimensions	109.7 (W) x 94.9 (H) x 7.9 (D) mm 4-5/16" (W) x 3-3/4" (H) x 5/16" (D)
Mass	Approx. 95g (0.21 lbs.)

Name scrolling module (GT-NSB)

Power source	DC 24V supplied from a power supply unit (PS-2420 etc.)
Ambient temperature	- 10°C - +60°C (+14°F - +140°F)
Material	Self-extinguishing ABS resin
Dimensions	104.6 (W) x 88.3 (H) x 49.1 (D) mm 4-1/8" (W) x 3-1/2" (H) x 1-15/16" (D)
Mass	Approx. 140g (0.31 lbs.)

Name scrolling module panel (GT-NSP-L)

Material	Panel: Zinc die cast Window: Polycarbonate Bottom: Chrome plated zinc die cast
Color	Metallic beige
Dimensions	110 (W) x 96 (H) x 31.2 (D) mm 4-5/16" (W) x 3-3/4" (H) x 1-3/4" (D)
Mass	Approx. 200g (0.49 lbs.)

Call switch module (GT-SW)

Power source	Supplied from GT-DB/GT-DB-V/GT-DB-VN
Ambient temperature	- 10°C - +60°C (+14°F - +140°F)
Material	Self-extinguishing ABS plastic
Dimensions	90.5 (W) x 106 (H) x 42.5 (D) mm 3-9/16" (W) x 4-3/16" (H) x 1-11/16" (D)
Mass	Approx. 90g (0.199 lbs.)

1-call button panel (GF-1P)/2-call button panel (GF-2P)/ 3-call button panel (GF-3P)/4-call button panel (GF-4P)

Material	Panel: Zinc die cast Window: Polycarbonate Bottom: Chrome plated zinc die cast
Color	Metallic beige
Dimensions	110 (W) x 95.2 (H) x 15.8 (D) mm 4-5/16" (W) x 3-3/4" (H) x 5/8" (D)
Mass	GF-1P: Approx. 180g (0.40 lbs.) GF-2P: Approx. 190g (0.42 lbs.) GF-3P: Approx. 190g (0.42 lbs.) GF-4P: Approx. 200g (0.45 lbs.)

10-key module panel (GF-10KP)

Material	Panel: Zinc die cast Box: Chrome plated steel
Color	Metallic beige
Dimensions	110 (W) x 96.1 (H) x 38.2 (D) mm 4-5/16" (W) x 3-13/16" (H) x 15/16" (D)
Mass	Approx. 310g (0.69 lbs.)

Address module (GF-AD)

Power source	Supplied from GT-DB/GT-DB-V/GT-DB-VN
Ambient temperature	- 10°C - +60°C (+14°F - +140°F)
Material	Self-extinguishing ABS plastic
Dimensions	105.6 (W) x 88.3 (H) x 42.5 (D) mm 4-3/16" (W) x 3-1/2" (H) x 1-11/16" (D)
Mass	Approx. 90g (0.199 lbs.)

Address module panel (GF-AP)

Material	Panel: Zinc die cast Window: Polycarbonate
Color	Metallic beige
Dimensions	110 (W) x 95.2 (H) x 14.3 (D) mm 4-5/16" (W) x 3-3/4" (H) x 9/16" (D)
Mass	Approx. 150g (0.34 lbs.)

Blank panel (GF-BP)

Material	Zinc die cast
Color	Metallic beige
Dimensions	110 (W) x 95.2 (H) x 14.3 (D) mm 4-5/16" (W) x 3-3/4" (H) x 9/16" (D)
Mass	Approx. 190g (0.42 lbs.)

4-module front frame (GF-4F)/3-module front frame (GF-3F)/2-module front frame (GF-2F)

Material	Front frame: Zinc die cast Mounting bracket: Stainless steel
Color	Metallic beige
Dimensions	GF-2F: 135 (W) x 225 (H) x 16 (D) mm 5-5/16" (W) x 8-7/8" (H) x 5/8" (D) GF-3F: 135 (W) x 320 (H) x 16 (D) mm 5-5/16" (W) x 12-5/8" (H) x 5/8" (D) GF-4F: 135 (W) x 425 (H) x 16 (D) mm 5-5/16" (W) x 16-3/4" (H) x 5/8" (D)
Mass	GF-2F: Front frame: Approx. 400g (0.89 lbs.) Mounting bracket: Approx. 200g (0.45 lbs.) GF-3F: Front frame: Approx. 490g (1.09 lbs.) Mounting bracket: Approx. 250g (0.56 lbs.) GF-4F: Front frame: Approx. 660g (1.46 lbs.) Mounting bracket: Approx. 290g (0.64 lbs.)

◆ Entrance station (all-in-one type)

All-in-one entrance station (GT-DMB-N/GT-DMB-LVN)

Power source	DC 24V supplied from a power supply unit (PS-2420 etc.)
Ambient temperature	- 10°C - +60°C (+14°F - +140°F)
Material	Panel: Stainless steel Case: Self-extinguishing ABS resin
Color	Panel: Stainless steel with hairline finishing Case: Black
Dimensions	GT-DMB-N: 150 (W) x 320 (H) x 38.5 (D) mm 5-7/8" (W) x 12-5/8" (H) x 1-1/2" (D) GT-DMB-LVN: 150 (W) x 425 (H) x 38.5 (D) mm 5-7/8" (W) x 16-3/4" (H) x 1-1/2" (D)
Mass	GT-DMB-N: Approx. 1,200g (2.70 lbs) GT-DMB-LVN: Approx. 1,500g (3.3 lbs)

◆ Guard station

Guard station (GT-MKB-N)

Power source	DC 24V supplied from a power supply unit (PS-2420 etc.)
Communication	Open voice: Voice-actuated Handset: Voice-actuated/Full-duplex (only when the other side is talking using the handset of GT-MKB-N or GT-1D)
Ambient temperature	0 - 40°C (+32°F - +104°F)
Monitor	3.5 inch TFT color LCD
Mounting	Desktop use (with desktop stand) or surface wall-mount
Material	Self-extinguishing ABS resin
Color	Black
Dimensions	250 (W) x 189 (H) x 59 (D) mm 9-13/16" (W) x 7-7/16" (H) x 2-5/16" (D)
Mass	Approx. 820g (1.81 lbs) When used with desk stand: Approx. 1,200g (2.70 lbs)

◆ Door station

Vandal-resistant video door station (surface-mount) (JO-DV)

Power source	Supplied from guard station
Communication	Open voice hands-free communication
Ambient temperature	- 20°C - +60°C (- 4°F - +140°F)
Material	Front panel: Zinc die cast Main unit: Self-extinguishing
Color	Front panel: Silver
Dimensions	98 (W) x 173 (H) x 27 (D) mm 3-7/8" (W) x 6-13/16" (H) x 1-1/16" (D)
Mass	Approx. 650g (1.44 lbs.)
Remarks	IP54, IK08

3 SOFTWARE LICENSE

Notice regarding software

Use of the software installed on this product has received direct or indirect authorization from third parties.

(1) GPL/LGPL

This product includes software components subject to the GPL/LGPL.

Customers can obtain, modify, and re-distribute the source code of the software components according to the GPL/LGPL.

----- Hereafter referred to as the link -----

Open source code

This product includes software components subject to the GPL/LGPL, and customers can obtain, modify, and re-distribute the source code of the software components according to the GPL/LGPL. In addition, you can find details on the GPL/LGPL through the following links.

<http://www.gnu.org/licenses/gpl.html>

<http://www.gnu.org/licenses/lgpl.html>

Please confirm the following contents when downloading.

<<Please confirm>>

- According to GPL/LGPL, the source code of the software components is not guaranteed, including warranty on "merchantability" or "suitability for a particular purpose."
- The source code of the software components are according to the "status quo," and are provided based on the GPL/LGPL.
- Please understand that we cannot answer questions regarding the content of the source code of the software components.

BSD License

Copyright (c) 2017, AIPHONE CO.,LTD

All rights reserved.

Redistribution and use in source and binary forms, with or without modification, are permitted provided that the following conditions are met:

1. Redistributions of source code must retain the above copyright notice, this list of conditions and the following disclaimer.
2. Redistributions in binary form must reproduce the above copyright notice, this list of conditions and the following disclaimer in the documentation and/or other materials provided with the distribution.

THIS SOFTWARE IS PROVIDED BY THE COPYRIGHT HOLDERS AND CONTRIBUTORS "AS IS" AND ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE ARE DISCLAIMED. IN NO EVENT SHALL THE COPYRIGHT OWNER OR CONTRIBUTORS BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

The views and conclusions contained in the software and documentation are those of the authors and should not be interpreted as representing official policies, either expressed or implied, of the FreeBSD Project.

4 REGULATIONS

FCC

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

INDUSTRY CANADA

CAN ICES-3 (B)/NMB-3(B)

This device complies with Industry Canada's licence-exempt RSSs. Operation is subject to the following two conditions: (1) This device may not cause interference; and (2) This device must accept any interference, including interference that may cause undesired operation of the device.

RED

Hereby, Aiphone Co., Ltd. declares that the radio equipment type [GT-DB-VN, GT-DMB-N, GT-DMB-LVN, GT-MKB-N, GT-BCXB-N] is in compliance with Directive 2014/53/EU.

The full text of the EU declaration of conformity is available at the following internet address:

<http://www.aiphone.net/>

GT-MKB-N: 13.56MHz / Max. 20.0 dBm
 GT-DMB-N: 13.56MHz / Max. 20.0 dBm
 GT-DMB-LVN: 13.56MHz / Max. 20.0 dBm
 GT-DB-VN: 13.56MHz / Max. 20.0 dBm
 GT-BCXB-N: 13.56MHz / Max. 20.0 dBm

NCC

電信法第48條

低功率電波輻射性電機管理辦法

第十二條

經型式認證合格之低功率射頻電機，非經許可，公司、商號或使用者均不得擅自變更頻率、加大功率或變更原設計之特性及功能。

第十四條

低功率射頻電機之使用不得影響飛航安全及干擾合法通信；經發現有干擾現象時，應立即停用，並改善至無干擾時方得繼續使用。

前項合法通信，指依電信法規定作業之無線電通信。

低功率射頻電機須忍受合法通信或工業、科學及醫療用電波輻射性電機設備之干擾。

WEEE

The object area of  is the EU.

5 WARRANTY

Aiphone warrants its products to be free from defects of material and workmanship under normal use and service for a period of 2 years after delivery to the ultimate user and will repair free of charge or replace at no charge, should it become defective upon which examination shall disclose to be defective and under warranty. Aiphone reserves unto itself the sole right to make the final decision whether there is a defect in materials and/or workmanship; and whether or not the product is within the warranty. This warranty shall not apply to any Aiphone product which has been subject to misuse, neglect, accident, power surge, or to use in violation of instructions furnished, nor extended to units which have been repaired or altered outside of the factory. This warranty does not cover batteries or damage caused by batteries used in connection with the unit. This warranty covers bench repairs only, and any repairs must be made at the shop or place designated in writing by Aiphone. This warranty is limited to the standard specifications listed in the operation manual. This warranty does not cover any supplementary function of a third party product that is added by users or suppliers. Please note that any damage or other issues caused by failure of function or interconnection with Aiphone products is also not covered by this warranty. Aiphone will not be responsible for any costs incurred involving on site service calls. Aiphone will not provide compensation for any loss or damage incurred by the breakdown or malfunction of its products during use, or for any consequent inconvenience or losses that may result.

 **AIPHONE®**
Providing Peace of Mind
<http://www.aiphone.net/>