

CONTENTS QUICK START 4-6 WARNING OF LOW BATTERY POWER 6-7 MULTIPLE MICROPHONES UESD 8-9 RESTORE TO FACTORY SETTINGS 9-11 TROUBLESHOOTING 12-15 IMPORTANT NOTICE 16 WHAT'S IN THE BOX? 1 x Receiver 1 x Microphone 1 x User manual 1 x Microphone Anti-rolling Protection Ring CONTACT US Get Social: f Facebook page : http://bit.ly/FifinePage Contact Info: e E-mail : web@fifine.cc Please take a few minutes to watch the video before you start using the microphone. Operation video: http://bit.ly/k025problemsolving More product FAQs can be found on the website. Company Website: https://fifinemicrophone.com/ 1	WARRANTY Easily get a 2-year extended warranty with online registration within 90 days of purchase. 1. Input the link: https://fifinemicrophone.com/ 2. Please roll down to the bottom of the page, fill in E-mail address and submit it. TWO-YEAR WARRANTY REGISTRATION Enter your email address >CLICK TO START WARRANTY REGISTRATION 3. Check your inbox or spam to confirm subscription email. 4. After you click the button "Subscribe me to the list"and next "manage your preferences" to finish registration, tell us the model you are interested, we will send you the promo info/discount code and 2-year warranty code as well. PS : If you cannot update your preferences, just re-do the subscription process. 2	PRODUCT DISPLAY 1.Microphone ① ② ③ ④ ⑤ ① LED Screen(when frequency changed, the screen is only blinking and remain CH001) ② Slide on-off button ③ Battery Compartment ④ Channel Button (Every short press the channel button brings 1MHz frequency variation.) ⑤ Microphone Anti-rolling Protection Ring 2.Receiver ⑥ ⑦ ⑧ ⑨ ⑩ ⑥ Signal Indicator(The indicator is green when pairing with transmitter.It turns RED when paired successfully) 3	⑦ On-off Button ⑧ Antenna (Pull it out to extend the range of signal transmission and get better connection with transmitter.) ⑨ Quarter Inch Jack-plug(6.35mm) ⑩ Battery Compartment QUICK START 1. Insert batteries confirming to "+" and "-". Incorrect installation will result in not working or damaging the microphone set. • Install the 2AA batteries to microphone. • Insert 2 AAA batteries to the receiver. Make sure the battery polarity is correct installation and the door is closed completely. 4	2. Make sure to turn down the volume of your speaker before you plugging the receiver into the 1/4" (6.35mm) mic input of it.
--	---	---	--	---

Note :

We do not recommend to use with portable bluetooth speakers lower than 15 watt, such as JBL charge, Doss touch.

3. Turn the microphone and receiver on. When the light on receiver turn from green to RED, they successfully paired. The light stay on RED when it is functioning.

5

3. If you have multiple K025 and some of microphone set don't work. Please follow the below steps to reset the mic set exactly: 1. Turn OFF the mic and the receiver before the process. 2. Turn the microphone on,unscrew the microphone battery cover, long press channel button for three seconds to enter reset mode.

3. The Led screen is blinking if you do it right.(Note:The figures on Led display will not change)

Note: The receiver must remain OFF at this moment.

10

FCC Warning

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any inte rference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user’s authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interferenceto radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.