

ARG-N1中英文说明书

版本	变更记录
A0	初版发行

225*205mm 横向6折竖向3折，折后尺寸75*34mm

无线音频传输系统ARG-N1

使用说明书

AROMN

广东省惠州市惠阳区淡水街道合顺工业园A栋
执行标准：Q/AROMA 010

注意事项

避免放置的地方
在以下地方使用本产品可能会导致功能失败。
• 高温或过度潮湿的地方
• 灰尘过多的地方
• 剧烈震动的地方
• 与液体接近的地方
电池维护
当产品出现低电量警告时，请尽快对产品进行充电，内部锂电池不能在没有电量的情况下存放，将会严重影响电池使用寿命。
小心操作
为了避免损坏耳机，请不要太过力按按钮或其他操作部件。
清洁
如果产品表面脏了，请用干净的干布擦拭。不要使用液体清洁剂，譬如：苯、稀释剂或者其他含有有机化学成分的清洁剂。
防止异物进入产品内
不要把含有液体的物品放置在产品旁边。如果液体落入本产品，可能会引起火灾、火灾或触电。请不要让金属物品进入产品内部。
保留说明书
阅读完此说明书后，请保留以备后用。

主要特征

本无线音频传输系统由发射器ARG-N1 TRANSMITTER和接收器ARG-N1 RECEIVER两个设备组成，采用2.4G频率。
适用于多种设备
兼容各类电声乐器，并可大范围转动，对不同的接口位置均可使用。
一发多收、多发多收
内置7个频道，支持7套同时使用，且本产品也支持一个发射器配合多个接收器的方式使用。
线干燥、稳定、距离远
无线传输的音频信号未经任何压缩处理，具有优秀的抗干扰能力、瞬态响应能力、能最大限度地还原信号，极大的避免信号的失真和衰减。
超频降噪
采用50mA大容量锂电池，可连续使用12小时以上，无论舞台演出、比赛等均可练习，都很合适。

结构和功能

1. 发射端：6.35mm音频插头；接收端：6.35mm音频插头
2. 频道指示灯（7种颜色分别指示7个频道）
3. 电量指示灯
4. 按键：长按为电源开关，短按为频道切换（特别说明：见省电模式章节-电源指示灯）
5. Type-C充电接口

一收一收

开/关机
长按按键2秒，设备开/关机，圆形电量指示灯点亮。
配对
本产品为自动配对，电源即开即通，无需人工干预。在使用过程中，若连续接收失败，改变了接收器频道，可以多次短按发射端接收任意一端的按键，切换到电筒的频道指示灯，即会自动恢复连接；也可以将接收器关机后再开机也会自动恢复发射信号并恢复连接。
要换频道
在使用中（发射和接收已经连接），短按发射端发射按钮，即会自动切换发射与接收的频道。
注意：若未连接成功时，接收端频道指示灯会闪烁闪烁。
省电模式
本产品支持7套同时使用，使用前应分别切换每组的频道，使每组的频道指示灯分别显示不同的颜色。比如第一组发射和接收显示为红色，第二组发射和接收显示为蓝色，依次类推……，调整完成后才能连接至相应的设备。
注意：同一场合若有两个同频道的发射信号，接收端会出现同频啸叫，为避免这一情况，多套使用时请严格按照上述步骤操作。

规格

电压：3.7V/950mAh聚合物锂电池
频道数量：7
传输距离：15~30米
频率范围：20Hz~20KHz
动态范围：90dB
信噪比：>85dB
工作时长：约12小时
充电时间：60-90分钟
尺寸：37.2*73.2*26.5mm
重量：93g
附件：说明书、Type-C充电线

充电及电量指示

如需充电，请使用本产品配套的USB充电线连接产品和适配器（或充电宝、电脑USB接口）进行充电。

无线音频传输系统ARG-N1

使用说明书

AROMN

广东省惠州市惠阳区淡水街道合顺工业园A栋
执行标准：Q/AROMA 010

注意事项

避免放置的地方
在以下地方使用本产品可能会导致功能失败。
• 高温或过度潮湿的地方
• 灰尘过多的地方
• 剧烈震动的地方
• 与液体接近的地方
电池维护
当产品出现低电量警告时，请尽快对产品进行充电，内部锂电池不能在没有电量的情况下存放，将会严重影响电池使用寿命。
小心操作
为了避免损坏耳机，请不要太过力按按钮或其他操作部件。
清洁
如果产品表面脏了，请用干净的干布擦拭。不要使用液体清洁剂，譬如：苯、稀释剂或者其他含有有机化学成分的清洁剂。
防止异物进入产品内
不要把含有液体的物品放置在产品旁边。如果液体落入本产品，可能会引起火灾、火灾或触电。请不要让金属物品进入产品内部。
保留说明书
阅读完此说明书后，请保留以备后用。

主要特征

本无线音频传输系统由发射器ARG-N1 TRANSMITTER和接收器ARG-N1 RECEIVER两个设备组成，采用2.4G频率。
适用于多种设备
兼容各类电声乐器，并可大范围转动，对不同的接口位置均可使用。
一发多收、多发多收
内置7个频道，支持7套同时使用，且本产品也支持一个发射器配合多个接收器的方式使用。
线干燥、稳定、距离远
无线传输的音频信号未经任何压缩处理，具有优秀的抗干扰能力、瞬态响应能力、能最大限度地还原信号，极大的避免信号的失真和衰减。
超频降噪
采用50mA大容量锂电池，可连续使用12小时以上，无论舞台演出、比赛等均可练习，都很合适。

结构和功能

1. 发射端：6.35mm音频插头；接收端：6.35mm音频插头
2. 频道指示灯（7种颜色分别指示7个频道）
3. 电量指示灯
4. 按键：长按为电源开关，短按为频道切换（特别说明：见省电模式章节-电源指示灯）
5. Type-C充电接口

一收一收

开/关机
长按按键2秒，设备开/关机，圆形电量指示灯点亮。
配对
本产品为自动配对，电源即开即通，无需人工干预。在使用过程中，若连续接收失败，改变了接收器频道，可以多次短按发射端接收任意一端的按键，切换到电筒的频道指示灯，即会自动恢复连接；也可以将接收器关机后再开机也会自动恢复发射信号并恢复连接。
要换频道
在使用中（发射和接收已经连接），短按发射端发射按钮，即会自动切换发射与接收的频道。
注意：若未连接成功时，接收端频道指示灯会闪烁闪烁。
省电模式
本产品支持7套同时使用，使用前应分别切换每组的频道，使每组的频道指示灯分别显示不同的颜色。比如第一组发射和接收显示为红色，第二组发射和接收显示为蓝色，依次类推……，调整完成后才能连接至相应的设备。
注意：同一场合若有两个同频道的发射信号，接收端会出现同频啸叫，为避免这一情况，多套使用时请严格按照上述步骤操作。

规格

电压：3.7V/950mAh聚合物锂电池
频道数量：7
传输距离：15~30米
频率范围：20Hz~20KHz
动态范围：90dB
信噪比：>85dB
工作时长：约12小时
充电时间：60-90分钟
尺寸：37.2*73.2*26.5mm
重量：93g
附件：说明书、Type-C充电线

充电及电量指示

如需充电，请使用本产品配套的USB充电线连接产品和适配器（或充电宝、电脑USB接口）进行充电。

WIRELESS AUDIO TRANSMISSION
ARG-N1

OPERATION MANUAL

AROMN

© 2023 Aroma Music Co., Ltd.

PRECATIONS

Location
Using the product in the following locations could result in a malfunction:
• Locations of extreme temperature or humidity
• Excessively dusty or dirty locations
• Locations of excessive vibration
• Locations near to magnetic
Battery maintenance
When there is a low battery alarm, please charge the product as soon as possible. The internal lithium battery cannot be stored without power, which will seriously affect the lifespan of battery.
Handling
To avoid breakage, please do not apply excessive force to the switch buttons or other control.
Care
If the exterior becomes dirty, wipe it with a clean and dry cloth. Do not apply liquid cleaners such as benzene, diluter, or other cleaners that contain flammable compounds.
Keep other things out of your product
Do not set any container with liquid in it close to this machine, if liquid gets into the machine, it may cause a breakdown, fire, or electrical shock. Be careful not to let metal objects get into the equipment.
Keep this owner's manual
After reading this manual, please keep it for later reference.

MAIN FEATURES

This wireless transmission system consists of two parts ARG-N1 TRANSMITTER and ARG-N1 RECEIVER, adopt 2.4GHz technology.
Suitable for multiple instruments
Compatible with all kinds of electro-acoustic instruments and can rotate in a large range, and can be used for different interface positions.
One transmitter to different receivers or more transmitters to more receivers
7 channels which allows 7 sets working at same time. And also workable to use as one transmitter to more receivers.
Anti-interference, stable, long distance
Wireless audio signals transmitted without any compression have excellent interference resistance and obstacle resistance. Object penetration capability allows for high-quality signal reconstruction, significantly preventing signal distortion and attenuation.
Super endurance
Adopt 950mA big capacity Li battery, able to use 12 hours continuously.

ONE TRANSMITTER TO ONE RECEIVER

ON/OFF
Long press button for 2 seconds, the power indicator light up.
Match
When turn on the device, it will automatically match. If press the button by mistake while using device, you can short press the transmitter or receiver button to switch and match the same light to Receiver Or turn off the transmitter and turn on again to match automatically.
Switch channel
While using the device (transmitter and receiver already matched) just need to short press the button to switch channels.
Notice: The indicator of transmitter will flash if not match successfully.

MORE TRANSMITTERS TO MORE RECEIVERS

This device support 7 sets working at same time, before usage please make sure every channel light match to each other, for instance one transmitter and receiver indicator color is both red, another set both blue etc.
Notice: The receiver will occur howround if use same frequency at same place, to avoid this situation, please follow above instruction when use more sets together.

CHARGING AND POWER INDICATION

Please use the USB cable which packed (or powerbank, computer USB jack) for charging.
Charging
Power indicator flash
Power indicator keep lighting when full charged
Working
Power=60%: indicator keep lighting
Power=30%~60%: indicator slowly flash (1s a time)
Power=5%~30%: indicator quickly flash (0.5s a time)
Power<5%: indicator vibration flash 1s to turn off automatically.

SAVING MODE

Transmitter will turn off automatically if no signal input for 30 minutes.
Receiver will turn off automatically if no connection with transmitter for 30 minutes.
Power indicator will display 30 sec when turn on, then the power is turned off and the power indicator is automatically awakened every 5 minutes, and the display time is 30 sec.
Power indicator will keep displaying while power below 30% to remind charging. When the power indicator goes out, the first short press of the power button is to wake up the power indicator, and the second short press is to switch channels.

SPECIFICATIONS

Power: 3.7V/950mAh Lithium polymer battery
Channel: 7
Distance: 15~30m
Frequency range: 20Hz~20KHz
Dynamic range: 90dB
Signal-to-noise ratio: >85dB
Working time: around 12 hours
Charging time: around 2 hours
Dimension: 37.2*73.2*26.5mm
Weight: 93g
Accessories: user manual, Type-C USB cable

Tips: When in use, put it vertically according to the receiver diagram to get the best transmission distance.

ONE TRANSMITTER TO MORE RECEIVERS

To use one transmitter to more receivers, please turn on the transmitter and receivers, it will be automatically match or switch transmitter channels to match same color receiver.

PARTS AND FUNCTIONS

1. 6.35mm audio jack(RECEIVER)
6.35mm audio jack(TRANSMITTER)
2. Channel indicator (7 colors for 7 channels)
3. Power indicator
4. Press and hold to turn ON/OFF, short press to switch channel (Special note: See POWER SAVING mode-power indicator.)
5. Type-C power charging port

受控文件

● 产品料号

1.5.03.0313000

● 版本号

A0

● 物料名称

ARG-N1中英文说明书

● 日期

20250630

● 材质/工艺

70g书写纸黑色印刷

● 设计师

邓丽颖

● 审核人

李承龙

● 核准人

易华

● 文件编号

AROMA-RD-BZ-02