


Smart Video Doorbell

Quick Start Guideline

* Please read it carefully before using the product, and safeguarding

Packing List

After opening the package, please make sure the doorbell (hereinafter referred to as the "Equipment") is in good condition. Verify parts below is complete.




Appearance Introduction



- IR LED** The ambient light is not enough, to enable the infrared light, increase the environmental brightness
- Light Sensor** Used to collect environmental brightness value, when the intensity of illumination is less than 2 Lux, enable the IR LED
- MIC** Audio capture
- Button** The doorbell button
- PIR** When human body movement in front of the equipment, the equipment could made the notification to your mobile phone.
- Lens** Video image capture
- Indicator Light** Blinking blue: configuration status. Long red light: failed to connect with. Blue light is on: the device is connected successfully. Red and blue light together: The device is connected to WiFi


Speaker Make a sound of the equipment, and voice intercom



- AC Input** Power is supplied to the equipment by installing the AC input supply hole on the mounting bracket.
- Reset Button** Equipment working status, long press 5 seconds to restore factory settings
- Battery Compartment** Mounting 18650 specification battery.
- Fixed Hole** Fit the support on the wall with the mounting screws for the mounting kit.
- AC Input Hole** The power supply of the equipment can be supplied by connecting the hole and the AC power supply on the wall.
- Stuck Hole** Mounting the equipment onto the bracket.
- Security Screw Hole** Mounting the security screw on the fittings to prevent the equipment from being removed

Installation Guide

As shown in the figure, take back



Setup Device

Thank you for choosing our product! Please follow the below instruction to setup and using your doorbell device.

1. Downloading and installing the App

Open the App Store (for iOS) or the Google Play Store (for Android) on your mobile devices. Search for "XSH cam" or scan the following QR Code to download and install to your device.



2. Setting up the App

Before you begin...

> Make sure the "XSH cam" app is installed to your device.

> Make sure that your device is connected to a 2.4GHz Wi-Fi network, NOT a 5GHz network.

Add the camera

1.) Launch the "XSH cam" app on your device and tap Add a Camera.

Setup the Camera


2.) Select Setup Camera. Note: If you have multiple cameras, only setup one at a time.



3.) Before setup, make sure the device is in configuration -- with a voice prompt: "The camera is now ready to begin pairing".



4.) If you didn't hear the voice prompt, press and hold the reset button for 5 seconds. Release after the LED indicator turned off, and the device will restart to configure automatically.



Note: In crowded environment, it is recommended to close or set the device to low sensitivity to reduce device arousal and call times to extend battery life.

4. Note for using

- 1.) The device is powered by rechargeable lithium batteries. With fully charged, the battery life approx be six months. The mobile device APP will be prompted while the battery voltage is low. Please charge the device after received the reminder.
- 2.) Keep the camera in range of your router. Make sure to pick a place within range of your network. Thick or insulated doors can greatly reduce the strength of your Wi-Fi signal even if your router is close to it, so you should try strengthening signal before you mount your camera.
- 3.) The device is a low power consumption intelligent products, can support remote view up from the APP. PIR function detection, press doorbell wake up. The device will be works for 30 seconds after wake up then be in the resting state automatically and wait to next waking up.

Technical Specification

Resolution	1280*720
Field of Angle View	160°
IR LED	6*550nm
IR LED	6*550nm
Wi-Fi	IEEE 802.11 b/g/n
Audio	Two-way talk with noise cancellation
Recording	Device SD Card recording(20 seconds)
Storage	8G/16G/32G
Battery	Two 18650 specification batteries
Monitoring	Device Button, Motion Detection, Remote Live View
Notifications	Push Notifications within 1 second
Device Wakeup	Within 600 ms
Power Consumption	Power Consumption Standby 200 uA, Working 125 mA

① Two 18650 specification batteries (total 6800 mAh), work regularly for 6 months.

Ding-dong Pairing (Needs to be purchased separately)

Code Pairing: 1. Short press the button of Ding-dong responder, indicator light is always on. 2. Press the button of doorbell to make the code successful.

Reset: 1. Press the button of Ding-dong for 5 seconds.

Number of connections: 1. Ding-dong can connect with 12 Doorbells.

1. Doorbell can connect with unlimited amount of Ding-dongs.

Function Introduction

- Two 18650 specification batteries work regularly for 6 months.
- Million HD pixels collocated with wide-angle lens.
- Support mobile phone remote live wakeup device within 1 second.
- 2.4G Wi-Fi connection.
- High quality two-way talk with noise cancellation.
- Support PIR motion detection when someone hovers at the door, immediately alerts push notifications to the mobile phone.
- Day and night mode automatic switching, whether day or night, the image is clearly visible, provide you a safe environment.

1. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) This device must accept any interference received, including interference that may cause undesired operation.

2. Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide

reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

The distance between user and products should be no less than 20cm.