一触多发

光亮随处可达

I5i智能无线同步子母灯
使用说明书

I5i智能无线同步子母灯以多功能床头灯为母灯、可充电的小夜灯为子灯（可布置于室内任何位置），母灯通过一键式触摸控制多种亮度和彩灯颜色、在橙色灯光时进入助眠模式，子灯根据母灯的亮灯模式　　开启（母灯在夜灯模式下）和关闭（母灯切换至其它模式时），其亮度根据自己需求通过子灯的按键自行设定。在使用前需进行配对设置，一个母灯可与无数个子灯配对，一个子灯可与最多10个母灯配对。配对后的母灯和子灯才能形成同步智能控制。

一、基本参数

1、母灯（床头灯）

A.灯光

白灯：四种亮度模式：小夜灯（80LM）、陪伴夜灯（160LM）、手机阅读灯（260LM）书报阅读灯（700LM）
色温(颜色)：～3000K（暖白）
显色指数(Ra)：≥95

灯光特点：无频闪、弱蓝光、接近自然光光谱、护眼

彩灯：橙色（助眠）、多彩（256X256X256种颜色）渐变模式（短触可定住所需要的彩色）

B. 对外充电
标准USB对外充电接口、输出5V⎓2A

C. 助眠
在橙色灯光模式助眠30分钟后　　关闭

D.尺寸及重量
尺寸：95mmX95mmX218mm，重量：400g

2、子灯（小夜灯）

A.灯光：
五种亮度:3LM、9LM、15LM、21LM、30LM可　　设定
色温(CCT)：～3000K（暖白）
显色指数(Ra): ≥80

B.聚合物锂电池容量及使用时间:
500mAh 满电最高亮度可持续7小时、最低亮度可持续60小时，纯待机时间为3个月、正常使用（按每天开灯15分钟中等亮度计算）超过1个月。

C.尺寸及重量：尺寸：85mmX85mmX38mm
重量：110g

D.固定方式: 磁吸、挂钉、挂绳



3、电源输入
母灯： AC 85V-260V　0-0.1A（220V）0-0.2A（110V）
子灯： DC 5V 1A

4、无线控制距离
室内≤30M　室外≤50M

5、包装内含：
母灯1台、子灯1个，说明书1份，充电线1条, Φ25mmX1mm不锈铁片1个。

不锈铁片　　使用说明书　　USB充电线

二、使用说明

1、配对

第一步：在子灯关灯状态下用手指按住子灯底部的按键，灯闪烁时，松开按键，子灯处于等待配对状态。

第二步：将母灯（床头灯）电源插头插入市电（交流）插座，如原来就插入市电插座的一定要拔出（断电），等一分钟以上放电完成后重新插入插座；用手指触摸住母灯的顶部触摸键（金属部分），母灯灯光闪烁时（约5秒）手指离开触摸键，

母灯处于可与子灯配对的状态，配对成功后的子灯常亮，长触母灯顶部触摸键(约3秒)闪烁的灯光熄灭，退出配对。

2、使用

A. 母灯（床头灯）

灯光控制：上电后长触顶部触摸键（约3秒）实现开、关灯切换，在开灯状态下点触其触摸键实现：小夜灯→陪伴夜灯→手机阅读灯→书报阅读灯→助眠灯（橙色）→七彩灯　　变换→彩灯颜色定住→小夜灯模式循环切换。

助　　眠：在助眠灯(橙色)模式下，30分钟后会自动关闭，其它模式下无　　关闭功能。

对外充电：在母灯上电状态下将需要充电的设备(手机、Pad等)通过USB线接入母灯背部USB口即可实现对外充电(输出为DC 5V-2A)。

B. 子灯（小夜灯）

母灯同步控制：母灯在小夜灯模式下停住3秒以上时，会同步开启与之配对成功过的所有子灯，子灯亮度为上一次

亮起的亮度（通过其底部按键可调）。当该母灯从小夜灯模式切换至其它模式或关灯时子灯全部关掉。

子灯单独控制：用手触摸顶部触摸键实现开、关灯切换。在开灯状态下点触其底部按键实现：亮度1（最低）→亮度2→亮度3→亮度4→亮度5（最高）循环切换，亮度具有记忆功能；子灯不能同步母灯。

充　　电：使用普通手机充电器(适配器5V)换成随机配的充电线即可，充电时灯内红色指示灯亮，充满后红灯灭、绿灯亮，充满电时间约1小时。

3. 使用注意事项

A.只有配对成功过的母灯和子灯才能同步控制。
B.配对和同步控制时，母灯和子灯的距离必须在无线控制范围内。
C. 开启母灯不需要同步开子灯时，在3秒之内尽快将母灯切换至其它模式，这时既不会同步开启子灯也不会关闭子灯。
D. 用手（手指、手掌均可）触摸子、母灯的触摸键时，皮肤一定要接触到顶部触摸键。
E. 多个母灯都在同步子灯时，按优先原则。

三 包 凭 证

客户姓名：……　联系电话：……
客户地址：……
产品型号：……　购机日期：……
购机商店：……
商店地址：……
发票号码：……

I5i Sync Bedside lamp User Manual

Thank you for choosing I5i Sync bedside lamp.

Description

I5i smart wireless sync light is a set of wireless connected lamps, a multifunctional bedside lamp as the master lamp, and a rechargeable night lamp as the servant lamp. By touching the power button on the top of the master lamp, users can adjust the brightness and RGB color. Switching into the orange lighting mode so that the Aid-sleeping would be activated. User can sync control the servant lamp by switch into low brightness of the bedside lamp, and all the servant lamps could be sync light off while the master lamp switch into other brightness mode except the low brightness. The servant lamp has 5 brightness levels of choice, it also has memory setting of brightness, and keep in mind that the brightness of servant lamp can only be adjusted by its own button but not by the master lamp. A master lamp could sync control any servants lamp within an effective control rang. (the servant lamp will be light up/off as the master lamp is turned on/off). One master lamp can pair with unlimited servant lamps, but one servant lamp could be sync control with 10 pieces master lamps at most. The sync control between master lamp and servant lamp only works under the situation that they've been paired successfully ahead of time.

Specification

1.Master lamp/Bedside lamp

A. **Brightness Level:** 4 brightness levels
a. low brightness　　80LM
b. Mid brightness　　160LM
c. High brightness　　260LM
d. Read lighting　　700LM

B. **Color temperature:**3000k warm white

C. **CRI:**≥95, no glare lights, weak blue light , flicker free, does not hurt the eyes.

D. **RGB lights:** Orange lights (aid-sleeping mode), 256x256x256 kinds of color.

E. **Output port:** 5V ,2A.

F. **Aid-sleeping mode:** In the aid-sleeping mode/orange lights, the device will be　　off after 30mins.

G. **Size and weight:** 95x95x218mm,500g.

2. Servant lamp/Night lamp

A. **Brightness Level:** 3LM,9LM,15LM,21LM,30LM.

B. **Color temperature:**3000k warm white

C. **CRI:** ≥80

D. **Polymer lithium battery**: 500mAh.

E. **Play time:** 7 hours with maximum brightness and 60 hours with low brightness. Lamp stand by time is 3 months. Standby mode could last around one month if the night lamp is on less than 15 minutes every day.

F .Size and weight:85x85x38mm,110g.

G. Hanging method: magnet, nails, or string.



3.Power Supply
Master lamp/bedside lamp: AC 85V-260V
0-0.1A（220V）0-0.2A（110V）
Servant lamp/Night lamp: DC 5V 1A

4.Wireless connected: Indoor≤30M,Outdoor≤50M
5.Packing:1x master lamp,1x servant lamp, 1x 1 M USB cable, 1x ⌀25mm mental,1x User Manual.

Iron sticker　　user manual　　USB charging cable

Operation

1.Pairing mode

a. Make sure the servant lamp is off, then hold the button of the bottom until it keeps flashing. The servant lamp is now ready for pairing.

b. Make sure the master lamp has been cut off the power for more than 1 minutes, then turn on the master lamp by long press the power button (the top metal) for 5 seconds. The master lamp would start flashing, then stop pressing the button, which means it is ready for pairing. The servant lamp

would turn into solid light if it has been paired with the master lamp successfully. Then long touch the power button for 3 seconds so that the master lamp will be off ,finishing the pairing process .

2.Lighting

A. Master lamp/Bedside lamp

How to control the lights?
Charge the master lamp and hold the power button for 3 seconds, then the lamp would light up. To turn off the lamp, just touch the power button for 3 seconds. To change brightness, just short touch the power button to select brightness level. The light will switch to low brightness, medium brightness, high brightness, reading lights, Aid-sleeping lights, and breathing RGB lights accordingly. Under the breathing RGB lights mode, the lights　　cycle has an extensive selection of colors, to stay in a certain color, just short touch the power button again.

Aid sleeping mode: Under the aid-sleeping mode/orange lighting mode, the device will be　　off after 30mins. Noticed that auto-off would not work under other lighting modes.

Output port: When the devices is in energizing status, user could charge the phones or tablets by connecting the output port. Output port (DC 5V-2A)

B. Servant lamp/Night lamp

How to control the servant lamp?
Short touch the power button on the top of the servant lamp to light up/off, singly click the button on the bottom of the servant lamp to change the brightness. The brightness would switch from level 1 to level5(the highest brightness). The servant lamp has the memory setting of brightness mode.

C. Sync control servant lamp

Light up the master lamp and stay in the low brightness mode for 3 seconds, then all the servant lamps which have been paired with the master lamp before would light up after three seconds . All the servant lamps will be turned off once the master lamp turns into other brightness mode except of low brightness.

D. Input: Using normal adaptor 5V with the charging cable to charge the night lamp. Red indicator light means charging successfully. When the light changes to green means it is fully charged, and it takes approximately one hour to fully charge.

3.Warning

A. The servant lamp must be paired with master lamp firstly, then the servant lamp can be sync control by the master lamp.

B. The Sync function of the servant lamp only work if the master lamp stays at low brightness for more than 3 seconds.

C. The sync control range is around 50 meters, all the operation only works within an effective control range.

D. If don't need to light up the servant lamp, please don't stay at the low brightness of the master lamp for more than 3 seconds.

E. Please use finger or palm to touch the power button to control the lamp.

F. When one servant lamp has been paired with more than one master lamps, all the sync operation would follow priority principle. (The servant lamp will be turned on by the master lamp that is turned on first, and the servant lamp will be turned off by the master lamp that is turned off first. These two master lamps could be two different lamps as long as they've been paired with the servant lamp.)

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.
If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
-- Reorient or relocate the receiving antenna.
-- Increase the separation between the equipment and receiver.
-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
-- Consult the dealer or an experienced radio/TV technician for help.

Warning: changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment