

技术要求：

1.材质:双铜128G

2.规格:单页尺寸85x110mm

展开尺寸850x110mm

3.性能要求:风琴折,10P9折,双面印刷

文字色号:PANTONE 431C

正面

Multi-Function Wireless Charger 无线充电 时钟 小夜灯 充电座 PRODUCT INSTRUCTIONS 无线充电 时钟 小夜灯 充电座 Thank you so much for choosing our product. please read the manual carefully before using the product.		FEATURES - Simple and exquisite shape. - LED mood lamp. - Alarm clock. - Wireless fast charger. - Charging distance ≤8mm. APPEARANCE FEATURES ① Mobile phone wireless charging area ② Screen display area ③ PP lampshade ④ Light adjustment touch switch ⑤ Mobile phone wires charging interface ⑥ Smart watch charging area ⑦ Function button ⑧ Type-C/USB output port ⑨ Charging indicator ⑩ Type-C input port ⑪ Storage box Type-C input port	OPERATION METHOD 1. Connect the USB port of the USB data cable to the power adapter and the Type-C port of the product. 2. After the product is powered on, the product indicator light is always red, and the required wireless charging device is placed in the charging indication area of this product and enter the charging state. 3. The product can also be used with an external cable. After the product is powered on, connect Type-C/USB to the product. Connect the other port to the mobile phone and enter the charging state. Type-C/USB interface USB data cable Lightning Type-C	STORAGE BOX INSTALLATION 1. The charging storage box has one interface, and the two adapters are Type-C interface and lightning connector. 2. The storage box can be charged separately and can be used outdoors. Connect the USB port of the USB data cable to the power adapter and the Type-C port to the product. Place the required device in the charging indicator area of the product to enter the charging state. Type-C Lightning Installation completed diagram	NIGHT LIGHT FUNCTION - Click to turn on the light to switch warm white/cool white/positive white/off. - Turn on the lights in sequence. - In any color temperature light mode, long touch to adjust the light brightness. FUNCTION BUTTON Screen Brightness Alarm Clock 2 Decrease/Downward Alarm Clock 1 Increase/Upward Mode	CLOCK SETTINGS In normal clock display mode: - Short press [] in the clock display area, the clock starts to flash, enter the clock Set status. Short press [] to increase the number, short press [] to decrease the number. - Short press [] again to switch minutes, the minutes will start flashing, and 99 minutes will be entered Set status. - Short press [] to increase the number, short press [] to decrease the number. - Long press [] to save the current settings and return to the time display. HOW TO SET AN ALARM In normal clock display mode: alarm setting method 1 - Long press [] in the clock display area, the alarm 1 [] icon and the clock start flashing and enters the alarm 1 clock setting state. Short press [] to increase the number, short press [] to decrease the number. - Short press [] again to switch minutes, the minutes will start to flash and enter the minute setting state. Short press [] to increase the number, short press [] to decrease the number. - The setting method of Alarm 2 is the same as Alarm 1. - Click display area alarm icon [], the alarm icon is displayed for which alarm is effective. In normal clock display mode: alarm setting method 2 - Short press [] 4 times, the clock display area, the alarm icon [] and the clock are at the same time flashing, enter the alarm clock setting state. Short press [] to increase the number, short press [] to decrease the number. - Short press [] again to switch to minutes, the alarm icon [] and minutes will flash at the same time, entering the minute setting state. Short press [] to increase the number, short press [] to decrease the number. - Short press [] again and the alarm icon [] and the clock will flash at the same time to enter Alarm 2 Settings, the setting method for Alarm 2 is the same as Alarm 1. - Press and hold [] to save the current settings. - Turn alarm on/off []. Short press [] to turn on or off Alarm 1. Short press [] to turn on or off Alarm 2.	snooze - When the alarm rings, briefly touch the night light switch [] to snooze. The snooze duration is 5 minutes. Can snooze 4 times. - The alarm clock enters the snooze state, and the icon in the screen display area [] flashes. The snooze is not over, and the touch the night light switch to cancel the snooze state. - When the alarm sounds and no operation is performed, it will sound once every 15 minutes for a total of 4 times. Long touch the night light switch [] to stop the current alarm sound. 12/24 HOUR SETTING - Short press [] 13 times, the clock display area, 12/24 hour setting flashes. - Short press [] to switch between 12/24 hours. - Long press [] to save the current settings. ADJUST SCREEN BRIGHTNESS In normal clock display mode: - Short press [] to adjust the clock screen brightness. High brightness - medium brightness - low brightness - off to adjust the screen brightness in sequence.	APPLICABLE DEVICE This product supports fast wireless charging, which complies with the Qi wireless charging standard. It realizes short-distance wireless power transmission through magnetic induction. This device supports all wireless charging devices that meet the Qi standard. When using a 5V output adapter, Wireless charging supports 5W load. When using an adapter that meets QC2.0 and above standards, the wireless charging supports 10W load. Support overcharge protection (9V) and overcurrent protection (2A). ATTENTION POINTS - Do not use or store the product in direct sunlight or high temperature places for a long time. - Do not charge in places too close to magnetic cards, magnetic recording media, and precision instruments. - Do not disassemble or modify this product. - Do not touch the AC adapter with wet hands. - Keep this product away from water or other liquids. - If you want to clean the product, please disconnect the power. SPECIFICATIONS Product Model: S32 Material: Imported ABS+PP+Hardware Input: DC5V/3A 9V/2.1A Charging efficiency: 75% Power: 5W/7.5W/10W/15W Product size: 188x155x42mm Product weight: 430g Charging port: Universal Type-C	FCC WARNING STATEMENT This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures: - Reorient or relocate the receiving antenna. - Increase the separation between the equipment and receiver. - Connect the equipment into an outlet on a circuit different from that to which the receiver is connected. - Consult the dealer or an experienced radio/TV technician for help. This equipment must be installed and operated with a minimum distance of 20 cm between the radiator and user body. CE RoHS Made in China
---	--	--	---	---	---	---	--	--	--

110.00 mm

反面

多功能无线充 无线充电 时钟 小夜灯 充电座 产品使用说明 无线充电 时钟 小夜灯 充电座 非常感谢您选择我们的产品,在使用产品的请认真阅读好产品说明		产品特点 - 造型简单易精致. - 小夜灯. - 时钟闹钟. - 无线快充. - 充电距离 ≤8mm. 外观特征 ① 手机无线充电区域 ② 屏幕显示区 ③ PP灯罩 ④ 灯光调节触摸开关 ⑤ 手机有线充电接口 ⑥ 智能手表充电区 ⑦ 功能按键 ⑧ Type-C/USB输出 ⑨ 充电指示灯 ⑩ Type-C输入口 ⑪ 收纳盒Type-C输入口	操作方法 1.将USB数据线的USB接口接入电源适配器,Type-C端口接入产品.2.产品通电后,产品指示灯红灯常亮,将需要的无线充电设备放在本产品充电指示区域,进入充电状态. 3.产品也可外接线使用,产品通电后将Type-C/USB接入产品,另一个端口接入手机,进入充电状态. Type-C/USB接口 USB数据线 Lightning Type-C	收纳盒安装 1.充电座线盒有一个接口,两个转接头分别是Type-C接口和Lightning接头. 2.收纳盒可单独充电,便捷户外使用.将USB数据线的USB接口接入电源适配器,Type-C端口接入产品.将需要的设备放在本产品充电指示区域,进入充电状态. Type-C Lightning 充电座线盒	小夜灯功能 - 单击开灯切换暖白/冷白/压白/关闭. - 依次循环开启灯光. - 在任意色温灯光模式下,长触摸调节灯光亮度. 功能按键 屏幕亮度 闹钟1 闹钟2 模式 闹钟1 闹钟2 模式	时钟设置 在正常时钟显示模式下: 短按 [] 4次,时钟显示区域,闹钟图标 [] 和闹钟同时闪烁,进入闹钟时钟设置状态.短按 [] 增加数字,短按 [] 减少数字. 再次短按 [] 切换分钟,分钟开始闪烁,进入分钟设置状态. 短按 [] 增加数字,短按 [] 减少数字. 长按 [] 保存当前设置,并返回时间显示. 闹钟如何设置 在正常时钟显示模式下: 闹钟设置方法1 - 长按 [] 时钟显示区域,闹钟1 [] 图标和闹钟开始闪烁,进入闹钟1时钟设置状态. - 短按 [] 增加数字,短按 [] 减少数字. - 再次短按 [] 切换分钟,分钟开始闪烁,进入分钟设置状态. - 短按 [] 增加数字,短按 [] 减少数字. - 长按 [] 保存当前设置. - 闹钟2设置方法同闹钟1. - 时钟显示区域闹钟图标 [] / [] 哪个图标显示为哪个闹钟生效状态. 在正常时钟显示模式下: 闹钟设置方法2 - 短按 [] 4次,时钟显示区域,闹钟图标 [] 和闹钟同时闪烁,进入闹钟时钟设置状态.短按 [] 增加数字,短按 [] 减少数字. - 再次短按 [] 切换分钟,分钟同时闪烁,进入分钟设置状态. - 短按 [] 增加数字,短按 [] 减少数字. - 长按 [] 保存当前设置,并返回时间显示.	杂音 - 闹钟响时,短触摸夜灯开关 [] 杂音,杂音时长为5分钟,可连续4次. - 闹钟进入杂音状态,屏幕显示区域 [] 图标闪烁.杂音未结束,长触摸夜灯开关则可消杂音状态. - 当前闹钟且未进行任何操作时,每10分钟响一次,共响4次,长触摸夜灯开关 [] 可停止当前闹钟铃声. 12/24小时设置 - 短按 [] 13次,时钟显示区域,12/24小时设置闪烁,短按 [] 切换12/24小时. - 长按 [] 保存当前设置. 调整屏幕亮度 在正常时钟显示模式下: - 短按 [] 调整时钟屏幕亮度,亮亮—中亮—低亮—关闭依次循环调整屏幕亮度.	通用设备 本产品支持快速无线充电功能,符合Qi无线充电标准;通过磁感应方式实现短距离无线电能传输,本设备支持所有符合Qi标准的无线充电设备.使用5V输出的适配器时,无线充电支持5W负载.使用符合QC2.0或以上标准的适配器时,无线充电支持10W负载;设有过充保护(9V)及过流保护(2A). 注意事项 - 请勿长时间在阳光直射或高温的地方使用,存放该产品. - 请勿在强磁场、强电磁场和精密的仪器太近的地方充电. - 请勿分解或者改造本产品. - 请勿用湿手触摸交流适配器. - 请将本产品远离火源或其它液体. - 如欲修理或退换本产品,请联系厂家. - 产品工作环境温度范围:-20~45℃.	无线充规格参数 产品材料:进口ABS+PP+五金 电源输入:DC5V/3A 9V/2.1A 充电效率:75% 输出功率:5W/7.5W/10W/15W 产品尺寸:188x155x42mm 产品重量:430G 电源充电口为国际通用Type-C接口
---	--	---	---	--	---	--	---	---	---

CE RoHS 中国制造