



Visit www.tapo.com/support

for technical support, user guides, warranty,
and more information



Palm Vein & Fingerprint Recognition Smart Lock

Quick Start Guide

Tapo DL130



tapo

Welcome to Tapo!

Installation Guide & Video

Scan QR code or visit

<https://www.tp-link.com/support/faq/4480/>



Contact Us

Our expert Technical Support team is ready to assist you. Please don't hesitate to reach out with any questions.



EMAIL



CHAT



CALL



<https://www.tp-link.com/support/contact-technical-support/>


*Images may differ from your actual product.




Contents

Parts in the Box	3
Installation Preparation	6
Installation	11
Setup	25
How to set a PIN code, fingerprint, and palm vein	27
What if the battery is dead while you are outside?	28
Appearance	29

Parts in the Box



Exterior Assembly




Interior Assembly



Battery Pack

Install the Bolt & Strike Plate

Packaged Together




Bolt




Strike Plate



Dust Box




Bolt Screws (ST4*25)×2



Strike Plate Screws (ST4*25)×2



Install Mounting Plate



Mounting
Plate

Actual Size


Screw Caps ×2



Secure Interior Assembly

Actual Size


(M4*7.5)×3




Actual Size

(ST4*20)×1






**Measuring Template
(For Door Lock)**



**Mounting Template
(For Door Sensor)**



**USB Adapter
Cable**



**Installation Reference
Line Sticker for
Interior Assembly**



**Installation Reference
Line Sticker for
Exterior Assembly**



**Quick Start
Guide**



Silicone Cover



Keys x2




Door Sensor


Installation Preparation

Check Door Lock Compatibility


1. Check your existing door lock type.




Compatible with Single
Cylinder Deadbolts



Lever Handle Lock Not
Compatible




Integrated Locks
Not Compatible



Mortise Locks Not
Compatible

2. Measure your door.


Place the measuring template on the door, aligning its door edge line with the door's edge.



Charge Your Battery

● When the battery is not installed

Plug the provided USB cable into the battery pack's Type-C port, then connect it to a power outlet via a USB adapter with 5V output.



LED Indication:


- **Charging:** Solid amber
- **Fully charged:** Solid green

Note:

1. Charge the battery before use. This will take a few hours. It is recommended to use a **5V/2A** adapter for optimal charging performance.
2. The USB adapter is not provided.

● When the battery is installed

Remove the battery cover. Plug the provided USB cable into the battery pack's Type-C port, then connect it to a power outlet via a USB adapter with 5V/2A (or higher current) output.




LED Indication:

- **Charging:** Solid amber
- **Fully charged:** Solid green

*The USB adapter is not provided.


Installation

Installation Overview





1 Remove your existing lock.

Remove your existing door lock and bolt.




2 Install the new bolt.

- A** Ensure the word **TOP** is facing up.




- B** If the latch hub is not centered in the door hole, twist the bolt to extend it.



Actual Size

Packaged together
with the bolt




3

Install the exterior assembly.


- A** Place the **exterior assembly sticker** on the door's exterior side, aligning its edge line with the door's edge.

Note: Choose the correct door edge line based on your backset distance.




Backset
2-3/8" (60 mm)

OR




Backset
2-3/4" (70 mm)


[OUTSIDE]




- B** Cable goes under the bolt.



[OUTSIDE]



- C** Insert the tailpiece and two prongs into the corresponding holes on the bolt and align the exterior assembly with the sticker.




4

Install the mounting plate.

[INSIDE]


- A** Place the interior assembly sticker on the door's exterior side, aligning its edge line with the door's edge.

Note: Choose the correct door edge line based on your backset distance.




Backset
2-3/8" (60 mm)


OR




Backset
2-3/4" (70 mm)



- A** Route the cable through the mounting plate's rectangular hole and insert the tailpiece into the center round hole.






- B** Align the mounting plate with the sticker, ensuring the two prongs of the exterior assembly match the two holes next to the center round hole. Secure it with the screws.




5

Install the interior assembly.






- C** Align the tailpiece with the key cylinder. Attach the interior assembly to the mounting plate.




- D** Rotate the thumb latch to ensure the latch retracts normally.



- E** Use the **three** provided M4*7.5 screws to affix the interior assembly.

Actual Size



- F** (Optional) Use the provided ST4×20 screw to secure the interior assembly.


Actual Size




This screw will firmly secure the interior assembly and mounting plate to the door's interior side.

6 Install the battery.

- A** Insert the battery into the interior assembly in the correct direction.



- B** Replace the cover by sliding it down.




- C** Insert the silicone cover into the bottom hole. Remove the stickers.

7

Install the door sensor.

Use the mounting template to locate the mounting location. Peel the adhesive on the back of the door sensor and stick it to the door frame, pressing for at least 15 seconds to ensure it's firmly attached.



Note: The adhesive is not suitable for rough or flaky walls.



8

Install the dust box & strike plate.

Insert the dust box and strike plate into the strike hole on the door frame. Ensure the depth of the strike hole is at least 1" (25.4 mm).



If the bolt operates smoothly without pushing or pulling the door, you can use your original strike plate.

If you need to push or pull the door for smooth operation, adjust the strike plate's position on the door frame.


Setup

Set Up Your Lock

1. Get the **Tapo** app from the App Store or Google Play and log in with your TP-Link ID. If you do not have an account, create one first.




2. Tap the **+** button in the app. Select **Door Locks** and then your model. Follow the app instructions to complete setup.



The Tapo app is needed to use this lock. If this lock was professionally installed (or installed by someone other than the homeowner), make sure this step is performed by the homeowner.

How to set a PIN code, fingerprint, and palm vein


The PIN code, fingerprint, and palm vein should be set in the Tapo app. Tapo will walk you through the process.



What if the battery is dead while you are outside?


- **Unlock via the provided key**

Gently open the cover to expose the cylinder. Unlock the door with the provided key.



- **Temporarily power up the lock**


Gently open the cover. Connect it to the Type-C port of a phone with reverse charging capability or a power bank for a temporary power supply. Note that this will not charge the battery and cannot transfer data.



Appearance

Appearance

Exterior Assembly



1 Palm Vein Reader

Lock/unlock with your palm vein.

2 Palm Vein Reader Indicator

Indicates the palm vein reader location and status. Hold your palm parallel to the indicator for recognition.

3 Keypad

Lock/unlock by entering the PIN code.

4 Unlock/Lock Button/Indicator

- After entering your PIN with scramble digits, press this button to confirm unlocking.
- Press this button alone to lock the door.
- As an indicator, it indicates the lock status.

5 Fingerprint Scanner

Lock/unlock with your fingerprint.

6 Ring Button

Press to ring the built-in doorbell.


7 Lock Cylinder

Unlock via the provided keys.

8 Type-C USB Cable

Temporarily power up the lock via phone (with a Type-C port) or power bank.

Interior Assembly



1 Battery Compartment

Insert the provided battery to power your lock and charge the built-in backup battery.

2 Reset

- Press and hold for 5 seconds to reset the Wi-Fi settings.
- Press and hold for 10 seconds to reset to factory default settings.

3 Thumb Latch

Rotate to lock/unlock the door.

Status LED Indications

Blinking red and green	Ready for setup
Pulsing green	Connecting to Wi-Fi
Blinking amber	Low battery
Blinking green	Lock updating
Solid red, red, turning off after 3 seconds	Updating failed
Blinking red three times	Door jammed

Specifications

Type-C Emergency Power Supply: 5V 

Battery Power: 3.6V 

Rainproof Rating: IP65 (only for the exterior assembly)

Safety Information

- Do not use damaged charger or USB cable to charge the device.
- Do not attempt to disassemble, repair, or modify the device. If you need service, please contact us.
- Do not use the device where wireless devices are not allowed.
- Do not use any other chargers than those recommended.
- Keep the device away from water, fire, humidity or hot environments.
- Do not place near automatically controlled devices such as fire alarms. Radio waves emitted from this product may cause such devices to malfunction resulting in an accident.
- Observe restrictions on using wireless products in fuel depots, chemical plants or when blasting operations are in progress.
- Never put metal objects inside the product. If a metal object enters the product turn off the circuit breaker and contact an authorised electrician.
- This product is not intended to be used when providing medical care. Consult the manufacturer of any personal medical devices, such as pacemakers or hearing aids to determine if they are adequately shielded from external RF (radio frequency) energy.
- Do not use this product in health care facilities. Hospitals or health care facilities may be using equipment that could be sensitive to external RF energy.
- This product may interfere with other electronic products such as TV, radios, personal computers, phones or other wireless devices.

Exterior Assembly Operating Temperature: -30 °C ~ 70°C (-22°F ~ 158°F)

Please read and follow the above safety information when operating the device. We cannot guarantee that no accidents or damage will occur due to improper use of the device. Please use this product with care and operate at your own risk.

CAUTION!

Risk of fire or explosion if the battery is replaced by an incorrect type

CAUTION!

Avoid replacement of a battery with an incorrect type that can defeat a safeguard. Avoid disposal of a battery into fire or a hot oven, or mechanically crushing or cutting of a battery, that can result in an explosion. Do not leave a battery in an extremely high temperature surrounding environment that can result in an explosion or the leakage of flammable liquid or gas. Do not leave a battery subjected to extremely low air pressure that may result in an explosion or the leakage of flammable liquid or gas.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/ TV technician for help.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

- 1) This device may not cause harmful interference.
- 2) This device must accept any interference received, including interference that may cause undesired operation.

Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Note: The manufacturer is not responsible for any radio or TV interference caused by unauthorized modifications to this equipment. Such modifications could void the user's authority to operate the equipment.

This equipment complies with FCC RF radiation exposure limits set forth for an uncontrolled environment. This device and its antenna must not be co-located or operating in conjunction with any other antenna or transmitter.

"To comply with FCC RF exposure compliance requirements, this grant is applicable to only Mobile Configurations. The antennas used for this transmitter must be installed to provide a separation distance of at least 20 cm from all persons and must not be co-located or operating in conjunction with any other antenna or transmitter."

Canadian Compliance Statement

This device contains licence-exempt transmitter(s)/receiver(s) that comply with Innovation, Science and Economic Development Canada's licence-exempt RSS(s). Operation is subject to the following two conditions:

- (1) This device may not cause interference.
- (2) This device must accept any interference, including interference that may cause undesired operation of the device.

L'émetteur/récepteur exempt de licence contenu dans le présent appareil est conforme aux CNR d'Innovation, Sciences et Développement économique Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes :

- 1) L'appareil ne doit pas produire de brouillage;
- 2) L'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

Radiation Exposure Statement:

This equipment complies with IC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 20cm between the radiator & your body.

Déclaration d'exposition aux radiations:

Cet équipement est conforme aux limites d'exposition aux rayonnements IC établies pour un environnement non contrôlé. Cet équipement doit être installé et utilisé avec un minimum de 20 cm de distance entre la source de rayonnement et votre corps.

Caution:

The device for operation in the band 5150–5250 MHz is only for indoor use to reduce the potential for harmful interference to co-channel mobile satellite systems;

DFS (Dynamic Frequency Selection) products that operate in the bands 5250–5350 MHz, 5470–5600MHz, and 5650–5725MHz.

Avertissement:

Le dispositif fonctionnant dans la bande 5150–5250 MHz est réservé uniquement pour une utilisation à l'intérieur afin de réduire les risques de brouillage préjudiciable aux systèmes de satellites mobiles utilisant les mêmes canaux;

Les produits utilisant la technique d'atténuation DFS (sélection dynamique des fréquences) sur les bandes 5250– 5350 MHz, 5470–5600MHz et 5650–5725MHz.

Industry Canada Statement CAN ICES-003 (B)/NMB-003(B)