材质：128g铜版纸
尺寸：540*100mm(折叠尺寸:60*100mm)

正面

KEMI MOTO

PRODUCT MANUAL

MOTORCYCLE PHONE MOUNT

EN / DE SKU: F0501-01903-BK



Disclaimer:
Thank you very much for choosing our product!
Before using this product, please read the instruction manual carefully. All information in this manual is subject to change without prior notice. The company reserves the right to make modifications or discontinue the product at any time without further notice.

PRODUCT DESCRIPTION

Thank you for choosing our motorcycle phone mount.
To ensure safe and convenient use of this product, please read the instructions carefully before use.

Features:
1. The main body of this motorcycle phone mount is made of PA66+30% GF (Nylon + Fiberglass) composite material.
2. The handlebar clamp comes with three rubber ring inserts with diameters of 12mm, 22mm, and 25.4mm respectively. You can remove or add the rubber ring inserts according to your handlebar size. When no rubber ring is inserted, the installation hole diameter of the handlebar ball base is 32mm.
3. The handlebar ball base features a TPU overmolded ball head, which is anti-slip and wear-resistant.
4. The phone mount is designed with a safety lock switch on the side: After placing your phone in the mount, lock the safety switch to ensure your phone remains secure even when riding at high speeds on bumpy roads. Before removing the phone, please unlock the safety switch first.
5. The damping device effectively reduces high-frequency vibrations from the motorcycle, thereby helping to minimize potential damage to your phone's camera.
6. This phone mount features a convenient phone placement and removal design: The locking switch allows for one-handed operation for both inserting and removing your phone, making it very convenient.
7. The charging model offers both wireless charging and wired charging modes, and can also charge two devices simultaneously.
8. Simple and quick installation, stable and secure. It fits a wide range of phone widths and can be adjusted according to your phone's width.
9. It can be fitted with a sunshade or an action camera.
10. Safety Note: The input voltage adaptation range for this motorcycle phone mount is 10-24V, which is compatible with motorcycle electrical systems. However, electric bicycle batteries are typically 36-72V. Using a voltage outside the adapted range may cause component ignition or explosion. Therefore, if installing this motorcycle phone mount on an electric bicycle, a voltage reduction module must be added to lower the electric bicycle's battery voltage to the compatible range before use. If you are not a professional, it is recommended to have this installation performed at a professional repair shop.

SPECIFICATIONS


Name: Motorcycle Phone Mount
Material: PA66+30%GF, Silicone, Stainless Steel, Aluminum Alloy
Compatible Phone Width: 64mm ~ 90mm
Compatible Phone Length: 120mm ~ 200mm
Compatible Phone Thickness: ≤ 12.5mm
Clamp Diameter Range: 12mm ~ 33mm

CHARGING PARAMETERS

Port Type: TYPE-C
Input Voltage: DC 12V-24V
Output:
*Wireless Charging: 15W (Max) (Backwards compatible with 5W, 7.5W, 10W)
*TYPE-C Port: 33W (Max)


ACCESSORIES

No.	Accessory Name	Quantity
①	6063 Aluminum Alloy CNC Handlebar Clamp (Pre-installed with 22mm Soft Rubber Insert)	1
②	CNC Handlebar Clamp 25.4mm Soft Rubber Insert	1
③	CNC Handlebar Clamp 12mm Soft Rubber Insert	1
④	Rubber Pad	1
⑤	Hex Key	1
⑥	Anti-Theft Key	1
⑦	Anti-Theft Connecting Clamp Assembly	1
⑧	Stainless Steel Washer	1
⑨	M5*15 Stainless Steel Hex Socket Screw	1
⑩	Phone Mount	1




ONE-TOUCH LOCKING SWITCH

The one-touch locking switch design allows for easy phone placement and removal.



LENGTH ADJUSTMENT KNOB

Adjust the width freely according to your phone's size, with an adjustable range of 64-90mm.




When using the mount for the first time, adjust this knob according to your phone's width until the phone can be easily inserted between the left and right clamp arms.

LENGTH ADJUSTMENT

Pull-down Stop Adjustment
1. Slide the lock button to the right side (as shown in the figure below) to release the pull-down stop. You can then adjust the extension length of the pull-down stop. Ensure it does not block the phone's power button or camera.
2. Depending on the length of the phone, fine-tune the position of the pull-down stop to align the phone's wireless charging coil with the central position of the product's wireless charging area. This ensures maximum wireless charging efficiency. (Generally, the wireless charging coil is located in the center of the back of the phone, while the central position of the product's wireless charging area is at the center of the "Kemimoto" logo on the front).
3. The extending stainless steel strip of the pull-down stop features a graduated scale, allowing for precise adjustment to the optimal center position for maximum wireless charging power. Adjust the scale on the stainless steel strip to half the length of your phone to achieve the best charging efficiency.
4. Extend the pull-down stop until it firmly supports the bottom of the phone, then slide the lock button to the left to secure the pull-down stop in place.

Freely adjust the length according to your phone's dimensions, with an adjustable length range of 120-200mm.




When using the mount for the first time, adjust this pull-down component according to your phone's length.

INSTALLATION INSTRUCTIONS


Installation Steps:
1. Install the Handlebar Clamp
1.1 Based on the handlebar diameter, fit the appropriate rubber ring insert onto the handlebar at the desired mounting location. Place component [1] over the rubber ring insert. After adjusting the angle to the desired position, insert component [8] into the groove of [1]. Secure the assembly to the handlebar using component [9]. The handlebar clamp installation is now complete.
2. Install the Phone Mount
Use component [6] to slightly loosen the anti-theft nuts on component [7]. Clamp one end of [7] onto the ball head of component [10] (the phone mount), and the other end onto the ball head of component [1] (the handlebar clamp). After adjusting component [10] to the desired viewing angle, use component [6] to tighten the anti-theft nuts on both sides of clamp [7] to secure the phone mount firmly. The phone mount installation is now complete.

Installation Diagram



No.	Accessory Name
①	6063 Aluminum Alloy CNC Handlebar Clamp (Pre-installed with 22mm Soft Rubber Insert)
②	CNC Handlebar Clamp 25.4mm Soft Rubber Insert
③	CNC Handlebar Clamp 12mm Soft Rubber Insert
④	Rubber Pad
⑤	Hex Key
⑥	Anti-Theft Key
⑦	Anti-Theft Connecting Clamp Assembly
⑧	Stainless Steel Washer
⑨	M5*15 Stainless Steel Hex Socket Screw
⑩	Phone Mount


Installation Completed Diagram



PHONE MOUNT WIRING

1. Wiring the Phone Mount:
Connect the SAE plug of the phone mount's power cable to the SAE plug of the power cable extension.
2. Motorcycle Wiring:
Connect the red terminal (positive wire) of the power cable to the positive power terminal of the motorcycle's ignition switch, or directly to the positive terminal ("+") of the motorcycle battery. Connect the black terminal (negative wire) to the negative terminal ("-") of the motorcycle battery or to any metal part of the frame. The mount can be used once power is connected.
3. Electric Bicycle Wiring Method:
(Important Note: This charger cannot be directly connected to an electric bicycle's power system.)
An additional DC-DC step-down module must be installed for use on an electric bicycle. This module steps down and converts the electric bicycle's battery voltage to DC 12V 10A. Then, connect the red terminal (positive wire) of the phone mount's power cable to the positive output terminal ("+") of the DC-DC step-down module converter. Connect the black terminal (negative wire) to the negative output terminal ("-") of the DC-DC step-down module converter. The mount can be used once power is connected. If you are not a professional, it is recommended to have this installation performed at a professional repair shop.

WIRING DIAGRAM



CUSTOMER SUPPORT

Contact us by email: support@kemimoto.com

Help center:

背面

KEMI MOTO

PRODUKTHANDBUCH

MOTORRAD-HANDYHALTERUNG

EN / DE SKU: F0501-01903-BK



Haftungsausschluss:
Vielen Dank, dass Sie sich für unser Produkt entschieden haben!
Bitte lesen Sie vor der Verwendung dieses Produkts die Bedienungsanleitung sorgfältig durch. Alle Informationen in diesem Handbuch können ohne vorherige Ankündigung geändert werden. Das Unternehmen behält sich das Recht vor, jederzeit Änderungen vorzunehmen oder das Produkt ohne weitere Ankündigung einzustellen.

PRODUKTBESCHREIBUNG

Vielen Dank, dass Sie sich für unsere Motorrad-Handyhalterung entschieden haben.
Um eine sichere und bequeme Verwendung dieses Produkts zu gewährleisten, lesen Sie bitte vor der Benutzung die Anleitung sorgfältig durch.

Merkmale:
1. Das Hauptgehäuse dieser Motorrad-Handyhalterung besteht aus einem Verbundwerkstoff aus PA66+ 30% GF (Nylon + Glasfaser).
2. Die Lenkerklemme wird mit drei Gummiring-Einsätzen mit den Durchmessern 12 mm, 22 mm und 25,4 mm geliefert. Sie können die Gummiring-Einsätze entsprechend der Größe Ihres Lenkers entfernen oder hinzufügen. Wenn kein Gummiring eingesetzt ist, beträgt der Montagelochdurchmesser der Lenkerkugelbasis 32 mm.
3. Die Lenkerkugelbasis verfügt über einen umspritzten TPU-Kugelkopf, der rutschfest und verschleißbeständig ist.
4. Die Handyhalterung ist mit einem Sicherheitsverriegelungsschalter an der Seite ausgestattet: Nachdem Sie das Handy in der Halterung platziert haben, verriegeln Sie den Sicherheitsschalter, um sicherzustellen, dass Ihr Handy auch bei hohen Geschwindigkeiten auf unebenen Straßen sicher bleibt. Bevor Sie das Handy entfernen, bitte zuerst den Sicherheitsschalter entriegeln.
5. Die Dämpfungsvorrichtung reduziert effektiv hochfrequente Vibrationen des Motorrads und trägt so dazu bei, mögliche Schäden an der Kamera Ihres Handys zu minimieren.
6. Diese Handyhalterung verfügt über ein praktisches Design zur Handyplatzierung und -entnahme: Der Verriegelungsschalter ermöglicht das Einhandbedienen sowohl zum Einsetzen als auch zum Entnehmen Ihres Handys, was sehr komfortabel ist.
7. Das Lade-Modell bietet sowohl drahtlose Lade- als auch kabelgebundene Lademodi und kann gleichzeitig zwei Geräte laden.
8. Einfache und schnelle Installation, stabil und sicher. Sie passt auf eine große Auswahl an Handybreiten und kann entsprechend der Breite Ihres Handys eingestellt werden.
9. Sie kann mit einem Sonnenschutz oder einer Action-Kamera ausgestattet werden.

SPEZIFIKATIONEN

Name: Motorrad-Handyhalterung
Material: PA66+30% GF, Silikon, Edelstahl, Aluminiumlegierung
Kompatible Handybreite: 64 mm - 90 mm
Kompatible Handylänge: 120 mm - 200 mm
Kompatible Handystärke: ≤ 12,5 mm
Klemmdurchmesserbereich: 12 mm - 33 mm


LADEPARAMETER

Anschlusstyp: TYPE-C
Eingangsspannung: DC 12V-24V
Ausgang:
*Drahtloses Laden: 15 W (Max.) (Abwärtskompatibel mit 5 W, 7,5 W, 10 W)
*TYPE-C-Anschluss: 33 W (Max.)

10. Sicherheitshinweis: Der Eingangsspannungs-Anpassungsbereich für diese Motorrad-Handyhalterung beträgt 10-24 V, was mit Motorradelektriksystemen kompatibel ist. Elektrofahrrad-Batterien sind jedoch typischerweise 36-72 V. Die Verwendung einer Spannung außerhalb des angepassten Bereichs kann die Zündung von Bauteilen oder eine Explosion verursachen. Daher muss, wenn diese Motorrad-Handyhalterung an einem Elektrofahrrad installiert wird, ein Spannungsreduzierungsmodul hinzugefügt werden, um die Batteriespannung des Elektrofahrrads vor der Benutzung auf den kompatiblen Bereich abzusenken. Wenn Sie kein Fachmann sind, wird empfohlen, diese Installation in einer Fachwerkstatt durchführen zu lassen.


ZUBEHÖR

Nr.	Zubehörbezeichnung	Menge
①	CNC-Lenkerklemme aus 6063-Aluminiumlegierung (mit voreingebauten 22 mm Weichgummi-Einsatz)	1
②	25,4-mm-Weichgummi-Einsatz für CNC-Lenkerklemme	1
③	12-mm-Weichgummi-Einsatz für CNC-Lenkerklemme	1
④	Gummischeibe	1
⑤	Inbusschlüssel	1
⑥	Diebstahlsicherungsschlüssel	1
⑦	Diebstahlgeschütztes Verbindungsklemmen-Bauteil	1
⑧	Edelstahl-Unterlegscheibe	1
⑨	M5 x 15 Edelstahl-Innensechskantschraube	1
⑩	Handyhalter	1




EIN-KLICK-VERRIEGELUNGSSCHALTER

Das Ein-Klick-Verriegelungsschalter-Design ermöglicht ein einfaches Einsetzen und Entnehmen des Telefons.



LÄNGENEINSTELLKNOPF

Stellen Sie die Breite je nach Größe Ihres Telefons frei ein, mit einem Einstellbereich von 64-90 mm.




When using the mount for the first time, adjust this knob according to your phone's width until the phone can be easily inserted between the left and right clamp arms.

LÄNGENEINSTELLUNG

Zugstopp-Einstellung
1. Schieben Sie den Verriegelungsknopf auf die rechte Seite (wie in der Abbildung unten gezeigt), um den Zugstopp zu lösen. Sie können dann die Auszugslänge des Zugstopps einstellen. Stellen Sie sicher, dass er den Einschaltknopf oder die Kamera des Telefons nicht blockiert.
2. Je nach Länge des Telefons justieren Sie die Position des Zugstopps fein, um die drahtlose Ladespule des Telefons mit der Mitte des drahtlosen Ladebereichs des Produkts auszurichten. Dies gewährleistet die maximale Effizienz des drahtlosen Ladens. (Im Allgemeinen befindet sich die drahtlose Ladespule in der Mitte der Rückseite des Telefons, während sich die Mitte des drahtlosen Ladebereichs des Produkts in der Mitte des "Kemimoto"-Logos auf der Vorderseite befindet).
3. Das ausziehbare Edelstahlband des Zugstopps verfügt über eine Skala, die eine präzise Einstellung auf die optimale Mittelposition für maximale Ladeleistung ermöglicht. Stellen Sie die Skala auf dem Edelstahlband auf die Hälfte der Länge Ihres Telefons ein, um die beste Ladeeffizienz zu erzielen.
4. Ziehen Sie den Zugstopp heraus, bis er fest an der Unterseite des Telefons anliegt, und schieben Sie dann den Verriegelungsknopf nach links, um den Zugstopp zu sichern.

Stellen Sie die Länge entsprechend der Größe Ihres Telefons frei ein, mit einem einstellbaren Längenbereich von 120-200 mm.




Stellen Sie diese Zugkomponente bei der ersten Verwendung der Halterung entsprechend der Länge Ihres Telefons ein.

MONTAGEANLEITUNG

Montageschritte:
1. Montage der Lenkerklemme
1.1 Wählen Sie entsprechend dem Lenkerdurchmesser den passenden Gummiring-Einsatz und setzen Sie ihn an der gewünschten Montagestelle auf den Lenker. Setzen Sie Bauteil [1] über den Gummiring-Einsatz. Nachdem Sie den Winkel in die gewünschte Position eingestellt haben, setzen Sie Bauteil [8] in die Nut von [1] ein. Befestigen Sie die Baugruppe mit Bauteil [9] am Lenker. Die Montage der Lenkerklemme ist damit abgeschlossen.
2. Montage der Handyhalterung
Verwenden Sie Bauteil [6], um die Diebstahlsicherungsmuttern an Bauteil [7] leicht zu lösen. Klemmen Sie ein Ende von [7] auf den Kugelkopf von Bauteil [10] (die Handyhalterung) und das andere Ende auf den Kugelkopf von Bauteil [1] (die Lenkerklemme). Nachdem Sie Bauteil [10] auf den gewünschten Betrachtungswinkel eingestellt haben, ziehen Sie die Diebstahlsicherung-smuttern an beiden Seiten der Klemme [7] mit Bauteil [6] fest, um die Handyhalterung sicher zu arretieren. Die Montage der Handyhalterung ist damit abgeschlossen.

Montagediagramm



Nr.	Zubehörbezeichnung
①	CNC-Lenkerklemme aus 6063-Aluminiumlegierung (mit voreingebauten 22 mm Weichgummi-Einsatz)
②	25,4-mm-Weichgummi-Einsatz für CNC-Lenkerklemme
③	12-mm-Weichgummi-Einsatz für CNC-Lenkerklemme
④	Gummischeibe
⑤	Inbusschlüssel
⑥	Diebstahlsicherungsschlüssel
⑦	Diebstahlgeschütztes Verbindungsklemmen-Bauteil
⑧	Edelstahl-Unterlegscheibe
⑨	M5 x 15 Edelstahl-Innensechskantschraube
⑩	Handyhalter


Diagramm der fertigen Montage



VERDRAHTUNG DER HANDYHALTERUNG

1. Verdrahtung der Handyhalterung:
Verbinden Sie den SAE-Stecker des Netzkabels der Handyhalterung mit dem SAE-Stecker des Verlängerungskabels.
2. Verdrahtung am Motorrad:
Verbinden Sie den roten Anschluss (Pluspolung) des Netzkabels mit dem Pluspol der Zündschloss-Stromversorgung des Motorrads oder direkt mit dem Pluspol ("+") der Motorradbatterie. Verbinden Sie den schwarzen Anschluss (Minuskleitung) mit dem Minuspol ("-") der Motorradbatterie oder mit einem beliebigen Metallteil des Rahmens. Die Halterung kann nach dem Anschließen an die Stromversorgung verwendet werden.
3. Verdrahtungsmethode für Elektrofahrräder:
Für die Verwendung an einem Elektrofahrrad muss ein zusätzliches DC-DC-Step-Down-Modul installiert werden. Dieses Modul senkt die Batteriespannung des Elektrofahrrads um und wandelt sie in DC 12V 10A um. Verbinden Sie dann den roten Anschluss (Pluspolung) des Netzkabels der Handyhalterung mit dem positiven Ausgangsanschluss ("+") des DC-DC-Step-Down-Modul-Konverters. Verbinden Sie den schwarzen Anschluss (Minuskleitung) mit dem negativen Ausgangsanschluss ("-") des DC-DC-Step-Down-Modul-Konverters. Die Halterung kann nach dem Anschließen an die Stromversorgung verwendet werden. Wenn Sie kein Fachmann sind, wird empfohlen, diese Installation von einer Fachwerkstatt durchführen zu lassen.

VERDRAHTUNGSDIAGRAMM



KUNDENSUPPORT

Kontakt per E-Mail: support@kemimoto.com

Helpdesk:

FCC STATEMENT :

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1) This device may not cause harmful interference, and
(2) This device must accept any interference received, including interference that may cause undesired operation.
Warning: Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.
This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

Reorient or relocate the receiving antenna.

Increase the separation between the equipment and receiver.

Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

Consult the dealer or an experienced radio/TV technician for help.

FCC Radiation Exposure Statement

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance of 20 cm between the radiator and your body. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.