

ALBION User Guide

www.mcgrathsmartlocks.com.au




DOWNLOAD & INSTALL



Download and install the McGrath Locks App
Enable your smart phone to scan QR code to download the app. Also you can search "McGrath Locks" on Apple Store or Google Play to download the app.


Exploded diagram

A. Lock mortice B. Exterior assembly C. Mounting plate D. Interior assembly




1. Install the lock mortice

This lock supports either a tubular latch or mortice lock as follows. Check what type you have in the box and install it first within the door. Ensure that the latch or mortice lock faceplate is flush with the edge of the door.




2. Reverse the direction of the lock handle (if required)


A. Remove the screw C B. Rotate the handle up 180° C. Fasten the screw C



3. Dismantle the mounting plate from the interior lock assembly as below




4. Tighten 2 screw studs on the exterior lock metal plate




Tubular latch hub setting

1 If the handle points to the left as below, rotate the letter A on the hub to point to the triangle icon as shown.




1 If the handle points to the right as below, rotate the letter A on the hub to point down, opposite from the triangle icon as shown.



Mortice lock hub setting

Rotate the letter B on the hub to point to the triangle icon as shown.



5. Install exterior lock assembly

A. Slide the spindle through the hub of the latch or mortice lock, feed the connecting cable through the top hole cut in the door while placing the exterior lock assembly on the door. Ensure the spindle sits within the lock hub.

B. Position the inside mounting plate on the door and feed the connecting cable through the top hole in the plate.

C. Use the two main fixing screws to attach the exterior lock assembly to

the interior mounting plate but do not fully tighten.

D. Align the mounting plate with the door edge ensuring the spindle is in the middle of the round hole in the mounting plate.

E. Place the interior lock assembly on the door and check that both levers operate smoothly.

F. Remove the interior lock assembly, then tighten the two fixing screws.

6. Install interior lock assembly


A. Connect the cable to interior lock assembly.

B. Place the interior lock assembly on the mounting plate ensuring not to pinch the connecting cable and tighten the 4 lock case screws.

C. Test the handle and the mechanical key override.

D. Insert the rubber plugs into the bottom two screw holes.

E. Insert 4 x AA Alkaline batteries.



RECOMMENDED: LOCK SETUP WITH APP

It is highly recommended to set up the lock using the McGrath Locks App.

The app simplifies programming and provides an esier way to manage your locks.



DOWNLOAD & INSTALL

Manual set up via keypad only

Please follow the instructions below to manually program the lock using the keypad.

You can add a BLE device after the lock is programmed manually provided you know the admin code.

*83# > Admin Code# > Add lock via app

CREATE NEW ACCESS

Add administrator (only 1)

*12# > 123 456# > New Code# > New Code#

- Enter *12#
- Input 123456# (the default code)
- Input new code#
- Repeat new code#

Tips: If you use the app a 4 digit admin code can be set.

Add a new user with an access / PIN code (250 maximum)

*80# > Admin Code# > New Code# > New Code#

- Enter *80#
- Input admin code#
- Input user code# (6-9 digits)
- Repeat new user code#

Tips: If you use the app a 4 digit user code can be set.

Add a new user with an RFID card (1000 maximum)

*80# > Admin Code# > RFID

- Enter *80#
- Input admin code#
- Present the card to the card sensor area

MODIFY CODE

Modify admin code

*12# > Admin Code# > New Code# > New Code#

- Enter *12#
- Input old admin code#
- Input new admin code#
- Repeat the new admin code#

Modify user code

*10# > User Code# > New Code# > New Code#

- Enter *10#
- Input old user code#
- Input new user code#
- Repeat the new user code#

DELETE USER

Delete specified PIN code

*72# > Admin Code# > Specified code#

- Enter *72#
- Input admin code#
- Input the specified code# that you wanted to delete

Tips: The admin code cannot be deleted.

Delete all user codes

*71# > Admin Code#

- Enter *71#
- Input admin code#

Delete all RFID cards

*69# > Admin Code#

- Enter *69#
- Input admin code#

MANAGE VOICE

Turn on the lock voice

*30# > Admin Code# > 1#

- Enter *30#
- Input admin code#
- Input 1#

Turn off the lock voice

*30# > Admin Code# > 0#

- Enter *30#
- Input admin code#
- Input 0#

RESET THE LOCK

Press and hold the reset button until you hear "please input initialization passcode" then input 000#. All PIN codes, cards, and BLE and fingerprint users will be deleted.

DEMO MODE

Demo mode is turned off by default prior to an Admin code being registered. If you wish to turn on demo mode input 24679#. Demo mode sets the lock access pin code to 123456# and any card or fingerprint will also open it. Registering an Administrator will take the lock out of demo mode.

LOW BATTERY ALERT

When battery power is less than 4.8V you will hear a low battery alert each time you wake the lock screen. Please replace batteries with new Alkaline type. Don't mix old and new batteries.

SCRAMBLING CODE FOR ANTI PEEP

Users may enter any random digits before or/and at the end of entering their correct PIN code and still gain access. This feature makes it harder for an unauthorised user who may be watching you to guess your PIN code.

INCORRECT CODE / CARD ALERT

If the wrong unlocking information is inputted five times the system will be locked out for 35 seconds. The lock can only be operated by the app during the lockout period.

PASSAGE MODE

Passage mode keeps the door unlocked, useful when gardening or bringing in groceries from the car etc.

To activate passage mode, enter a valid unlock code then press 123# within 5 seconds. The door will remain unlocked.

To remove from passage mode, unlock using a valid code or card. If you engage passage mode via the app you must use the app to disengage passage mode.

FAQS

Keypad on lock does not respond

- Please check the batteries are installed correctly.
- If the lock had been working OK, please replace the batteries with new AA Alkaline type.

The door will not lock

- Ensure the lock is not in demo mode.
- Check to see if the lock is in passage mode.
- Refer to installation guide to ensure the inside snib and cylinder bar are in correctly direction.

Battery performance is poor

- Ensure all batteries are new Alkaline type.
- Ensure the lock connecting cable is not pinched.
- Check for and update lock firmware.

Gateway

Gateway type



G2(Wi-Fi)
Network:2.4GWIFI



G3/ G3P(P oE)
Network:RJ45




G4(4G)
Network:TLE (4G)



G5(Wi-Fi)
Network:2.4G/5GWIFI

Add Gateway

- Open the McGrath Locks App and log in to your administrator account.
- Tap the menu icon (≡) in the top left corner of the home screen.
- Select 'Gateway' from the sidebar menu.
- Tap the "+" symbol in the top right corner.
- Choose your gateway model from the list provided.
- Connect the gateway to power, while the light is alternatively flashing red and blue, press the "+" symbol.
- Select the network required, enter the Wi-Fi password, enter the gateway name.



Notice: If the process times out, please disconnect from power and try again.

*Gateway coverage distance: 10 meters without obstruction

Gateway functionality

The gateway is an accessory for the lock that connects it to the network. With a gateway connected you can remotely manage the lock, such as opening the door or deleting a passcode.

Gateway Functions			The door lock can function normally without a gateway. However, to remotely modify or delete PIN codes, issue fingerprints or cards, open the door remotely and access other features, a gateway is required.
	Without Gateway	With Gateway	
Assign random PIN codes	✓	✓	
Door opening with app	✓	✓	
Set permissions	✓	✓	
Remotely modify and delete PIN codes	✗	✓	
Remote card issuance	✗	✓	
Open door remotely	✗	✓	
Upload door records log in real time	✗	✓	

FCC Caution

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

IMPORTANT NOTE

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

—Reorient or relocate the receiving antenna.

—Increase the separation between the equipment and receiver.

—Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

—Consult the dealer or an experienced radio/TV technician for help.

FCC Radiation Exposure Statement:

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 20cm between the radiator & your body.