

- Volume adjustment:
- Increase the volume: Press the `\*` key in a loop when making a call or playing media.
- Reduce the volume: When talking or playing media, press the `#` key in a loop.

IV. Call and dialing functions

- Call back the last number: In the hands-free call or in the waiting state of the handle, press the `#` key (redial key) to automatically redial the last outgoing number.
- Voice assistant: After Bluetooth is connected to the mobile phone, long press the hands-free key or the `\*` key for about 3 seconds to trigger the voice assistant of the mobile phone (such as Siri, Xiaoi, etc.).
- Important premise: This function requires your mobile phone to be turned on and configured with the voice assistant.

V. Personalized settings (operate when the device is idle)

The following settings need to be completed by entering specific code on the keyboard.

1. Change the ringtone of the call:

- Operation: Loop input *03#
- Options: There are 3 modes to choose from:
- Mode 1 & 2: Built-in ringtone of the device.
- Mode 3: Synchronize the ringtone of the mobile phone. After selecting this mode, the ringtone set by your mobile phone will be played when you receive an incoming call.

2. Change the dial tone:

- Operation: Loop input *04#
- Option: Switch between two modes:
- Dual audio dial tone: The standard DTMF sound is emitted when the key is pressed.
- Voice announcement: When you press the button, the device will read the number by voice (for example, pressing "1" will report "1").



使用说明书

Product Manual



免提/存储拨号
HF/STORE

重拨键/REDIAL



1960R-BT 蓝牙电话 用户手册

一、设备简介与充电

- 充电接口: Type-C USB 充电口。
- 电池规格: 3.7V 锂电池, 容量 2000mAh。
- 充电方法: 使用标准的 USB 充电器和 Type-C 数据线连接设备即可充电。

提示: 首次使用前, 建议为设备充满电。

二、基本操作

1. 开机/关机:

- 开机: 设备接通电源后会自动开机。或长按底座上的 开/关键 即可开机。
- 关机: 长按底座上的 开/关键 即可关机。

2. 蓝牙连接:

- 配对名称: 在手机的蓝牙搜索列表中, 请选择 “BTphone8019”。
- 自动回连: 开机后, 设备会优先尝试自动连接最近配对过的手机。若 3 次尝试失败, 将进入可被发现的等待连接状态。
- 低功耗模式: 如果长时间未连接, 设备会进入休眠以省电。按下任意键或提起手柄即可唤醒设备。

三、媒体播放与音量控制

- 播放手机音频: 蓝牙连接成功后, 您可以在手机上播放音乐、播客等任何媒体音频, 声音将通过蓝牙电话播放。
- 注: 来电时媒体音频会自动暂停, 通话结束后需要您手动在手机上恢复播放。
- 音量调节:
- 增大音量: 在通话或播放媒体时, 循环按压 `\*` 号键。
- 减小音量: 在通话或播放媒体时, 循环按压 `#` 号键。

四、通话与拨号功能

- 回拨最后号码: 在免提通话或提起手柄的待拨号状态下, 按一下 `#` 键 (重拨键), 即可自动重拨上一次呼出的号码。
- 语音助手: 蓝牙连接手机后, 长按免提键或 `\*` 号键约 3 秒, 即可触发手机的语音助手 (如 Siri、小爱同学等)。
- 重要前提: 此功能需要您的手机已开启并配置好语音助手。

五、个性化设置 (在设备空闲状态下操作)

以下设置需要通过键盘输入特定代码来完成。

1. 更改来电铃声:

- 操作: 循环输入 *03#
- 选项: 共有 3 种模式可选:
 - 模式 1 & 2: 设备内置铃声。
 - 模式 3: 手机同步铃声。选择此模式后, 来电时将播放您手机设置的铃声。

2. 更改拨号音:

- 操作: 循环输入 *04#
- 选项: 在两种模式间切换:
- 双音频拨号音: 按下按键时发出标准的 DTMF 音。
- 语音报号: 按下按键时, 设备会用语音读出该数字 (如: 按 “1” 会报 “一”)。

1960R-BT Bluetooth Phone User Manual

I. Introduction and charging of equipment

- Charging interface: Type-C USB charging port.
- Battery specification: 3.7V lithium battery, capacity 2000mAh.

- Charging method: Use the standard USB charger and Type-C data cable to connect the device to charge.

Tip: Before using it for the first time, it is recommended to fully charge the device.

II. Basic operation

1. Turn on/off:

- Power-on: The device will automatically turn on after the power is turned on. Or long press the on/key on the base to turn it on.

- Shut down: Press and hold the on/key on the base to turn off the power.

2. Bluetooth connection:

- Pairing name: In the Bluetooth search list of the mobile phone, please select “BTphone8019”.

- Automatic reconnection: After power-on, the device will give priority to automatically connecting to the recently paired mobile phone. If 3 attempts fail, it will enter a detectible waiting connection state.

- Low-power mode: If it is not connected for a long time, the device will go into hibernation to save power. Press any key or lift the handle to wake up the device.

III. Media playback and volume control

- Play mobile phone audio: After the Bluetooth connection is successful, you can play music, podcasts and other media audio on your mobile phone, and the sound will be played through the Bluetooth phone.

- Note: The media audio will be automatically paused when an incoming call, and you need to manually resume playback on your mobile phone after the call.

FCC caution:

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any

interference received, including interference that may cause undesired operation.

Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection

against harmful interference in a residential installation. This

equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions,

may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular

installation.

If this equipment does cause harmful interference to radio or television reception,

which can be determined by turning the equipment off and on, the

user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from

that to which the receiver is connected.

- Consult the dealer or an experienced radio/TV technician for help.

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.