



HCT Co., Ltd.

74, Seoicheon-ro 578beon-gil, Majang-myeon, Icheon-si, Gyeonggi-do, 17383 KOREA
Tel. +82 31 634 6300 Fax. +82 31 645 6401

TAS Validation Report

Applicant Name:

SAMSUNG Electronics Co., Ltd.

129, Samsung-ro, Yeongtong-gu, Suwon-Si, Gyeonggi-do, 16677 Rep. of Korea

Date of Issue: Nov. 27, 2023

Test Report No.: HCT-SR-2311-FC006

Test Site: HCT CO., LTD.

FCC ID:

A3LSMA256U

Equipment Type:

Mobile Phone

Application Type:

Class II Permissive Change

FCC Rule Part(s):

CFR §2.1093

Model name:

SM-A256U

Additional Model Name:

SM-A256U1/DS, SM-S256VL

Date of Test:

Nov. 16, 2023 ~ Nov. 27, 2023

Results:

Pass

Only operations relevant to this Class II permissive change were evaluated for compliance. Please see the original compliance evaluation in Report no # HCT-SR-2309-FC007-R2 for complete evaluation of all other operating modes

I attest to the accuracy of data. All measurements reported herein were performed by me or were made under my supervision and are correct to the best of my knowledge and belief. I assume full responsibility for the completeness of these measurements and vouch for the qualifications of all persons taking them.

Tested By

Reviewed By

Byeong-Chul, Yoon
Test Engineer
SAR Team
Certification Division

Yun-leang, Heo
Technical Manager
SAR Team
Certification Division

This report only responds to the tested sample and may not be reproduced, except in full, without written approval of the HCT Co., Ltd.

REVISION HISTORY

The revision history for this test report is shown in table.

Revision No.	Date of Issue	Description
0	Nov. 27, 2023	Initial Release

This test results were applied only to the test methods required by the standard.

The above Test Report is not related to the accredited test result by (KS Q) ISO/IEC 17025 and KOLAS(Korea Laboratory Accreditation Scheme), which signed the ILAC-MRA.

Table of Contents

1. Introduction.....	4
2. Test Result of the DUT	6
3. Tx Varying Transmission Test Cases and Test Proposal.	7
4. SAR Time Averaging Validation Test Procedures	8
5. Test Configurations	18
7. Conducted Power Test Results for Sub-6 TAS validation	21
8. Conclusions	31
9. Equipment List.....	32
10. References	33
Appendix A. Test sequence	34
Appendix B. Test setup Photo	

1. Introduction

This Process of TAS Validation is to demonstrate that the DUT complies with FCC RF exposure compliance requirement under varying Tx power transmission scenarios, thus validation the Samsung S.LSI TAS algorithm feature for FCC equipment authorization of the mobile phone. The value of Plimit used in this report per scenarios are determined.

FCC RF exposure limits are comprised of SAR (Specific Absorption Rate) and limits depending on frequency of operation. Both SAR regulatory specifications are defined over certain measurement duration allowing for time-averaging. The Samsung S.LSI proprietary TAS (Time Average SAR) algorithm has been designed to meet the compliance limits over the required duration, while still allowing dynamic control of transmit power for meeting system performance.

1.1 RF Exposure Limits for Frequencies < 6 GHz

HUMAN EXPOSURE	UNCONTROLLED ENVIRONMENT General Population (W/kg) or (mW/g)	CONTROLLED ENVIRONMENT Occupational (W/kg) or (mW/g)
SPATIAL PEAK SAR * (Partial Body)	1.6	8.0
SPATIAL AVERAGE SAR ** (Whole Body)	0.08	0.4
SPATIAL PEAK SAR *** (Hands / Feet / Ankle / Wrist)	4.0	20.0

NOTES:

* The Spatial Peak value of the SAR averaged over any 1 g of tissue (defined as a tissue volume in the shape of a cube) and over the appropriate averaging time.

** The Spatial Average value of the SAR averaged over the whole-body.

*** The Spatial Peak value of the SAR averaged over any 10 g of tissue (defined as a tissue volume in the shape of a cube) and over the appropriate averaging time.

1.2 Interim Guidance for Time Averaging

Per October 2018 TCB Workshop Notes, the below time-averaging windows can be used for assessing time-averaged exposures for devices that are capable of actively monitoring and adjusting power output over time to comply with exposure limits.

Interim Guidance	Frequency (GHz)	Maximum Averaging Time (sec)
SAR	< 3	100
	3 – 6	60
MPE	6 - 10	30
	10 - 16	14
	16 – 24	8
	24 – 42	4
	42 – 95	2

2. Test Result of the DUT

2.1 Measurement Results Summary Table

Test Case #	Test Scenario	Tech	Band	Antenna	RSI	SAR Limit 1g [W/kg]	Max time averaged 1g SAR[W/kg]	Test Results
2-2	Time-varying Tx power transmission	SA/FR1	41	Main 2	3	1.6	0.954	Verified
4-2		SA/FR1	41	Main 2	3	1.6	0.892	Verified
6-2	Re-selection	SA/FR1	41	Main 2	3	1.6	0.966	Verified
		LTE	66	Main 2	3			
7-2	SAR exposure switch	LTE	12	Main 1	3	1.6	0.987	Verified
		NSA/FR1	41	Main 2	3			
12-2	Antenna Switching with Spatial TAS	SA/FR1	41	Main 2	3	1.6	0.931	Verified
			77	Sub 3	3			
13-2	NSA with Spatial TAS	LTE	66	Main 3	3	1.6	0.949	Verified
		NSA/FR1	41	Main 2	3			
14	NSA antenna switching with Spatial TAS	LTE	12	Main 1	3	1.6	1.13	Verified
		NSA/FR1	41	Main 2	3			
		NSA/FR1	77	Sub 3	3			

Note : RSI (4) – Reduced-RCV ON, RSI(3) – Reduced-Hotspot Mode ON

FCC SAR Limit [W/kg]: 1.6W/kg,1g / Total exposure Limit :1.0

This report is revised due to changes in the Plimit values of NR TDD Band n41 Power Class 3, 2, and NR TDD Band n48. More detail information is specified in the manufacturer's technical documentation.

3. Tx Varying Transmission Test Cases and Test Proposal.

The following scenarios are covered in this report to demonstrate compliance with FCC RF exposure in Tx-varying transmission conditions.

1. During a time-varying Tx power transmission – to prove that TAS feature accounts for Tx power variations in time accurately.
2. During a call disconnect and re-establish scenario – to prove that the TAS feature accounts for history of Tx power from past accurately
3. During a technology/band handover – to prove that TAS feature accounts for history across transitions in band/technology
4. During RSI (Radio SAR index) change – to prove that TAS feature functions correctly to meet compliance limits across RSI changes
5. During UL CA- to prove that TAS feature can handle adding/removing CC and can handle both single CC and CA

As described in SAR Char.Report, the RF exposure is proportional to the Tx power for FR1. Thus, we rely on conducted power measurements (FR1) dynamic case to demonstrate that overall RF exposure is within the FCC limit.

The overall procedure for validating the test is summarized below:

1. Measure conducted power (FR1) over time, denoted as $TxPower(t)$, with time index t
2. Convert measured powers to RF exposure values using linear relationship shown below. In below expression, $P_{limit,FR1}$ would be the measured power at which FR1 technology meets measured SAR level of SAR_{design_target} as described in SAR Char Report .

$$SAR(t) = \frac{TxPower(t)}{P_{limit,FR1}} \times SAR_{design_target}$$

Eqn. (1)

3. Compute the average RF exposure over the most recent measurement duration which are denoted as T_{SAR} for FR1, respectively. These durations are as specified by FCC. This measurement duration interval is then given by $[t - T_{SAR}, t]$ for FR1, respectively

4. Divide the RF exposure for FR1 by corresponding FCC limits and ensure the sum denoted as TER (total exposure ratio) is less than 1 for all t . Please refer following to following equations which describe the calculation of TER and its target constraint. The expressions below is general considering a number of FR1 radios in general denoted by L_{SAR} .

For FR1 transmissions only:

$$\sum_{i_{SAR}=0}^{L_{SAR}-1} \frac{1}{T_{SAR}} \int_{t-T_{SAR}}^t \frac{SAR_{i_{SAR}}}{FCC \ SAR_{limit}} \leq 1$$

4. SAR Time Averaging Validation Test Procedures

Test Plan and test procedure for validating Samsung S.LSI TAS algorithm for FR1 scenarios.

4.1 Test sequence determination for validation

Two sequences for time varying Tx power are pre-defined as given below for FR1 case.

1. Test sequence A which is generated with one or two levels where one of the levels is maximum power level (P_{max}) which is applied at least for 100s. Based on the second level this test sequence is sub-categorized into four different sequences used
 - a. Test Sequence A.i where after P_{max} , a second level of P_{limit} is requested till the end of the test
 - b. Test Sequence A.ii where after P_{max} , a second level of $P_{max}-3dB$ is requested till the end of the test
 - c. Test Sequence A.iii where after P_{max} , a second level of $P_{limit}-3dB$ is requested till the end of the test
 - d. Test Sequence A.iv where only P_{max} is requested till the end of the test
2. Test Sequence B is generated at multiple power levels that are specified in the Appendix as a function of P_{max} and P_{limit} .

4.2. Test configuration selection for Validation TAS

This section provides general guidance for selecting test cases in TAS algorithm validation.

4.2.1 Test configuration selection for time-varying Tx power transmission

The Samsung S.LSI TAS algorithm is independent of band, modes or channel of any technology. Hence, we can validate using one or two combinations of band/mode/channel per technology. The criteria for selecting these would be based on the relative value of P_{limit} and P_{max} as determined in SAR Char Report. Essentially, we need to pick this combination such that P_{limit} is less than P_{max} so that the TAS algorithm will enforce power restriction.

4.2.2 Test configuration selection for change in call

The criteria to select the technology/band for transition between call setup and call drop is to choose the one with least P_{limit} among all bands. The test is performed with DUT requested power at P_{max} so that the Samsung S.LSI TAS feature enforces power restriction for longest duration. The call change is performed when the DUT is operating with restricted power. One such test is sufficient since behavior is not dependent on band/technology.

4.2.3 Test configuration for change in technology/band

FCC specifies different measurement durations for time averaging based on operating frequency. The change of operating frequency can result in change of time window for averaging, for e.g. change from 100s averaging for frequency below 3GHz to 60s averaging for frequency above 3GHz in FR1. The criteria for selecting test case to demonstrate compliance across time window change is to pick a technology/band corresponding to each time window such that P_{limit} is less than P_{max} . However, to show the performance of the TAS algorithm in this document, the case of low P_{limit} is considered, which is shown in SAR Char Report.

4.2.4 Test configuration for change in RSI (radio SAR index)

The criteria for selecting test case to demonstrate compliance across RSI change within a radio. The two RSI states are chosen by pick a technology/band from SAR Char. Report such that Plimit is less than Pmax for both states. However, to show the performance of the TAS algorithm in this document, the case of low Plimit is considered, which is shown in Table 7.2.1.

4.2.5 Test configuration for SAR exposure switching

The criteria for selecting test case is to pick an LTE band and a NR band with Plimit lower than Pmax in each case. The test is performed with both RATs connected in an EN-DC scenario. In the first portion of the test, DUT is requested to transmit at maximum power for NR and minimum power for LTE. In the second portion of the test, DUT is requested to transmit at maximum power for both NR and LTE. In the final portion of the test, DUT is requested to transmit at minimum power for NR and maximum power for LTE.

4.2.6 Test configuration for Uplink CA

The criteria for selecting this test case is to demonstrate the compliance of the TAS algorithm when an LTE transmission is done over multiple CC. This test shows that the TAS algorithm compliance is independent on the Transmission scenarios (single CC or CA).

4.2.7 Test configuration for WCDMA time-varying Tx power

The criteria of selecting this test configuration is to demonstrate that Samsung S.LSI algorithm is independent on bands or technology used. We will show that the algorithm can control the transmitted power of a WCDMA transmission with varying requested power as in the LTE and NR technologies.

4.2.8 Test configuration for 2G time-varying Tx power

The criteria of selecting this test configuration is to demonstrate that Samsung S.LSI algorithm is independent on bands or technology used. We will show that the algorithm can control the transmitted power of a 2G transmission with varying requested power as in the LTE and NR technologies.

4.2.9 Test configuration for Spatial TAS

The criteria of selecting these tests configuration is to demonstrate the compliance of the TAS algorithm while transmitting on multiple antennas with a coupling factor of 0. This spatial TAS algorithm will show that we can achieve enhanced performance based on the antenna coupling while ensuring compliance with FCC target level.

4.3 Test procedures for conducted power measurements

This section provides general conducted power measurement procedures to perform compliance test under dynamic scenarios.

4.3.1 Time-varying Tx power transmission scenario

This test is performed with two pre-defined test sequences as described in Section 4.1 for all technologies operating on sub-6GHz applying to both LTE and NR. The purpose of the test is to demonstrate the maximum power limiting enforcement and that the time-averaged SAR does not exceed the FCC limit at all times.

4.3.1.1 Test procedure

1. Using the Pmax and Plimit obtained in Table 7.2.1, generate the test sequence of power levels for each selected technology/band. Both test sequences A and B are generated. Maximum power can be changed according to DUT test results.
2. Establish the connection of the DUT to the call box in the selected RAT, with the call box requesting the DUT Tx power to be according to the sequence determined in Step 1. An initial value of Tx power will be set to 0dBm for 100s before the desired test sequence starts to help with post-processing of the time-average value with the very first value in the sequence. This is illustrated in the figure below




Figure 4.3-1 SAR measurement from Tx power using block-wise processing

3. Release connection.
4. After the completion of the test, prepare one plot with the following information:
 - A. Instantaneous Tx power versus time measured in Step 2
 - B. Requested Tx power versus time used in Step 2
 - C. Time-averaged power over 100s using instantaneous values from Step 2
 - D. Power level Plimit which is determined as meeting SAR target in Table 7.2.1(Pmax Plimit Table)
5. Make a second plot containing the following information:
 - A. Computed time-averaged 1gSAR versus time determined in Step 2
 - B. b. FCC 1gSAR limit of 1.6W/kg

The pass condition is to demonstrate time-averaged 1gSAR versus time shown in Step 5 value versus time does not exceed the FCC limit of 1.6 W/kg throughout the test duration. We would also demonstrate that time-averaged power does not exceed the Plimit at any time in the plot in Step 4.

4.3.2 Change in call scenario

This test is to demonstrate that Samsung S.LSI TAS feature correctly accounts for past Tx powers during time averaging when a new call is established. The call change has to be carried out when the power limit enforcement is ongoing.

4.3.2.1 Test procedure

1. Establish radio connection of DUT with call box e.g. using LTE technology
2. Configure call box to set DUT Tx power to a low value of -10dBm for 100s.
3. Configure call box to send “ALL UP” power control commands and continue LTE transmission from DUT so that maximum power of Pmax is achieved.
4. After 60s of transmission at Pmax power level, release the call from call box.
5. After 10s, re-establish the LTE connection from call box to DUT and repeat sending “ALL UP” power control command to bring the Tx power to Pmax level again and continue till the end of the test.
6. Release LTE connection.
7. After the completion of the test, prepare one plot with the following information (a) Instantaneous Tx power versus time (b) Requested Tx power versus time (c) Time-averaged power over 100s using instantaneous values and (d) Power level Plimit which is determined as meeting SAR target
8. Make a second plot containing the following information (a) Computed time-averaged 1gSAR versus time and (b) FCC 1gSAR limit of 1.6W/kg.

Pass condition is to demonstrate time-averaged 1gSAR value versus time does not exceed the FCC limit of 1.6 W/kg throughout the test duration. It is required to check if SAR calculation is accounting for call drop and connection. Current TAS algorithm software makes the UE estimate the exact amount of Tx power and average SAR even during call drop and call re-establishment event. The UE stores time information when it goes into a sleep mode and wake-up to calculate Tx power on / off duration.

4.3.3 Change in technology/band

This test is to demonstrate that Samsung S.LSI TAS feature can properly handle change of technology/band and consequently time window as necessary during handover scenarios. Since both Plimit and window duration can change across bands, we have to use separate equations below for converting Tx power to SAR as well as apply some combined SAR exposure criteria as shown below.

$$SAR_1(t) = \frac{TxPower_1(t)}{P_{limit,1,FR1}} * SAR_design_target_1 \quad (4.3-1)$$

$$SAR_2(t) = \frac{TxPower_2(t)}{P_{limit,2,FR1}} * SAR_design_target_2 \quad (4.3-2)$$

where $P_{limit,1,FR1}$ would correspond to measured power at which first technology/band meets measured SAR level of $SAR_design_target_1$ as described in Table 7.2.1 with time-averaging duration of $T_{1,SAR}$. Similarly, the quantities $P_{limit,2,FR1}$, $SAR_design_target_2$, $T_{2,SAR}$ are defined for the second technology/band. When first band is chosen below 3GHz, we would have $T_{1,SAR} = 100s$, and by choosing second band to be above 3GHz, we would use $T_{2,SAR} = 60s$. On the other hand, when first band is chosen above 3GHz and second band below 3GHz, we would use $T_{1,SAR} = 60s$ and $T_{2,SAR} = 100s$.

4.3.4 Test procedure for handover between two TAS RATs

1. Establish radio connection of DUT with call box e.g. using 5G FR1 NR technology
2. Configure call box to set DUT Tx power to a low value of 0dBm for 100s.
3. Configure call box to send “ALL UP” power control commands and continue NR transmission from DUT so that maximum power of Pmax is achieved. Continue transmission at the maximum power for 410s.
4. Change RAT from NR to LTE and configure call box to send “ALL UP” power control commands in LTE
5. Continue call in LTE at maximum power for 400s.
6. Release LTE connection
7. After the completion of the test, prepare one plot with the following information for each RAT (a) Instantaneous Tx power versus time (b) Time-averaged power for each RAT according to the averaging duration and (c) Plimit corresponding to each RAT
8. Make a second plot containing the following information (a) Computed time-averaged 1gSAR versus time for each RAT (b) Sum of time-averaged SAR computed according to Eqn.(4.3-1) and (4.3-2), and (c) FCC 1g SAR limit of 1.6W/kg

Pass condition is to demonstrate total time-averaged 1gSAR value versus time does not exceed the FCC limit of 1.6 W/kg throughout the test duration. It is required to check if power limiting enforcement is operated as expected when RAT change occurs in-between.

4.3.5 Change in RSI

This test is to demonstrate that Samsung S.LSI TAS feature can properly handle change of RSI resulting from different SAR index state detected by host platform software. It involves changing the Plimit value during the test for the same technology to emulate RSI change, while the SAR_design_target remains the same. Note that the DUT has a proximity sensor to manage extremity exposure, which is represented using RSI = 2, the DUT has a Hotspot mode to manage body exposure, which is represented using RSI = 3, the head exposure can be distinguished through audio receiver mode, represented as RSI = 4; similarly, the body worn with 15mm distance exposure is represented as RSI = 0

4.3.5.1 Test procedure for change in RSI

1. Establish radio connection of DUT with call box e.g. using NR SA FR1
2. Configure DUT to send at low Tx power of 0 dBm for 110s and set the RSI index corresponding to Plimit of 18dBm
3. Configure call box to send “ALL UP” power control commands and continue SA FR 1 transmission from DUT so that maximum power of Pmax is achieved. Continue the transmission for 200s.
4. Change the RSI index corresponding to lower value of 16dBm and continue the transmission for another 300s
5. Release the SA FR1 connection.

Pass condition is to demonstrate time-averaged 1gSAR value versus time does not exceed the FCC limit 1.6 W/kg throughout the test duration. It is required to check if power limiting enforcement is operated as expected when RSI index is changed during the test. Test Configurations

4.3.6 SAR exposure switching

This test is to demonstrate that Samsung S.LSI TAS feature can properly handle change of dominant SAR exposure radio in the case of two simultaneous active RATs. It involves changing the required power of both radios such that either one or both of the RATs becomes dominant contributor to total exposure ratio at different times of the test.

4.3.6.1 Test procedure for SAR exposure switching

1. Establish LTE and NR radio connection in NSA case with both call boxes, e.g. LTE and NR FR1 Technology.
2. Configure the LTE call box to send “ALL DOWN” power control commands for LTE and configure the NR call box to send “ALL UP” power control commands. This would correspond to NR dominant SAR scenario and continue this stage for about 220s.
3. In the second part of test, configure the LTE call box to send “ALL UP” power control commands and all transmissions are continued, resulting in maximum power requested from DUT for both LTE and NR. This stage of test is continued for another 110s.
4. In the third part of test, configure the NR call box to send “ALL DOWN” power control commands so that LTE becomes the dominant SAR radio. This stage is continued for another 110s.
5. Finally, both LTE and NR connections are released.

4.3.7 LTE Uplink CA

The test is to demonstrate that Samsung S.LSI TAS feature can properly handle the SAR exposure for LTE with the addition and/or removal of another intra-band LTE CC.

4.3.7.1 Test procedure for uplink CA

1. Establish LTE connection of DUT with call box over Cell 1 E.g. one cell of the band Combo CA_41C.
2. Configure the call box to send “ALL down” power control commands and continue this stage for about 100s.
3. Configure Call box to send “ALL UP” command for transmission on cell 1 and continue transmission for 200s
4. Establish LTE connection of DUT with call box over Cell 2 E.g. other cell of the band Combo CA_41C.
5. Configure Call box to send “ALL UP” command for transmission on cell 2 and continue transmission for 200s
6. Release LTE connection for both cells

4.3.8 WCDMA time-varying Tx power

The test is to demonstrate that Samsung S.LSI TAS feature can properly handle the SAR exposure for WCDMA with varying requested power over time.

4.3.8.1 Test Procedure for WCDMA_Time_varying_Tx_power_Case1

1. Establish WCDMA connection of DUT with call box
2. Configure call box to set DUT Tx power to a low value of 0dBm for 100s.
3. Configure call box to send “ALL UP” power control commands and continue WCDMA transmission for 80s from

DUT so that maximum power of Pmax is achieved.

4. Configure call box to set DUT Tx power to a lower value of Plimit(dBm)-3dB for 420s
5. Release WCDMA connection.

4.3.8.2 Test Procedure for WCDMA_Time_varying_Tx_power_Case2

1. Establish WCDMA connection of DUT with call box
2. Configure call box to set DUT Tx power to a low value of 0dBm for 100s.
3. Configure call box with requesting the DUT Tx power to be according to the sequence B generated and continue 2G transmission till the end of the test.
4. Release WCDMA connection

4.3.9 2G time-varying Tx power

The test is to demonstrate that Samsung S.LSI TAS feature can properly handle the SAR exposure for 2G with varying requested power over time.

4.3.9.1 Test Procedure for 2G_Time_varying_Tx_power_Case1

1. Establish 2G connection of DUT with call box
2. Configure call box to set DUT Tx power to a low value of 0dBm for 100s.
3. Configure call box to send "ALL UP" power control commands and continue 2G transmission for 500s from DUT so that maximum power of Pmax is achieved.
4. Release 2G connection.

4.3.9.2 Test Procedure for 2G_Time_varying_Tx_power_Case2

1. Establish 2G connection of DUT with call box
2. Configure call box to set DUT Tx power to a low value of 0dBm for 100s.
3. Configure call box with requesting the DUT Tx power to be according to the sequence B generated and continue 2G transmission till the end of the test.
4. Release 2G connection.

4.4 Spatial TAS

For the test cases with spatial TAS, we will consider 4 antennas (Main 1, Main 2, Main 3 and Sub 3) with two antenna groups where each antenna group consists of two antennas and multiple bands as in Table 4-1.

Table 4-1 Antennas and bands used in the spatial TAS conducted tests

AG#	Antenna	Band
AG0	Main 1, 2	GSM 1900, UMTS B2 LTE 7, 12, 41, 66 NR n25, n41
AG1	Main 3, Sub 3	LTE 48 NR n48, n77

The coupling matrix considered during the tests is

$$R = \begin{bmatrix} 1 & 0 \\ 0 & 1 \end{bmatrix}$$

4.4.1 Test procedure for LTE Antenna switching with spatial TAS

1. Establish radio connection of DUT with call box e.g. using LTE technology (AG0)
2. Configure call box to set DUT Tx power to a low value of -10dBm for 100s.
3. Configure call box to send "ALL UP" power control commands and continue LTE transmission from DUT so that maximum power of Pmax is achieved for 240s.
4. Change the band from AG0 to AG1 so that the transmitting antenna changes to AG1 and continue transmission for 90s.
5. Change the band from AG1 to AG0 so that the transmitting antenna changes to AG0 and continue transmission till the end of the test.
6. Release LTE connection

4.4.2 Test procedure for SA FR1 Antenna switching with spatial TAS

1. Establish radio connection of DUT with call box e.g. using LTE technology (AG0)
2. Configure call box to set DUT Tx power to a low value of -10dBm for 140s.
3. Configure call box to send "ALL UP" power control commands and continue LTE transmission from DUT so that maximum power of Pmax is achieved for 140s.
4. Change the band from AG0 to AG1 so that the transmitting antenna changes to AG1 and continue transmission for 140s.
5. Change the band from Band AG1 to AG0 so that the transmitting antenna changes to AG0 and continue transmission till the end of the test.

4.4.3 Test procedure for NSA with spatial TAS

1. Establish LTE and NR radio connection in NSA case with both call boxes, e.g. LTE (AG0) and NR (AG1)
2. Configure the LTE call box to send “ALL Down” power control commands for LTE and configure the NR call box to send “ALL Down” power control commands and continue for 150s.
3. Configure the LTE call box to send “ALL Up” power control commands for LTE while keeping the configuration of the NR call box at “ALL Down” power control commands. This would correspond to LTE dominant SAR scenario and continue this stage for about 140s.
4. Configure the NR call box to send “ALL UP” power control commands and all transmissions are continued, resulting in maximum power requested from DUT for both LTE and NR. This stage of test is continued for another 140s.
5. Configure the LTE call box to send “ALL DOWN” power control commands so that NR becomes the dominant SAR radio and continue transmission till the end of the test.
6. Finally, both LTE and NR connections are released.

4.4.4 Test procedure for NSA antenna switching with spatial TAS

1. Establish LTE and NR radio connection in NSA case with both call boxes, e.g. LTE (AG0) and NR (AG0)
2. Configure the LTE call box to send “ALL Down” power control commands for LTE and configure the NR call box to send “ALL Down” power control commands and continue for 150s.
3. Configure the LTE call box to send “ALL Up” power control commands for LTE and configure the NR call box to send “ALL Down” power control commands. This would correspond to LTE dominant SAR scenario and continue this stage for about 200s.
4. Configure the NR call box to send “ALL UP” power control commands and all transmissions are continued, resulting in maximum power requested from DUT for both LTE and NR. This stage of test is continued for another 200s.
5. Change NR (AG1) so that NR transmitting antenna is switched to AG1 and continue transmission for 200s
6. Configure the LTE call box to send “ALL DOWN” power control commands so that NR becomes the dominant SAR radio and continue transmission till the end of the test.
7. Finally, both LTE and NR connections are released.

5. Test Configurations

Plim values in green indicate Plimit < Pmax			Plim values in grey indicate Plim > Pmax						
Plimit corresponding to 1 W/kg (1g) 2.5W/kg(10g) SAR_Design_target							Pmax	Pmax	
SAR Exposure Position			Body-worn/ Phablet(Free)	Head (RCV ON)	Hotspot (Hotspot on)	Phablet (Grip On) /Earjack	Maximum Tune-up Output Power (Burst Average Power) [dBm]	Maximum Tune-up Output Power (Frame Averaged Power) [dBm]	UL:DL Ratio
Averaging volume			1g/10g	1g	1g	10g			
seperation Distance			15 mm/ 16mm,4mm,12mm	0 mm	10 mm	0 mm			
Mode	Band	Antenna	RSI=0	RSI=4	RSI=3	RSI=1,2			
GSM/GPRS/EDGE	850	MAIN 1	27.4	29.4	20.7	20.7	29.0	24.7	37.5%
GSM/GPRS/EDGE	1900	MAIN 2	27.2	30.2	19.0	19.0	25.0	22.0	50.0%
UMTS	2	MAIN 2	26.8	28.0	20.5	20.5	24.0	24.0	100%
UMTS	4	MAIN 2	27.4	29.0	20.5	20.5	24.0	24.0	100%
UMTS	5	MAIN 1	29.6	29.9	24.9	27.2	24.5	24.5	100%
LTE FDD	2	MAIN 3	21.0	21.0	21.0	21.0	24.5	24.5	100%
LTE FDD	5	MAIN 1	28.5	29.5	28.7	28.8	24.5	24.5	100%
LTE FDD	7	MAIN 2	26.4	28.7	21.0	21.0	23.5	23.5	100%
LTE FDD	12	MAIN 1	30.7	32.8	31.3	28.4	24.5	24.5	100%
LTE FDD	13	MAIN 1	28.5	30.8	29.5	30.1	23.5	23.5	100%
LTE FDD	14	MAIN 1	29.7	31.0	28.1	30.6	23.5	23.5	100%
LTE FDD	25(2)	MAIN 2	28.0	30.2	21.5	21.5	24.0	24.0	100%
LTE FDD	26	MAIN 1	28.9	29.9	27.0	29.1	24.5	24.5	100%
LTE FDD	30	MAIN 2	28.5	30.0	21.0	21.0	23.0	23.0	100%
LTE TDD PC3	41(38)	MAIN 2	28.2	28.6	17.5	17.5	24.5	22.5	63.3%
LTE TDD PC3	41 ULCA	MAIN 2	27.8	28.5	17.5	17.5	23.5	21.5	63.3%
LTE TDD PC2	41	MAIN 2	27.7	28.9	17.9	17.9	26.0	22.4	43.3%
LTE TDD PC3	48	SUB 3	18.0	14.0	18.0	18.0	22.0	20.0	63.3%
LTE TDD PC3	48 ULCA	SUB 3	18.0	14.0	18.0	18.0	22.0	20.0	63.3%
LTE FDD	66(4)	MAIN 2	29.0	30.3	21.5	21.5	24.0	24.0	100%
LTE FDD	66(4)	MAIN 3	21.0	21.0	21.0	21.0	24.5	24.5	100%
LTE FDD	71	MAIN 1	30.9	32.3	28.4	28.9	23.5	23.5	100%
NR FDD	5	MAIN 1	28.7	29.8	26.3	28.1	24.5	24.5	100%
NR FDD	25(2)	MAIN 2	28.7	29.8	20.5	20.5	23.5	23.5	100%
NR FDD	30	MAIN 2	28.8	29.6	21.0	21.0	23.0	23.0	100%
NR TDD PC3	41	MAIN 2	25.6	26.8	17.0	17.0	23.0	23.0	100%
NR TDD PC2	41	MAIN 2	26.8	28.0	17.0	17.0	25.5	25.5	100%
NR TDD	48	SUB 3	17.0	13.5	17.0	17.0	17.0	17.0	100%
NR TDD SRS 1	48	MAIN 2	13.0	13.0	13.0	13.0	18.5	18.5	100%
NR TDD SRS 2	48	SUB 2	13.0	13.0	13.0	13.0	18.5	18.5	100%
NR TDD SRS 3	48	SUB 5	13.0	13.0	13.0	13.0	18.5	18.5	100%
NR FDD	66	MAIN 2	29.4	30.8	21.0	21.0	23.5	23.5	100%
NR FDD	70	MAIN 2	29.6	31.8	21.5	21.5	24.0	24.0	100%
NR FDD	71	MAIN 1	29.8	31.7	28.3	29.1	24.0	24.0	100%
NR TDD SRS 0 PC3	77	SUB 3	18.0	16.0	18.0	18.0	23.0	23.0	100%
NR TDD SRS 1	77	MAIN 2	13.5	13.5	13.5	13.5	21.5	21.5	100%
NR TDD SRS 2	77	SUB 2	12.5	12.5	12.5	12.5	20.5	20.5	100%
NR TDD SRS 3	77	SUB 5	12.5	12.5	12.5	12.5	20.0	20.0	100%
NR TDD SRS 0 PC2	77	SUB 3	18.0	16.0	18.0	18.0	25.5	25.5	100%
NR TDD SRS 1	77	MAIN 2	13.5	13.5	13.5	13.5	21.5	21.5	100%
NR TDD SRS 2	77	SUB 2	12.5	12.5	12.5	12.5	20.5	20.5	100%
NR TDD SRS 3	77	SUB 5	12.5	12.5	12.5	12.5	20.0	20.0	100%
NR TDD SRS 0 PC3	77 DoD	SUB 3	18.0	16.0	18.0	18.0	23.0	23.0	100%
NR TDD SRS 1	77 DoD	MAIN 2	13.5	13.5	13.5	13.5	21.5	21.5	100%
NR TDD SRS 2	77 DoD	SUB 2	12.5	12.5	12.5	12.5	20.5	20.5	100%
NR TDD SRS 3	77 DoD	SUB 5	12.5	12.5	12.5	12.5	20.0	20.0	100%
NR TDD SRS 0 PC2	77 DoD	SUB 3	18.0	16.0	18.0	18.0	25.5	25.5	100%
NR TDD SRS 1	77 DoD	MAIN 2	13.5	13.5	13.5	13.5	21.5	21.5	100%
NR TDD SRS 2	77 DoD	SUB 2	12.5	12.5	12.5	12.5	20.5	20.5	100%
NR TDD SRS 3	77 DoD	SUB 5	12.5	12.5	12.5	12.5	20.0	20.0	100%

Note:

1. Radio SAR indicator (RSI) in the table above means the SAR test configuration of each mobile communication technology.
2. WLAN/BT mode are not controlled by The Samsung S.LSI proprietary TAS (Time Average SAR) algorithm.
2. Plimit and Tune up output power Pmax above table correspond to average power level accounting for duty cycle in the case of TDD Modulation schemes (GSM,LTE TDD,NR TDD)
3. Maximum tune up output Power Pmax is used to configure DUT during RF tune up procedure. The maximum allowed output power is equal to Tune up power +1 dB device design uncertainty.
4. Compared with the Plimit (Tune up Powers) declared in each RSI by the manufacturer and the Plimit (calculation) calculated by the SAR measurement of each RSI, the lower power is applied to the DUT as the Plimit at each RSI configurations.
5. when Hotspot Mode (RSI=3), Grip sensor (RSI=2) and Ear-jack mode(RSI=1) are triggered at the same time, RSI =4(RCV) takes higher priority. The Priority for power reduction was given in the order of hotspot(RSI=3), ear-jack.(RSI=1), and grip (RSI=2).
6. This report is revised due to changes in the Plimit values of NR TDD Band n41 Power Class 3, 2, and NR TDD Band n48. More detail information is specified in the manufacturer's technical documentation.

6.1 Test case list for sub-6GHz transmissions

To validate TAS algorithm in various sub-6GHz conditions, the chosen TC (Test Case) list is defined as in Table

6.1-1

Table 6.1-1 Sub-6GHz TAS validation test case list

No.	Test Scenario	Test case	Test configuration
TC01	Time-varying Tx power transmission	LTE_Time_Varying_Tx_Power_Case_1	LTE Band 7, 41, 48 Test Seq. A
TC02		SA_FR1_Time_Varying_Tx_Power_Case_1	NR Band n25, n41, n48 Test Seq. A
TC03		LTE_Time_Varying_Tx_Power_Case_2	LTE Band 7, 41, 48 Test Seq. B
TC04		SA_FR1_Time_Varying_Tx_Power_Case_2	NR Band n25, n41, n48 Test Seq. B
TC05	Change in call	LTE_Call_Disconnect_Reestablishment	LTE Band 7, 41, 48
TC06	Re-selection in call	SA_FR1_to_LTE_RAT_Re-selection	NR Band n25 to LTE Band 41 NR Band n41 to LTE Band 66 NR Band n48 to LTE band 48
TC07	SAR exposure switch	NSA_FR1_Dominant_Power_Switching	LTE Band 12 and NR Band n25 LTE Band 12 and NR Band n41
TC08	Change in RSI	SA_FR1_RF_SAR_Index_Change	NR Band n77
TC09	LTE ULCA.	LTE_UL_CA	LTE Band 41
TC10-1	WCDMA time varying Tx power	WCDMA_Time_varying_Tx_power_Case1	WCDMA Band 2
TC10-2		WCDMA_Time_varying_Tx_power_Case2	
TC11-1	2G time varying Tx power	2G_Time_varying_Tx_power_Case1	GSM1900
TC11-2		2G_Time_varying_Tx_power_Case2	
TC12	Antenna Switching with Spatial TAS	LTE_Ant_switching_Spatial_TAS	LTE Band 7, 48
		NR_Ant_switching_Spatial_TAS	NR Band n41, 77
TC13	NSA with Spatial TAS	NSA_Spatial_TAS	LTE Band 66 and NR Band 77 LTE Band 66 and NR band 41
TC14	NSA antenna switching with Spatial TAS	NSA_Ant_switching_Spatial_TAS	LTE Band 12 and NR Band n41 and NR Band n77

This document contains the TAS test results for the C2PC evaluated test results of 5G NR n41PC2 and n48 bands. Please refer to the manufacturer's technical documentation for detailed changes.

7. Conducted Power Test Results for Sub-6 TAS validation

7.1 Measurement set-up




Figure 7.1-1 Test set-up for legacy and sub 6GHz

The test setup for TAS validation with sub-6GHz RATs only is shown in Figure 5.1-1. Normally, a power sensor would measure total power in the entire frequency of its specification e.g. 10MHz to 50GHz for the MA2475D unit. However, when two radios are active, we need to measure their powers separately for using the corresponding SAR mapping table. Therefore, this test setup considers scenarios where two radios would be transmitting from different ports of the DUT so that separate power sensors measure them individually. A common power meter is able to display and record the readings for each sensor at the same time for post processing at a PC. The signaling call boxes MT8000A and MT8821C are used to establish the call and data connection to the DUT on those same ports for NR and LTE, respectively.

The couplers are able to provide the transmit signal from DUT to power sensors while uplink and downlink signaling messages exchanged with the call boxes on the same paths. We can build scripts to program a certain sequence of power control commands from the call boxes to the DUT which can essentially instruct the DUT to change its transmit power.

Thus, if we want DUT to transmit at maximum power in LTE, then continuous power up commands are sent by MT8821C. Similarly, continuous power up commands from MT8000A will try to increase NR power up to its maximum limit. Other power control scenarios which mimic real field behavior such as sequence of power up followed by power down are also possible as described in Section 4. All the path losses from RF port of DUT to the callbox and the power meters are calibrated and automatically entered as offsets in the callbox and power meter, which are also connected to the control PC used in the test setup. We use an Anritsu AMS tool, which is capable of executing the entire test sequence including requested power variation over time and call setup/disconnect scenarios based on pre-configured test case definition.

Power readings for each active technology are recorded every 100ms and dumped in an excel file. A post

processing tool is used to extract data from the excel file and plot the required metrics such as time-averaged power, SAR values versus time as described in Section 4.

In summary, the tests have to be executed as following procedure.

1. Measure conduction sub 6GHz Tx power corresponds to SAR regulation.
2. Set sub 6GHz power level with some margin. And start the test
3. Execute time-varying test scenarios. And record sub 6GHz power using sub 6GHz power meter equipment.
4. Plot the recorded results over measurement time. And evaluate the results for validation.

Note that Plimit is different according to the used OEM, so it is necessary to set the Plimit suitable for each terminal.

7.2 Plimit and Pmax measurement results

The measured *Plimit* for all the selected radio configurations are listed in Table 7.2.1. *Pmax* was also measured for radio configurations selected for testing time-varying Tx power transmission scenario in order to generate test sequences following the test procedures. Note that Table 7.2.1 is not actual Plimit corresponding to 1W/kg SAR, but our measured averaged power when forcing Plimit in our SW based on Table 7.2.1.

TC#	Test scenario	Tech	Band	Antenna	RSI	RB/offset/BW	Mode	Configuration	Plimit setting (dBm)	Pmax setting (dBm)	measured Plimit (dBm)	measured Pmax (dBm)
2	Time varying Tx power case	SA/FR1	41	Main 2	3	1/137/100MHz	DFT-s	1g/10mm/Hotspot	17	23.0*	16.8	22.78
							QPSK					
4		SA/FR1	41	Main 2	3	1/137/100MHz	DFT-s	1g/10mm/Hotspot	17	23.0*	16.8	22.78
							QPSK					
6	FR1 to LTE IRAT Reselection	LTE	66	Main 2	3	50/49/20MHz	QPSK	1g/10mm/Hotspot	21.5	23	22.1	23.31
		SA/FR1	41	Main 2	3	1/137/100MHz	DFT-s	1g/10mm/Hotspot	17	23.0*	16.8	22.78
							QPSK					
7	FR1 dominant power change	LTE	12	Main 1	3	1/0/10MHz	QPSK	1g/10mm/Hotspot	24.5	24.5	24.5	24.5
		NSA/FR1	41	Main 2	3	1/137/100MHz	DFT-s	1g/10mm/Hotspot	17	23.0*	16.8	22.78
							QPSK					
12	Antenna switching with Spatial TAS	SA/FR1	41	Main 2	3	1/137/100MHz	DFT-s	1g/10mm/Hotspot	17	23.0*	16.8	22.78
							QPSK					
			77	Sub 3	3	1/137/100MHz	DFT-s	1g/10mm/Hotspot	18	23.0*	18.17	23.28
							QPSK					
13	NSA with spatial TAS	LTE	66	Main 3	3	1/0/20MHz	QPSK	1g/10mm/Hotspot	21	24.5	21.47	24
		NSA/FR1	41	Main 2	3	1/137/100MHz	DFT-s	1g/10mm/Hotspot	17	23.0*	16.8	22.78
							QPSK					
14	NSA antenna switching with spatial TAS	LTE	12	Main 1	3	1/0/10MHz	QPSK	1g/10mm/Hotspot	24.5	24.5	24.5	24.5
		NSA/FR1	41	Main 2	3	1/137/100MHz	DFT-s	1g/10mm/Hotspot	17	23.0*	16.8	22.78
							QPSK					
		NSA/FR1	77	Sub 3	3	1/137/100MHz	DFT-s	1g/10mm/Hotspot	18	23.0*	18.17	23.28
							QPSK					

Table 7.2.1.

* Plimit and Tune up output power Pmax in above table correspond to average power level after accounting for duty cycle in the case of TDD Modulation schemes (GSM, LTE TDD, NR TDD)

Note: This report is revised due to changes in the Plimit values of NR TDD Band n41 Power Class 3, 2, and NR TDD Band n48. More detail information is specified in the manufacturer's technical documentation.

7.3 Time-varying Tx power measurement results

Following the test procedure in Section 4.3.1, the conducted Tx power measurement results for all selected test cases are listed in this section. In all conducted Tx power plots, the blue line shows the measured instantaneous power using the power meter, the red line shows the time-averaged Tx power and yellow line shows the Plimit value corresponding to design target. In all SAR plots, the dotted blue line shows the time-averaged 1g SAR while the red line shows the corresponding FCC limit of 1.6W/kg. Time-varying Tx power measurements were conducted for TC #1-4 in Table 7.2.1 by generating the test sequence A or B given in Appendix.

TC02: SA_FR1_Time_Varying_Tx_Power_Case_1 [n41]




Figure 7.3-9 Time-average conducted power of SA FR1 n41 in TC02

Figure 7.3-9 shows the instantaneous and time-averaged Tx power for this test. As shown in Figure 7.3-9, it is confirmed for time-average Tx power that the FCC limit was not exceeded, and that the averaged Tx power is lower than the value of Plimit. Figure 7.3-10 shows the plot of calculated time-averaged 1gSAR for this test demonstrating that exposure is well below the FCC limit of 1.6W/kg.




Figure 7.3-10 Total time-averaged SAR in TC02

FCC 1gSAR limit	1.6 W/kg
Max 100s-time average 1gSAR (blue curve)	0.954 W/kg
Device uncertainty	1 dB

TC04: SA_FR1_Time_Varying_Tx_Power_Case_2 [n41]




Figure 7.3-21 Conducted Tx power for SA FR1 n41 in TC04

Figure 7.3-21 shows the instantaneous and time-averaged Tx power for this test. As shown in Figure 7.3-21, it is confirmed for time-average Tx power that the FCC limit was not exceeded, and that the averaged Tx power is lower than the value of Plimit. Figure 7.3-22 shows the plot of calculated time-averaged 1gSAR for this test demonstrating that exposure is well below the FCC limit of 1.6W/kg.




Figure 7.3-22 Total time-averaged SAR in TC04

FCC 1gSAR limit	1.6 W/kg
Max 100s-time average 1gSAR (blue curve)	0.892 W/kg
Device uncertainty	1 dB

7.5 Re-selection in call test results

The test results in this section are obtained following the procedure in Section 4.3.4. The test cases correspond to TC#6 in Table 7.2.1.

TC06: FR1 to LTE IRAT Re-selection




Figure 7.5-3 Conducted Tx power for SAR IRAT re-selection in test TC06 [n41 to LTE Band 66]




Figure 7.5-3 shows the instantaneous and time-averaged conducted Tx power for both LTE Band 66 and NR FR1 Band n41 for the duration of the test. Around time stamp of ~510s, a RAT re-selection from NR Band 41 to LTE Band 66 was executed, resulting in reduction of time-averaged power of Band 66 and simultaneous increase in time-averaged power of Band n41. Figure 7.5-4 shows the time-averaged 1gSAR value for each of LTE Band 66 and NR FR1 Band n41, as well as the total SAR value. We can see that the total 1gSAR is higher during the band transitions, but is always under the total FCC limit of 1.6W/kg.

Figure 7.5-4 Conducted Tx power for SAR IRAT re-selection in test TC06

FCC 1gSAR limit	1.6 W/kg
Max 100s-time average 1gSAR (yellow curve)	0.966 W/kg
Device uncertainty	1 dB

7.6 Switch in SAR exposure test results

The test results in this section are obtained following the procedure in Section 4.3.6 The test cases correspond to TC#7 in Table 7.2.1.

TC07: NSA_FR1_Dominant_Power_Switching




Figure 7.6-3 Time average SAR of LTE Band 12 and FR1 n41 EN-DC case

Figure 7.6-3 shows the instantaneous and time-averaged Tx power for both LTE band B12 and NR FR1 band n41 versus time. When both LTE and FR1 operate, the SAR value was the highest instantaneously, but it can be seen that sum of average power in LTE and FR1 decreases again as soon as it is turned off. Figure 7.6-4 shows the computed time-averaged SAR value for LTE and FR1 as well as the sum. It was confirmed that algorithm operated under the total SAR design target limit of 1W/kg, while also being under the FCC limit of 1.6W/kg at all times. After the operation of FR1 is turned off, it can also be seen that the average power of LTE increases.




Figure 7.6-4 Total time-averaged SAR in TC07

FCC 1gSAR limit	1.6 W/kg
Max 100s-time average 1gSAR (yellow curve)	0.987 W/kg
Device uncertainty	1 dB

7.11 Antenna switching with spatial TAS

The test results in this section are obtained following the procedure in Section 4.4.2. The test cases correspond to TC#12 in Table 7.2.1.

TC12: SA_FR1_Ant_switching_Spatial_TAS




Figure 7.11-3 Conducted Transmitted power for NR Band 41 and NR band 77 in Test TC12

Figure 7.11-3 shows the instantaneous and time-averaged conducted Tx power at antenna(Main2) with SA FR1 band n41 (AG0) and at antenna(Sub3) with SA FR1 band n77 (AG1). Transmission is initialized on AG0 where it was set for very low power for ~140s. After that, a maximum power is requested and the TAS starts to cycle. After ~150s a band change happens to SA FR1 n77 (AG1) which operates at antenna(Sub3) and a maximum power is requested. Since the coupling between AG0 and AG1 is 0, then transmission at Antenna(Sub3) will start from maximum power regardless of the transmission at Antenna(main2) and will continue transmission for ~150s. Next, another band change is done to the first band n41 and so an antenna switching to Antenna (Main2) happens where a maximum power is requested. Consequently, the total average SAR shown in Figure 7.11-4 at each antenna Group is below 1W/kg which is below the FCC limit of 1.6W/kg.




Figure 7.11-4 Total time-averaged SAR in TC12

FCC 1gSAR limit	1.6 W/kg
Sum of calculated average SAR (yellow curve)	0.931 W/kg
Device uncertainty	1 dB

7.12 NSA with spatial TAS

The test results in this section are obtained following the procedure in Section 4.4.3. The test cases correspond to TC#13 in Table 7.2.1.

TC13: NSA_Spatial_TAS




Figure 7.12-3 Conducted Transmitted power for LTE Band 66 and NR band n41 in Test TC13

Figure 7.12-3 shows the instantaneous and time-averaged conducted Tx power for a NSA operation where LTE is transmitting at antenna(Main3) band B66 (AG1) and FR1 at antenna(Main2) with band n41 (AG0). After the ENDC connection establishment, Both LTE and FR1 are set to no transmission for ~150s. Next, a transmission starts with LTE Band 66 (AG1) requesting full max power and no transmission for FR1 and continue for ~140s. After that, a maximum power is requested for FR1 band n41 (AG0) and transmission is done on Antenna(main2) and continue for ~140s. Since both AGs are fully uncoupled, each RAT will operate with full Plimit. Next, The LTE transmission is down while FR1 continues transmission. Consequently, the total average SAR is shown in Figure 7.12-4 at each antenna Group is about 1W/kg which is below the FCC limit of 1.6W/kg.




Figure 7.12-4 Total time-averaged SAR in TC13

FCC 1gSAR limit	1.6 W/kg
Sum of calculated average SAR (yellow curve)	0.949 W/kg
Device uncertainty	1 dB

7.13 NSA antenna switching with spatial TAS

The test results in this section are obtained following the procedure in Section 4.4.4. The test cases correspond to TC#14 in Table 7.2.1.

TC14: NSA_Ant_switching_Spatial_TAS




Figure 7.13-1 Conducted Transmitted power for LTE Band 12 and NR band n41, n77 in Test TC14

Figure 7.13-1 shows the instantaneous and time-averaged conducted Tx power for a NSA operation where LTE is transmitting at antenna(Main1) band B12 (AG0) and FR1 at antennas(Main2, Sub3) with bands n41(AG0) and n77 (AG1) respectively. After the ENDC connection establishment, Both LTE band 12(Main1) and FR1 n41(Main2) are set to no transmission for ~150s. Next, a transmission starts with LTE requesting full max power and no transmission for FR1 and continue for ~200s. After that, a maximum power is requested for FR1 band n41 and transmission is done on Antenna(Main2) and continue for ~200s. Since LTE Band 12 and FR1 n41 are fully coupled, each RAT will operate, the SAR value was the highest instantaneously, but it can be seen that sum of average power in LTE Band 12(AG0) and FR1 n41(AG0) decreases again as soon as it is turned off. Next, FR1 will switch to band n77 (AG1) where FR1 requests maximum power and transmission continues for ~200s. Next, The LTE transmission is down while FR1 continues transmission. Consequently, the total average SAR (100s average+60s average) shown in Figure 7.13-2 at each antenna group is about 1W/kg which is below the FCC limit of 1.6W/kg.




Figure 7.13-2 Total time-averaged SAR in TC14

FCC 1gSAR limit	1.6 W/kg
Sum of calculated average SAR (purple curve)	1.130 W/kg
Device uncertainty	1 dB

8. Conclusions

Samsung Time-Averaging SAR (TAS) feature employed in Samsung Mobile Phone(FCC A3LSMA256U) has been validated through conducted power measurement as well as SAR measurement. As demonstrated in this report, TAS feature limit the transmit power effectively and shows that SAR value does not exceed 1.6 W/kg for all the transmission scenarios.

9. Equipment List

Manufacturer	Type / Model	S/N	Calib. Date	Calib.Interval	Calib.Due
Narda	Directional Coupler / 4216-10	01490	11/29/2022	Annual	11/29/2023
Narda	Directional Coupler / 4216-10	01489	11/29/2022	Annual	11/29/2023
HP	Power Divider/11636B	50659	05/26/2023	Annual	05/26/2024
HP	Power Divider/11636B	58698	01/26/2023	Annual	01/26/2024
RFCOREA	2Way Splitter	473842	12/21/2022	Annual	12/21/2023
RFCOREA	2Way Splitter	473841	12/21/2022	Annual	12/21/2023
Anritsu	Radio Communication Analyzer / MT8821C	6262044720	12/07/2022	Annual	12/07/2023
Anritsu	Radio Communication Analyzer / MT8821C	6262116770	08/02/2023	Annual	08/02/2024
Anritsu	Radio Communication Test Station / MT8000A	6262036812	12/08/2022	Annual	12/08/2023
Anritsu	Power Meter / ML2496A	2041001	11/29/2022	Annual	11/29/2023
Anritsu	Power Sensor / MA2475D	1911225	11/29/2022	Annual	11/29/2023
Anritsu	Power Sensor / MA2475D	1911226	11/29/2022	Annual	11/29/2023

10. References

The following documents contain reference in this technical document.

[1] [ForOEM][Samsung+S.LSI]+Time+average+SAR+algorithm(FCC)_v.2.7_v0.2_PDF_v0.0

Appendix A. Test sequence

1.1 Test sequence is generated based on below parameters of the DUT:

1. Measured maximum power (P_{max})
2. Measured Tx power (P_{limit}) to satisfy SAR Compliance
3. Setup time to make SAR Remaining be full
4. Do test according to test sequence

1.2 Test Sequence A waveform:

Based on the parameters above, the test sequence A is generated with one or two levels where one of the levels is maximum power level (P_{max}) which is applied at least for 100s. Based on the second level this test sequence is sub-categorized into four different sequences used

- a. Test Sequence A.i where after P_{max} , a second level of P_{limit} is requested till the end of the test
- b. Test Sequence A.ii where after P_{max} , a second level of $P_{max}-3dB$ is requested till the end of the test
- c. Test Sequence A.iii where after P_{max} , a second level of $P_{limit}-3dB$ is requested till the end of the test
- d. Test Sequence A.iv where only P_{max} is requested till the end of the test

1.3 Test Sequence B waveform:

Based on the parameters above, the Test Type B is generated with pre-defined power levels, which is described in Table 1.3.1

Table 1.3.1 Table of test sequence B

Time duration (second)	Power level (dB)
15	$P_{limit} - 5$
20	P_{limit}
20	$P_{limit} + 5$
10	$P_{limit} - 6$
20	P_{max}
15	P_{limit}
15	$P_{limit} - 7$
20	P_{max}
10	$P_{limit} - 5$
15	P_{limit}
10	$P_{limit} - 6$
20	$P_{limit} + 5$
10	$P_{limit} - 4$
15	P_{limit}
10	$P_{limit} - 6$
20	P_{max}
15	$P_{limit} - 8$
15	P_{limit}
20	P_{max}
10	$P_{limit} - 9$
20	$P_{limit} + 5$
20	P_{limit}
15	$P_{limit} - 5$