Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

A.3 MAXIMUM CONDUCTED OUTPUT POWER

Test Date	2023/10/05	Temp./Hum.	23°C/53%
Cable Loss	1.00dB	Tested By	Hua Wu
Test Voltage	AC 120V, 60Hz (via AC Adapter)		

A.3.1 Conducted Output Power Result

- **SPOT CHECK Power**

Test SKU: SKU #1 [with (INPAQ) WA-P-LELE-04-011 Antenna]

- OFDM Modulation

Modulation Type	U-NII Band	Centre Frequency (MHz)	Average Coneduted Output Power (dBm)		Duty Cycle Factor (dB) 10log(1/X)	Directional Gain (dBi) Note3	Total E.I.R.P. (dBm) Note2	Limit
			AUX	Main				
802.11ax-HE20	5	5955	1.47	1.21	N/A	3.35	7.70	24dBm
		6175	1.50	1.14		3.35	7.68	
		6415	1.19	1.11		2.60	6.76	
	6	6435	1.25	1.30		2.60	6.89	
		6475	1.49	1.42		2.60	7.07	
		6515	1.42	1.23		2.60	6.94	
	7	6535	0.77	0.44		2.60	6.22	
		6695	0.84	0.09		2.60	6.09	
		6855	0.93	0.09		2.30	5.84	
	8	6875	0.90	0.35		2.30	5.94	
		6995	0.84	0.09		2.30	5.79	
		7115	-3.48	-2.97		2.30	2.09	
802.11ax-HE40	5	5965	5.03	5.17	N/A	3.35	11.46	
		6165	4.97	5.11		3.35	11.40	
		6405	4.74	4.97		2.60	10.47	
	6	6445	4.90	5.24		2.60	10.68	
		6485	4.91	4.99		2.60	10.56	
	7	6525	5.05	5.06		2.60	10.67	
		6685	4.31	4.03		2.60	9.78	
		6845	4.33	3.96		2.30	9.46	
	8	6885	4.38	4.17		2.30	9.59	
		7005	4.37	3.89		2.30	9.45	
		7085	4.56	4.29		2.30	9.74	

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. According to KDB 662911 D01 E)1), Total E.I.R.P. (dBm) = Sum to individual output power (dBm)+ Directional gain (dBi) + duty cycle factor(dB) when duty cycle is less than 98%.
3. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = 10 log[$(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}$] dBi
Directional gain:
5925MHz: Directional gain = 10 log[$(10^{3.20/10} + 10^{3.50/10})/2$]= 3.35dBi
6525MHz: Directional gain = 10 log[$(10^{2.50/10} + 10^{2.70/10})/2$]= 2.60dBi
7125MHz: Directional gain = 10 log[$(10^{2.10/10} + 10^{2.50/10})/2$]= 2.30dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Modulation Type	U-NII Band	Centre Frequency (MHz)	Average Coneduted Output Power (dBm)		Duty Cycle Factor (dB) 10log(1/X)	Directional Gain (dBi) Note3	Total E.I.R.P. (dBm) Note2	Limit
			AUX	Main				
802.11ax-HE80	5	5985	7.06	6.67	N/A	3.35	13.23	24dBm
		6145	6.93	6.25		3.35	12.96	
		6385	7.23	6.71		2.60	12.59	
	6	6465	7.24	6.32		2.60	12.41	
		6545	7.05	6.43		2.60	12.36	
	7	6625	6.11	5.55		2.60	11.45	
		6705	6.21	5.25		2.60	11.37	
		6785	6.19	5.19		2.60	11.33	
	8	6865	5.92	5.33		2.30	10.95	
		6945	6.34	5.43		2.30	11.22	
		7025	6.35	5.76		2.30	11.38	
802.11ax-HE160	5	6025	9.93	9.15	N/A	3.35	15.92	
		6185	9.85	9.15		3.35	15.87	
		6345	10.04	9.43		2.60	15.36	
	6	6505	9.82	9.11		2.60	15.09	
	7	6665	9.08	8.20		2.60	14.27	
		6825	8.99	8.25		2.30	13.95	
	8	6985	9.37	8.48		2.30	14.26	

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]

2. According to KDB 662911 D01 E)1), Total E.I.R.P. (dBm) = Sum to individual output power (dBm)+ Directional gain (dBi) + duty cycle factor(dB) when duty cycle is less than 98%.

3. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then

Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi

Directional gain:

5925MHz: Directional gain = $10 \log[(10^{3.20/10} + 10^{3.50/10})/2]$= 3.35dBi

6525MHz: Directional gain = $10 \log[(10^{2.50/10} + 10^{2.70/10})/2]$= 2.60dBi

7125MHz: Directional gain = $10 \log[(10^{2.10/10} + 10^{2.50/10})/2]$= 2.30dBi

The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

- OFDMA Modulation

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 0			RU Index 4			RU Index 8				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE20	5	5955	26T	-6.16	-5.88	0.223	-6.03	-5.95	0.223	-6.29	-6.16	0.223	3.35	0.59
		6175		-7.53	-7.63	0.223	-7.10	-7.47	0.223	-7.44	-7.74	0.223	3.35	-0.70
		6415		-7.80	-8.14	0.223	-7.62	-8.01	0.223	-8.10	-8.23	0.223	2.60	-1.98
	6	6435		-7.68	-8.01	0.223	-7.77	-7.83	0.223	-7.93	-8.14	0.223	2.60	-1.97
		6475		-8.16	-8.14	0.223	-7.83	-8.13	0.223	-7.98	-8.42	0.223	2.60	-2.14
		6515		-8.23	-8.42	0.223	-7.84	-8.20	0.223	-8.40	-8.55	0.223	2.60	-2.18
	7	6535		-8.95	-9.10	0.223	-8.99	-9.08	0.223	-9.12	-9.31	0.223	2.60	-3.19
		6695		-9.54	-9.00	0.223	-9.38	-8.78	0.223	-9.67	-9.04	0.223	2.60	-3.24
		6855		-8.88	-8.72	0.223	-8.98	-8.49	0.223	-8.98	-8.87	0.223	2.30	-3.19
	8	6875		-9.18	-8.91	0.223	-9.29	-8.56	0.223	-9.57	-8.84	0.223	2.30	-3.38
		6995		-8.30	-7.97	0.223	-8.05	-7.94	0.223	-8.23	-8.08	0.223	2.30	-2.46
		7115		-8.08	-7.73	0.223	-7.75	-7.59	0.223	-8.00	-7.66	0.223	2.30	-2.14

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 0			RU Index 8			RU Index 17				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE40	5	5965	26T	-6.35	-5.95	0.223	-6.08	-6.12	0.223	-6.21	-6.06	0.223	3.35	0.48
		6165		-7.22	-7.41	0.223	-7.30	-7.65	0.223	-7.32	-7.68	0.223	3.35	-0.73
		6405		-7.64	-8.10	0.223	-7.80	-8.12	0.223	-7.96	-8.27	0.223	2.60	-2.03
	6	6445		-7.83	-7.99	0.223	-8.19	-8.07	0.223	-8.07	-8.16	0.223	2.60	-2.08
		6485		-8.11	-8.08	0.223	-8.34	-8.28	0.223	-8.18	-8.54	0.223	2.60	-2.26
	7	6525		-8.19	-8.44	0.223	-8.32	-8.49	0.223	-8.28	-8.49	0.223	2.60	-2.48
		6685		-9.50	-9.14	0.223	-9.59	-9.10	0.223	-9.41	-9.10	0.223	2.60	-3.42
		6845		-8.80	-8.62	0.223	-8.97	-8.71	0.223	-9.09	-8.68	0.223	2.30	-3.18
	8	6885		-9.29	-8.79	0.223	-9.49	-8.95	0.223	-9.50	-9.19	0.223	2.30	-3.50
		7005		-8.08	-8.05	0.223	-8.44	-8.26	0.223	-8.47	-8.31	0.223	2.30	-2.53
		7085		-7.65	-7.44	0.223	-7.82	-7.74	0.223	-8.77	-8.45	0.223	2.30	-2.01

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{3.20/10} + 10^{3.50/10})/2]$= 3.35dBi
6525MHz: Directional gain = $10 \log[(10^{2.50/10} + 10^{2.70/10})/2]$= 2.60dBi
7125MHz: Directional gain = $10 \log[(10^{2.10/10} + 10^{2.50/10})/2]$= 2.30dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan

Tel: +886 2 26099301
Fax: +886 2 26099303

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 0			RU Index 18			RU Index 36				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	26T	-6.24	-5.71	0.223	-5.61	-5.45	0.223	-6.33	-6.27	0.223	3.35	1.05
		6145		-7.09	-7.17	0.223	-6.91	-7.02	0.223	-7.71	-7.62	0.223	3.35	-0.38
		6385		-7.69	-8.02	0.223	-7.29	-7.38	0.223	-8.15	-8.18	0.223	2.60	-1.50
	6	6465		-8.43	-8.09	0.223	-7.84	-7.63	0.223	-8.58	-8.59	0.223	2.60	-1.90
		6545		-8.61	-8.41	0.223	-8.36	-8.16	0.223	-9.28	-8.95	0.223	2.60	-2.43
	7	6625		-9.74	-9.20	0.223	-9.21	-8.46	0.223	-9.98	-9.11	0.223	2.60	-2.99
		6705		-9.90	-8.99	0.223	-9.22	-8.50	0.223	-10.21	-8.96	0.223	2.60	-3.01
		6785		-8.97	-8.47	0.223	-8.33	-7.86	0.223	-9.22	-8.61	0.223	2.60	-2.26
	8	6865		-9.27	-8.60	0.223	-8.78	-8.14	0.223	-9.90	-9.21	0.223	2.30	-2.91
		6945		-8.30	-7.59	0.223	-7.51	-7.25	0.223	-8.61	-8.05	0.223	2.30	-1.84
		7025		-8.59	-8.13	0.223	-8.04	-7.80	0.223	-9.10	-8.71	0.223	2.30	-2.39

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 0			RU Index 18			RU Index 36				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80L)	5	6025	26T	-7.72	-7.93	0.223	-6.63	-6.67	0.223	-6.39	-6.07	0.223	3.35	0.36
		6185		-9.04	-8.67	0.223	-7.90	-7.72	0.223	-7.51	-7.28	0.223	3.35	-0.81
		6345		-9.58	-8.86	0.223	-8.31	-7.65	0.223	-7.94	-7.31	0.223	2.60	-1.78
	6	6505		-9.81	-9.38	0.223	-8.73	-8.28	0.223	-8.28	-7.98	0.223	2.60	-2.29
	7	6665		-10.90	-11.01	0.223	-9.46	-9.67	0.223	-9.08	-9.36	0.223	2.60	-3.38
		6825		-10.22	-10.45	0.223	-8.69	-9.14	0.223	-8.25	-8.75	0.223	2.30	-2.96
	8	6985		-9.41	-9.40	0.223	-8.46	-8.53	0.223	-7.97	-7.83	0.223	2.30	-2.37

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index S0			RU Index S18			RU Index S36				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80H)	5	6025	26T	-6.24	-6.08	0.223	-6.95	-6.47	0.223	-8.56	-8.08	0.223	3.35	0.42
		6185		-7.52	-7.26	0.223	-8.07	-7.84	0.223	-9.55	-9.46	0.223	3.35	-0.80
		6345		-7.93	-7.34	0.223	-8.37	-7.98	0.223	-10.06	-9.71	0.223	2.60	-1.79
	6	6505		-8.23	-8.03	0.223	-9.10	-8.80	0.223	-10.55	-10.57	0.223	2.60	-2.30
	7	6665		-8.82	-9.31	0.223	-9.45	-9.85	0.223	-10.71	-11.29	0.223	2.60	-3.22
		6825		-8.30	-8.88	0.223	-9.15	-9.46	0.223	-10.57	-11.14	0.223	2.30	-3.05
	8	6985		-7.96	-8.05	0.223	-8.74	-8.88	0.223	-10.04	-10.39	0.223	2.30	-2.47

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{3.20/10} + 10^{3.50/10})/2]$= 3.35dBi
6525MHz: Directional gain = $10 \log[(10^{2.50/10} + 10^{2.70/10})/2]$= 2.60dBi
7125MHz: Directional gain = $10 \log[(10^{2.10/10} + 10^{2.50/10})/2]$= 2.30dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Tones: 52T

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 37			RU Index 39			RU Index 40				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE20	5	5955	52T	-3.08	-2.57	0.132	-2.79	-2.67	0.132	-2.92	-2.92	0.132	3.35	3.763
		6175		-4.03	-4.47	0.132	-4.03	-4.30	0.132	-4.19	-4.55	0.132	3.35	2.329
		6415		-4.33	-5.02	0.132	-4.40	-5.03	0.132	-4.66	-5.11	0.132	2.60	1.081
	6	6435		-4.68	-5.02	0.132	-4.52	-4.86	0.132	-4.79	-4.88	0.132	2.60	1.056
		6475		-4.80	-5.12	0.132	-4.87	-4.95	0.132	-4.83	-5.04	0.132	2.60	0.832
		6515		-4.97	-5.15	0.132	-4.79	-5.08	0.132	-4.98	-5.19	0.132	2.60	0.810
	7	6535		-5.67	-6.03	0.132	-5.83	-6.04	0.132	-5.92	-6.09	0.132	2.60	-0.104
		6695		-6.40	-5.89	0.132	-6.05	-5.87	0.132	-6.10	-5.80	0.132	2.60	-0.205
		6855		-5.70	-5.61	0.132	-5.85	-5.49	0.132	-5.84	-5.57	0.132	2.30	-0.212
	8	6875		-6.10	-5.67	0.132	-5.93	-5.55	0.132	-6.01	-5.70	0.132	2.30	-0.294
		6995		-4.98	-4.77	0.132	-5.00	-4.82	0.132	-5.13	-4.90	0.132	2.30	0.569
		7115		-4.65	-4.64	0.132	-4.80	-4.53	0.132	-8.67	-8.32	0.132	2.30	0.797

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 37			RU Index 40			RU Index 44				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE40	5	5965	52T	-3.25	-2.81	0.132	-3.17	-2.95	0.132	-3.14	-2.98	0.132	3.35	3.47
		6165		-4.15	-4.39	0.132	-4.18	-4.55	0.132	-4.24	-4.63	0.132	3.35	2.22
		6405		-4.41	-5.10	0.132	-4.52	-5.05	0.132	-4.67	-5.26	0.132	2.60	1.00
	6	6445		-4.91	-4.97	0.132	-4.86	-5.06	0.132	-4.87	-5.00	0.132	2.60	0.81
		6485		-4.87	-5.12	0.132	-4.81	-5.04	0.132	-4.88	-5.31	0.132	2.60	0.82
	7	6525		-5.19	-5.15	0.132	-5.13	-5.42	0.132	-5.09	-5.36	0.132	2.60	0.57
		6685		-6.22	-5.88	0.132	-6.29	-6.05	0.132	-6.47	-5.81	0.132	2.60	-0.30
		6845		-5.84	-5.46	0.132	-6.06	-5.43	0.132	-6.12	-5.75	0.132	2.30	-0.20
	8	6885		-6.13	-5.60	0.132	-6.24	-5.66	0.132	-6.28	-6.02	0.132	2.30	-0.41
		7005		-5.03	-4.78	0.132	-5.17	-4.99	0.132	-5.36	-5.08	0.132	2.30	0.54
		7085		-4.59	-4.28	0.132	-4.66	-4.46	0.132	-4.99	-4.67	0.132	2.30	1.01

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{3.20/10} + 10^{3.50/10})/2]$= 3.35dBi
6525MHz: Directional gain = $10 \log[(10^{2.50/10} + 10^{2.70/10})/2]$= 2.60dBi
7125MHz: Directional gain = $10 \log[(10^{2.10/10} + 10^{2.50/10})/2]$= 2.30dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan

Tel: +886 2 26099301
Fax: +886 2 26099303

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 37			RU Index 44			RU Index 52				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	52T	-2.84	-3.30	0.132	-2.45	-2.89	0.132	-3.32	-3.28	0.132	3.35	3.83
		6145		-4.29	-4.10	0.132	-3.94	-3.93	0.132	-4.67	-4.61	0.132	3.35	2.56
		6385		-5.06	-4.72	0.132	-4.52	-4.56	0.132	-5.42	-5.39	0.132	2.60	1.20
	6	6465		-5.11	-5.45	0.132	-4.95	-5.09	0.132	-5.46	-5.68	0.132	2.60	0.72
		6545		-5.43	-5.83	0.132	-5.19	-5.53	0.132	-5.80	-6.20	0.132	2.60	0.39
	7	6625		-5.99	-6.82	0.132	-5.85	-6.50	0.132	-6.21	-7.20	0.132	2.60	-0.42
		6705		-6.28	-7.16	0.132	-5.58	-6.84	0.132	-6.08	-7.29	0.132	2.60	-0.42
		6785		-5.49	-6.28	0.132	-5.28	-6.04	0.132	-5.59	-6.46	0.132	2.60	0.10
	8	6865		-5.63	-6.72	0.132	-5.24	-6.40	0.132	-6.19	-7.19	0.132	2.30	-0.34
		6945		-4.99	-5.41	0.132	-4.27	-5.14	0.132	-5.07	-5.73	0.132	2.30	0.76
		7025		-5.31	-5.91	0.132	-4.97	-5.52	0.132	-5.61	-6.29	0.132	2.30	0.21

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 37			RU Index 44			RU Index 52				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80L)	5	6025	52T	-4.43	-4.55	0.132	-3.46	-3.44	0.132	-3.05	-2.89	0.132	3.35	3.52
		6185		-5.80	-5.39	0.132	-4.75	-4.52	0.132	-4.30	-4.12	0.132	3.35	2.28
		6345		-6.28	-5.93	0.132	-5.21	-4.54	0.132	-4.64	-4.17	0.132	2.60	1.34
	6	6505		-6.47	-6.51	0.132	-5.62	-5.47	0.132	-5.16	-4.99	0.132	2.60	0.67
	7	6665		-7.60	-7.85	0.132	-6.25	-6.72	0.132	-5.95	-6.28	0.132	2.60	-0.37
		6825		-7.07	-7.38	0.132	-5.93	-6.20	0.132	-5.40	-5.74	0.132	2.30	-0.12
	8	6985		-5.90	-6.40	0.132	-5.06	-5.38	0.132	-4.89	-5.02	0.132	2.30	0.49

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index S37			RU Index S44			RU Index S52				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80H)	5	6025	52T	-2.98	-3.02	0.132	-3.59	-3.42	0.132	-5.30	-5.02	0.132	3.35	3.49
		6185		-4.48	-4.09	0.132	-5.06	-4.78	0.132	-6.24	-6.37	0.132	3.35	2.21
		6345		-4.63	-4.30	0.132	-5.20	-4.69	0.132	-6.97	-6.37	0.132	2.60	1.28
	6	6505		-4.99	-4.99	0.132	-5.99	-5.55	0.132	-7.46	-7.09	0.132	2.60	0.75
	7	6665		-5.83	-6.35	0.132	-6.36	-6.86	0.132	-7.58	-8.33	0.132	2.60	-0.34
		6825		-5.26	-6.01	0.132	-6.01	-6.53	0.132	-7.60	-8.11	0.132	2.30	-0.18
	8	6985		-4.82	-5.24	0.132	-5.57	-5.54	0.132	-7.25	-7.24	0.132	2.30	0.42

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{3.20/10} + 10^{3.50/10})/2]$= 3.35dBi
6525MHz: Directional gain = $10 \log[(10^{2.50/10} + 10^{2.70/10})/2]$= 2.60dBi
7125MHz: Directional gain = $10 \log[(10^{2.10/10} + 10^{2.50/10})/2]$= 2.30dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Tones: 106T

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 53			RU Index 54				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE20	5	5955	106T	0.15	0.21	N/A	-0.09	0.20	N/A	3.35	6.54
		6175		-0.98	-1.18	N/A	-1.14	-1.34	N/A	3.35	5.28
		6415		-1.26	-1.88	N/A	-1.52	-2.09	N/A	2.60	4.05
	6	6435		-1.76	-1.67	N/A	-1.54	-1.76	N/A	2.60	3.96
		6475		-1.66	-1.89	N/A	-1.78	-1.93	N/A	2.60	3.84
		6515		-1.91	-1.93	N/A	-1.84	-2.11	N/A	2.60	3.69
	7	6535		-2.73	-2.95	N/A	-2.85	-2.99	N/A	2.60	2.77
		6695		-3.30	-2.93	N/A	-3.08	-2.89	N/A	2.60	2.63
		6855		-2.73	-2.36	N/A	-2.80	-2.53	N/A	2.30	2.77
	8	6875		-2.97	-2.45	N/A	-2.97	-2.71	N/A	2.30	2.61
		6995		-1.75	-1.82	N/A	-1.91	-1.95	N/A	2.30	3.53
		7115		-1.58	-1.46	N/A	-8.74	-8.12	N/A	2.30	3.79

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 53			RU Index 54			RU Index 56				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE40	5	5965	106T	-0.03	0.17	N/A	0.04	0.21	N/A	0.06	-0.10	N/A	3.35	6.49
		6165		-1.04	-1.32	N/A	-1.21	-1.38	N/A	-1.27	-1.45	N/A	3.35	5.18
		6405		-1.50	-2.06	N/A	-1.55	-1.93	N/A	-1.72	-2.23	N/A	2.60	3.87
	6	6445		-1.72	-1.85	N/A	-1.46	-1.83	N/A	-1.66	-1.86	N/A	2.60	3.97
		6485		-1.85	-1.97	N/A	-1.64	-1.99	N/A	-2.00	-2.06	N/A	2.60	3.80
	7	6525		-2.00	-2.14	N/A	-2.01	-2.32	N/A	-2.00	-2.47	N/A	2.60	3.54
		6685		-3.25	-2.96	N/A	-3.29	-2.87	N/A	-3.32	-2.77	N/A	2.60	2.57
		6845		-2.74	-2.34	N/A	-2.91	-2.35	N/A	-3.07	-2.56	N/A	2.30	2.77
	8	6885		-3.06	-2.70	N/A	-3.17	-2.75	N/A	-3.26	-2.99	N/A	2.30	2.43
		7005		-2.04	-1.81	N/A	-1.91	-1.94	N/A	-2.22	-2.08	N/A	2.30	3.39
		7085		-1.64	-1.41	N/A	-1.74	-1.40	N/A	-1.86	-1.54	N/A	2.30	3.79

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{3.20/10} + 10^{3.50/10})/2]$= 3.35dBi
6525MHz: Directional gain = $10 \log[(10^{2.50/10} + 10^{2.70/10})/2]$= 2.60dBi
7125MHz: Directional gain = $10 \log[(10^{2.10/10} + 10^{2.50/10})/2]$= 2.30dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 53			RU Index 56			RU Index 60				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	106T	-0.18	-0.30	N/A	0.46	0.10	N/A	-0.33	-0.43	N/A	3.35	6.64
		6145		-1.32	-1.18	N/A	-1.26	-0.96	N/A	-1.62	-1.75	N/A	3.35	5.25
		6385		-2.09	-1.83	N/A	-1.82	-1.57	N/A	-2.45	-2.27	N/A	2.60	3.92
	6	6465		-2.07	-2.43	N/A	-1.65	-2.14	N/A	-2.36	-2.65	N/A	2.60	3.72
		6545		-2.28	-2.85	N/A	-2.24	-2.66	N/A	-2.87	-3.21	N/A	2.60	3.17
	7	6625		-3.23	-3.86	N/A	-2.85	-3.58	N/A	-3.08	-4.17	N/A	2.60	2.41
		6705		-3.09	-4.19	N/A	-2.69	-3.96	N/A	-3.05	-4.42	N/A	2.60	2.33
		6785		-2.00	-3.02	N/A	-1.77	-2.81	N/A	-2.45	-3.40	N/A	2.60	3.35
	8	6865		-2.53	-3.37	N/A	-2.34	-3.11	N/A	-2.83	-3.81	N/A	2.30	2.60
		6945		-1.58	-2.25	N/A	-1.33	-1.93	N/A	-2.15	-2.47	N/A	2.30	3.69
		7025		-2.10	-2.41	N/A	-1.65	-2.40	N/A	-2.53	-3.02	N/A	2.30	3.30

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 53			RU Index 56			RU Index 60				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80L)	5	6025	106T	-1.49	-1.46	N/A	-0.35	-0.41	N/A	0.05	0.24	N/A	3.35	6.51
		6185		-2.64	-2.37	N/A	-1.61	-1.41	N/A	-1.33	-1.24	N/A	3.35	5.08
		6345		-3.38	-2.51	N/A	-2.17	-1.60	N/A	-1.76	-1.13	N/A	2.60	4.18
	6	6505		-3.27	-3.25	N/A	-2.32	-2.27	N/A	-1.98	-1.94	N/A	2.60	3.65
	7	6665		-4.59	-4.71	N/A	-3.60	-3.49	N/A	-2.84	-3.06	N/A	2.60	2.66
		6825		-4.03	-3.89	N/A	-3.24	-3.12	N/A	-2.56	-2.39	N/A	2.30	2.84
	8	6985		-3.04	-2.90	N/A	-2.07	-2.08	N/A	-1.70	-1.70	N/A	2.30	3.61

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index S53			RU Index S56			RU Index S60				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80H)	5	6025	106T	0.06	0.00	N/A	-0.69	-0.35	N/A	-2.19	-1.85	N/A	3.35	6.39
		6185		-1.45	-1.02	N/A	-1.85	-1.74	N/A	-3.35	-3.31	N/A	3.35	5.13
		6345		-1.64	-1.32	N/A	-2.23	-1.67	N/A	-3.53	-3.10	N/A	2.60	4.13
	6	6505		-2.18	-1.95	N/A	-2.58	-2.38	N/A	-4.07	-4.10	N/A	2.60	3.55
	7	6665		-3.07	-3.34	N/A	-3.66	-3.64	N/A	-5.15	-4.94	N/A	2.60	2.41
		6825		-2.46	-2.40	N/A	-3.21	-3.07	N/A	-4.60	-4.76	N/A	2.30	2.88
	8	6985		-1.68	-1.65	N/A	-2.56	-2.18	N/A	-4.00	-3.76	N/A	2.30	3.65

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{3.20/10} + 10^{3.50/10})/2]$= 3.35dBi
6525MHz: Directional gain = $10 \log[(10^{2.50/10} + 10^{2.70/10})/2]$= 2.60dBi
7125MHz: Directional gain = $10 \log[(10^{2.10/10} + 10^{2.50/10})/2]$= 2.30dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Tones: 242T

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm) RU Index 61 AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
802.11ax-HE20	5	5955	242T	1.95	2.38	0.15	3.35	8.68
		6175		1.79	2.2	0.15	3.35	8.51
		6415		1.76	2.23	0.15	2.60	7.76
	6	6435		1.2	1.69	0.15	2.60	7.21
		6475		1.26	1.64	0.15	2.60	7.21
		6515		1.66	1.57	0.15	2.60	7.38
	7	6535		1.21	1.42	0.15	2.60	7.08
		6695		1.57	1.61	0.15	2.60	7.35
		6855		1.33	1.52	0.15	2.30	6.89
	8	6875		0.81	1.01	0.15	2.30	6.37
		6995		0.76	0.7	0.15	2.30	6.19
		7115		-2.98	-2.9	0.15	2.30	2.52

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm) RU Index 61 AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	RU Index 62 AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
802.11ax-HE40	5	5965	242T	1.88	1.2	0.15	1.65	1.01	0.15	3.35	8.06
		6165		1.58	1.28	0.15	1.31	0.99	0.15	3.35	7.94
		6405		1.58	1.1	0.15	1.41	1.19	0.15	2.60	7.11
	6	6445		0.93	0.97	0.15	1.17	0.92	0.15	2.60	6.81
		6485		1.02	0.62	0.15	0.78	1.25	0.15	2.60	6.78
	7	6525		1.14	0.76	0.15	1.97	1.26	0.15	2.60	7.39
		6685		0.89	0.04	0.15	1.24	0.09	0.15	2.60	6.46
		6845		0.9	-0.16	0.15	1.18	0.05	0.15	2.30	6.11
	8	6885		0.64	-0.27	0.15	0.51	-0.29	0.15	2.30	5.67
		7005		0.54	-0.46	0.15	0.73	-0.38	0.15	2.30	5.67
		7085		0.75	-0.15	0.15	1.01	0.25	0.15	2.30	6.11

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = 10 log[$(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}$] dBi
Directional gain:
5925MHz: Directional gain = 10 log[$(10^{3.20/10} + 10^{3.50/10})/2$]= 3.35dBi
6525MHz: Directional gain = 10 log[$(10^{2.50/10} + 10^{2.70/10})/2$]= 2.60dBi
7125MHz: Directional gain = 10 log[$(10^{2.10/10} + 10^{2.50/10})/2$]= 2.30dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 61			RU Index 62			RU Index 64				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	242T	2.21	2.52	0.15	2.15	2.62	0.15	2.13	2.17	0.15	3.35	8.90
		6145		2.33	2.38	0.15	2.36	2.3	0.15	2.03	2.09	0.15	3.35	8.87
		6385		1.95	1.9	0.15	2.15	2.23	0.15	2.12	2.27	0.15	2.60	7.96
	6	6465		1.59	1.48	0.15	2.61	2.58	0.15	1.59	1.42	0.15	2.60	8.36
		6545		1.24	1.88	0.15	2.09	2.68	0.15	1.82	2.18	0.15	2.60	8.16
	7	6625		0.72	1.37	0.15	0.96	1.6	0.15	0.66	1.49	0.15	2.60	7.05
		6705		0.89	1.61	0.15	1.01	1.62	0.15	0.71	1.53	0.15	2.60	7.09
		6785		0.78	1.45	0.15	0.77	1.53	0.15	0.57	1.6	0.15	2.60	6.93
	8	6865		0.65	1.19	0.15	1.08	1.64	0.15	0.18	0.57	0.15	2.30	6.83
		6945		0.28	0.77	0.15	1.21	1.85	0.15	0.32	0.75	0.15	2.30	7.00
		7025		0.02	0.7	0.15	1.03	1.71	0.15	-0.3	0.88	0.15	2.30	6.84

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 61			RU Index 62			RU Index 64				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80L)	5	6025	242T	1.72	2.48	0.15	2.11	2.92	0.15	1.5	2.32	0.15	3.35	9.04
		6185		1.65	2.27	0.15	1.96	2.73	0.15	1.56	2.24	0.15	3.35	8.87
		6345		1.65	2.36	0.15	2.21	2.35	0.15	1.63	2.3	0.15	2.60	8.04
	6	6505		1.37	1.83	0.15	2.39	2.82	0.15	1.35	1.68	0.15	2.60	8.37
	7	6665		-0.12	1.3	0.15	0.44	1.61	0.15	0	1.66	0.15	2.60	6.82
		6825		-0.27	1.24	0.15	0.25	1.49	0.15	-0.45	0.97	0.15	2.30	6.37
	8	6985		-0.75	0.48	0.15	0.53	1.75	0.15	-0.94	0.73	0.15	2.30	6.64

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index S61			RU Index S62			RU Index S64				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80H)	5	6025	242T	1.26	2.51	0.15	1.3	2.41	0.15	1.5	2.3	0.15	3.35	8.44
		6185		1.6	2.3	0.15	1.32	2.27	0.15	1.7	2.41	0.15	3.35	8.58
		6345		1.65	2.18	0.15	1.41	2.16	0.15	1.79	2.28	0.15	2.60	7.80
	6	6505		1.43	1.69	0.15	1.9	2.43	0.15	1.62	2.37	0.15	2.60	7.93
	7	6665		-0.39	1.41	0.15	-0.7	1.19	0.15	-0.65	1.49	0.15	2.60	6.36
		6825		-0.77	1.13	0.15	0.07	1.22	0.15	-0.51	0.73	0.15	2.30	6.14
	8	6985		-0.72	0.55	0.15	-0.02	1.35	0.15	-0.55	0.87	0.15	2.30	6.18

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{3.20/10} + 10^{3.50/10})/2]$= 3.35dBi
6525MHz: Directional gain = $10 \log[(10^{2.50/10} + 10^{2.70/10})/2]$= 2.60dBi
7125MHz: Directional gain = $10 \log[(10^{2.10/10} + 10^{2.50/10})/2]$= 2.30dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Tones: 484T

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)			Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 65				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE40	5	5965	484T	5.17	5.38	N/A	3.35	11.64
		6165		4.96	5.25	N/A	3.35	11.47
		6405		4.96	5	N/A	2.60	10.59
	6	6445		5.11	5.45	N/A	2.60	10.89
		6485		5.14	5.3	N/A	2.60	10.83
	7	6525		5.24	5.26	N/A	2.60	10.86
		6685		4.57	4.7	N/A	2.60	10.25
		6845		4.44	4.44	N/A	2.30	9.75
	8	6885		4.63	4.64	N/A	2.30	9.95
		7005		4.34	4.3	N/A	2.30	9.63
		7085		4.62	4.85	N/A	2.30	10.05

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 65			RU Index 66				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	484T	5.23	5.13	N/A	5.08	5.27	N/A	3.35	11.54
		6145		5.2	5.19	N/A	5.25	4.99	N/A	3.35	11.56
		6385		4.82	5.01	N/A	5.21	4.95	N/A	2.60	10.69
	6	6465		5.2	4.94	N/A	5.14	5.2	N/A	2.60	10.78
		6545		4.89	5.39	N/A	4.91	5.02	N/A	2.60	10.76
	7	6625		4.2	4.29	N/A	4.08	4.27	N/A	2.60	9.86
		6705		4.22	4.18	N/A	4.09	4.46	N/A	2.60	9.89
		6785		3.9	4.35	N/A	4.23	4.51	N/A	2.60	9.98
	8	6865		3.99	4.33	N/A	4.25	4.38	N/A	2.30	9.63
		6945		4.45	4.11	N/A	4.17	4.37	N/A	2.30	9.59
		7025		4.08	4.38	N/A	4.26	4.3	N/A	2.30	9.59

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{3.20/10} + 10^{3.50/10})/2]$= 3.35dBi
6525MHz: Directional gain = $10 \log[(10^{2.50/10} + 10^{2.70/10})/2]$= 2.60dBi
7125MHz: Directional gain = $10 \log[(10^{2.10/10} + 10^{2.50/10})/2]$= 2.30dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 65			RU Index 66				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80L)	5	6025	484T	4.72	5.15	N/A	4.41	5.38	N/A	3.35	11.30
		6185		4.79	5.09	N/A	4.82	5.03	N/A	3.35	11.30
		6345		4.69	4.93	N/A	4.79	5.04	N/A	2.60	10.53
	6	6505		5.09	4.96	N/A	5.07	5.25	N/A	2.60	10.77
	7	6665		3.83	4.41	N/A	3.38	4.28	N/A	2.60	9.74
		6825		3.72	4.23	N/A	3.58	4.48	N/A	2.30	9.36
	8	6985		4.12	4.12	N/A	3.85	4.47	N/A	2.30	9.48

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index S65			RU Index S66				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80H)	5	6025	484T	4.58	5.13	N/A	4.6	5.14	N/A	3.35	11.24
		6185		4.68	5.09	N/A	4.64	4.97	N/A	3.35	11.25
		6345		4.51	5.07	N/A	4.7	4.92	N/A	2.60	10.42
	6	6505		4.8	5.3	N/A	4.68	5.02	N/A	2.60	10.67
	7	6665		3.72	4.23	N/A	3.79	4.36	N/A	2.60	9.69
		6825		3.87	4.33	N/A	3.89	4.43	N/A	2.30	9.48
	8	6985		3.97	4.31	N/A	3.8	4.64	N/A	2.30	9.55

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = 10 log[($10^{G1/10}$ + $10^{G2/10}$ + … + $10^{GN/10}$)/N_{ANT}] dBi
Directional gain:
5925MHz: Directional gain = 10 log[($10^{3.20/10}$ +$10^{3.50/10}$)/2]= 3.35dBi
6525MHz: Directional gain = 10 log[($10^{2.50/10}$ +$10^{2.70/10}$)/2]= 2.60dBi
7125MHz: Directional gain = 10 log[($10^{2.10/10}$ +$10^{2.50/10}$)/2]= 2.30dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Tones: 996T

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)			Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 67				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	996T	7	6.29	0.159	3.35	13.18
		6145		6.97	6.01	0.159	3.35	13.04
		6385		7.34	6.33	0.159	2.60	12.63
	6	6465		7.21	6.08	0.159	2.60	12.45
		6545		7.31	6.06	0.159	2.60	12.50
	7	6625		6.62	5.32	0.159	2.60	11.79
		6705		6.26	5.04	0.159	2.60	11.46
		6785		6.11	4.98	0.159	2.60	11.35
	8	6865		5.97	5.09	0.159	2.30	11.02
		6945		6.43	5.32	0.159	2.30	11.38
		7025		6.53	5.59	0.159	2.30	11.55

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 67			RU Index S67				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160	5	6025	996T	7.35	6.54	0.159	7.17	6.64	0.159	3.35	13.48
		6185		7.44	6.76	0.159	7.53	6.55	0.159	3.35	13.63
		6345		7.66	6.48	0.159	7.36	6.67	0.159	2.60	12.88
	6	6505		6.93	5.96	0.159	6.89	6.03	0.159	2.60	12.25
	7	6665		6.68	5.47	0.159	6.53	5.32	0.159	2.60	11.89
		6825		6.39	5.49	0.159	5.95	5.29	0.159	2.30	11.43
	8	6985		6.4	5.52	0.159	6.31	5.46	0.159	2.30	11.45

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = 10 log[($10^{G1/10}$ + $10^{G2/10}$ + … + $10^{GN/10}$)/N_{ANT}] dBi
Directional gain:
5925MHz: Directional gain = 10 log[($10^{3.20/10}$ +$10^{3.50/10}$)/2]= 3.35dBi
6525MHz: Directional gain = 10 log[($10^{2.50/10}$ +$10^{2.70/10}$)/2]= 2.60dBi
7125MHz: Directional gain = 10 log[($10^{2.10/10}$ +$10^{2.50/10}$)/2]= 2.30dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Test SKU: SKU #2 [with (LUXSHARE-ICT) L1LRF009-CS-H Antenna]

- OFDM Modulation

Modulation Type	U-NII Band	Centre Frequency (MHz)	Average Coneduted Output Power (dBm)		Duty Cycle Factor (dB) 10log(1/X)	Directional Gain (dBi) Note3	Total E.I.R.P. (dBm) Note2	Limit
			AUX	Main				
802.11ax-HE20	5	5955	1.47	1.21	N/A	4.49	8.84	24dBm
		6175	1.50	1.14		4.49	8.82	
		6415	1.19	1.11		1.29	5.45	
	6	6435	1.25	1.30		1.29	5.58	
		6475	1.49	1.42		1.29	5.76	
		6515	1.42	1.23		1.29	5.63	
	7	6535	0.77	0.44		1.29	4.91	
		6695	0.84	0.09		1.29	4.78	
		6855	0.93	0.09		3.07	6.61	
	8	6875	0.90	0.35		3.07	6.71	
		6995	0.84	0.09		3.07	6.56	
		7115	-3.48	-2.97		3.07	2.86	
802.11ax-HE40	5	5965	5.03	5.17	N/A	4.49	12.60	
		6165	4.97	5.11		4.49	12.54	
		6405	4.74	4.97		1.29	9.16	
	6	6445	4.90	5.24		1.29	9.37	
		6485	4.91	4.99		1.29	9.25	
	7	6525	5.05	5.06		1.29	9.36	
		6685	4.31	4.03		1.29	8.47	
		6845	4.33	3.96		3.07	10.23	
	8	6885	4.38	4.17		3.07	10.36	
		7005	4.37	3.89		3.07	10.22	
		7085	4.56	4.29		3.07	10.51	

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. According to KDB 662911 D01 E)1), Total E.I.R.P. (dBm) = Sum to individual output power (dBm)+ Directional gain (dBi) + duty cycle factor(dB) when duty cycle is less than 98%.
3. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{2.48/10} + 10^{5.85/10})/2]$= 4.49dBi
6525MHz: Directional gain = $10 \log[(10^{1.38/10} + 10^{1.19/10})/2]$= 1.29dBi
7125MHz: Directional gain = $10 \log[(10^{1.89/10} + 10^{3.99/10})/2]$= 3.07dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Modulation Type	U-NII Band	Centre Frequency (MHz)	Average Coneduted Output Power (dBm)		Duty Cycle Factor (dB) 10log(1/X)	Directional Gain (dBi) Note3	Total E.I.R.P. (dBm) Note2	Limit
			AUX	Main				
802.11ax-HE80	5	5985	7.06	6.67	N/A	4.49	14.37	24dBm
		6145	6.93	6.25		4.49	14.10	
		6385	7.23	6.71		1.29	11.28	
	6	6465	7.24	6.32		1.29	11.10	
		6545	7.05	6.43		1.29	11.05	
	7	6625	6.11	5.55		1.29	10.14	
		6705	6.21	5.25		1.29	10.06	
		6785	6.19	5.19		1.29	10.02	
	8	6865	5.92	5.33		3.07	11.72	
		6945	6.34	5.43		3.07	11.99	
		7025	6.35	5.76		3.07	12.15	
802.11ax-HE160	5	6025	9.93	9.15	N/A	4.49	17.06	
		6185	9.85	9.15		4.49	17.01	
		6345	10.04	9.43		1.29	14.05	
	6	6505	9.82	9.11		1.29	13.78	
	7	6665	9.08	8.20		1.29	12.96	
		6825	8.99	8.25		3.07	14.72	
	8	6985	9.37	8.48		3.07	15.03	

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. According to KDB 662911 D01 E)1), Total E.I.R.P. (dBm) = Sum to individual output power (dBm)+ Directional gain (dBi) + duty cycle factor(dB) when duty cycle is less than 98%.
3. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{2.48/10} + 10^{5.85/10})/2]$= 4.49dBi
6525MHz: Directional gain = $10 \log[(10^{1.38/10} + 10^{1.19/10})/2]$= 1.29dBi
7125MHz: Directional gain = $10 \log[(10^{1.89/10} + 10^{3.99/10})/2]$= 3.07dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

● OFDMA Modulation

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 0			RU Index 4			RU Index 8				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE20	5	5955	26T	-6.16	-5.88	0.223	-6.03	-5.95	0.223	-6.29	-6.16	0.223	4.49	1.73
		6175		-7.53	-7.63	0.223	-7.10	-7.47	0.223	-7.44	-7.74	0.223	4.49	0.44
		6415		-7.80	-8.14	0.223	-7.62	-8.01	0.223	-8.10	-8.23	0.223	1.29	-3.29
	6	6435		-7.68	-8.01	0.223	-7.77	-7.83	0.223	-7.93	-8.14	0.223	1.29	-3.28
		6475		-8.16	-8.14	0.223	-7.83	-8.13	0.223	-7.98	-8.42	0.223	1.29	-3.45
		6515		-8.23	-8.42	0.223	-7.84	-8.20	0.223	-8.40	-8.55	0.223	1.29	-3.49
	7	6535		-8.95	-9.10	0.223	-8.99	-9.08	0.223	-9.12	-9.31	0.223	1.29	-4.50
		6695		-9.54	-9.00	0.223	-9.38	-8.78	0.223	-9.67	-9.04	0.223	1.29	-4.55
		6855		-8.88	-8.72	0.223	-8.98	-8.49	0.223	-8.98	-8.87	0.223	3.07	-2.42
	8	6875		-9.18	-8.91	0.223	-9.29	-8.56	0.223	-9.57	-8.84	0.223	3.07	-2.61
		6995		-8.30	-7.97	0.223	-8.05	-7.94	0.223	-8.23	-8.08	0.223	3.07	-1.69
		7115		-8.08	-7.73	0.223	-7.75	-7.59	0.223	-8.00	-7.66	0.223	3.07	-1.37

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 0			RU Index 8			RU Index 17				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE40	5	5965	26T	-6.35	-5.95	0.223	-6.08	-6.12	0.223	-6.21	-6.06	0.223	4.49	1.62
		6165		-7.22	-7.41	0.223	-7.30	-7.65	0.223	-7.32	-7.68	0.223	4.49	0.41
		6405		-7.64	-8.10	0.223	-7.80	-8.12	0.223	-7.96	-8.27	0.223	1.29	-3.34
	6	6445		-7.83	-7.99	0.223	-8.19	-8.07	0.223	-8.07	-8.16	0.223	1.29	-3.39
		6485		-8.11	-8.08	0.223	-8.34	-8.28	0.223	-8.18	-8.54	0.223	1.29	-3.57
	7	6525		-8.19	-8.44	0.223	-8.32	-8.49	0.223	-8.28	-8.49	0.223	1.29	-3.79
		6685		-9.50	-9.14	0.223	-9.59	-9.10	0.223	-9.41	-9.10	0.223	1.29	-4.73
		6845		-8.80	-8.62	0.223	-8.97	-8.71	0.223	-9.09	-8.68	0.223	3.07	-2.41
	8	6885		-9.29	-8.79	0.223	-9.49	-8.95	0.223	-9.50	-9.19	0.223	3.07	-2.73
		7005		-8.08	-8.05	0.223	-8.44	-8.26	0.223	-8.47	-8.31	0.223	3.07	-1.76
		7085		-7.65	-7.44	0.223	-7.82	-7.74	0.223	-8.77	-8.45	0.223	3.07	-1.24

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = 10 log[($10^{G1/10}$ + $10^{G2/10}$ + … + $10^{GN/10}$)/N_{ANT}] dBi
Directional gain:
5925MHz: Directional gain = 10 log[($10^{2.48/10}$ +$10^{5.85/10}$)/2]= 4.49dBi
6525MHz: Directional gain = 10 log[($10^{1.38/10}$ +$10^{1.19/10}$)/2]= 1.29dBi
7125MHz: Directional gain = 10 log[($10^{1.89/10}$ +$10^{3.99/10}$)/2]= 3.07dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 0			RU Index 18			RU Index 36				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	26T	-6.24	-5.71	0.223	-5.61	-5.45	0.223	-6.33	-6.27	0.223	4.49	2.19
		6145		-7.09	-7.17	0.223	-6.91	-7.02	0.223	-7.71	-7.62	0.223	4.49	0.76
		6385		-7.69	-8.02	0.223	-7.29	-7.38	0.223	-8.15	-8.18	0.223	1.29	-2.81
	6	6465		-8.43	-8.09	0.223	-7.84	-7.63	0.223	-8.58	-8.59	0.223	1.29	-3.21
		6545		-8.61	-8.41	0.223	-8.36	-8.16	0.223	-9.28	-8.95	0.223	1.29	-3.74
	7	6625		-9.74	-9.20	0.223	-9.21	-8.46	0.223	-9.98	-9.11	0.223	1.29	-4.30
		6705		-9.90	-8.99	0.223	-9.22	-8.50	0.223	-10.21	-8.96	0.223	1.29	-4.32
		6785		-8.97	-8.47	0.223	-8.33	-7.86	0.223	-9.22	-8.61	0.223	1.29	-3.57
	8	6865		-9.27	-8.60	0.223	-8.78	-8.14	0.223	-9.90	-9.21	0.223	3.07	-2.14
		6945		-8.30	-7.59	0.223	-7.51	-7.25	0.223	-8.61	-8.05	0.223	3.07	-1.07
		7025		-8.59	-8.13	0.223	-8.04	-7.80	0.223	-9.10	-8.71	0.223	3.07	-1.62

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 0			RU Index 18			RU Index 36				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80L)	5	6025	26T	-7.72	-7.93	0.223	-6.63	-6.67	0.223	-6.39	-6.07	0.223	4.49	1.50
		6185		-9.04	-8.67	0.223	-7.90	-7.72	0.223	-7.51	-7.28	0.223	4.49	0.33
		6345		-9.58	-8.86	0.223	-8.31	-7.65	0.223	-7.94	-7.31	0.223	1.29	-3.09
	6	6505		-9.81	-9.38	0.223	-8.73	-8.28	0.223	-8.28	-7.98	0.223	1.29	-3.60
	7	6665		-10.90	-11.01	0.223	-9.46	-9.67	0.223	-9.08	-9.36	0.223	1.29	-4.69
		6825		-10.22	-10.45	0.223	-8.69	-9.14	0.223	-8.25	-8.75	0.223	3.07	-2.19
	8	6985		-9.41	-9.40	0.223	-8.46	-8.53	0.223	-7.97	-7.83	0.223	3.07	-1.60

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index S0			RU Index S18			RU Index S36				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80H)	5	6025	26T	-6.24	-6.08	0.223	-6.95	-6.47	0.223	-8.56	-8.08	0.223	4.49	1.56
		6185		-7.52	-7.26	0.223	-8.07	-7.84	0.223	-9.55	-9.46	0.223	4.49	0.34
		6345		-7.93	-7.34	0.223	-8.37	-7.98	0.223	-10.06	-9.71	0.223	1.29	-3.10
	6	6505		-8.23	-8.03	0.223	-9.10	-8.80	0.223	-10.55	-10.57	0.223	1.29	-3.61
	7	6665		-8.82	-9.31	0.223	-9.45	-9.85	0.223	-10.71	-11.29	0.223	1.29	-4.53
		6825		-8.30	-8.88	0.223	-9.15	-9.46	0.223	-10.57	-11.14	0.223	3.07	-2.28
	8	6985		-7.96	-8.05	0.223	-8.74	-8.88	0.223	-10.04	-10.39	0.223	3.07	-1.70

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{2.48/10} + 10^{5.85/10})/2]$= 4.49dBi
6525MHz: Directional gain = $10 \log[(10^{1.38/10} + 10^{1.19/10})/2]$= 1.29dBi
7125MHz: Directional gain = $10 \log[(10^{1.89/10} + 10^{3.99/10})/2]$= 3.07dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Tones: 52T

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 37			RU Index 39			RU Index 40				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE20	5	5955	52T	-3.08	-2.57	0.132	-2.79	-2.67	0.132	-2.92	-2.92	0.132	4.49	3.469
		6175		-4.03	-4.47	0.132	-4.03	-4.30	0.132	-4.19	-4.55	0.132	4.49	-0.229
		6415		-4.33	-5.02	0.132	-4.40	-5.03	0.132	-4.66	-5.11	0.132	1.29	-0.254
	6	6435		-4.68	-5.02	0.132	-4.52	-4.86	0.132	-4.79	-4.88	0.132	1.29	-0.478
		6475		-4.80	-5.12	0.132	-4.87	-4.95	0.132	-4.83	-5.04	0.132	1.29	-0.500
		6515		-4.97	-5.15	0.132	-4.79	-5.08	0.132	-4.98	-5.19	0.132	1.29	-1.414
	7	6535		-5.67	-6.03	0.132	-5.83	-6.04	0.132	-5.92	-6.09	0.132	1.29	-1.515
		6695		-6.40	-5.89	0.132	-6.05	-5.87	0.132	-6.10	-5.80	0.132	1.29	0.558
		6855		-5.70	-5.61	0.132	-5.85	-5.49	0.132	-5.84	-5.57	0.132	3.07	0.476
	8	6875		-6.10	-5.67	0.132	-5.93	-5.55	0.132	-6.01	-5.70	0.132	3.07	1.339
		6995		-4.98	-4.77	0.132	-5.00	-4.82	0.132	-5.13	-4.90	0.132	3.07	1.567
		7115		-4.65	-4.64	0.132	-4.80	-4.53	0.132	-8.67	-8.32	0.132	3.07	3.469

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 37			RU Index 40			RU Index 44				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE40	5	5965	52T	-3.25	-2.81	0.132	-3.17	-2.95	0.132	-3.14	-2.98	0.132	4.49	4.61
		6165		-4.15	-4.39	0.132	-4.18	-4.55	0.132	-4.24	-4.63	0.132	4.49	3.36
		6405		-4.41	-5.10	0.132	-4.52	-5.05	0.132	-4.67	-5.26	0.132	1.29	-0.31
	6	6445		-4.91	-4.97	0.132	-4.86	-5.06	0.132	-4.87	-5.00	0.132	1.29	-0.50
		6485		-4.87	-5.12	0.132	-4.81	-5.04	0.132	-4.88	-5.31	0.132	1.29	-0.49
	7	6525		-5.19	-5.15	0.132	-5.13	-5.42	0.132	-5.09	-5.36	0.132	1.29	-0.74
		6685		-6.22	-5.88	0.132	-6.29	-6.05	0.132	-6.47	-5.81	0.132	1.29	-1.61
		6845		-5.84	-5.46	0.132	-6.06	-5.43	0.132	-6.12	-5.75	0.132	3.07	0.57
	8	6885		-6.13	-5.60	0.132	-6.24	-5.66	0.132	-6.28	-6.02	0.132	3.07	0.36
		7005		-5.03	-4.78	0.132	-5.17	-4.99	0.132	-5.36	-5.08	0.132	3.07	1.31
		7085		-4.59	-4.28	0.132	-4.66	-4.46	0.132	-4.99	-4.67	0.132	3.07	1.78

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{2.48/10} + 10^{5.85/10})/2]$= 4.49dBi
6525MHz: Directional gain = $10 \log[(10^{1.38/10} + 10^{1.19/10})/2]$= 1.29dBi
7125MHz: Directional gain = $10 \log[(10^{1.89/10} + 10^{3.99/10})/2]$= 3.07dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan

Tel: +886 2 26099301
Fax: +886 2 26099303

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 37			RU Index 44			RU Index 52				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	52T	-2.84	-3.30	0.132	-2.45	-2.89	0.132	-3.32	-3.28	0.132	4.49	4.97
		6145		-4.29	-4.10	0.132	-3.94	-3.93	0.132	-4.67	-4.61	0.132	4.49	3.70
		6385		-5.06	-4.72	0.132	-4.52	-4.56	0.132	-5.42	-5.39	0.132	1.29	-0.11
	6	6465		-5.11	-5.45	0.132	-4.95	-5.09	0.132	-5.46	-5.68	0.132	1.29	-0.59
		6545		-5.43	-5.83	0.132	-5.19	-5.53	0.132	-5.80	-6.20	0.132	1.29	-0.92
	7	6625		-5.99	-6.82	0.132	-5.85	-6.50	0.132	-6.21	-7.20	0.132	1.29	-1.73
		6705		-6.28	-7.16	0.132	-5.58	-6.84	0.132	-6.08	-7.29	0.132	1.29	-1.73
		6785		-5.49	-6.28	0.132	-5.28	-6.04	0.132	-5.59	-6.46	0.132	1.29	-1.21
	8	6865		-5.63	-6.72	0.132	-5.24	-6.40	0.132	-6.19	-7.19	0.132	3.07	0.43
		6945		-4.99	-5.41	0.132	-4.27	-5.14	0.132	-5.07	-5.73	0.132	3.07	1.53
		7025		-5.31	-5.91	0.132	-4.97	-5.52	0.132	-5.61	-6.29	0.132	3.07	0.98

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 37			RU Index 44			RU Index 52				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80L)	5	6025	52T	-4.43	-4.55	0.132	-3.46	-3.44	0.132	-3.05	-2.89	0.132	4.49	4.66
		6185		-5.80	-5.39	0.132	-4.75	-4.52	0.132	-4.30	-4.12	0.132	4.49	3.42
		6345		-6.28	-5.93	0.132	-5.21	-4.54	0.132	-4.64	-4.17	0.132	1.29	0.03
	6	6505		-6.47	-6.51	0.132	-5.62	-5.47	0.132	-5.16	-4.99	0.132	1.29	-0.64
	7	6665		-7.60	-7.85	0.132	-6.25	-6.72	0.132	-5.95	-6.28	0.132	1.29	-1.68
		6825		-7.07	-7.38	0.132	-5.93	-6.20	0.132	-5.40	-5.74	0.132	3.07	0.65
	8	6985		-5.90	-6.40	0.132	-5.06	-5.38	0.132	-4.89	-5.02	0.132	3.07	1.26

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index S37			RU Index S44			RU Index S52				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80H)	5	6025	52T	-2.98	-3.02	0.132	-3.59	-3.42	0.132	-5.30	-5.02	0.132	4.49	4.63
		6185		-4.48	-4.09	0.132	-5.06	-4.78	0.132	-6.24	-6.37	0.132	4.49	3.35
		6345		-4.63	-4.30	0.132	-5.20	-4.69	0.132	-6.97	-6.37	0.132	1.29	-0.03
	6	6505		-4.99	-4.99	0.132	-5.99	-5.55	0.132	-7.46	-7.09	0.132	1.29	-0.56
	7	6665		-5.83	-6.35	0.132	-6.36	-6.86	0.132	-7.58	-8.33	0.132	1.29	-1.65
		6825		-5.26	-6.01	0.132	-6.01	-6.53	0.132	-7.60	-8.11	0.132	3.07	0.59
	8	6985		-4.82	-5.24	0.132	-5.57	-5.54	0.132	-7.25	-7.24	0.132	3.07	1.19

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{2.48/10} + 10^{5.85/10})/2]$= 4.49dBi
6525MHz: Directional gain = $10 \log[(10^{1.38/10} + 10^{1.19/10})/2]$= 1.29dBi
7125MHz: Directional gain = $10 \log[(10^{1.89/10} + 10^{3.99/10})/2]$= 3.07dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Tones: 106T

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 53			RU Index 54				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE20	5	5955	106T	0.15	0.21	N/A	-0.09	0.20	N/A	4.49	7.68
		6175		-0.98	-1.18	N/A	-1.14	-1.34	N/A	4.49	6.42
		6415		-1.26	-1.88	N/A	-1.52	-2.09	N/A	1.29	2.74
	6	6435		-1.76	-1.67	N/A	-1.54	-1.76	N/A	1.29	2.65
		6475		-1.66	-1.89	N/A	-1.78	-1.93	N/A	1.29	2.53
		6515		-1.91	-1.93	N/A	-1.84	-2.11	N/A	1.29	2.38
	7	6535		-2.73	-2.95	N/A	-2.85	-2.99	N/A	1.29	1.46
		6695		-3.30	-2.93	N/A	-3.08	-2.89	N/A	1.29	1.32
		6855		-2.73	-2.36	N/A	-2.80	-2.53	N/A	3.07	3.54
	8	6875		-2.97	-2.45	N/A	-2.97	-2.71	N/A	3.07	3.38
		6995		-1.75	-1.82	N/A	-1.91	-1.95	N/A	3.07	4.30
		7115		-1.58	-1.46	N/A	-8.74	-8.12	N/A	3.07	4.56

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 53			RU Index 54			RU Index 56				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE40	5	5965	106T	-0.03	0.17	N/A	0.04	0.21	N/A	0.06	-0.10	N/A	4.49	7.63
		6165		-1.04	-1.32	N/A	-1.21	-1.38	N/A	-1.27	-1.45	N/A	4.49	6.32
		6405		-1.50	-2.06	N/A	-1.55	-1.93	N/A	-1.72	-2.23	N/A	1.29	2.56
	6	6445		-1.72	-1.85	N/A	-1.46	-1.83	N/A	-1.66	-1.86	N/A	1.29	2.66
		6485		-1.85	-1.97	N/A	-1.64	-1.99	N/A	-2.00	-2.06	N/A	1.29	2.49
	7	6525		-2.00	-2.14	N/A	-2.01	-2.32	N/A	-2.00	-2.47	N/A	1.29	2.23
		6685		-3.25	-2.96	N/A	-3.29	-2.87	N/A	-3.32	-2.77	N/A	1.29	1.26
		6845		-2.74	-2.34	N/A	-2.91	-2.35	N/A	-3.07	-2.56	N/A	3.07	3.54
	8	6885		-3.06	-2.70	N/A	-3.17	-2.75	N/A	-3.26	-2.99	N/A	3.07	3.20
		7005		-2.04	-1.81	N/A	-1.91	-1.94	N/A	-2.22	-2.08	N/A	3.07	4.16
		7085		-1.64	-1.41	N/A	-1.74	-1.40	N/A	-1.86	-1.54	N/A	3.07	4.56

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = 10 log[$(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}$] dBi
Directional gain:
5925MHz: Directional gain = 10 log[$(10^{2.48/10} + 10^{5.85/10})/2$]= 4.49dBi
6525MHz: Directional gain = 10 log[$(10^{1.38/10} + 10^{1.19/10})/2$]= 1.29dBi
7125MHz: Directional gain = 10 log[$(10^{1.89/10} + 10^{3.99/10})/2$]= 3.07dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 53			RU Index 56			RU Index 60				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	106T	-0.18	-0.30	N/A	0.46	0.10	N/A	-0.33	-0.43	N/A	4.49	7.78
		6145		-1.32	-1.18	N/A	-1.26	-0.96	N/A	-1.62	-1.75	N/A	4.49	6.39
		6385		-2.09	-1.83	N/A	-1.82	-1.57	N/A	-2.45	-2.27	N/A	1.29	2.61
	6	6465		-2.07	-2.43	N/A	-1.65	-2.14	N/A	-2.36	-2.65	N/A	1.29	2.41
		6545		-2.28	-2.85	N/A	-2.24	-2.66	N/A	-2.87	-3.21	N/A	1.29	1.86
	7	6625		-3.23	-3.86	N/A	-2.85	-3.58	N/A	-3.08	-4.17	N/A	1.29	1.10
		6705		-3.09	-4.19	N/A	-2.69	-3.96	N/A	-3.05	-4.42	N/A	1.29	1.02
		6785		-2.00	-3.02	N/A	-1.77	-2.81	N/A	-2.45	-3.40	N/A	1.29	2.04
	8	6865		-2.53	-3.37	N/A	-2.34	-3.11	N/A	-2.83	-3.81	N/A	3.07	3.37
		6945		-1.58	-2.25	N/A	-1.33	-1.93	N/A	-2.15	-2.47	N/A	3.07	4.46
		7025		-2.10	-2.41	N/A	-1.65	-2.40	N/A	-2.53	-3.02	N/A	3.07	4.07

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 53			RU Index 56			RU Index 60				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80L)	5	6025	106T	-1.49	-1.46	N/A	-0.35	-0.41	N/A	0.05	0.24	N/A	4.49	7.65
		6185		-2.64	-2.37	N/A	-1.61	-1.41	N/A	-1.33	-1.24	N/A	4.49	6.22
		6345		-3.38	-2.51	N/A	-2.17	-1.60	N/A	-1.76	-1.13	N/A	1.29	2.87
	6	6505		-3.27	-3.25	N/A	-2.32	-2.27	N/A	-1.98	-1.94	N/A	1.29	2.34
	7	6665		-4.59	-4.71	N/A	-3.60	-3.49	N/A	-2.84	-3.06	N/A	1.29	1.35
		6825		-4.03	-3.89	N/A	-3.24	-3.12	N/A	-2.56	-2.39	N/A	3.07	3.61
	8	6985		-3.04	-2.90	N/A	-2.07	-2.08	N/A	-1.70	-1.70	N/A	3.07	4.38

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index S53			RU Index S56			RU Index S60				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80H)	5	6025	106T	0.06	0.00	N/A	-0.69	-0.35	N/A	-2.19	-1.85	N/A	4.49	7.53
		6185		-1.45	-1.02	N/A	-1.85	-1.74	N/A	-3.35	-3.31	N/A	4.49	6.27
		6345		-1.64	-1.32	N/A	-2.23	-1.67	N/A	-3.53	-3.10	N/A	1.29	2.82
	6	6505		-2.18	-1.95	N/A	-2.58	-2.38	N/A	-4.07	-4.10	N/A	1.29	2.24
	7	6665		-3.07	-3.34	N/A	-3.66	-3.64	N/A	-5.15	-4.94	N/A	1.29	1.10
		6825		-2.46	-2.40	N/A	-3.21	-3.07	N/A	-4.60	-4.76	N/A	3.07	3.65
	8	6985		-1.68	-1.65	N/A	-2.56	-2.18	N/A	-4.00	-3.76	N/A	3.07	4.42

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{2.48/10} + 10^{5.85/10})/2]$= 4.49dBi
6525MHz: Directional gain = $10 \log[(10^{1.38/10} + 10^{1.19/10})/2]$= 1.29dBi
7125MHz: Directional gain = $10 \log[(10^{1.89/10} + 10^{3.99/10})/2]$= 3.07dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Tones: 242T

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm) RU Index 61 AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
802.11ax-HE20	5	5955	242T	1.95	2.38	0.15	4.49	9.82
		6175		1.79	2.2	0.15	4.49	9.65
		6415		1.76	2.23	0.15	1.29	6.45
	6	6435		1.2	1.69	0.15	1.29	5.90
		6475		1.26	1.64	0.15	1.29	5.90
		6515		1.66	1.57	0.15	1.29	6.07
	7	6535		1.21	1.42	0.15	1.29	5.77
		6695		1.57	1.61	0.15	1.29	6.04
		6855		1.33	1.52	0.15	3.07	7.66
	8	6875		0.81	1.01	0.15	3.07	7.14
		6995		0.76	0.7	0.15	3.07	6.96
		7115		-2.98	-2.9	0.15	3.07	3.29

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm) RU Index 61 AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	RU Index 62 AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
802.11ax-HE40	5	5965	242T	1.88	1.2	0.15	1.65	1.01	0.15	4.49	9.20
		6165		1.58	1.28	0.15	1.31	0.99	0.15	4.49	9.08
		6405		1.58	1.1	0.15	1.41	1.19	0.15	1.29	5.80
	6	6445		0.93	0.97	0.15	1.17	0.92	0.15	1.29	5.50
		6485		1.02	0.62	0.15	0.78	1.25	0.15	1.29	5.47
	7	6525		1.14	0.76	0.15	1.97	1.26	0.15	1.29	6.08
		6685		0.89	0.04	0.15	1.24	0.09	0.15	1.29	5.15
		6845		0.9	-0.16	0.15	1.18	0.05	0.15	3.07	6.88
	8	6885		0.64	-0.27	0.15	0.51	-0.29	0.15	3.07	6.44
		7005		0.54	-0.46	0.15	0.73	-0.38	0.15	3.07	6.44
		7085		0.75	-0.15	0.15	1.01	0.25	0.15	3.07	6.88

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{2.48/10} + 10^{5.85/10})/2]$= 4.49dBi
6525MHz: Directional gain = $10 \log[(10^{1.38/10} + 10^{1.19/10})/2]$= 1.29dBi
7125MHz: Directional gain = $10 \log[(10^{1.89/10} + 10^{3.99/10})/2]$= 3.07dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan

Tel: +886 2 26099301
Fax: +886 2 26099303

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 61			RU Index 62			RU Index 64				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	242T	2.21	2.52	0.15	2.15	2.62	0.15	2.13	2.17	0.15	4.49	10.04
		6145		2.33	2.38	0.15	2.36	2.3	0.15	2.03	2.09	0.15	4.49	10.01
		6385		1.95	1.9	0.15	2.15	2.23	0.15	2.12	2.27	0.15	1.29	6.65
	6	6465		1.59	1.48	0.15	2.61	2.58	0.15	1.59	1.42	0.15	1.29	7.05
		6545		1.24	1.88	0.15	2.09	2.68	0.15	1.82	2.18	0.15	1.29	6.85
	7	6625		0.72	1.37	0.15	0.96	1.6	0.15	0.66	1.49	0.15	1.29	5.74
		6705		0.89	1.61	0.15	1.01	1.62	0.15	0.71	1.53	0.15	1.29	5.78
		6785		0.78	1.45	0.15	0.77	1.53	0.15	0.57	1.6	0.15	1.29	5.62
	8	6865		0.65	1.19	0.15	1.08	1.64	0.15	0.18	0.57	0.15	3.07	7.60
		6945		0.28	0.77	0.15	1.21	1.85	0.15	0.32	0.75	0.15	3.07	7.77
		7025		0.02	0.7	0.15	1.03	1.71	0.15	-0.3	0.88	0.15	3.07	7.61

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 61			RU Index 62			RU Index 64				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80L)	5	6025	242T	1.72	2.48	0.15	2.11	2.92	0.15	1.5	2.32	0.15	4.49	10.18
		6185		1.65	2.27	0.15	1.96	2.73	0.15	1.56	2.24	0.15	4.49	10.01
		6345		1.65	2.36	0.15	2.21	2.35	0.15	1.63	2.3	0.15	1.29	6.73
	6	6505		1.37	1.83	0.15	2.39	2.82	0.15	1.35	1.68	0.15	1.29	7.06
	7	6665		-0.12	1.3	0.15	0.44	1.61	0.15	0	1.66	0.15	1.29	5.51
		6825		-0.27	1.24	0.15	0.25	1.49	0.15	-0.45	0.97	0.15	3.07	7.14
	8	6985		-0.75	0.48	0.15	0.53	1.75	0.15	-0.94	0.73	0.15	3.07	7.41

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index S61			RU Index S62			RU Index S64				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80H)	5	6025	242T	1.26	2.51	0.15	1.3	2.41	0.15	1.5	2.3	0.15	4.49	9.58
		6185		1.6	2.3	0.15	1.32	2.27	0.15	1.7	2.41	0.15	4.49	9.72
		6345		1.65	2.18	0.15	1.41	2.16	0.15	1.79	2.28	0.15	1.29	6.49
	6	6505		1.43	1.69	0.15	1.9	2.43	0.15	1.62	2.37	0.15	1.29	6.62
	7	6665		-0.39	1.41	0.15	-0.7	1.19	0.15	-0.65	1.49	0.15	1.29	5.05
		6825		-0.77	1.13	0.15	0.07	1.22	0.15	-0.51	0.73	0.15	3.07	6.91
	8	6985		-0.72	0.55	0.15	-0.02	1.35	0.15	-0.55	0.87	0.15	3.07	6.95

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{2.48/10} + 10^{5.85/10})/2]$= 4.49dBi
6525MHz: Directional gain = $10 \log[(10^{1.38/10} + 10^{1.19/10})/2]$= 1.29dBi
7125MHz: Directional gain = $10 \log[(10^{1.89/10} + 10^{3.99/10})/2]$= 3.07dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Tones: 484T

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)			Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 65				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE40	5	5965	484T	5.17	5.38	N/A	4.49	12.78
		6165		4.96	5.25	N/A	4.49	12.61
		6405		4.96	5	N/A	1.29	9.28
	6	6445		5.11	5.45	N/A	1.29	9.58
		6485		5.14	5.3	N/A	1.29	9.52
	7	6525		5.24	5.26	N/A	1.29	9.55
		6685		4.57	4.7	N/A	1.29	8.94
		6845		4.44	4.44	N/A	3.07	10.52
	8	6885		4.63	4.64	N/A	3.07	10.72
		7005		4.34	4.3	N/A	3.07	10.40
		7085		4.62	4.85	N/A	3.07	10.82

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 65			RU Index 66				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	484T	5.23	5.13	N/A	5.08	5.27	N/A	4.49	12.68
		6145		5.2	5.19	N/A	5.25	4.99	N/A	4.49	12.70
		6385		4.82	5.01	N/A	5.21	4.95	N/A	1.29	9.38
	6	6465		5.2	4.94	N/A	5.14	5.2	N/A	1.29	9.47
		6545		4.89	5.39	N/A	4.91	5.02	N/A	1.29	9.45
	7	6625		4.2	4.29	N/A	4.08	4.27	N/A	1.29	8.55
		6705		4.22	4.18	N/A	4.09	4.46	N/A	1.29	8.58
		6785		3.9	4.35	N/A	4.23	4.51	N/A	1.29	8.67
	8	6865		3.99	4.33	N/A	4.25	4.38	N/A	3.07	10.40
		6945		4.45	4.11	N/A	4.17	4.37	N/A	3.07	10.36
		7025		4.08	4.38	N/A	4.26	4.3	N/A	3.07	10.36

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{2.48/10} + 10^{5.85/10})/2]$= 4.49dBi
6525MHz: Directional gain = $10 \log[(10^{1.38/10} + 10^{1.19/10})/2]$= 1.29dBi
7125MHz: Directional gain = $10 \log[(10^{1.89/10} + 10^{3.99/10})/2]$= 3.07dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 65			RU Index 66				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80L)	5	6025	484T	4.72	5.15	N/A	4.41	5.38	N/A	4.49	12.44
		6185		4.79	5.09	N/A	4.82	5.03	N/A	4.49	12.44
		6345		4.69	4.93	N/A	4.79	5.04	N/A	1.29	9.22
	6	6505		5.09	4.96	N/A	5.07	5.25	N/A	1.29	9.46
	7	6665		3.83	4.41	N/A	3.38	4.28	N/A	1.29	8.43
		6825		3.72	4.23	N/A	3.58	4.48	N/A	3.07	10.13
	8	6985		4.12	4.12	N/A	3.85	4.47	N/A	3.07	10.25

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index S65			RU Index S66				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80H)	5	6025	484T	4.58	5.13	N/A	4.6	5.14	N/A	4.49	12.38
		6185		4.68	5.09	N/A	4.64	4.97	N/A	4.49	12.39
		6345		4.51	5.07	N/A	4.7	4.92	N/A	1.29	9.11
	6	6505		4.8	5.3	N/A	4.68	5.02	N/A	1.29	9.36
	7	6665		3.72	4.23	N/A	3.79	4.36	N/A	1.29	8.38
		6825		3.87	4.33	N/A	3.89	4.43	N/A	3.07	10.25
	8	6985		3.97	4.31	N/A	3.8	4.64	N/A	3.07	10.32

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = 10 log[($10^{G1/10}$ + $10^{G2/10}$ + … + $10^{GN/10}$)/N_{ANT}] dBi
Directional gain:
5925MHz: Directional gain = 10 log[($10^{2.48/10}$ +$10^{5.85/10}$)/2]= 4.49dBi
6525MHz: Directional gain = 10 log[($10^{1.38/10}$ +$10^{1.19/10}$)/2]= 1.29dBi
7125MHz: Directional gain = 10 log[($10^{1.89/10}$ +$10^{3.99/10}$)/2]= 3.07dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Tones: 996T

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)			Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 67				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	996T	7	6.29	0.159	4.49	14.32
		6145		6.97	6.01	0.159	4.49	14.18
		6385		7.34	6.33	0.159	1.29	11.32
	6	6465		7.21	6.08	0.159	1.29	11.14
		6545		7.31	6.06	0.159	1.29	11.19
	7	6625		6.62	5.32	0.159	1.29	10.48
		6705		6.26	5.04	0.159	1.29	10.15
		6785		6.11	4.98	0.159	1.29	10.04
	8	6865		5.97	5.09	0.159	3.07	11.79
		6945		6.43	5.32	0.159	3.07	12.15
		7025		6.53	5.59	0.159	3.07	12.32

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 67			RU Index S67				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160	5	6025	996T	7.35	6.54	0.159	7.17	6.64	0.159	4.49	14.62
		6185		7.44	6.76	0.159	7.53	6.55	0.159	4.49	14.77
		6345		7.66	6.48	0.159	7.36	6.67	0.159	1.29	11.57
	6	6505		6.93	5.96	0.159	6.89	6.03	0.159	1.29	10.94
	7	6665		6.68	5.47	0.159	6.53	5.32	0.159	1.29	10.58
		6825		6.39	5.49	0.159	5.95	5.29	0.159	3.07	12.20
	8	6985		6.4	5.52	0.159	6.31	5.46	0.159	3.07	12.22

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{2.48/10} + 10^{5.85/10})/2]$= 4.49dBi
6525MHz: Directional gain = $10 \log[(10^{1.38/10} + 10^{1.19/10})/2]$= 1.29dBi
7125MHz: Directional gain = $10 \log[(10^{1.89/10} + 10^{3.99/10})/2]$= 3.07dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Test SKU: SKU #3 [with (INPAQ) WA-P-LBLB-04-108 Antenna]

Modulation Type	U-NII Band	Centre Frequency (MHz)	Average Coneduted Output Power (dBm)		Duty Cycle Factor (dB) 10log(1/X)	Directional Gain (dBi) Note3	Total E.I.R.P. (dBm) Note2	Limit
			AUX	Main				
802.11ax-HE20	5	5955	1.47	0.92	N/A	4.28	8.49	24dBm
		6175	1.17	0.92		4.28	8.34	
		6415	1.11	0.98		4.28	8.34	
	6	6435	1.23	1.18		0.11	4.33	
		6475	1.48	1.22		0.11	4.47	
		6515	1.11	1.16		0.11	4.26	
	7	6535	0.52	0.42		2.24	5.72	
		6695	0.71	-0.09		2.24	5.58	
		6855	0.71	-0.05		2.24	5.60	
	8	6875	0.76	-0.03		2.24	5.63	
		6995	0.73	-0.17		1.26	4.57	
		7115	-3.65	-3.04		1.26	0.94	
802.11ax-HE40	5	5965	4.94	5.08	N/A	4.28	12.30	
		6165	4.92	4.78		4.28	12.14	
		6405	4.57	4.74		4.28	11.95	
	6	6445	4.69	5.20		0.11	8.07	
		6485	4.86	5.13		0.11	8.12	
	7	6525	5.01	4.95		2.24	10.23	
		6685	4.09	3.89		2.24	9.24	
		6845	4.23	3.84		2.24	9.29	
	8	6885	4.29	3.86		1.26	8.35	
		7005	4.22	3.92		1.26	8.34	
		7085	4.35	4.14		1.26	8.52	

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]

2. According to KDB 662911 D01 E)1), Total E.I.R.P. (dBm) = Sum to individual output power (dBm)+ Directional gain (dBi) + duty cycle factor(dB) when duty cycle is less than 98%.

3. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925-6425MHz: Directional gain = $10 \log[(10^{3.70/10} + 10^{4.80/10})/2]$= 4.28dBi
6425-6525MHz: Directional gain = $10 \log[(10^{-1.0/10} + 10^{1.0/10})/2]$= 0.11dBi
6525-6875MHz: Directional gain = $10 \log[(10^{2.86/10} + 10^{1.60/10})/2]$= 0.24dBi
6875-7125MHz: Directional gain = $10 \log[(10^{-1.40/10} + 10^{2.90/10})/2]$= 1.26dBi

The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).

3. We did spot check for output power and all output power values keep identical thus other conducted items is exempt.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Modulation Type	U-NII Band	Centre Frequency (MHz)	Average Coneduted Output Power (dBm)		Duty Cycle Factor (dB) 10log(1/X)	Directional Gain (dBi) Note3	Total E.I.R.P. (dBm) Note2	Limit
			AUX	Main				
802.11ax-HE80	5	5985	6.56	6.15	N/A	4.28	13.65	24dBm
		6145	6.26	5.73		4.28	13.29	
		6385	6.70	6.02		4.28	13.66	
	6	6465	6.85	5.93		0.11	9.53	
		6545	6.82	5.83		2.24	11.60	
	7	6625	5.65	5.12		2.24	10.64	
		6705	5.75	5.09		2.24	10.68	
		6785	5.73	4.92		2.24	10.59	
	8	6865	5.82	4.75		2.24	10.57	
		6945	5.79	5.16		1.26	9.76	
		7025	5.82	5.41		1.26	9.89	
802.11ax-HE160	5	6025	9.67	8.84	N/A	4.28	16.57	
		6185	9.57	8.83		4.28	16.51	
		6345	9.93	9.01		4.28	16.78	
	6	6505	9.53	8.86		0.11	12.33	
	7	6665	8.72	7.88		2.24	13.57	
		6825	8.77	7.92		2.24	13.62	
	8	6985	8.80	8.12		1.26	12.74	

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]

2. According to KDB 662911 D01 E)1), Total E.I.R.P. (dBm) = Sum to individual output power (dBm)+ Directional gain (dBi) + duty cycle factor(dB) when duty cycle is less than 98%.

3. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then

Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi

Directional gain:

5925-6425MHz: Directional gain = $10 \log[(10^{3.70/10} + 10^{4.80/10})/2] = 4.28$dBi

6425-6525MHz: Directional gain = $10 \log[(10^{-1.0/10} + 10^{1.0/10})/2] = 0.11$dBi

6525-6875MHz: Directional gain = $10 \log[(10^{2.86/10} + 10^{1.60/10})/2] = 0.24$dBi

6875-7125MHz: Directional gain = $10 \log[(10^{-1.40/10} + 10^{2.90/10})/2] = 1.26$dBi

The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).

3. We did spot check for output power and all output power values keep identical thus other conducted items is exempt.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

● OFDMA Modulation

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 0			RU Index 4			RU Index 8				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE20	5	5955	26T	-6.36	-6.08	0.223	-6.36	-6.14	0.223	-6.43	-6.15	0.223	4.28	1.30
		6175		-7.60	-7.79	0.223	-7.35	-7.66	0.223	-7.71	-7.94	0.223	4.28	0.01
		6415		-7.74	-8.32	0.223	-7.87	-8.20	0.223	-8.28	-8.58	0.223	4.28	-0.51
	6	6435		-7.88	-8.17	0.223	-7.93	-8.00	0.223	-7.97	-8.34	0.223	0.11	-4.62
		6475		-8.19	-8.23	0.223	-8.05	-8.33	0.223	-8.22	-8.49	0.223	0.11	-4.84
		6515		-8.43	-8.50	0.223	-8.09	-8.48	0.223	-8.43	-8.59	0.223	0.11	-4.94
	7	6535		-9.04	-9.37	0.223	-8.99	-9.27	0.223	-9.30	-9.61	0.223	2.24	-3.65
		6695		-9.62	-9.20	0.223	-9.38	-9.00	0.223	-9.81	-9.16	0.223	2.24	-3.71
		6855		-9.02	-8.86	0.223	-9.14	-8.65	0.223	-9.14	-8.94	0.223	2.24	-3.41
	8	6875		-9.33	-9.02	0.223	-9.38	-8.73	0.223	-9.62	-9.01	0.223	2.24	-3.57
		6995		-8.36	-8.30	0.223	-8.05	-8.02	0.223	-8.41	-8.26	0.223	1.26	-3.54
		7115		-8.14	-7.89	0.223	-8.07	-7.58	0.223	-8.21	-7.84	0.223	1.26	-3.32

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 0			RU Index 8			RU Index 17				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE40	5	5965	26T	-6.39	-6.15	0.223	-6.14	-6.27	0.223	-6.17	-6.17	0.223	4.28	1.34
		6165		-7.23	-7.60	0.223	-7.38	-7.92	0.223	-7.51	-7.72	0.223	4.28	0.10
		6405		-7.71	-8.27	0.223	-7.99	-8.36	0.223	-8.16	-8.32	0.223	4.28	-0.47
	6	6445		-7.85	-7.97	0.223	-8.14	-8.34	0.223	-8.17	-8.34	0.223	0.11	-4.57
		6485		-8.29	-8.18	0.223	-8.42	-8.44	0.223	-8.43	-8.48	0.223	0.11	-4.89
	7	6525		-8.35	-8.62	0.223	-8.43	-8.67	0.223	-8.35	-8.81	0.223	2.24	-3.01
		6685		-9.58	-9.22	0.223	-9.74	-9.20	0.223	-9.66	-9.30	0.223	2.24	-3.92
		6845		-9.02	-8.64	0.223	-9.18	-8.84	0.223	-9.25	-8.79	0.223	2.24	-3.35
	8	6885		-9.48	-8.97	0.223	-9.54	-9.01	0.223	-9.43	-9.30	0.223	1.26	-4.72
		7005		-8.15	-8.30	0.223	-8.48	-8.29	0.223	-8.58	-8.27	0.223	1.26	-3.73
		7085		-7.86	-7.52	0.223	-7.95	-7.73	0.223	-8.85	-8.66	0.223	1.26	-3.19

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925-6425MHz: Directional gain = $10 \log[(10^{3.70/10} + 10^{4.80/10})/2]$= 4.28dBi
6425-6525MHz: Directional gain = $10 \log[(10^{-1.0/10} + 10^{1.0/10})/2]$= 0.11dBi
6525-6875MHz: Directional gain = $10 \log[(10^{2.86/10} + 10^{1.60/10})/2]$= 0.24dBi
6875-7125MHz: Directional gain = $10 \log[(10^{-1.40/10} + 10^{2.90/10})/2]$= 1.26dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.
6. We did spot check for output power and all output power values keep identical thus other conducted items is exempt.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 0			RU Index 18			RU Index 36				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	26T	-6.38	-5.95	0.223	-5.69	-5.47	0.223	-6.56	-6.40	0.223	4.28	1.93
		6145		-7.23	-7.37	0.223	-7.06	-7.00	0.223	-7.84	-7.76	0.223	4.28	0.48
		6385		-7.76	-8.08	0.223	-7.44	-7.52	0.223	-8.26	-8.49	0.223	4.28	0.03
	6	6465		-8.41	-8.25	0.223	-7.98	-7.68	0.223	-8.67	-8.71	0.223	0.11	-4.48
		6545		-8.65	-8.50	0.223	-8.40	-8.25	0.223	-9.23	-9.02	0.223	2.24	-2.85
	7	6625		-9.98	-9.39	0.223	-9.24	-8.68	0.223	-10.17	-9.08	0.223	2.24	-3.48
		6705		-9.92	-9.07	0.223	-9.50	-8.62	0.223	-10.33	-9.28	0.223	2.24	-3.56
		6785		-9.05	-8.68	0.223	-8.65	-8.23	0.223	-9.45	-8.75	0.223	2.24	-2.96
	8	6865		-9.38	-8.71	0.223	-8.90	-8.31	0.223	-10.13	-9.26	0.223	2.24	-3.12
		6945		-8.35	-7.66	0.223	-7.65	-7.37	0.223	-8.81	-8.14	0.223	1.26	-3.01
		7025		-8.58	-8.40	0.223	-8.22	-7.85	0.223	-9.15	-8.72	0.223	1.26	-3.54

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 0			RU Index 18			RU Index 36				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80L)	5	6025	26T	-7.91	-8.10	0.223	-6.54	-6.91	0.223	-6.44	-6.04	0.223	4.28	1.28
		6185		-9.28	-8.86	0.223	-7.98	-7.77	0.223	-7.55	-7.47	0.223	4.28	0.00
		6345		-9.86	-8.92	0.223	-8.39	-7.91	0.223	-8.07	-7.47	0.223	4.28	-0.25
	6	6505		-9.89	-9.51	0.223	-8.98	-8.59	0.223	-8.32	-8.17	0.223	0.11	-4.90
	7	6665		-10.91	-11.23	0.223	-9.47	-9.87	0.223	-9.24	-9.48	0.223	2.24	-3.89
		6825		-10.27	-10.48	0.223	-9.01	-9.35	0.223	-8.50	-8.89	0.223	2.24	-3.22
	8	6985		-9.43	-9.45	0.223	-8.53	-8.72	0.223	-8.08	-7.97	0.223	1.26	-3.53

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index S0			RU Index S18			RU Index S36				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80H)	5	6025	26T	-6.28	-6.08	0.223	-6.96	-6.70	0.223	-8.73	-8.27	0.223	4.28	1.33
		6185		-7.68	-7.30	0.223	-8.16	-7.90	0.223	-9.65	-9.37	0.223	4.28	0.03
		6345		-8.11	-7.55	0.223	-8.40	-8.00	0.223	-10.08	-9.87	0.223	4.28	-0.31
	6	6505		-8.33	-8.29	0.223	-9.09	-8.96	0.223	-10.77	-10.52	0.223	0.11	-4.97
	7	6665		-9.06	-9.55	0.223	-9.37	-10.05	0.223	-10.66	-11.34	0.223	2.24	-3.82
		6825		-8.49	-8.89	0.223	-9.28	-9.58	0.223	-10.86	-11.13	0.223	2.24	-3.21
	8	6985		-8.08	-8.14	0.223	-8.74	-8.95	0.223	-10.19	-10.45	0.223	1.26	-3.62

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925-6425MHz: Directional gain = $10 \log[(10^{3.70/10} + 10^{4.80/10})/2]$= 4.28dBi
6425-6525MHz: Directional gain = $10 \log[(10^{-1.0/10} + 10^{1.0/10})/2]$= 0.11dBi
6525-6875MHz: Directional gain = $10 \log[(10^{2.86/10} + 10^{1.60/10})/2]$= 0.24dBi
6875-7125MHz: Directional gain = $10 \log[(10^{-1.40/10} + 10^{2.90/10})/2]$= 1.26dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.
6. We did spot check for output power and all output power values keep identical thus other conducted items is exempt.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Tones: 52T

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 37			RU Index 39			RU Index 40				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE20	5	5955	52T	-3.26	-2.81	0.132	-2.83	-2.80	0.132	-3.08	-2.87	0.132	4.28	4.607
		6175		-4.21	-4.63	0.132	-4.35	-4.32	0.132	-4.36	-4.56	0.132	4.28	3.087
		6415		-4.57	-5.02	0.132	-4.54	-5.10	0.132	-4.86	-5.27	0.132	4.28	2.633
	6	6435		-4.82	-5.12	0.132	-4.65	-5.02	0.132	-4.89	-5.08	0.132	0.11	-1.579
		6475		-5.01	-5.19	0.132	-4.97	-5.14	0.132	-4.95	-5.21	0.132	0.11	-1.802
		6515		-5.07	-5.29	0.132	-4.90	-5.29	0.132	-4.99	-5.37	0.132	0.11	-1.838
	7	6535		-5.89	-5.96	0.132	-5.96	-6.26	0.132	-6.14	-6.21	0.132	2.24	-0.543
		6695		-6.38	-6.00	0.132	-6.19	-5.86	0.132	-6.43	-5.97	0.132	2.24	-0.640
		6855		-5.98	-5.70	0.132	-5.91	-5.63	0.132	-5.96	-5.57	0.132	2.24	-0.378
	8	6875		-6.33	-5.76	0.132	-6.02	-5.64	0.132	-6.23	-5.88	0.132	2.24	-0.444
		6995		-5.08	-5.03	0.132	-5.05	-5.04	0.132	-5.40	-5.10	0.132	1.26	-0.643
		7115		-4.92	-4.74	0.132	-4.89	-4.52	0.132	-8.77	-8.48	0.132	1.26	-0.299

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 37			RU Index 40			RU Index 44				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE40	5	5965	52T	-3.45	-2.94	0.132	-3.07	-3.25	0.132	-3.31	-2.97	0.132	4.28	4.29
		6165		-4.34	-4.61	0.132	-4.22	-4.57	0.132	-4.46	-4.73	0.132	4.28	3.03
		6405		-4.58	-5.16	0.132	-4.71	-5.14	0.132	-5.00	-5.31	0.132	4.28	2.56
	6	6445		-5.08	-5.07	0.132	-4.87	-5.08	0.132	-4.84	-5.17	0.132	0.11	-1.72
		6485		-4.94	-5.24	0.132	-5.02	-5.20	0.132	-4.97	-5.34	0.132	0.11	-1.84
	7	6525		-5.34	-5.33	0.132	-5.34	-5.45	0.132	-5.29	-5.43	0.132	2.24	0.05
		6685		-6.44	-6.08	0.132	-6.34	-6.04	0.132	-6.50	-6.15	0.132	2.24	-0.81
		6845		-5.93	-5.63	0.132	-5.99	-5.67	0.132	-6.21	-5.90	0.132	2.24	-0.40
	8	6885		-6.16	-5.96	0.132	-6.42	-5.83	0.132	-6.31	-6.09	0.132	1.26	-1.66
		7005		-5.05	-4.84	0.132	-5.18	-5.24	0.132	-5.29	-5.31	0.132	1.26	-0.54
		7085		-4.71	-4.47	0.132	-4.72	-4.75	0.132	-4.89	-4.72	0.132	1.26	-0.19

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925-6425MHz: Directional gain = $10 \log[(10^{3.70/10} + 10^{4.80/10})/2]$= 4.28dBi
6425-6525MHz: Directional gain = $10 \log[(10^{-1.0/10} + 10^{1.0/10})/2]$= 0.11dBi
6525-6875MHz: Directional gain = $10 \log[(10^{2.86/10} + 10^{1.60/10})/2]$= 0.24dBi
6875-7125MHz: Directional gain = $10 \log[(10^{-1.40/10} + 10^{2.90/10})/2]$= 1.26dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.
6. We did spot check for output power and all output power values keep identical thus other conducted items is exempt.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 37			RU Index 44			RU Index 52				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	52T	-2.95	-3.40	0.132	-2.64	-2.89	0.132	-3.37	-3.43	0.132	4.28	4.66
		6145		-4.27	-4.21	0.132	-4.02	-4.00	0.132	-4.80	-4.96	0.132	4.28	3.41
		6385		-5.12	-4.84	0.132	-4.77	-4.64	0.132	-5.53	-5.60	0.132	4.28	2.72
	6	6465		-5.22	-5.63	0.132	-5.02	-5.23	0.132	-5.49	-5.86	0.132	0.11	-1.87
		6545		-5.51	-5.86	0.132	-5.44	-5.53	0.132	-6.02	-6.33	0.132	2.24	-0.10
	7	6625		-6.07	-6.89	0.132	-5.95	-6.46	0.132	-6.42	-7.36	0.132	2.24	-0.82
		6705		-6.35	-7.14	0.132	-5.59	-6.87	0.132	-6.26	-7.36	0.132	2.24	-0.80
		6785		-5.66	-6.53	0.132	-5.47	-6.02	0.132	-5.74	-6.78	0.132	2.24	-0.35
	8	6865		-5.81	-6.84	0.132	-5.41	-6.47	0.132	-6.38	-7.29	0.132	2.24	-0.53
		6945		-5.08	-5.53	0.132	-4.30	-5.23	0.132	-5.26	-5.77	0.132	1.26	-0.34
		7025		-5.17	-6.10	0.132	-5.06	-5.56	0.132	-5.64	-6.45	0.132	1.26	-0.90

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 37			RU Index 44			RU Index 52				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80L)	5	6025	52T	-4.64	-4.69	0.132	-3.48	-3.67	0.132	-3.16	-2.84	0.132	4.28	4.43
		6185		-5.99	-5.37	0.132	-4.82	-4.63	0.132	-4.54	-4.20	0.132	4.28	3.06
		6345		-6.43	-5.94	0.132	-5.33	-4.77	0.132	-4.65	-4.16	0.132	4.28	3.02
	6	6505		-6.64	-6.70	0.132	-5.77	-5.54	0.132	-5.34	-5.26	0.132	0.11	-2.05
	7	6665		-7.60	-8.04	0.132	-6.35	-6.98	0.132	-6.00	-6.43	0.132	2.24	-0.83
		6825		-7.16	-7.49	0.132	-5.90	-6.47	0.132	-5.41	-5.94	0.132	2.24	-0.28
	8	6985		-6.02	-6.61	0.132	-5.31	-5.47	0.132	-4.81	-5.22	0.132	1.26	-0.61

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index S37			RU Index S44			RU Index S52				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80H)	5	6025	52T	-3.24	-3.20	0.132	-3.85	-3.62	0.132	-5.61	-4.92	0.132	4.28	4.20
		6185		-4.70	-4.19	0.132	-5.02	-4.83	0.132	-6.39	-6.59	0.132	4.28	2.98
		6345		-4.67	-4.53	0.132	-5.38	-4.96	0.132	-7.08	-6.48	0.132	4.28	2.82
	6	6505		-5.07	-5.15	0.132	-6.17	-5.66	0.132	-7.60	-7.32	0.132	0.11	-1.86
	7	6665		-5.97	-6.63	0.132	-6.38	-6.93	0.132	-7.79	-8.31	0.132	2.24	-0.91
		6825		-5.34	-6.19	0.132	-6.03	-6.51	0.132	-7.63	-8.29	0.132	2.24	-0.36
	8	6985		-4.80	-5.38	0.132	-5.63	-5.78	0.132	-7.34	-7.28	0.132	1.26	-0.68

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = 10 log[$(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}$] dBi
Directional gain:
5925-6425MHz: Directional gain = 10 log[$(10^{3.70/10} + 10^{4.80/10})/2$]= 4.28dBi
6425-6525MHz: Directional gain = 10 log[$(10^{-1.0/10} + 10^{1.0/10})/2$]= 0.11dBi
6525-6875MHz: Directional gain = 10 log[$(10^{2.86/10} + 10^{1.60/10})/2$]= 0.24dBi
6875-7125MHz: Directional gain = 10 log[$(10^{-1.40/10} + 10^{2.90/10})/2$]= 1.26dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.
6. We did spot check for output power and all output power values keep identical thus other conducted items is exempt.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Tones: 106T

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 53			RU Index 54				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE20	5	5955	106T	-0.04	0.09	N/A	0.00	0.05	N/A	4.28	7.32
		6175		-0.94	-1.38	N/A	-1.15	-1.52	N/A	4.28	6.14
		6415		-1.52	-2.18	N/A	-1.50	-2.16	N/A	4.28	5.47
	6	6435		-1.73	-1.94	N/A	-1.66	-1.79	N/A	0.11	1.40
		6475		-1.66	-1.93	N/A	-2.04	-1.99	N/A	0.11	1.33
		6515		-1.78	-2.02	N/A	-1.80	-2.27	N/A	0.11	1.22
	7	6535		-2.80	-3.22	N/A	-3.03	-3.21	N/A	2.24	2.25
		6695		-3.46	-3.04	N/A	-3.22	-2.92	N/A	2.24	2.18
		6855		-2.89	-2.40	N/A	-3.13	-2.45	N/A	2.24	2.61
	8	6875		-2.86	-2.69	N/A	-2.96	-2.70	N/A	2.24	2.48
		6995		-1.96	-1.86	N/A	-2.01	-1.84	N/A	1.26	2.36
		7115		-1.88	-1.66	N/A	-8.88	-8.30	N/A	1.26	2.50

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 53			RU Index 54			RU Index 56				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE40	5	5965	106T	-0.19	-0.18	N/A	-0.11	0.02	N/A	-0.07	-0.17	N/A	4.28	7.25
		6165		-1.32	-1.62	N/A	-1.44	-1.65	N/A	-1.40	-1.60	N/A	4.28	5.82
		6405		-1.51	-2.29	N/A	-1.64	-2.06	N/A	-1.77	-2.15	N/A	4.28	5.45
	6	6445		-1.82	-2.00	N/A	-1.59	-1.90	N/A	-1.63	-2.15	N/A	0.11	1.38
		6485		-1.89	-2.15	N/A	-1.92	-2.12	N/A	-2.06	-2.37	N/A	0.11	1.10
	7	6525		-1.92	-2.26	N/A	-1.97	-2.40	N/A	-2.19	-2.62	N/A	2.24	3.16
		6685		-3.54	-3.11	N/A	-3.45	-2.94	N/A	-3.40	-3.03	N/A	2.24	2.06
		6845		-2.82	-2.45	N/A	-3.15	-2.66	N/A	-3.22	-2.79	N/A	2.24	2.62
	8	6885		-3.31	-2.76	N/A	-3.13	-2.75	N/A	-3.54	-3.12	N/A	1.26	1.33
		7005		-2.23	-1.99	N/A	-1.93	-2.02	N/A	-2.42	-2.32	N/A	1.26	2.30
		7085		-1.71	-1.54	N/A	-1.92	-1.70	N/A	-2.06	-1.62	N/A	1.26	2.65

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = 10 log[($10^{G1/10}$ + $10^{G2/10}$ + … + $10^{GN/10}$)/N_{ANT}] dBi
Directional gain:
5925-6425MHz: Directional gain = 10 log[($10^{3.70/10}$ +$10^{4.80/10}$)/2]= 4.28dBi
6425-6525MHz: Directional gain = 10 log[($10^{-1.0/10}$ +$10^{1.0/10}$)/2]= 0.11dBi
6525-6875MHz: Directional gain = 10 log[($10^{2.86/10}$ +$10^{1.60/10}$)/2]= 0.24dBi
6875-7125MHz: Directional gain = 10 log[($10^{-1.40/10}$ +$10^{2.90/10}$)/2]= 1.26dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.
6. We did spot check for output power and all output power values keep identical thus other conducted items is exempt.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 53			RU Index 56			RU Index 60				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	106T	-0.20	-0.42	N/A	0.26	-0.02	N/A	-0.54	-0.42	N/A	4.28	7.41
		6145		-1.58	-1.48	N/A	-1.31	-1.12	N/A	-1.65	-1.73	N/A	4.28	6.08
		6385		-2.20	-2.09	N/A	-1.94	-1.66	N/A	-2.52	-2.37	N/A	4.28	5.49
	6	6465		-2.27	-2.61	N/A	-1.78	-2.37	N/A	-2.32	-2.75	N/A	0.11	1.06
		6545		-2.28	-2.87	N/A	-2.43	-2.82	N/A	-2.95	-3.35	N/A	2.24	2.69
	7	6625		-3.42	-4.09	N/A	-2.91	-3.85	N/A	-3.27	-4.31	N/A	2.24	1.90
		6705		-3.19	-4.36	N/A	-2.73	-3.90	N/A	-3.12	-4.44	N/A	2.24	1.97
		6785		-2.04	-3.11	N/A	-1.86	-2.76	N/A	-2.58	-3.43	N/A	2.24	2.96
	8	6865		-2.44	-3.58	N/A	-2.31	-3.36	N/A	-2.83	-3.97	N/A	2.24	2.45
		6945		-1.62	-2.29	N/A	-1.23	-2.04	N/A	-2.30	-2.59	N/A	1.26	2.65
		7025		-2.30	-2.54	N/A	-1.89	-2.61	N/A	-2.60	-3.09	N/A	1.26	2.04

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 53			RU Index 56			RU Index 60				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80L)	5	6025	106T	-1.58	-1.59	N/A	-0.55	-0.55	N/A	-0.24	0.07	N/A	4.28	7.21
		6185		-2.73	-2.43	N/A	-1.79	-1.62	N/A	-1.48	-1.38	N/A	4.28	5.86
		6345		-3.45	-2.67	N/A	-2.40	-1.55	N/A	-1.79	-1.40	N/A	4.28	5.70
	6	6505		-3.48	-3.50	N/A	-2.49	-2.44	N/A	-2.15	-1.92	N/A	0.11	1.09
	7	6665		-4.56	-4.78	N/A	-3.71	-3.71	N/A	-2.99	-3.34	N/A	2.24	2.09
		6825		-4.02	-3.99	N/A	-3.39	-3.18	N/A	-2.57	-2.53	N/A	2.24	2.70
	8	6985		-3.08	-3.04	N/A	-2.18	-2.13	N/A	-1.83	-1.83	N/A	1.26	2.44

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index S53			RU Index S56			RU Index S60				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80H)	5	6025	106T	-0.17	-0.06	N/A	-0.87	-0.36	N/A	-2.45	-2.08	N/A	4.28	7.18
		6185		-1.65	-1.04	N/A	-1.89	-1.76	N/A	-3.52	-3.27	N/A	4.28	5.96
		6345		-1.61	-1.38	N/A	-2.19	-1.92	N/A	-3.64	-3.21	N/A	4.28	5.80
	6	6505		-2.32	-1.94	N/A	-2.61	-2.63	N/A	-4.19	-4.30	N/A	0.11	0.99
	7	6665		-3.29	-3.43	N/A	-3.80	-3.83	N/A	-5.20	-5.23	N/A	2.24	1.89
		6825		-2.63	-2.53	N/A	-3.36	-3.23	N/A	-4.61	-4.77	N/A	2.24	2.67
	8	6985		-1.90	-1.69	N/A	-2.53	-2.41	N/A	-4.00	-3.74	N/A	1.26	2.48

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = 10 log[$(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}$] dBi
Directional gain:
5925-6425MHz: Directional gain = 10 log[$(10^{3.70/10} + 10^{4.80/10})/2$]= 4.28dBi
6425-6525MHz: Directional gain = 10 log[$(10^{-1.0/10} + 10^{1.0/10})/2$]= 0.11dBi
6525-6875MHz: Directional gain = 10 log[$(10^{2.86/10} + 10^{1.60/10})/2$]= 0.24dBi
6875-7125MHz: Directional gain = 10 log[$(10^{-1.40/10} + 10^{2.90/10})/2$]= 1.26dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.
6. We did spot check for output power and all output power values keep identical thus other conducted items is exempt..

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Tones: 242T

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)			Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 61				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE20	5	5955	242T	1.71	2.23	0.15	4.28	9.42
		6175		1.66	2.09	0.15	4.28	9.32
		6415		1.57	2.19	0.15	4.28	9.33
	6	6435		0.99	1.46	0.15	0.11	4.50
		6475		1.17	1.47	0.15	0.11	4.59
		6515		1.37	1.51	0.15	0.11	4.71
	7	6535		1.17	1.2	0.15	2.24	6.59
		6695		1.33	1.22	0.15	2.24	6.68
		6855		1.27	1.5	0.15	2.24	6.79
	8	6875		0.64	0.81	0.15	2.24	6.13
		6995		0.64	0.53	0.15	1.26	5.01
		7115		-3.11	-2.98	0.15	1.26	1.38

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 61			RU Index 62				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE40	5	5965	242T	1.75	0.98	0.15	1.44	0.87	0.15	4.28	8.82
		6165		1.46	1.05	0.15	1.32	0.77	0.15	4.28	8.70
		6405		1.37	1.15	0.15	1.46	1.13	0.15	4.28	8.74
	6	6445		0.81	0.76	0.15	0.93	0.66	0.15	0.11	4.07
		6485		0.9	0.64	0.15	0.86	1.18	0.15	0.11	4.29
	7	6525		1.28	0.55	0.15	1.92	1.22	0.15	2.24	6.98
		6685		0.88	-0.09	0.15	1	-0.09	0.15	2.24	5.89
		6845		0.83	-0.16	0.15	1.05	-0.01	0.15	2.24	5.95
	8	6885		0.54	-0.38	0.15	0.42	-0.41	0.15	1.26	4.52
		7005		0.53	-0.66	0.15	0.39	-0.56	0.15	1.26	4.40
		7085		0.73	-0.24	0.15	0.78	0.25	0.15	1.26	4.94

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925-6425MHz: Directional gain = $10 \log[(10^{3.70/10} + 10^{4.80/10})/2]$= 4.28dBi
6425-6525MHz: Directional gain = $10 \log[(10^{-1.0/10} + 10^{1.0/10})/2]$= 0.11dBi
6525-6875MHz: Directional gain = $10 \log[(10^{2.86/10} + 10^{1.60/10})/2]$= 0.24dBi
6875-7125MHz: Directional gain = $10 \log[(10^{-1.40/10} + 10^{2.90/10})/2]$= 1.26dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.
6. We did spot check for output power and all output power values keep identical thus other conducted items is exempt.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 61			RU Index 62			RU Index 64				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	242T	1.92	2.3	0.15	2.02	2.66	0.15	1.99	2.17	0.15	4.28	9.79
		6145		2.12	2.07	0.15	2.21	2.13	0.15	1.85	2.06	0.15	4.28	9.61
		6385		1.65	1.9	0.15	2.01	2.06	0.15	1.88	1.97	0.15	4.28	9.48
	6	6465		1.66	1.34	0.15	2.46	2.27	0.15	1.51	1.36	0.15	0.11	5.64
		6545		0.98	1.75	0.15	2.08	2.74	0.15	1.72	2.11	0.15	2.24	7.82
	7	6625		0.67	1.37	0.15	0.91	1.47	0.15	0.72	1.19	0.15	2.24	6.60
		6705		0.9	1.28	0.15	0.98	1.56	0.15	0.47	1.34	0.15	2.24	6.68
		6785		0.78	1.28	0.15	0.74	1.41	0.15	0.45	1.36	0.15	2.24	6.49
	8	6865		0.43	1.01	0.15	1	1.64	0.15	0.01	0.55	0.15	2.24	6.73
		6945		0.15	0.52	0.15	0.93	1.78	0.15	0.15	0.46	0.15	1.26	5.80
		7025		-0.18	0.65	0.15	0.86	1.48	0.15	-0.33	0.89	0.15	1.26	5.60

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 61			RU Index 62			RU Index 64				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80L)	5	6025	242T	1.65	2.33	0.15	2.12	2.72	0.15	1.35	2.27	0.15	4.28	9.87
		6185		1.58	2.1	0.15	1.86	2.61	0.15	1.5	2.09	0.15	4.28	9.69
		6345		1.62	2.04	0.15	2	2.44	0.15	1.6	2.06	0.15	4.28	9.67
	6	6505		1.26	1.64	0.15	2.26	2.63	0.15	1.16	1.52	0.15	0.11	5.72
	7	6665		-0.28	1.07	0.15	0.29	1.57	0.15	-0.08	1.6	0.15	2.24	6.38
		6825		-0.46	1.07	0.15	0.09	1.4	0.15	-0.47	1.03	0.15	2.24	6.19
	8	6985		-0.81	0.43	0.15	0.44	1.63	0.15	-0.98	0.55	0.15	1.26	5.50

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index S61			RU Index S62			RU Index S64				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80H)	5	6025	242T	1.24	2.38	0.15	1	2.28	0.15	1.53	2.17	0.15	4.28	9.30
		6185		1.36	2.13	0.15	1.21	2.34	0.15	1.63	2.16	0.15	4.28	9.34
		6345		1.44	2.09	0.15	1.43	2.01	0.15	1.75	2.3	0.15	4.28	9.47
	6	6505		1.31	1.61	0.15	1.74	2.35	0.15	1.54	2.11	0.15	0.11	5.33
	7	6665		-0.58	1.26	0.15	-0.8	1.09	0.15	-0.67	1.2	0.15	2.24	5.84
		6825		-0.78	1.02	0.15	0.13	1.15	0.15	-0.66	0.57	0.15	2.24	6.07
	8	6985		-0.99	0.43	0.15	-0.2	1.25	0.15	-0.71	0.73	0.15	1.26	5.01

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925-6425MHz: Directional gain = $10 \log[(10^{3.70/10} + 10^{4.80/10})/2]$= 4.28dBi
6425-6525MHz: Directional gain = $10 \log[(10^{-1.0/10} + 10^{1.0/10})/2]$= 0.11dBi
6525-6875MHz: Directional gain = $10 \log[(10^{2.86/10} + 10^{1.60/10})/2]$= 0.24dBi
6875-7125MHz: Directional gain = $10 \log[(10^{-1.40/10} + 10^{2.90/10})/2]$= 1.26dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.
6. We did spot check for output power and all output power values keep identical thus other conducted items is exempt.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Tones: 484T

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)			Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 65				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE40	5	5965	484T	4.91	5.08	N/A	4.28	12.29
		6165		4.94	5.16	N/A	4.28	12.34
		6405		4.84	5.09	N/A	4.28	12.26
	6	6445		4.96	5.25	N/A	0.11	8.23
		6485		4.96	5.23	N/A	0.11	8.22
	7	6525		5.02	5.04	N/A	2.24	10.28
		6685		4.37	4.42	N/A	2.24	9.65
		6845		4.26	4.21	N/A	2.24	9.49
	8	6885		4.4	4.53	N/A	1.26	8.74
		7005		4.2	4.28	N/A	1.26	8.51
		7085		4.34	4.51	N/A	1.26	8.70

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 65			RU Index 66				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	484T	4.91	4.94	N/A	4.93	5	N/A	4.28	12.26
		6145		5.16	4.9	N/A	5.06	4.97	N/A	4.28	12.32
		6385		4.69	4.82	N/A	5.09	4.74	N/A	4.28	12.21
	6	6465		5.08	4.67	N/A	4.88	5.21	N/A	0.11	8.17
		6545		4.91	5.11	N/A	4.81	4.94	N/A	2.24	10.26
	7	6625		4.17	4.23	N/A	3.91	4.23	N/A	2.24	9.45
		6705		4.15	4.11	N/A	4.08	4.26	N/A	2.24	9.42
		6785		3.86	4.33	N/A	3.95	4.47	N/A	2.24	9.47
	8	6865		3.97	4.26	N/A	4.19	4.1	N/A	2.24	9.40
		6945		4.33	3.94	N/A	3.97	4.38	N/A	1.26	8.45
		7025		4.01	4.18	N/A	4.16	4.15	N/A	1.26	8.43

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925-6425MHz: Directional gain = $10 \log[(10^{3.70/10} + 10^{4.80/10})/2]$= 4.28dBi
6425-6525MHz: Directional gain = $10 \log[(10^{-1.0/10} + 10^{1.0/10})/2]$= 0.11dBi
6525-6875MHz: Directional gain = $10 \log[(10^{2.86/10} + 10^{1.60/10})/2]$= 0.24dBi
6875-7125MHz: Directional gain = $10 \log[(10^{-1.40/10} + 10^{2.90/10})/2]$= 1.26dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.
6. We did spot check for output power and all output power values keep identical thus other conducted items is exempt.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 65			RU Index 66				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80L)	5	6025	484T	4.62	5.15	N/A	4.39	5.11	N/A	4.28	12.18
		6185		4.68	4.9	N/A	4.74	5.01	N/A	4.28	12.17
		6345		4.49	4.9	N/A	4.69	4.98	N/A	4.28	12.13
	6	6505		5.03	4.84	N/A	5.01	4.98	N/A	0.11	8.12
	7	6665		3.6	4.14	N/A	3.24	4.2	N/A	2.24	9.13
		6825		3.57	4.18	N/A	3.37	4.38	N/A	2.24	9.15
	8	6985		4.07	4.05	N/A	3.9	4.43	N/A	1.26	8.44

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index S65			RU Index S66				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80H)	5	6025	484T	4.47	5.1	N/A	4.42	5.16	N/A	4.28	12.10
		6185		4.5	5.05	N/A	4.61	4.72	N/A	4.28	12.07
		6345		4.42	4.78	N/A	4.64	4.8	N/A	4.28	12.01
	6	6505		4.75	5.04	N/A	4.61	4.91	N/A	0.11	8.02
	7	6665		3.62	4.13	N/A	3.56	4.18	N/A	2.24	9.13
		6825		3.67	4.3	N/A	3.66	4.22	N/A	2.24	9.25
	8	6985		3.61	4.03	N/A	3.71	4.39	N/A	1.26	8.33

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925-6425MHz: Directional gain = $10 \log[(10^{3.70/10} + 10^{4.80/10})/2]$= 4.28dBi
6425-6525MHz: Directional gain = $10 \log[(10^{-1.0/10} + 10^{1.0/10})/2]$= 0.11dBi
6525-6875MHz: Directional gain = $10 \log[(10^{2.86/10} + 10^{1.60/10})/2]$= 0.24dBi
6875-7125MHz: Directional gain = $10 \log[(10^{-1.40/10} + 10^{2.90/10})/2]$= 1.26dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.
6. We did spot check for output power and all output power values keep identical thus other conducted items is exempt.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Tones: 996T

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)			Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 67				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	996T	6.49	6.28	0.159	4.28	13.84
		6145		6.72	5.79	0.159	4.28	13.73
		6385		6.8	6.05	0.159	4.28	13.89
	6	6465		6.79	5.97	0.159	0.11	9.68
		6545		6.73	5.74	0.159	2.24	11.67
	7	6625		6.02	4.92	0.159	2.24	10.91
		6705		6.03	4.83	0.159	2.24	10.88
		6785		5.87	4.68	0.159	2.24	10.72
	8	6865		5.74	5.04	0.159	2.24	10.81
		6945		5.77	4.94	0.159	1.26	9.80
		7025		5.85	5.23	0.159	1.26	9.98

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 67			RU Index S67				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160	5	6025	996T	6.85	6.08	0.159	6.62	5.98	0.159	4.28	13.93
		6185		6.63	5.89	0.159	6.73	5.9	0.159	4.28	13.78
		6345		6.94	6.45	0.159	7.02	6.07	0.159	4.28	14.15
	6	6505		6.74	5.42	0.159	6.7	5.71	0.159	0.11	9.51
	7	6665		6.65	5.33	0.159	6.38	4.96	0.159	2.24	11.45
		6825		6.26	5.06	0.159	5.96	4.67	0.159	2.24	11.11
	8	6985		6.01	5.13	0.159	5.81	5.15	0.159	1.26	10.02

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925-6425MHz: Directional gain = $10 \log[(10^{3.70/10} + 10^{4.80/10})/2]$= 4.28dBi
6425-6525MHz: Directional gain = $10 \log[(10^{-1.0/10} + 10^{1.0/10})/2]$= 0.11dBi
6525-6875MHz: Directional gain = $10 \log[(10^{2.86/10} + 10^{1.60/10})/2]$= 0.24dBi
6875-7125MHz: Directional gain = $10 \log[(10^{-1.40/10} + 10^{2.90/10})/2]$= 1.26dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.
6. We did spot check for output power and all output power values keep identical thus other conducted items is exempt.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

● Original Conducted Output Power (FCC ID: BEJNT-17Z90R)

Test SKU: SKU #1 [with (INPAQ) WA-P-LELE-04-011 Antenna]

● OFDM Modulation

Modulation Type	U-NII Band	Centre Frequency (MHz)	Average Coneduted Output Power (dBm)		Duty Cycle Factor (dB) 10log(1/X)	Directional Gain (dBi) Note3	Total E.I.R.P. (dBm) Note2	Limit
			AUX	Main				
802.11ax-HE20	5	5955	1.75	1.42	N/A	3.35	7.95	24dBm
		6175	1.62	1.40		3.35	7.87	
		6415	1.44	1.40		2.60	7.03	
	6	6435	1.43	1.53		2.60	7.09	
		6475	1.75	1.54		2.60	7.26	
		6515	1.63	1.40		2.60	7.13	
	7	6535	0.95	0.63		2.60	6.40	
		6695	0.97	0.26		2.60	6.24	
		6855	1.05	0.31		2.30	6.01	
	8	6875	1.16	0.48		2.30	6.14	
		6995	1.01	0.29		2.30	5.98	
		7115	-3.35	-2.76		2.30	2.27	
802.11ax-HE40	5	5965	5.32	5.30	N/A	3.35	11.67	
		6165	5.19	5.21		3.35	11.56	
		6405	5.00	5.12		2.60	10.67	
	6	6445	5.03	5.36		2.60	10.81	
		6485	5.19	5.23		2.60	10.82	
	7	6525	5.34	5.24		2.60	10.90	
		6685	4.48	4.27		2.60	9.99	
		6845	4.58	4.14		2.30	9.68	
	8	6885	4.62	4.34		2.30	9.79	
		7005	4.53	4.19		2.30	9.67	
		7085	4.73	4.49		2.30	9.92	

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. According to KDB 662911 D01 E)1), Total E.I.R.P. (dBm) = Sum to individual output power (dBm)+ Directional gain (dBi) + duty cycle factor(dB) when duty cycle is less than 98%.
3. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = 10 log[$(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}$] dBi
Directional gain:
5925MHz: Directional gain = 10 log[$(10^{3.20/10} + 10^{3.50/10})/2$]= 3.35dBi
6525MHz: Directional gain = 10 log[$(10^{2.50/10} + 10^{2.70/10})/2$]= 2.60dBi
7125MHz: Directional gain = 10 log[$(10^{2.10/10} + 10^{2.50/10})/2$]= 2.30dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Modulation Type	U-NII Band	Centre Frequency (MHz)	Average Coneduted Output Power (dBm)		Duty Cycle Factor (dB) 10log(1/X)	Directional Gain (dBi) Note3	Total E.I.R.P. (dBm) Note2	Limit
			AUX	Main				
802.11ax-HE80	5	5985	7.23	6.80	N/A	3.35	13.38	24dBm
		6145	7.07	6.51		3.35	13.16	
		6385	7.44	6.86		2.60	12.77	
	6	6465	7.38	6.50		2.60	12.57	
		6545	7.29	6.58		2.60	12.56	
	7	6625	6.48	5.67		2.60	11.70	
		6705	6.39	5.50		2.60	11.58	
		6785	6.26	5.47		2.60	11.49	
	8	6865	6.19	5.54		2.30	11.19	
		6945	6.53	5.78		2.30	11.48	
		7025	6.61	5.99		2.30	11.62	
802.11ax-HE160	5	6025	10.05	9.43	N/A	3.35	16.11	
		6185	10.06	9.41		3.35	16.11	
		6345	10.33	9.62		2.60	15.60	
	6	6505	10.02	9.31		2.60	15.29	
	7	6665	9.40	8.37		2.60	14.53	
		6825	9.24	8.39		2.30	14.15	
	8	6985	9.56	8.69		2.30	14.46	

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]

2. According to KDB 662911 D01 E)1), Total E.I.R.P. (dBm) = Sum to individual output power (dBm)+ Directional gain (dBi) + duty cycle factor(dB) when duty cycle is less than 98%.

3. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then

Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi

Directional gain:

5925MHz: Directional gain = $10 \log[(10^{3.20/10} + 10^{3.50/10})/2]$= 3.35dBi

6525MHz: Directional gain = $10 \log[(10^{2.50/10} + 10^{2.70/10})/2]$= 2.60dBi

7125MHz: Directional gain = $10 \log[(10^{2.10/10} + 10^{2.50/10})/2]$= 2.30dBi

The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

● OFDMA Modulation

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 0			RU Index 4			RU Index 8				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE20	5	5955	26T	-5.99	-5.71	0.223	-5.91	-5.68	0.223	-6.00	-5.86	0.223	3.35	0.65
		6175		-7.35	-7.50	0.223	-6.99	-7.21	0.223	-7.28	-7.53	0.223	3.35	-0.82
		6415		-7.50	-7.98	0.223	-7.43	-7.89	0.223	-7.92	-8.10	0.223	2.60	-2.18
	6	6435		-7.53	-7.84	0.223	-7.56	-7.64	0.223	-7.63	-8.00	0.223	2.60	-1.98
		6475		-7.90	-8.01	0.223	-7.65	-7.90	0.223	-7.85	-8.21	0.223	2.60	-2.19
		6515		-8.04	-8.22	0.223	-7.73	-8.02	0.223	-8.11	-8.26	0.223	2.60	-2.35
	7	6535		-8.68	-8.99	0.223	-8.71	-8.85	0.223	-9.02	-9.18	0.223	2.60	-3.27
		6695		-9.30	-8.89	0.223	-9.11	-8.62	0.223	-9.39	-8.84	0.223	2.60	-3.27
		6855		-8.76	-8.51	0.223	-8.77	-8.31	0.223	-8.84	-8.59	0.223	2.30	-3.18
	8	6875		-9.05	-8.65	0.223	-9.04	-8.41	0.223	-9.27	-8.73	0.223	2.30	-3.46
		6995		-8.02	-7.83	0.223	-7.81	-7.68	0.223	-8.08	-7.93	0.223	2.30	-2.47
		7115		-7.79	-7.60	0.223	-7.65	-7.33	0.223	-7.80	-7.53	0.223	2.30	-2.13

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 0			RU Index 8			RU Index 17				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE40	5	5965	26T	-6.09	-5.78	0.223	-5.89	-5.83	0.223	-5.92	-5.79	0.223	3.35	0.73
		6165		-6.92	-7.30	0.223	-7.04	-7.49	0.223	-7.18	-7.45	0.223	3.35	-0.73
		6405		-7.45	-7.87	0.223	-7.64	-7.95	0.223	-7.73	-8.07	0.223	2.60	-2.06
	6	6445		-7.65	-7.77	0.223	-7.93	-7.92	0.223	-7.85	-8.05	0.223	2.60	-2.12
		6485		-7.81	-7.97	0.223	-8.07	-8.11	0.223	-8.08	-8.25	0.223	2.60	-2.33
	7	6525		-8.02	-8.14	0.223	-8.18	-8.36	0.223	-8.10	-8.37	0.223	2.60	-2.40
		6685		-9.22	-8.84	0.223	-9.34	-8.94	0.223	-9.31	-8.90	0.223	2.60	-3.27
		6845		-8.68	-8.34	0.223	-8.77	-8.45	0.223	-8.99	-8.54	0.223	2.30	-3.23
	8	6885		-8.99	-8.56	0.223	-9.21	-8.70	0.223	-9.21	-8.99	0.223	2.30	-3.57
		7005		-7.85	-7.89	0.223	-8.15	-8.07	0.223	-8.20	-8.09	0.223	2.30	-2.61
		7085		-7.50	-7.27	0.223	-7.64	-7.48	0.223	-8.55	-8.17	0.223	2.30	-2.82

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{3.20/10} + 10^{3.50/10})/2]$= 3.35dBi
6525MHz: Directional gain = $10 \log[(10^{2.50/10} + 10^{2.70/10})/2]$= 2.60dBi
7125MHz: Directional gain = $10 \log[(10^{2.10/10} + 10^{2.50/10})/2]$= 2.30dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 0			RU Index 18			RU Index 36				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	26T	-6.10	-5.60	0.223	-5.42	-5.22	0.223	-6.20	-5.99	0.223	3.35	0.49
		6145		-6.99	-7.06	0.223	-6.69	-6.72	0.223	-7.57	-7.49	0.223	3.35	-0.95
		6385		-7.51	-7.73	0.223	-7.18	-7.27	0.223	-8.00	-8.06	0.223	2.60	-2.20
	6	6465		-8.18	-7.91	0.223	-7.58	-7.48	0.223	-8.42	-8.34	0.223	2.60	-2.55
		6545		-8.35	-8.27	0.223	-8.07	-7.89	0.223	-8.98	-8.75	0.223	2.60	-3.03
	7	6625		-9.64	-8.95	0.223	-8.92	-8.31	0.223	-9.85	-8.89	0.223	2.60	-3.51
		6705		-9.60	-8.85	0.223	-9.08	-8.31	0.223	-9.95	-8.84	0.223	2.60	-3.53
		6785		-8.85	-8.33	0.223	-8.23	-7.76	0.223	-9.11	-8.43	0.223	2.60	-2.92
	8	6865		-9.04	-8.46	0.223	-8.63	-7.94	0.223	-9.71	-9.00	0.223	2.30	-3.81
		6945		-8.03	-7.35	0.223	-7.36	-6.97	0.223	-8.47	-7.88	0.223	2.30	-2.63
		7025		-8.34	-8.00	0.223	-7.92	-7.52	0.223	-8.90	-8.42	0.223	2.30	-3.12

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 0			RU Index 18			RU Index 36				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80L)	5	6025	26T	-6.10	-5.60	0.223	-6.10	-5.60	0.223	-6.10	-5.60	0.223	3.35	0.65
		6185		-6.99	-7.06	0.223	-6.99	-7.06	0.223	-6.99	-7.06	0.223	3.35	-0.65
		6345		-7.51	-7.73	0.223	-7.51	-7.73	0.223	-7.51	-7.73	0.223	2.60	-1.62
	6	6505		-8.18	-7.91	0.223	-8.18	-7.91	0.223	-8.18	-7.91	0.223	2.60	-2.12
	7	6665		-8.35	-8.27	0.223	-8.35	-8.27	0.223	-8.35	-8.27	0.223	2.60	-3.22
		6825		-9.64	-8.95	0.223	-9.64	-8.95	0.223	-9.64	-8.95	0.223	2.30	-2.77
	8	6985		-9.60	-8.85	0.223	-9.60	-8.85	0.223	-9.60	-8.85	0.223	2.30	-2.21

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index S0			RU Index S18			RU Index S36				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80H)	5	6025	26T	-5.96	-5.84	0.223	-6.73	-6.36	0.223	-8.34	-7.93	0.223	3.35	-1.55
		6185		-7.40	-7.07	0.223	-7.89	-7.66	0.223	-9.34	-9.19	0.223	3.35	-2.68
		6345		-7.64	-7.24	0.223	-8.09	-7.72	0.223	-9.88	-9.42	0.223	2.60	-3.81
	6	6505		-7.99	-7.89	0.223	-8.93	-8.63	0.223	-10.44	-10.28	0.223	2.60	-4.53
	7	6665		-8.66	-9.13	0.223	-9.15	-9.73	0.223	-10.41	-11.02	0.223	2.60	-4.87
		6825		-8.13	-8.71	0.223	-8.85	-9.28	0.223	-10.46	-10.94	0.223	2.30	-5.16
	8	6985		-7.74	-7.83	0.223	-8.46	-8.61	0.223	-9.91	-10.21	0.223	2.30	-4.52

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{3.20/10} + 10^{3.50/10})/2]$= 3.35dBi
6525MHz: Directional gain = $10 \log[(10^{2.50/10} + 10^{2.70/10})/2]$= 2.60dBi
7125MHz: Directional gain = $10 \log[(10^{2.10/10} + 10^{2.50/10})/2]$= 2.30dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Tones: 52T

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 37			RU Index 39			RU Index 40				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE20	5	5955	52T	-2.78	-2.42	0.119	-2.55	-2.54	0.119	-2.62	-2.68	0.119	3.35	3.83
		6175		-3.80	-4.25	0.119	-3.89	-4.12	0.119	-4.08	-4.26	0.119	3.35	2.31
		6415		-4.20	-4.75	0.119	-4.20	-4.81	0.119	-4.54	-4.94	0.119	2.60	0.99
	6	6435		-4.52	-4.72	0.119	-4.36	-4.68	0.119	-4.52	-4.69	0.119	2.60	1.13
		6475		-4.69	-4.88	0.119	-4.67	-4.77	0.119	-4.63	-4.84	0.119	2.60	1.00
		6515		-4.74	-4.99	0.119	-4.69	-4.97	0.119	-4.78	-5.07	0.119	2.60	0.81
	7	6535		-5.47	-5.79	0.119	-5.67	-5.81	0.119	-5.76	-5.91	0.119	2.60	-0.11
		6695		-6.13	-5.63	0.119	-5.86	-5.62	0.119	-6.00	-5.67	0.119	2.60	-0.10
		6855		-5.56	-5.32	0.119	-5.62	-5.26	0.119	-5.68	-5.40	0.119	2.30	-0.11
	8	6875		-5.88	-5.42	0.119	-5.68	-5.39	0.119	-5.90	-5.48	0.119	2.30	-0.26
		6995		-4.86	-4.65	0.119	-4.79	-4.63	0.119	-4.97	-4.76	0.119	2.30	0.57
		7115		-4.51	-4.36	0.119	-4.55	-4.35	0.119	-8.39	-8.10	0.119	2.30	-2.81

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 37			RU Index 40			RU Index 44				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE40	5	5965	52T	-3.01	-2.58	0.119	-2.91	-2.78	0.119	-2.95	-2.77	0.119	3.35	3.62
		6165		-3.88	-4.25	0.119	-3.89	-4.32	0.119	-4.07	-4.37	0.119	3.35	2.26
		6405		-4.22	-4.92	0.119	-4.35	-4.91	0.119	-4.52	-5.03	0.119	2.60	0.96
	6	6445		-4.67	-4.71	0.119	-4.58	-4.76	0.119	-4.61	-4.88	0.119	2.60	0.99
		6485		-4.66	-4.93	0.119	-4.67	-4.92	0.119	-4.65	-5.02	0.119	2.60	0.90
	7	6525		-4.89	-5.02	0.119	-4.96	-5.19	0.119	-4.91	-5.19	0.119	2.60	0.68
		6685		-6.01	-5.73	0.119	-6.05	-5.77	0.119	-6.22	-5.71	0.119	2.60	-0.23
		6845		-5.66	-5.30	0.119	-5.83	-5.31	0.119	-5.86	-5.45	0.119	2.30	-0.22
	8	6885		-5.87	-5.49	0.119	-6.08	-5.54	0.119	-6.10	-5.82	0.119	2.30	-0.53
		7005		-4.90	-4.64	0.119	-5.02	-4.87	0.119	-5.09	-4.94	0.119	2.30	0.41
		7085		-4.44	-4.15	0.119	-4.48	-4.31	0.119	-4.70	-4.42	0.119	2.30	0.87

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{3.20/10} + 10^{3.50/10})/2]$= 3.35dBi
6525MHz: Directional gain = $10 \log[(10^{2.50/10} + 10^{2.70/10})/2]$= 2.60dBi
7125MHz: Directional gain = $10 \log[(10^{2.10/10} + 10^{2.50/10})/2]$= 2.30dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 37			RU Index 44			RU Index 52				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	52T	-2.74	-3.08	0.119	-2.30	-2.67	0.119	-3.07	-3.13	0.119	3.35	3.38
		6145		-4.02	-3.94	0.119	-3.68	-3.73	0.119	-4.41	-4.46	0.119	3.35	2.04
		6385		-4.81	-4.56	0.119	-4.39	-4.28	0.119	-5.28	-5.18	0.119	2.60	0.50
	6	6465		-4.92	-5.27	0.119	-4.68	-4.87	0.119	-5.25	-5.55	0.119	2.60	0.33
		6545		-5.28	-5.53	0.119	-5.03	-5.26	0.119	-5.58	-6.03	0.119	2.60	-0.07
	7	6625		-5.85	-6.64	0.119	-5.60	-6.31	0.119	-5.99	-6.95	0.119	2.60	-0.71
		6705		-6.02	-6.87	0.119	-5.32	-6.54	0.119	-5.88	-7.12	0.119	2.60	-0.73
		6785		-5.29	-6.14	0.119	-4.99	-5.75	0.119	-5.37	-6.34	0.119	2.60	-0.10
	8	6865		-5.50	-6.42	0.119	-5.12	-6.24	0.119	-6.00	-6.97	0.119	2.30	-1.03
		6945		-4.83	-5.21	0.119	-4.04	-4.89	0.119	-4.90	-5.51	0.119	2.30	0.24
		7025		-5.01	-5.70	0.119	-4.78	-5.39	0.119	-5.44	-6.11	0.119	2.30	-0.33

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 37			RU Index 44			RU Index 52				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80L)	5	6025	52T	-4.19	-4.33	0.119	-3.25	-3.26	0.119	-2.86	-2.65	0.119	3.35	3.73
		6185		-5.66	-5.20	0.119	-4.52	-4.23	0.119	-4.13	-3.91	0.119	3.35	2.46
		6345		-6.09	-5.66	0.119	-4.96	-4.39	0.119	-4.42	-3.88	0.119	2.60	1.59
	6	6505		-6.36	-6.31	0.119	-5.37	-5.27	0.119	-4.97	-4.82	0.119	2.60	0.83
	7	6665		-7.30	-7.69	0.119	-6.10	-6.53	0.119	-5.68	-6.08	0.119	2.60	-0.15
		6825		-6.79	-7.19	0.119	-5.69	-6.07	0.119	-5.20	-5.64	0.119	2.30	0.01
	8	6985		-5.76	-6.18	0.119	-4.90	-5.21	0.119	-4.63	-4.86	0.119	2.30	0.69

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index S37			RU Index S44			RU Index S52				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80H)	5	6025	52T	-2.84	-2.88	0.119	-3.47	-3.30	0.119	-5.17	-4.72	0.119	3.35	1.54
		6185		-4.33	-3.94	0.119	-4.78	-4.53	0.119	-6.13	-6.18	0.119	3.35	0.32
		6345		-4.44	-4.11	0.119	-4.94	-4.57	0.119	-6.85	-6.12	0.119	2.60	-0.74
	6	6505		-4.82	-4.78	0.119	-5.75	-5.35	0.119	-7.23	-6.97	0.119	2.60	-1.37
	7	6665		-5.71	-6.18	0.119	-6.06	-6.67	0.119	-7.36	-8.03	0.119	2.60	-1.95
		6825		-5.11	-5.81	0.119	-5.85	-6.30	0.119	-7.40	-7.98	0.119	2.30	-2.25
	8	6985		-4.55	-5.02	0.119	-5.33	-5.38	0.119	-7.07	-7.08	0.119	2.30	-1.65

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{3.20/10} + 10^{3.50/10})/2]$= 3.35dBi
6525MHz: Directional gain = $10 \log[(10^{2.50/10} + 10^{2.70/10})/2]$= 2.60dBi
7125MHz: Directional gain = $10 \log[(10^{2.10/10} + 10^{2.50/10})/2]$= 2.30dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Tones: 106T

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 53			RU Index 54				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE20	5	5955	106T	0.35	0.41	N/A	0.20	0.40	N/A	3.35	6.66
		6175		-0.72	-1.01	N/A	-0.88	-1.19	N/A	3.35	5.33
		6415		-1.13	-1.74	N/A	-1.30	-1.87	N/A	2.60	4.03
	6	6435		-1.47	-1.49	N/A	-1.30	-1.52	N/A	2.60	4.20
		6475		-1.38	-1.68	N/A	-1.63	-1.75	N/A	2.60	3.92
		6515		-1.61	-1.82	N/A	-1.62	-1.87	N/A	2.60	3.87
	7	6535		-2.44	-2.78	N/A	-2.57	-2.83	N/A	2.60	2.91
		6695		-3.19	-2.71	N/A	-2.93	-2.59	N/A	2.60	2.85
		6855		-2.56	-2.14	N/A	-2.68	-2.23	N/A	2.30	2.86
	8	6875		-2.67	-2.34	N/A	-2.76	-2.47	N/A	2.30	2.70
		6995		-1.64	-1.58	N/A	-1.71	-1.65	N/A	2.30	3.63
		7115		-1.47	-1.28	N/A	-8.47	-7.97	N/A	2.30	-2.90

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 53			RU Index 54			RU Index 56				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE40	5	5965	106T	0.21	0.29	N/A	0.14	0.35	N/A	0.28	0.18	N/A	3.35	6.59
		6165		-0.85	-1.17	N/A	-0.98	-1.23	N/A	-1.06	-1.26	N/A	3.35	5.20
		6405		-1.24	-1.79	N/A	-1.30	-1.79	N/A	-1.55	-1.98	N/A	2.60	3.85
	6	6445		-1.56	-1.69	N/A	-1.33	-1.66	N/A	-1.45	-1.76	N/A	2.60	4.01
		6485		-1.65	-1.82	N/A	-1.54	-1.80	N/A	-1.78	-1.92	N/A	2.60	3.76
	7	6525		-1.71	-1.98	N/A	-1.73	-2.03	N/A	-1.85	-2.29	N/A	2.60	3.55
		6685		-3.05	-2.72	N/A	-3.14	-2.65	N/A	-3.09	-2.66	N/A	2.60	2.74
		6845		-2.63	-2.24	N/A	-2.79	-2.23	N/A	-2.87	-2.44	N/A	2.30	2.66
	8	6885		-2.92	-2.43	N/A	-2.92	-2.50	N/A	-3.08	-2.73	N/A	2.30	2.41
		7005		-1.83	-1.68	N/A	-1.72	-1.70	N/A	-2.01	-1.85	N/A	2.30	3.38
		7085		-1.52	-1.19	N/A	-1.49	-1.22	N/A	-1.60	-1.34	N/A	2.30	3.84

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{3.20/10} + 10^{3.50/10})/2]$= 3.35dBi
6525MHz: Directional gain = $10 \log[(10^{2.50/10} + 10^{2.70/10})/2]$= 2.60dBi
7125MHz: Directional gain = $10 \log[(10^{2.10/10} + 10^{2.50/10})/2]$= 2.30dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 53			RU Index 56			RU Index 60				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	106T	0.09	-0.09	N/A	0.65	0.36	N/A	-0.18	-0.18	N/A	3.35	6.18
		6145		-1.16	-1.06	N/A	-1.03	-0.86	N/A	-1.49	-1.47	N/A	3.35	4.88
		6385		-1.86	-1.71	N/A	-1.65	-1.45	N/A	-2.21	-2.07	N/A	2.60	3.47
	6	6465		-1.88	-2.28	N/A	-1.54	-2.04	N/A	-2.09	-2.55	N/A	2.60	3.30
		6545		-2.11	-2.59	N/A	-1.95	-2.36	N/A	-2.77	-3.01	N/A	2.60	2.72
	7	6625		-2.98	-3.74	N/A	-2.60	-3.44	N/A	-2.95	-3.98	N/A	2.60	2.18
		6705		-2.82	-3.99	N/A	-2.42	-3.70	N/A	-2.81	-4.12	N/A	2.60	2.19
		6785		-1.80	-2.76	N/A	-1.56	-2.53	N/A	-2.29	-3.25	N/A	2.60	2.87
	8	6865		-2.24	-3.17	N/A	-2.08	-2.99	N/A	-2.63	-3.71	N/A	2.30	2.17
		6945		-1.33	-2.00	N/A	-1.06	-1.70	N/A	-1.89	-2.28	N/A	2.30	3.23
		7025		-1.87	-2.30	N/A	-1.53	-2.21	N/A	-2.35	-2.74	N/A	2.30	2.77

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 53			RU Index 56			RU Index 60				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80L)	5	6025	106T	-1.20	-1.28	N/A	-0.22	-0.25	N/A	0.16	0.43	N/A	3.35	6.66
		6185		-2.37	-2.08	N/A	-1.45	-1.30	N/A	-1.16	-0.98	N/A	3.35	5.29
		6345		-3.25	-2.32	N/A	-2.02	-1.34	N/A	-1.46	-0.98	N/A	2.60	4.40
	6	6505		-3.07	-3.05	N/A	-2.13	-2.11	N/A	-1.79	-1.75	N/A	2.60	3.84
	7	6665		-4.31	-4.41	N/A	-3.39	-3.39	N/A	-2.71	-2.86	N/A	2.60	2.83
		6825		-3.76	-3.71	N/A	-2.98	-2.82	N/A	-2.31	-2.26	N/A	2.30	3.03
	8	6985		-2.74	-2.73	N/A	-1.82	-1.94	N/A	-1.49	-1.51	N/A	2.30	3.81

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index S53			RU Index S56			RU Index S60				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80H)	5	6025	106T	0.21	0.28	N/A	-0.40	-0.05	N/A	-2.09	-1.72	N/A	3.35	4.46
		6185		-1.22	-0.82	N/A	-1.59	-1.45	N/A	-3.06	-3.01	N/A	3.35	3.33
		6345		-1.36	-1.04	N/A	-1.93	-1.47	N/A	-3.37	-2.99	N/A	2.60	2.43
	6	6505		-1.90	-1.69	N/A	-2.32	-2.28	N/A	-3.88	-3.80	N/A	2.60	1.77
	7	6665		-2.92	-3.12	N/A	-3.45	-3.54	N/A	-4.90	-4.81	N/A	2.60	0.76
		6825		-2.29	-2.24	N/A	-3.03	-2.93	N/A	-4.37	-4.56	N/A	2.30	0.85
	8	6985		-1.56	-1.45	N/A	-2.26	-1.97	N/A	-3.75	-3.53	N/A	2.30	1.67

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{3.20/10} + 10^{3.50/10})/2]$= 3.35dBi
6525MHz: Directional gain = $10 \log[(10^{2.50/10} + 10^{2.70/10})/2]$= 2.60dBi
7125MHz: Directional gain = $10 \log[(10^{2.10/10} + 10^{2.50/10})/2]$= 2.30dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Tones: 242T

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)			Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 61				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE20	5	5955	242T	2.13	2.48	0.15	3.35	8.82
		6175		2.07	2.41	0.15	3.35	8.75
		6415		1.95	2.42	0.15	2.60	7.95
	6	6435		1.38	1.86	0.15	2.60	7.39
		6475		1.51	1.8	0.15	2.60	7.42
		6515		1.76	1.8	0.15	2.60	7.54
	7	6535		1.43	1.61	0.15	2.60	7.28
		6695		1.71	1.72	0.15	2.60	7.48
		6855		1.59	1.76	0.15	2.30	7.14
	8	6875		0.96	1.11	0.15	2.30	6.50
		6995		0.91	0.89	0.15	2.30	6.36
		7115		-2.82	-2.64	0.15	2.30	2.73

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 61			RU Index 62				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE40	5	5965	242T	2.01	1.3	0.15	1.89	1.19	0.15	3.35	8.06
		6165		1.73	1.4	0.15	1.54	1.16	0.15	3.35	7.86
		6405		1.69	1.4	0.15	1.7	1.45	0.15	2.60	7.34
	6	6445		1.07	1.07	0.15	1.38	1.02	0.15	2.60	6.96
		6485		1.22	0.92	0.15	1.07	1.44	0.15	2.60	7.02
	7	6525		1.44	0.89	0.15	2.21	1.51	0.15	2.60	7.63
		6685		1.12	0.19	0.15	1.34	0.25	0.15	2.60	6.59
		6845		1.14	0.04	0.15	1.29	0.17	0.15	2.30	6.23
	8	6885		0.87	-0.15	0.15	0.71	-0.06	0.15	2.30	5.80
		7005		0.78	-0.33	0.15	0.84	-0.22	0.15	2.30	5.80
		7085		0.91	0.06	0.15	1.16	0.55	0.15	2.30	6.33

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = 10 log[$(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}$] dBi
Directional gain:
5925MHz: Directional gain = 10 log[$(10^{3.20/10} + 10^{3.50/10})/2$]= 3.35dBi
6525MHz: Directional gain = 10 log[$(10^{2.50/10} + 10^{2.70/10})/2$]= 2.60dBi
7125MHz: Directional gain = 10 log[$(10^{2.10/10} + 10^{2.50/10})/2$]= 2.30dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan

Tel: +886 2 26099301
Fax: +886 2 26099303

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 61			RU Index 62			RU Index 64				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	242T	2.35	2.73	0.15	2.36	2.91	0.15	2.34	2.44	0.15	3.35	8.90
		6145		2.57	2.56	0.15	2.49	2.58	0.15	2.13	2.35	0.15	3.35	8.75
		6385		2.08	2.17	0.15	2.33	2.41	0.15	2.27	2.4	0.15	2.60	8.10
	6	6465		1.81	1.58	0.15	2.72	2.72	0.15	1.81	1.65	0.15	2.60	7.49
		6545		1.38	1.99	0.15	2.34	2.91	0.15	1.97	2.43	0.15	2.60	7.97
	7	6625		0.94	1.67	0.15	1.13	1.84	0.15	0.87	1.6	0.15	2.60	7.01
		6705		1.16	1.74	0.15	1.25	1.86	0.15	0.89	1.65	0.15	2.60	7.05
		6785		0.99	1.58	0.15	1.03	1.74	0.15	0.87	1.72	0.15	2.60	7.08
	8	6865		0.83	1.44	0.15	1.25	1.86	0.15	0.42	0.86	0.15	2.30	6.11
		6945		0.53	0.93	0.15	1.36	1.97	0.15	0.42	0.86	0.15	2.30	6.11
		7025		0.23	0.89	0.15	1.2	1.89	0.15	0	1.18	0.15	2.30	6.09

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 61			RU Index 62			RU Index 64				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80L)	5	6025	242T	1.95	2.74	0.15	2.36	3.03	0.15	1.74	2.56	0.15	3.35	8.68
		6185		1.93	2.37	0.15	2.14	2.93	0.15	1.84	2.42	0.15	3.35	8.65
		6345		1.89	2.52	0.15	2.33	2.63	0.15	1.87	2.4	0.15	2.60	7.90
	6	6505		1.63	1.93	0.15	2.5	2.95	0.15	1.5	1.92	0.15	2.60	7.48
	7	6665		0.09	1.4	0.15	0.57	1.91	0.15	0.23	1.85	0.15	2.60	6.88
		6825		-0.01	1.39	0.15	0.38	1.62	0.15	-0.2	1.25	0.15	2.30	6.05
	8	6985		-0.48	0.65	0.15	0.74	2	0.15	-0.69	0.85	0.15	2.30	5.61

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index S61			RU Index S62			RU Index S64				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80H)	5	6025	242T	1.54	2.75	0.15	1.49	2.6	0.15	1.76	2.54	0.15	3.35	8.68
		6185		1.72	2.48	0.15	1.54	2.54	0.15	1.88	2.57	0.15	3.35	8.75
		6345		1.78	2.31	0.15	1.69	2.45	0.15	2.01	2.51	0.15	2.60	8.03
	6	6505		1.53	1.98	0.15	2.08	2.6	0.15	1.82	2.51	0.15	2.60	7.94
	7	6665		-0.15	1.52	0.15	-0.41	1.36	0.15	-0.37	1.66	0.15	2.60	6.52
		6825		-0.47	1.43	0.15	0.31	1.34	0.15	-0.24	0.87	0.15	2.30	5.81
	8	6985		-0.58	0.74	0.15	0.26	1.64	0.15	-0.34	1.02	0.15	2.30	5.85

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = 10 log[($10^{G1/10}$ + $10^{G2/10}$ + … + $10^{GN/10}$)/N_{ANT}] dBi
Directional gain:
5925MHz: Directional gain = 10 log[($10^{3.20/10}$ +$10^{3.50/10}$)/2]= 3.35dBi
6525MHz: Directional gain = 10 log[($10^{2.50/10}$ +$10^{2.70/10}$)/2]= 2.60dBi
7125MHz: Directional gain = 10 log[($10^{2.10/10}$ +$10^{2.50/10}$)/2]= 2.30dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Tones: 484T

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)			Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 65				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE40	5	5965	484T	5.33	5.57	N/A	3.35	11.81
		6165		5.17	5.5	N/A	3.35	11.70
		6405		5.18	5.29	N/A	2.60	10.85
	6	6445		5.32	5.56	N/A	2.60	11.05
		6485		5.25	5.59	N/A	2.60	11.03
	7	6525		5.44	5.46	N/A	2.60	11.06
		6685		4.68	4.84	N/A	2.60	10.37
		6845		4.61	4.66	N/A	2.30	9.95
	8	6885		4.74	4.88	N/A	2.30	10.12
		7005		4.56	4.53	N/A	2.30	9.86
		7085		4.73	4.98	N/A	2.30	10.17

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 65			RU Index 66				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	484T	5.33	5.36	N/A	5.31	5.41	N/A	3.35	11.72
		6145		5.46	5.3	N/A	5.45	5.29	N/A	3.35	11.73
		6385		5.03	5.12	N/A	5.45	5.17	N/A	2.60	10.92
	6	6465		5.47	5.1	N/A	5.3	5.44	N/A	2.60	10.98
		6545		5.17	5.61	N/A	5.19	5.24	N/A	2.60	10.83
	7	6625		4.39	4.53	N/A	4.29	4.45	N/A	2.60	9.98
		6705		4.49	4.46	N/A	4.37	4.64	N/A	2.60	10.12
		6785		4.15	4.5	N/A	4.33	4.68	N/A	2.60	10.12
	8	6865		4.28	4.62	N/A	4.52	4.52	N/A	2.30	9.83
		6945		4.58	4.36	N/A	4.3	4.58	N/A	2.30	9.75
		7025		4.22	4.51	N/A	4.44	4.55	N/A	2.30	9.81

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{3.20/10} + 10^{3.50/10})/2]$= 3.35dBi
6525MHz: Directional gain = $10 \log[(10^{2.50/10} + 10^{2.70/10})/2]$= 2.60dBi
7125MHz: Directional gain = $10 \log[(10^{2.10/10} + 10^{2.50/10})/2]$= 2.30dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 65			RU Index 66				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80L)	5	6025	484T	4.98	5.44	N/A	4.67	5.49	N/A	3.35	11.46
		6185		5.05	5.3	N/A	5.04	5.32	N/A	3.35	11.54
		6345		4.93	5.19	N/A	5.01	5.27	N/A	2.60	10.75
	6	6505		5.23	5.12	N/A	5.25	5.39	N/A	2.60	10.93
	7	6665		3.96	4.53	N/A	3.61	4.42	N/A	2.60	9.64
		6825		3.96	4.47	N/A	3.7	4.63	N/A	2.30	9.50
	8	6985		4.25	4.42	N/A	4.09	4.75	N/A	2.30	9.74

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index S65			RU Index S66				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80H)	5	6025	484T	4.81	5.42	N/A	4.83	5.41	N/A	3.35	11.49
		6185		4.81	5.36	N/A	4.85	5.12	N/A	3.35	11.35
		6345		4.62	5.19	N/A	4.93	5.16	N/A	2.60	10.66
	6	6505		5.06	5.45	N/A	4.94	5.31	N/A	2.60	10.74
	7	6665		3.99	4.52	N/A	3.93	4.51	N/A	2.60	9.84
		6825		3.97	4.56	N/A	4.03	4.61	N/A	2.30	9.64
	8	6985		4.09	4.41	N/A	4.06	4.74	N/A	2.30	9.72

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{3.20/10} + 10^{3.50/10})/2]$= 3.35dBi
6525MHz: Directional gain = $10 \log[(10^{2.50/10} + 10^{2.70/10})/2]$= 2.60dBi
7125MHz: Directional gain = $10 \log[(10^{2.10/10} + 10^{2.50/10})/2]$= 2.30dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Tones: 996T

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)			Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 67				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	996T	7.25	6.58	0.159	3.35	13.45
		6145		7.22	6.24	0.159	3.35	13.28
		6385		7.49	6.52	0.159	2.60	12.80
	6	6465		7.36	6.43	0.159	2.60	12.69
		6545		7.41	6.35	0.159	2.60	12.68
	7	6625		6.72	5.45	0.159	2.60	11.90
		6705		6.44	5.37	0.159	2.60	11.71
		6785		6.3	5.3	0.159	2.60	11.60
	8	6865		6.14	5.3	0.159	2.30	11.21
		6945		6.54	5.58	0.159	2.30	11.56
		7025		6.71	5.73	0.159	2.30	11.72

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 67			RU Index S67				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160	5	6025	996T	7.57	6.67	0.159	7.34	6.68	0.159	3.35	13.54
		6185		7.58	6.76	0.159	7.59	6.66	0.159	3.35	13.67
		6345		7.76	6.81	0.159	7.58	6.81	0.159	2.60	12.98
	6	6505		7.14	6.23	0.159	7.04	6.18	0.159	2.60	12.40
	7	6665		6.95	5.69	0.159	6.75	5.61	0.159	2.60	11.99
		6825		6.62	5.62	0.159	6.22	5.36	0.159	2.30	11.28
	8	6985		6.58	5.72	0.159	6.48	5.75	0.159	2.30	11.60

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = 10 log[($10^{G1/10}$ + $10^{G2/10}$ + … + $10^{GN/10}$)/N_{ANT}] dBi
Directional gain:
5925MHz: Directional gain = 10 log[($10^{3.20/10}$ +$10^{3.50/10}$)/2]= 3.35dBi
6525MHz: Directional gain = 10 log[($10^{2.50/10}$ +$10^{2.70/10}$)/2]= 2.60dBi
7125MHz: Directional gain = 10 log[($10^{2.10/10}$ +$10^{2.50/10}$)/2]= 2.30dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Test SKU: SKU #2 [with (LUXSHARE-ICT) L1LRF009-CS-H Antenna]

- OFDM Modulation

Modulation Type	U-NII Band	Centre Frequency (MHz)	Average Coneduted Output Power (dBm)		Duty Cycle Factor (dB) 10log(1/X)	Directional Gain (dBi) Note3	Total E.I.R.P. (dBm) Note2	Limit
			AUX	Main				
802.11ax-HE20	5	5955	1.75	1.42	N/A	4.49	9.09	24dBm
		6175	1.62	1.40		4.49	9.01	
		6415	1.44	1.40		1.29	5.72	
	6	6435	1.43	1.53		1.29	5.78	
		6475	1.75	1.54		1.29	5.95	
		6515	1.63	1.40		1.29	5.82	
	7	6535	0.95	0.63		1.29	5.09	
		6695	0.97	0.26		1.29	4.93	
		6855	1.05	0.31		3.07	6.78	
	8	6875	1.16	0.48		3.07	6.91	
		6995	1.01	0.29		3.07	6.75	
		7115	-3.35	-2.76		3.07	3.04	
802.11ax-HE40	5	5965	5.32	5.30	N/A	4.49	12.81	
		6165	5.19	5.21		4.49	12.70	
		6405	5.00	5.12		1.29	9.36	
	6	6445	5.03	5.36		1.29	9.50	
		6485	5.19	5.23		1.29	9.51	
	7	6525	5.34	5.24		1.29	9.59	
		6685	4.48	4.27		1.29	8.68	
		6845	4.58	4.14		3.07	10.45	
	8	6885	4.62	4.34		3.07	10.56	
		7005	4.53	4.19		3.07	10.44	
		7085	4.73	4.49		3.07	10.69	

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. According to KDB 662911 D01 E)1), Total E.I.R.P. (dBm) = Sum to individual output power (dBm)+ Directional gain (dBi) + duty cycle factor(dB) when duty cycle is less than 98%.
3. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{2.48/10} + 10^{5.85/10})/2]$= 4.49dBi
6525MHz: Directional gain = $10 \log[(10^{1.38/10} + 10^{1.19/10})/2]$= 1.29dBi
7125MHz: Directional gain = $10 \log[(10^{1.89/10} + 10^{3.99/10})/2]$= 3.07dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Modulation Type	U-NII Band	Centre Frequency (MHz)	Average Coneduted Output Power (dBm)		Duty Cycle Factor (dB) 10log(1/X)	Directional Gain (dBi) Note3	Total E.I.R.P. (dBm) Note2	Limit
			AUX	Main				
802.11ax-HE80	5	5985	7.23	6.80	N/A	4.49	14.52	24dBm
		6145	7.07	6.51		4.49	14.30	
		6385	7.44	6.86		1.29	11.46	
	6	6465	7.38	6.50		1.29	11.26	
		6545	7.29	6.58		1.29	11.25	
	7	6625	6.48	5.67		1.29	10.39	
		6705	6.39	5.50		1.29	10.27	
		6785	6.26	5.47		1.29	10.18	
	8	6865	6.19	5.54		3.07	11.96	
		6945	6.53	5.78		3.07	12.25	
		7025	6.61	5.99		3.07	12.39	
802.11ax-HE160	5	6025	10.05	9.43	N/A	4.49	17.25	
		6185	10.06	9.41		4.49	17.25	
		6345	10.33	9.62		1.29	14.29	
	6	6505	10.02	9.31		1.29	13.98	
	7	6665	9.40	8.37		1.29	13.22	
		6825	9.24	8.39		3.07	14.92	
	8	6985	9.56	8.69		3.07	15.23	

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. According to KDB 662911 D01 E)1), Total E.I.R.P. (dBm) = Sum to individual output power (dBm)+ Directional gain (dBi) + duty cycle factor(dB) when duty cycle is less than 98%.
3. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{2.48/10} + 10^{5.85/10})/2]$= 4.49dBi
6525MHz: Directional gain = $10 \log[(10^{1.38/10} + 10^{1.19/10})/2]$= 1.29dBi
7125MHz: Directional gain = $10 \log[(10^{1.89/10} + 10^{3.99/10})/2]$= 3.07dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

● OFDMA Modulation

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 0			RU Index 4			RU Index 8				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE20	5	5955	26T	-5.99	-5.71	0.223	-5.91	-5.68	0.223	-6.00	-5.86	0.223	4.49	1.79
		6175		-7.35	-7.50	0.223	-6.99	-7.21	0.223	-7.28	-7.53	0.223	4.49	0.32
		6415		-7.50	-7.98	0.223	-7.43	-7.89	0.223	-7.92	-8.10	0.223	1.29	-3.49
	6	6435		-7.53	-7.84	0.223	-7.56	-7.64	0.223	-7.63	-8.00	0.223	1.29	-3.29
		6475		-7.90	-8.01	0.223	-7.65	-7.90	0.223	-7.85	-8.21	0.223	1.29	-3.50
		6515		-8.04	-8.22	0.223	-7.73	-8.02	0.223	-8.11	-8.26	0.223	1.29	-3.66
	7	6535		-8.68	-8.99	0.223	-8.71	-8.85	0.223	-9.02	-9.18	0.223	1.29	-4.58
		6695		-9.30	-8.89	0.223	-9.11	-8.62	0.223	-9.39	-8.84	0.223	1.29	-4.58
		6855		-8.76	-8.51	0.223	-8.77	-8.31	0.223	-8.84	-8.59	0.223	3.07	-2.41
	8	6875		-9.05	-8.65	0.223	-9.04	-8.41	0.223	-9.27	-8.73	0.223	3.07	-2.69
		6995		-8.02	-7.83	0.223	-7.81	-7.68	0.223	-8.08	-7.93	0.223	3.07	-1.70
		7115		-7.79	-7.60	0.223	-7.65	-7.33	0.223	-7.80	-7.53	0.223	3.07	-1.36

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 0			RU Index 8			RU Index 17				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE40	5	5965	26T	-6.09	-5.78	0.223	-5.89	-5.83	0.223	-5.92	-5.79	0.223	4.49	1.87
		6165		-6.92	-7.30	0.223	-7.04	-7.49	0.223	-7.18	-7.45	0.223	4.49	0.41
		6405		-7.45	-7.87	0.223	-7.64	-7.95	0.223	-7.73	-8.07	0.223	1.29	-3.37
	6	6445		-7.65	-7.77	0.223	-7.93	-7.92	0.223	-7.85	-8.05	0.223	1.29	-3.43
		6485		-7.81	-7.97	0.223	-8.07	-8.11	0.223	-8.08	-8.25	0.223	1.29	-3.64
	7	6525		-8.02	-8.14	0.223	-8.18	-8.36	0.223	-8.10	-8.37	0.223	1.29	-3.71
		6685		-9.22	-8.84	0.223	-9.34	-8.94	0.223	-9.31	-8.90	0.223	1.29	-4.58
		6845		-8.68	-8.34	0.223	-8.77	-8.45	0.223	-8.99	-8.54	0.223	3.07	-2.46
	8	6885		-8.99	-8.56	0.223	-9.21	-8.70	0.223	-9.21	-8.99	0.223	3.07	-2.80
		7005		-7.85	-7.89	0.223	-8.15	-8.07	0.223	-8.20	-8.09	0.223	3.07	-1.84
		7085		-7.50	-7.27	0.223	-7.64	-7.48	0.223	-8.55	-8.17	0.223	3.07	-2.05

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{2.48/10} + 10^{5.85/10})/2]$= 4.49dBi
6525MHz: Directional gain = $10 \log[(10^{1.38/10} + 10^{1.19/10})/2]$= 1.29dBi
7125MHz: Directional gain = $10 \log[(10^{1.89/10} + 10^{3.99/10})/2]$= 3.07dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 0			RU Index 18			RU Index 36				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	26T	-6.10	-5.60	0.223	-5.42	-5.22	0.223	-6.20	-5.99	0.223	4.49	1.63
		6145		-6.99	-7.06	0.223	-6.69	-6.72	0.223	-7.57	-7.49	0.223	4.49	0.19
		6385		-7.51	-7.73	0.223	-7.18	-7.27	0.223	-8.00	-8.06	0.223	1.29	-3.51
	6	6465		-8.18	-7.91	0.223	-7.58	-7.48	0.223	-8.42	-8.34	0.223	1.29	-3.86
		6545		-8.35	-8.27	0.223	-8.07	-7.89	0.223	-8.98	-8.75	0.223	1.29	-4.34
	7	6625		-9.64	-8.95	0.223	-8.92	-8.31	0.223	-9.85	-8.89	0.223	1.29	-4.82
		6705		-9.60	-8.85	0.223	-9.08	-8.31	0.223	-9.95	-8.84	0.223	1.29	-4.84
		6785		-8.85	-8.33	0.223	-8.23	-7.76	0.223	-9.11	-8.43	0.223	1.29	-4.23
	8	6865		-9.04	-8.46	0.223	-8.63	-7.94	0.223	-9.71	-9.00	0.223	3.07	-3.04
		6945		-8.03	-7.35	0.223	-7.36	-6.97	0.223	-8.47	-7.88	0.223	3.07	-1.86
		7025		-8.34	-8.00	0.223	-7.92	-7.52	0.223	-8.90	-8.42	0.223	3.07	-2.35

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 0			RU Index 18			RU Index 36				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80L)	5	6025	26T	-6.10	-5.60	0.223	-6.10	-5.60	0.223	-6.10	-5.60	0.223	4.49	1.79
		6185		-6.99	-7.06	0.223	-6.99	-7.06	0.223	-6.99	-7.06	0.223	4.49	0.49
		6345		-7.51	-7.73	0.223	-7.51	-7.73	0.223	-7.51	-7.73	0.223	1.29	-2.93
	6	6505		-8.18	-7.91	0.223	-8.18	-7.91	0.223	-8.18	-7.91	0.223	1.29	-3.43
	7	6665		-8.35	-8.27	0.223	-8.35	-8.27	0.223	-8.35	-8.27	0.223	1.29	-4.53
		6825		-9.64	-8.95	0.223	-9.64	-8.95	0.223	-9.64	-8.95	0.223	3.07	-2.00
	8	6985		-9.60	-8.85	0.223	-9.60	-8.85	0.223	-9.60	-8.85	0.223	3.07	-1.44

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index S0			RU Index S18			RU Index S36				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80H)	5	6025	26T	-5.96	-5.84	0.223	-6.73	-6.36	0.223	-8.34	-7.93	0.223	4.49	-0.41
		6185		-7.40	-7.07	0.223	-7.89	-7.66	0.223	-9.34	-9.19	0.223	4.49	-1.54
		6345		-7.64	-7.24	0.223	-8.09	-7.72	0.223	-9.88	-9.42	0.223	1.29	-5.12
	6	6505		-7.99	-7.89	0.223	-8.93	-8.63	0.223	-10.44	-10.28	0.223	1.29	-5.84
	7	6665		-8.66	-9.13	0.223	-9.15	-9.73	0.223	-10.41	-11.02	0.223	1.29	-6.18
		6825		-8.13	-8.71	0.223	-8.85	-9.28	0.223	-10.46	-10.94	0.223	3.07	-4.39
	8	6985		-7.74	-7.83	0.223	-8.46	-8.61	0.223	-9.91	-10.21	0.223	3.07	-3.75

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{2.48/10} + 10^{5.85/10})/2]$= 4.49dBi
6525MHz: Directional gain = $10 \log[(10^{1.38/10} + 10^{1.19/10})/2]$= 1.29dBi
7125MHz: Directional gain = $10 \log[(10^{1.89/10} + 10^{3.99/10})/2]$= 3.07dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Tones: 52T

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 37			RU Index 39			RU Index 40				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE20	5	5955	52T	-2.78	-2.42	0.119	-2.55	-2.54	0.119	-2.62	-2.68	0.119	4.49	4.97
		6175		-3.80	-4.25	0.119	-3.89	-4.12	0.119	-4.08	-4.26	0.119	4.49	3.45
		6415		-4.20	-4.75	0.119	-4.20	-4.81	0.119	-4.54	-4.94	0.119	1.29	-0.32
	6	6435		-4.52	-4.72	0.119	-4.36	-4.68	0.119	-4.52	-4.69	0.119	1.29	-0.18
		6475		-4.69	-4.88	0.119	-4.67	-4.77	0.119	-4.63	-4.84	0.119	1.29	-0.31
		6515		-4.74	-4.99	0.119	-4.69	-4.97	0.119	-4.78	-5.07	0.119	1.29	-0.50
	7	6535		-5.47	-5.79	0.119	-5.67	-5.81	0.119	-5.76	-5.91	0.119	1.29	-1.42
		6695		-6.13	-5.63	0.119	-5.86	-5.62	0.119	-6.00	-5.67	0.119	1.29	-1.41
		6855		-5.56	-5.32	0.119	-5.62	-5.26	0.119	-5.68	-5.40	0.119	3.07	0.66
	8	6875		-5.88	-5.42	0.119	-5.68	-5.39	0.119	-5.90	-5.48	0.119	3.07	0.51
		6995		-4.86	-4.65	0.119	-4.79	-4.63	0.119	-4.97	-4.76	0.119	3.07	1.34
		7115		-4.51	-4.36	0.119	-4.55	-4.35	0.119	-8.39	-8.10	0.119	3.07	-2.04

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 37			RU Index 40			RU Index 44				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE40	5	5965	52T	-3.01	-2.58	0.119	-2.91	-2.78	0.119	-2.95	-2.77	0.119	4.49	4.76
		6165		-3.88	-4.25	0.119	-3.89	-4.32	0.119	-4.07	-4.37	0.119	4.49	3.40
		6405		-4.22	-4.92	0.119	-4.35	-4.91	0.119	-4.52	-5.03	0.119	1.29	-0.35
	6	6445		-4.67	-4.71	0.119	-4.58	-4.76	0.119	-4.61	-4.88	0.119	1.29	-0.32
		6485		-4.66	-4.93	0.119	-4.67	-4.92	0.119	-4.65	-5.02	0.119	1.29	-0.41
	7	6525		-4.89	-5.02	0.119	-4.96	-5.19	0.119	-4.91	-5.19	0.119	1.29	-0.63
		6685		-6.01	-5.73	0.119	-6.05	-5.77	0.119	-6.22	-5.71	0.119	1.29	-1.54
		6845		-5.66	-5.30	0.119	-5.83	-5.31	0.119	-5.86	-5.45	0.119	3.07	0.55
	8	6885		-5.87	-5.49	0.119	-6.08	-5.54	0.119	-6.10	-5.82	0.119	3.07	0.24
		7005		-4.90	-4.64	0.119	-5.02	-4.87	0.119	-5.09	-4.94	0.119	3.07	1.18
		7085		-4.44	-4.15	0.119	-4.48	-4.31	0.119	-4.70	-4.42	0.119	3.07	1.64

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{2.48/10} + 10^{5.85/10})/2]$= 4.49dBi
6525MHz: Directional gain = $10 \log[(10^{1.38/10} + 10^{1.19/10})/2]$= 1.29dBi
7125MHz: Directional gain = $10 \log[(10^{1.89/10} + 10^{3.99/10})/2]$= 3.07dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 37			RU Index 44			RU Index 52				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	52T	-2.74	-3.08	0.119	-2.30	-2.67	0.119	-3.07	-3.13	0.119	4.49	4.52
		6145		-4.02	-3.94	0.119	-3.68	-3.73	0.119	-4.41	-4.46	0.119	4.49	3.18
		6385		-4.81	-4.56	0.119	-4.39	-4.28	0.119	-5.28	-5.18	0.119	1.29	-0.81
	6	6465		-4.92	-5.27	0.119	-4.68	-4.87	0.119	-5.25	-5.55	0.119	1.29	-0.98
		6545		-5.28	-5.53	0.119	-5.03	-5.26	0.119	-5.58	-6.03	0.119	1.29	-1.38
	7	6625		-5.85	-6.64	0.119	-5.60	-6.31	0.119	-5.99	-6.95	0.119	1.29	-2.02
		6705		-6.02	-6.87	0.119	-5.32	-6.54	0.119	-5.88	-7.12	0.119	1.29	-2.04
		6785		-5.29	-6.14	0.119	-4.99	-5.75	0.119	-5.37	-6.34	0.119	1.29	-1.41
	8	6865		-5.50	-6.42	0.119	-5.12	-6.24	0.119	-6.00	-6.97	0.119	3.07	-0.26
		6945		-4.83	-5.21	0.119	-4.04	-4.89	0.119	-4.90	-5.51	0.119	3.07	1.01
		7025		-5.01	-5.70	0.119	-4.78	-5.39	0.119	-5.44	-6.11	0.119	3.07	0.44

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 37			RU Index 44			RU Index 52				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80L)	5	6025	52T	-4.19	-4.33	0.119	-3.25	-3.26	0.119	-2.86	-2.65	0.119	4.49	4.87
		6185		-5.66	-5.20	0.119	-4.52	-4.23	0.119	-4.13	-3.91	0.119	4.49	3.60
		6345		-6.09	-5.66	0.119	-4.96	-4.39	0.119	-4.42	-3.88	0.119	1.29	0.28
	6	6505		-6.36	-6.31	0.119	-5.37	-5.27	0.119	-4.97	-4.82	0.119	1.29	-0.48
	7	6665		-7.30	-7.69	0.119	-6.10	-6.53	0.119	-5.68	-6.08	0.119	1.29	-1.46
		6825		-6.79	-7.19	0.119	-5.69	-6.07	0.119	-5.20	-5.64	0.119	3.07	0.78
	8	6985		-5.76	-6.18	0.119	-4.90	-5.21	0.119	-4.63	-4.86	0.119	3.07	1.46

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index S37			RU Index S44			RU Index S52				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80H)	5	6025	52T	-2.84	-2.88	0.119	-3.47	-3.30	0.119	-5.17	-4.72	0.119	4.49	2.68
		6185		-4.33	-3.94	0.119	-4.78	-4.53	0.119	-6.13	-6.18	0.119	4.49	1.46
		6345		-4.44	-4.11	0.119	-4.94	-4.57	0.119	-6.85	-6.12	0.119	1.29	-2.05
	6	6505		-4.82	-4.78	0.119	-5.75	-5.35	0.119	-7.23	-6.97	0.119	1.29	-2.68
	7	6665		-5.71	-6.18	0.119	-6.06	-6.67	0.119	-7.36	-8.03	0.119	1.29	-3.26
		6825		-5.11	-5.81	0.119	-5.85	-6.30	0.119	-7.40	-7.98	0.119	3.07	-1.48
	8	6985		-4.55	-5.02	0.119	-5.33	-5.38	0.119	-7.07	-7.08	0.119	3.07	-0.88

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{2.48/10} + 10^{5.85/10})/2]$= 4.49dBi
6525MHz: Directional gain = $10 \log[(10^{1.38/10} + 10^{1.19/10})/2]$= 1.29dBi
7125MHz: Directional gain = $10 \log[(10^{1.89/10} + 10^{3.99/10})/2]$= 3.07dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Tones: 106T

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 53			RU Index 54				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE20	5	5955	106T	0.35	0.41	N/A	0.20	0.40	N/A	4.49	7.80
		6175		-0.72	-1.01	N/A	-0.88	-1.19	N/A	4.49	6.47
		6415		-1.13	-1.74	N/A	-1.30	-1.87	N/A	1.29	2.72
	6	6435		-1.47	-1.49	N/A	-1.30	-1.52	N/A	1.29	2.89
		6475		-1.38	-1.68	N/A	-1.63	-1.75	N/A	1.29	2.61
		6515		-1.61	-1.82	N/A	-1.62	-1.87	N/A	1.29	2.56
	7	6535		-2.44	-2.78	N/A	-2.57	-2.83	N/A	1.29	1.60
		6695		-3.19	-2.71	N/A	-2.93	-2.59	N/A	1.29	1.54
		6855		-2.56	-2.14	N/A	-2.68	-2.23	N/A	3.07	3.63
	8	6875		-2.67	-2.34	N/A	-2.76	-2.47	N/A	3.07	3.47
		6995		-1.64	-1.58	N/A	-1.71	-1.65	N/A	3.07	4.40
		7115		-1.47	-1.28	N/A	-8.47	-7.97	N/A	3.07	-2.13

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 53			RU Index 54			RU Index 56				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE40	5	5965	106T	0.21	0.29	N/A	0.14	0.35	N/A	0.28	0.18	N/A	4.49	7.73
		6165		-0.85	-1.17	N/A	-0.98	-1.23	N/A	-1.06	-1.26	N/A	4.49	6.34
		6405		-1.24	-1.79	N/A	-1.30	-1.79	N/A	-1.55	-1.98	N/A	1.29	2.54
	6	6445		-1.56	-1.69	N/A	-1.33	-1.66	N/A	-1.45	-1.76	N/A	1.29	2.70
		6485		-1.65	-1.82	N/A	-1.54	-1.80	N/A	-1.78	-1.92	N/A	1.29	2.45
	7	6525		-1.71	-1.98	N/A	-1.73	-2.03	N/A	-1.85	-2.29	N/A	1.29	2.24
		6685		-3.05	-2.72	N/A	-3.14	-2.65	N/A	-3.09	-2.66	N/A	1.29	1.43
		6845		-2.63	-2.24	N/A	-2.79	-2.23	N/A	-2.87	-2.44	N/A	3.07	3.43
	8	6885		-2.92	-2.43	N/A	-2.92	-2.50	N/A	-3.08	-2.73	N/A	3.07	3.18
		7005		-1.83	-1.68	N/A	-1.72	-1.70	N/A	-2.01	-1.85	N/A	3.07	4.15
		7085		-1.52	-1.19	N/A	-1.49	-1.22	N/A	-1.60	-1.34	N/A	3.07	4.61

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{2.48/10} + 10^{5.85/10})/2]$= 4.49dBi
6525MHz: Directional gain = $10 \log[(10^{1.38/10} + 10^{1.19/10})/2]$= 1.29dBi
7125MHz: Directional gain = $10 \log[(10^{1.89/10} + 10^{3.99/10})/2]$= 3.07dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 53			RU Index 56			RU Index 60				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	106T	0.09	-0.09	N/A	0.65	0.36	N/A	-0.18	-0.18	N/A	4.49	7.32
		6145		-1.16	-1.06	N/A	-1.03	-0.86	N/A	-1.49	-1.47	N/A	4.49	6.02
		6385		-1.86	-1.71	N/A	-1.65	-1.45	N/A	-2.21	-2.07	N/A	1.29	2.16
	6	6465		-1.88	-2.28	N/A	-1.54	-2.04	N/A	-2.09	-2.55	N/A	1.29	1.99
		6545		-2.11	-2.59	N/A	-1.95	-2.36	N/A	-2.77	-3.01	N/A	1.29	1.41
	7	6625		-2.98	-3.74	N/A	-2.60	-3.44	N/A	-2.95	-3.98	N/A	1.29	0.87
		6705		-2.82	-3.99	N/A	-2.42	-3.70	N/A	-2.81	-4.12	N/A	1.29	0.88
		6785		-1.80	-2.76	N/A	-1.56	-2.53	N/A	-2.29	-3.25	N/A	1.29	1.56
	8	6865		-2.24	-3.17	N/A	-2.08	-2.99	N/A	-2.63	-3.71	N/A	3.07	2.94
		6945		-1.33	-2.00	N/A	-1.06	-1.70	N/A	-1.89	-2.28	N/A	3.07	4.00
		7025		-1.87	-2.30	N/A	-1.53	-2.21	N/A	-2.35	-2.74	N/A	3.07	3.54

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 53			RU Index 56			RU Index 60				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80L)	5	6025	106T	-1.20	-1.28	N/A	-0.22	-0.25	N/A	0.16	0.43	N/A	4.49	7.80
		6185		-2.37	-2.08	N/A	-1.45	-1.30	N/A	-1.16	-0.98	N/A	4.49	6.43
		6345		-3.25	-2.32	N/A	-2.02	-1.34	N/A	-1.46	-0.98	N/A	1.29	3.09
	6	6505		-3.07	-3.05	N/A	-2.13	-2.11	N/A	-1.79	-1.75	N/A	1.29	2.53
	7	6665		-4.31	-4.41	N/A	-3.39	-3.39	N/A	-2.71	-2.86	N/A	1.29	1.52
		6825		-3.76	-3.71	N/A	-2.98	-2.82	N/A	-2.31	-2.26	N/A	3.07	3.80
	8	6985		-2.74	-2.73	N/A	-1.82	-1.94	N/A	-1.49	-1.51	N/A	3.07	4.58

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index S53			RU Index S56			RU Index S60				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80H)	5	6025	106T	0.21	0.28	N/A	-0.40	-0.05	N/A	-2.09	-1.72	N/A	4.49	5.60
		6185		-1.22	-0.82	N/A	-1.59	-1.45	N/A	-3.06	-3.01	N/A	4.49	4.47
		6345		-1.36	-1.04	N/A	-1.93	-1.47	N/A	-3.37	-2.99	N/A	1.29	1.12
	6	6505		-1.90	-1.69	N/A	-2.32	-2.28	N/A	-3.88	-3.80	N/A	1.29	0.46
	7	6665		-2.92	-3.12	N/A	-3.45	-3.54	N/A	-4.90	-4.81	N/A	1.29	-0.55
		6825		-2.29	-2.24	N/A	-3.03	-2.93	N/A	-4.37	-4.56	N/A	3.07	1.62
	8	6985		-1.56	-1.45	N/A	-2.26	-1.97	N/A	-3.75	-3.53	N/A	3.07	2.44

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{2.48/10} + 10^{5.85/10})/2]$= 4.49dBi
6525MHz: Directional gain = $10 \log[(10^{1.38/10} + 10^{1.19/10})/2]$= 1.29dBi
7125MHz: Directional gain = $10 \log[(10^{1.89/10} + 10^{3.99/10})/2]$= 3.07dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Tones: 242T

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm) RU Index 61 AUX	Average Conducted Output power (dBm) RU Index 61 Main	Average Conducted Output power (dBm) RU Index 61 Duty Cycle Factor 10log(1/X) Note 3	Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
802.11ax-HE20	5	5955	242T	2.13	2.48	0.15	4.49	9.96
		6175		2.07	2.41	0.15	4.49	9.89
		6415		1.95	2.42	0.15	1.29	6.64
	6	6435		1.38	1.86	0.15	1.29	6.08
		6475		1.51	1.8	0.15	1.29	6.11
		6515		1.76	1.8	0.15	1.29	6.23
	7	6535		1.43	1.61	0.15	1.29	5.97
		6695		1.71	1.72	0.15	1.29	6.17
		6855		1.59	1.76	0.15	3.07	7.91
	8	6875		0.96	1.11	0.15	3.07	7.27
		6995		0.91	0.89	0.15	3.07	7.13
		7115		-2.82	-2.64	0.15	3.07	3.50

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm) RU Index 61 AUX	RU Index 61 Main	RU Index 61 Duty Cycle Factor 10log(1/X) Note 3	RU Index 62 AUX	RU Index 62 Main	RU Index 62 Duty Cycle Factor 10log(1/X) Note 3	Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
802.11ax-HE40	5	5965	242T	2.01	1.3	0.15	1.89	1.19	0.15	4.49	9.20
		6165		1.73	1.4	0.15	1.54	1.16	0.15	4.49	9.00
		6405		1.69	1.4	0.15	1.7	1.45	0.15	1.29	6.03
	6	6445		1.07	1.07	0.15	1.38	1.02	0.15	1.29	5.65
		6485		1.22	0.92	0.15	1.07	1.44	0.15	1.29	5.71
	7	6525		1.44	0.89	0.15	2.21	1.51	0.15	1.29	6.32
		6685		1.12	0.19	0.15	1.34	0.25	0.15	1.29	5.28
		6845		1.14	0.04	0.15	1.29	0.17	0.15	3.07	7.00
	8	6885		0.87	-0.15	0.15	0.71	-0.06	0.15	3.07	6.57
		7005		0.78	-0.33	0.15	0.84	-0.22	0.15	3.07	6.57
		7085		0.91	0.06	0.15	1.16	0.55	0.15	3.07	7.10

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{2.48/10} + 10^{5.85/10})/2]$= 4.49dBi
6525MHz: Directional gain = $10 \log[(10^{1.38/10} + 10^{1.19/10})/2]$= 1.29dBi
7125MHz: Directional gain = $10 \log[(10^{1.89/10} + 10^{3.99/10})/2]$= 3.07dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 61			RU Index 62			RU Index 64				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	242T	2.35	2.73	0.15	2.36	2.91	0.15	2.34	2.44	0.15	4.49	10.04
		6145		2.57	2.56	0.15	2.49	2.58	0.15	2.13	2.35	0.15	4.49	9.89
		6385		2.08	2.17	0.15	2.33	2.41	0.15	2.27	2.4	0.15	1.29	6.79
	6	6465		1.81	1.58	0.15	2.72	2.72	0.15	1.81	1.65	0.15	1.29	6.18
		6545		1.38	1.99	0.15	2.34	2.91	0.15	1.97	2.43	0.15	1.29	6.66
	7	6625		0.94	1.67	0.15	1.13	1.84	0.15	0.87	1.6	0.15	1.29	5.70
		6705		1.16	1.74	0.15	1.25	1.86	0.15	0.89	1.65	0.15	1.29	5.74
		6785		0.99	1.58	0.15	1.03	1.74	0.15	0.87	1.72	0.15	1.29	5.77
	8	6865		0.83	1.44	0.15	1.25	1.86	0.15	0.42	0.86	0.15	3.07	6.88
		6945		0.53	0.93	0.15	1.36	1.97	0.15	0.42	0.86	0.15	3.07	6.88
		7025		0.23	0.89	0.15	1.2	1.89	0.15	0	1.18	0.15	3.07	6.86

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 61			RU Index 62			RU Index 64				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80L)	5	6025	242T	1.95	2.74	0.15	2.36	3.03	0.15	1.74	2.56	0.15	4.49	9.82
		6185		1.93	2.37	0.15	2.14	2.93	0.15	1.84	2.42	0.15	4.49	9.79
		6345		1.89	2.52	0.15	2.33	2.63	0.15	1.87	2.4	0.15	1.29	6.59
	6	6505		1.63	1.93	0.15	2.5	2.95	0.15	1.5	1.92	0.15	1.29	6.17
	7	6665		0.09	1.4	0.15	0.57	1.91	0.15	0.23	1.85	0.15	1.29	5.57
		6825		-0.01	1.39	0.15	0.38	1.62	0.15	-0.2	1.25	0.15	3.07	6.82
	8	6985		-0.48	0.65	0.15	0.74	2	0.15	-0.69	0.85	0.15	3.07	6.38

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index S61			RU Index S62			RU Index S64				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80H)	5	6025	242T	1.54	2.75	0.15	1.49	2.6	0.15	1.76	2.54	0.15	4.49	9.82
		6185		1.72	2.48	0.15	1.54	2.54	0.15	1.88	2.57	0.15	4.49	9.89
		6345		1.78	2.31	0.15	1.69	2.45	0.15	2.01	2.51	0.15	1.29	6.72
	6	6505		1.53	1.98	0.15	2.08	2.6	0.15	1.82	2.51	0.15	1.29	6.63
	7	6665		-0.15	1.52	0.15	-0.41	1.36	0.15	-0.37	1.66	0.15	1.29	5.21
		6825		-0.47	1.43	0.15	0.31	1.34	0.15	-0.24	0.87	0.15	3.07	6.58
	8	6985		-0.58	0.74	0.15	0.26	1.64	0.15	-0.34	1.02	0.15	3.07	6.62

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{2.48/10} + 10^{5.85/10})/2]$= 4.49dBi
6525MHz: Directional gain = $10 \log[(10^{1.38/10} + 10^{1.19/10})/2]$= 1.29dBi
7125MHz: Directional gain = $10 \log[(10^{1.89/10} + 10^{3.99/10})/2]$= 3.07dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Tones: 484T

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)			Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 65				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE40	5	5965	484T	5.33	5.57	N/A	4.49	12.95
		6165		5.17	5.5	N/A	4.49	12.84
		6405		5.18	5.29	N/A	1.29	9.54
	6	6445		5.32	5.56	N/A	1.29	9.74
		6485		5.25	5.59	N/A	1.29	9.72
	7	6525		5.44	5.46	N/A	1.29	9.75
		6685		4.68	4.84	N/A	1.29	9.06
		6845		4.61	4.66	N/A	3.07	10.72
	8	6885		4.74	4.88	N/A	3.07	10.89
		7005		4.56	4.53	N/A	3.07	10.63
		7085		4.73	4.98	N/A	3.07	10.94

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 65			RU Index 66				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	484T	5.33	5.36	N/A	5.31	5.41	N/A	4.49	12.86
		6145		5.46	5.3	N/A	5.45	5.29	N/A	4.49	12.87
		6385		5.03	5.12	N/A	5.45	5.17	N/A	1.29	9.61
	6	6465		5.47	5.1	N/A	5.3	5.44	N/A	1.29	9.67
		6545		5.17	5.61	N/A	5.19	5.24	N/A	1.29	9.52
	7	6625		4.39	4.53	N/A	4.29	4.45	N/A	1.29	8.67
		6705		4.49	4.46	N/A	4.37	4.64	N/A	1.29	8.81
		6785		4.15	4.5	N/A	4.33	4.68	N/A	1.29	8.81
	8	6865		4.28	4.62	N/A	4.52	4.52	N/A	3.07	10.60
		6945		4.58	4.36	N/A	4.3	4.58	N/A	3.07	10.52
		7025		4.22	4.51	N/A	4.44	4.55	N/A	3.07	10.58

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{2.48/10} + 10^{5.85/10})/2]$= 4.49dBi
6525MHz: Directional gain = $10 \log[(10^{1.38/10} + 10^{1.19/10})/2]$= 1.29dBi
7125MHz: Directional gain = $10 \log[(10^{1.89/10} + 10^{3.99/10})/2]$= 3.07dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 65			RU Index 66				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80L)	5	6025	484T	4.98	5.44	N/A	4.67	5.49	N/A	4.49	12.60
		6185		5.05	5.3	N/A	5.04	5.32	N/A	4.49	12.68
		6345		4.93	5.19	N/A	5.01	5.27	N/A	1.29	9.44
	6	6505		5.23	5.12	N/A	5.25	5.39	N/A	1.29	9.62
	7	6665		3.96	4.53	N/A	3.61	4.42	N/A	1.29	8.33
		6825		3.96	4.47	N/A	3.7	4.63	N/A	3.07	10.27
	8	6985		4.25	4.42	N/A	4.09	4.75	N/A	3.07	10.51

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index S65			RU Index S66				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80H)	5	6025	484T	4.81	5.42	N/A	4.83	5.41	N/A	4.49	12.63
		6185		4.81	5.36	N/A	4.85	5.12	N/A	4.49	12.49
		6345		4.62	5.19	N/A	4.93	5.16	N/A	1.29	9.35
	6	6505		5.06	5.45	N/A	4.94	5.31	N/A	1.29	9.43
	7	6665		3.99	4.52	N/A	3.93	4.51	N/A	1.29	8.53
		6825		3.97	4.56	N/A	4.03	4.61	N/A	3.07	10.41
	8	6985		4.09	4.41	N/A	4.06	4.74	N/A	3.07	10.49

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = 10 log[($10^{G1/10}$ + $10^{G2/10}$ + … + $10^{GN/10}$)/N_{ANT}] dBi
Directional gain:
5925MHz: Directional gain = 10 log[($10^{2.48/10}$ +$10^{5.85/10}$)/2]= 4.49dBi
6525MHz: Directional gain = 10 log[($10^{1.38/10}$ +$10^{1.19/10}$)/2]= 1.29dBi
7125MHz: Directional gain = 10 log[($10^{1.89/10}$ +$10^{3.99/10}$)/2]= 3.07dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Tones: 996T

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)			Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 67				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	996T	7.25	6.58	0.159	4.49	14.59
		6145		7.22	6.24	0.159	4.49	14.42
		6385		7.49	6.52	0.159	1.29	11.49
	6	6465		7.36	6.43	0.159	1.29	11.38
		6545		7.41	6.35	0.159	1.29	11.37
	7	6625		6.72	5.45	0.159	1.29	10.59
		6705		6.44	5.37	0.159	1.29	10.40
		6785		6.3	5.3	0.159	1.29	10.29
	8	6865		6.14	5.3	0.159	3.07	11.98
		6945		6.54	5.58	0.159	3.07	12.33
		7025		6.71	5.73	0.159	3.07	12.49

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 67			RU Index S67				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160	5	6025	996T	7.57	6.67	0.159	7.34	6.68	0.159	4.49	14.68
		6185		7.58	6.76	0.159	7.59	6.66	0.159	4.49	14.81
		6345		7.76	6.81	0.159	7.58	6.81	0.159	1.29	11.67
	6	6505		7.14	6.23	0.159	7.04	6.18	0.159	1.29	11.09
	7	6665		6.95	5.69	0.159	6.75	5.61	0.159	1.29	10.68
		6825		6.62	5.62	0.159	6.22	5.36	0.159	3.07	12.05
	8	6985		6.58	5.72	0.159	6.48	5.75	0.159	3.07	12.37

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925MHz: Directional gain = $10 \log[(10^{2.48/10} + 10^{5.85/10})/2]$= 4.49dBi
6525MHz: Directional gain = $10 \log[(10^{1.38/10} + 10^{1.19/10})/2]$= 1.29dBi
7125MHz: Directional gain = $10 \log[(10^{1.89/10} + 10^{3.99/10})/2]$= 3.07dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Test SKU: SKU #3 [with (INPAQ) WA-P-LBLB-04-108 Antenna]

Modulation Type	U-NII Band	Centre Frequency (MHz)	Average Coneduted Output Power (dBm)		Duty Cycle Factor (dB) 10log(1/X)	Directional Gain (dBi) Note3	Total E.I.R.P. (dBm) Note2	Limit
			AUX	Main				
802.11ax-HE20	5	5955	1.65	1.17	N/A	4.28	8.71	24dBm
		6175	1.45	1.19		4.28	8.61	
		6415	1.37	1.22		4.28	8.59	
	6	6435	1.33	1.31		0.11	4.44	
		6475	1.60	1.41		0.11	4.63	
		6515	1.41	1.30		0.11	4.48	
	7	6535	0.77	0.58		2.24	5.93	
		6695	0.85	0.10		2.24	5.74	
		6855	0.97	0.09		2.24	5.80	
	8	6875	1.04	0.25		2.24	5.91	
		6995	0.83	0.12		1.26	4.76	
		7115	-3.53	-2.88		1.26	1.08	
802.11ax-HE40	5	5965	5.10	5.23	N/A	4.28	12.46	
		6165	5.06	5.05		4.28	12.35	
		6405	4.82	4.92		4.28	12.16	
	6	6445	4.94	5.31		0.11	8.25	
		6485	5.12	5.18		0.11	8.27	
	7	6525	5.15	5.18		2.24	10.42	
		6685	4.36	4.16		2.24	9.51	
		6845	4.51	4.07		2.24	9.55	
	8	6885	4.49	4.15		1.26	8.59	
		7005	4.46	4.09		1.26	8.55	
		7085	4.57	4.35		1.26	8.73	

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. According to KDB 662911 D01 E)1), Total E.I.R.P. (dBm) = Sum to individual output power (dBm)+ Directional gain (dBi) + duty cycle factor(dB) when duty cycle is less than 98%.
3. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925-6425MHz: Directional gain = $10 \log[(10^{3.70/10} + 10^{4.80/10})/2]$= 4.28dBi
6425-6525MHz: Directional gain = $10 \log[(10^{-1.0/10} + 10^{1.0/10})/2]$= 0.11dBi
6525-6875MHz: Directional gain = $10 \log[(10^{2.86/10} + 10^{1.60/10})/2]$= 0.24dBi
6875-7125MHz: Directional gain = $10 \log[(10^{-1.40/10} + 10^{2.90/10})/2]$= 1.26dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
3. We did spot check for output power and all output power values keep identical thus other conducted items is exempt.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Modulation Type	U-NII Band	Centre Frequency (MHz)	Average Coneduted Output Power (dBm)		Duty Cycle Factor (dB) 10log(1/X)	Directional Gain (dBi) Note3	Total E.I.R.P. (dBm) Note2	Limit
			AUX	Main				
802.11ax-HE80	5	5985	6.78	6.35	N/A	4.28	13.86	24dBm
		6145	6.55	6.06		4.28	13.60	
		6385	7.02	6.34		4.28	13.98	
	6	6465	7.16	6.18		0.11	9.82	
		6545	6.92	6.16		2.24	11.81	
	7	6625	6.01	5.33		2.24	10.93	
		6705	5.97	5.25		2.24	10.88	
		6785	5.94	5.02		2.24	10.75	
	8	6865	6.02	5.02		2.24	10.80	
		6945	5.94	5.29		1.26	9.90	
		7025	6.10	5.53		1.26	10.09	
802.11ax-HE160	5	6025	9.88	9.03	N/A	4.28	16.77	
		6185	9.69	8.99		4.28	16.64	
		6345	10.09	9.20		4.28	16.96	
	6	6505	9.68	9.05		0.11	12.50	
	7	6665	8.79	7.95		2.24	13.64	
		6825	8.92	8.04		2.24	13.75	
	8	6985	9.01	8.28		1.26	12.93	

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]

2. According to KDB 662911 D01 E)1), Total E.I.R.P. (dBm) = Sum to individual output power (dBm)+ Directional gain (dBi) + duty cycle factor(dB) when duty cycle is less than 98%.

3. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925-6425MHz: Directional gain = $10 \log[(10^{3.70/10} + 10^{4.80/10})/2] = 4.28$dBi
6425-6525MHz: Directional gain = $10 \log[(10^{-1.0/10} + 10^{1.0/10})/2] = 0.11$dBi
6525-6875MHz: Directional gain = $10 \log[(10^{2.86/10} + 10^{1.60/10})/2] = 0.24$dBi
6875-7125MHz: Directional gain = $10 \log[(10^{-1.40/10} + 10^{2.90/10})/2] = 1.26$dBi

The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).

3. We did spot check for output power and all output power values keep identical thus other conducted items is exempt.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

● OFDMA Modulation

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 0			RU Index 4			RU Index 8				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE20	5	5955	26T	-6.09	-5.87	0.223	-6.09	-5.87	0.223	-6.20	-6.00	0.223	4.28	1.53
		6175		-7.47	-7.64	0.223	-7.16	-7.40	0.223	-7.48	-7.73	0.223	4.28	0.23
		6415		-7.61	-8.16	0.223	-7.62	-7.97	0.223	-8.03	-8.28	0.223	4.28	-0.28
	6	6435		-7.59	-8.04	0.223	-7.74	-7.79	0.223	-7.83	-8.07	0.223	0.11	-4.42
		6475		-7.97	-8.06	0.223	-7.76	-8.03	0.223	-8.02	-8.27	0.223	0.11	-4.55
		6515		-8.14	-8.27	0.223	-7.87	-8.22	0.223	-8.29	-8.45	0.223	0.11	-4.70
	7	6535		-8.79	-9.16	0.223	-8.78	-9.04	0.223	-9.17	-9.38	0.223	2.24	-3.43
		6695		-9.41	-9.08	0.223	-9.20	-8.71	0.223	-9.54	-8.93	0.223	2.24	-3.47
		6855		-8.87	-8.70	0.223	-8.94	-8.40	0.223	-9.01	-8.75	0.223	2.24	-3.19
	8	6875		-9.16	-8.85	0.223	-9.18	-8.55	0.223	-9.33	-8.78	0.223	2.24	-3.38
		6995		-8.10	-8.03	0.223	-7.90	-7.88	0.223	-8.13	-7.98	0.223	1.26	-3.40
		7115		-7.93	-7.68	0.223	-7.80	-7.46	0.223	-7.96	-7.71	0.223	1.26	-3.13

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 0			RU Index 8			RU Index 17				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE40	5	5965	26T	-6.26	-5.90	0.223	-5.94	-5.97	0.223	-6.02	-5.99	0.223	4.28	1.56
		6165		-7.11	-7.50	0.223	-7.16	-7.67	0.223	-7.30	-7.50	0.223	4.28	0.21
		6405		-7.59	-7.98	0.223	-7.78	-8.11	0.223	-7.87	-8.13	0.223	4.28	-0.27
	6	6445		-7.73	-7.83	0.223	-8.02	-8.04	0.223	-7.92	-8.18	0.223	0.11	-4.44
		6485		-8.01	-8.03	0.223	-8.16	-8.25	0.223	-8.16	-8.31	0.223	0.11	-4.68
	7	6525		-8.12	-8.34	0.223	-8.25	-8.43	0.223	-8.21	-8.53	0.223	2.24	-2.76
		6685		-9.38	-8.98	0.223	-9.45	-9.08	0.223	-9.38	-9.04	0.223	2.24	-3.70
		6845		-8.81	-8.45	0.223	-8.93	-8.57	0.223	-9.12	-8.62	0.223	2.24	-3.15
	8	6885		-9.18	-8.76	0.223	-9.26	-8.76	0.223	-9.29	-9.18	0.223	1.26	-4.47
		7005		-7.98	-8.03	0.223	-8.23	-8.12	0.223	-8.28	-8.15	0.223	1.26	-3.51
		7085		-7.63	-7.39	0.223	-7.72	-7.57	0.223	-8.62	-8.36	0.223	1.26	-3.02

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925-6425MHz: Directional gain = $10 \log[(10^{3.70/10} + 10^{4.80/10})/2]$= 4.28dBi
6425-6525MHz: Directional gain = $10 \log[(10^{-1.0/10} + 10^{1.0/10})/2]$= 0.11dBi
6525-6875MHz: Directional gain = $10 \log[(10^{2.86/10} + 10^{1.60/10})/2]$= 0.24dBi
6875-7125MHz: Directional gain = $10 \log[(10^{-1.40/10} + 10^{2.90/10})/2]$= 1.26dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.
6. We did spot check for output power and all output power values keep identical thus other conducted items is exempt.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan

Tel: +886 2 26099301
Fax: +886 2 26099303

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 0			RU Index 18			RU Index 36				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	26T	-6.17	-5.78	0.223	1.54	-7.00	0.223	-6.27	-6.15	0.223	4.28	2.05
		6145		-7.11	-7.16	0.223	0.38	-7.00	0.223	-7.69	-7.66	0.223	4.28	0.68
		6385		-7.62	-7.91	0.223	-0.25	-7.00	0.223	-8.07	-8.23	0.223	4.28	0.24
	6	6465		-8.31	-7.97	0.223	-4.79	-7.00	0.223	-8.52	-8.42	0.223	0.11	-4.31
		6545		-8.46	-8.32	0.223	-2.92	-7.00	0.223	-9.04	-8.82	0.223	2.24	-2.60
	7	6625		-9.82	-9.13	0.223	-3.99	-7.75	0.223	-9.95	-8.94	0.223	2.24	-3.21
		6705		-9.78	-8.97	0.223	-3.88	-7.75	0.223	-10.06	-9.03	0.223	2.24	-3.36
		6785		-8.95	-8.53	0.223	-3.26	-7.75	0.223	-9.17	-8.55	0.223	2.24	-2.67
	8	6865		-9.23	-8.55	0.223	-3.40	-7.75	0.223	-9.85	-9.05	0.223	2.24	-2.87
		6945		-8.15	-7.45	0.223	-3.29	-7.75	0.223	-8.64	-8.01	0.223	1.26	-2.79
		7025		-8.40	-8.12	0.223	-3.76	-7.75	0.223	-8.98	-8.49	0.223	1.26	-3.33

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 0			RU Index 18			RU Index 36				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80L)	5	6025	26T	-7.79	-7.96	0.223	-6.40	-6.62	0.223	-6.23	-5.84	0.223	4.28	1.48
		6185		-9.05	-8.61	0.223	-7.85	-7.61	0.223	-7.41	-7.24	0.223	4.28	0.19
		6345		-9.59	-8.81	0.223	-8.27	-7.65	0.223	-7.93	-7.21	0.223	4.28	-0.04
	6	6505		-9.76	-9.38	0.223	-8.74	-8.29	0.223	-8.17	-7.99	0.223	0.11	-4.74
	7	6665		-10.70	-10.94	0.223	-9.37	-9.61	0.223	-9.11	-9.33	0.223	2.24	-3.75
		6825		-10.00	-10.24	0.223	-8.77	-9.06	0.223	-8.26	-8.66	0.223	2.24	-2.98
	8	6985		-9.29	-9.28	0.223	-8.36	-8.54	0.223	-7.96	-7.77	0.223	1.26	-3.37

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index S0			RU Index S18			RU Index S36				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80H)	5	6025	26T	-6.04	-5.89	0.223	-6.81	-6.55	0.223	-8.45	-7.98	0.223	4.28	1.55
		6185		-7.54	-7.18	0.223	-7.97	-7.75	0.223	-9.42	-9.27	0.223	4.28	0.16
		6345		-7.84	-7.31	0.223	-8.19	-7.84	0.223	-9.97	-9.60	0.223	4.28	-0.05
	6	6505		-8.04	-8.05	0.223	-8.99	-8.70	0.223	-10.64	-10.35	0.223	0.11	-4.70
	7	6665		-8.83	-9.29	0.223	-9.21	-9.87	0.223	-10.54	-11.16	0.223	2.24	-3.58
		6825		-8.29	-8.77	0.223	-8.98	-9.47	0.223	-10.66	-11.01	0.223	2.24	-3.05
	8	6985		-7.92	-7.99	0.223	-8.53	-8.69	0.223	-10.04	-10.32	0.223	1.26	-3.46

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925-6425MHz: Directional gain = $10 \log[(10^{3.70/10} + 10^{4.80/10})/2]$= 4.28dBi
6425-6525MHz: Directional gain = $10 \log[(10^{-1.0/10} + 10^{1.0/10})/2]$= 0.11dBi
6525-6875MHz: Directional gain = $10 \log[(10^{2.86/10} + 10^{1.60/10})/2]$= 0.24dBi
6875-7125MHz: Directional gain = $10 \log[(10^{-1.40/10} + 10^{2.90/10})/2]$= 1.26dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.
6. We did spot check for output power and all output power values keep identical thus other conducted items is exempt.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Tones: 52T

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 37			RU Index 39			RU Index 40				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE20	5	5955	52T	-2.97	-2.55	0.119	-2.65	-2.62	0.119	-2.80	-2.76	0.119	4.28	4.774
		6175		-3.98	-4.40	0.119	-4.08	-4.17	0.119	-4.17	-4.42	0.119	4.28	3.285
		6415		-4.31	-4.82	0.119	-4.32	-4.98	0.119	-4.70	-5.00	0.119	4.28	2.852
	6	6435		-4.63	-4.85	0.119	-4.53	-4.78	0.119	-4.69	-4.88	0.119	0.11	-1.414
		6475		-4.75	-4.96	0.119	-4.87	-4.91	0.119	-4.81	-4.92	0.119	0.11	-1.614
		6515		-4.80	-5.15	0.119	-4.75	-5.12	0.119	-4.84	-5.13	0.119	0.11	-1.692
	7	6535		-5.64	-5.86	0.119	-5.74	-6.01	0.119	-5.87	-5.96	0.119	2.24	-0.379
		6695		-6.21	-5.72	0.119	-6.03	-5.67	0.119	-6.14	-5.79	0.119	2.24	-0.477
		6855		-5.71	-5.41	0.119	-5.79	-5.46	0.119	-5.82	-5.45	0.119	2.24	-0.188
	8	6875		-6.03	-5.61	0.119	-5.85	-5.52	0.119	-6.05	-5.61	0.119	2.24	-0.313
		6995		-4.98	-4.74	0.119	-4.93	-4.83	0.119	-5.13	-4.93	0.119	1.26	-0.469
		7115		-4.70	-4.54	0.119	-4.61	-4.42	0.119	-8.49	-8.22	0.119	1.26	-0.125

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 37			RU Index 40			RU Index 44				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE40	5	5965	52T	-3.19	-2.71	0.119	-2.96	-2.95	0.119	-3.14	-2.83	0.119	4.28	4.47
		6165		-4.07	-4.43	0.119	-3.99	-4.40	0.119	-4.25	-4.51	0.119	4.28	3.22
		6405		-4.41	-5.02	0.119	-4.52	-4.99	0.119	-4.71	-5.10	0.119	4.28	2.71
	6	6445		-4.82	-4.83	0.119	-4.75	-4.90	0.119	-4.71	-5.02	0.119	0.11	-1.59
		6485		-4.80	-5.03	0.119	-4.77	-5.07	0.119	-4.71	-5.16	0.119	0.11	-1.67
	7	6525		-5.09	-5.20	0.119	-5.14	-5.32	0.119	-5.11	-5.30	0.119	2.24	0.22
		6685		-6.19	-5.83	0.119	-6.21	-5.84	0.119	-6.28	-5.87	0.119	2.24	-0.64
		6845		-5.73	-5.44	0.119	-5.89	-5.41	0.119	-6.00	-5.61	0.119	2.24	-0.21
	8	6885		-5.95	-5.69	0.119	-6.21	-5.65	0.119	-6.18	-5.99	0.119	1.26	-1.43
		7005		-4.95	-4.74	0.119	-5.07	-4.95	0.119	-5.15	-5.01	0.119	1.26	-0.45
		7085		-4.60	-4.26	0.119	-4.61	-4.51	0.119	-4.77	-4.50	0.119	1.26	-0.04

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925-6425MHz: Directional gain = $10 \log[(10^{3.70/10} + 10^{4.80/10})/2]$= 4.28dBi
6425-6525MHz: Directional gain = $10 \log[(10^{-1.0/10} + 10^{1.0/10})/2]$= 0.11dBi
6525-6875MHz: Directional gain = $10 \log[(10^{2.86/10} + 10^{1.60/10})/2]$= 0.24dBi
6875-7125MHz: Directional gain = $10 \log[(10^{-1.40/10} + 10^{2.90/10})/2]$= 1.26dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.
6. We did spot check for output power and all output power values keep identical thus other conducted items is exempt.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 37			RU Index 44			RU Index 52				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	52T	-2.85	-3.22	0.119	-2.49	-2.74	0.119	-3.12	-3.25	0.119	4.28	4.80
		6145		-4.14	-4.06	0.119	-3.81	-3.86	0.119	-4.55	-4.66	0.119	4.28	3.57
		6385		-4.86	-4.64	0.119	-4.53	-4.38	0.119	-5.43	-5.32	0.119	4.28	2.95
	6	6465		-5.11	-5.40	0.119	-4.87	-5.02	0.119	-5.39	-5.75	0.119	0.11	-1.71
		6545		-5.37	-5.65	0.119	-5.20	-5.33	0.119	-5.78	-6.14	0.119	2.24	0.10
	7	6625		-5.93	-6.71	0.119	-5.75	-6.36	0.119	-6.19	-7.14	0.119	2.24	-0.67
		6705		-6.08	-6.95	0.119	-5.49	-6.61	0.119	-5.98	-7.22	0.119	2.24	-0.64
		6785		-5.42	-6.27	0.119	-5.18	-5.86	0.119	-5.48	-6.49	0.119	2.24	-0.14
	8	6865		-5.60	-6.55	0.119	-5.18	-6.30	0.119	-6.11	-7.17	0.119	2.24	-0.33
		6945		-4.94	-5.39	0.119	-4.16	-5.07	0.119	-5.10	-5.62	0.119	1.26	-0.20
		7025		-5.07	-5.87	0.119	-4.89	-5.46	0.119	-5.53	-6.22	0.119	1.26	-0.78

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 37			RU Index 44			RU Index 52				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80L)	5	6025	52T	-4.34	-4.44	0.119	-3.33	-3.45	0.119	-2.91	-2.71	0.119	4.28	4.60
		6185		-5.79	-5.27	0.119	-4.61	-4.34	0.119	-4.25	-4.04	0.119	4.28	3.27
		6345		-6.22	-5.82	0.119	-5.14	-4.49	0.119	-4.54	-4.04	0.119	4.28	3.13
	6	6505		-6.54	-6.46	0.119	-5.49	-5.38	0.119	-5.15	-4.96	0.119	0.11	-1.81
	7	6665		-7.40	-7.87	0.119	-6.16	-6.70	0.119	-5.78	-6.25	0.119	2.24	-0.64
		6825		-6.91	-7.32	0.119	-5.75	-6.20	0.119	-5.28	-5.81	0.119	2.24	-0.17
	8	6985		-5.83	-6.37	0.119	-5.04	-5.31	0.119	-4.68	-4.94	0.119	1.26	-0.42

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index S37			RU Index S44			RU Index S52				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80H)	5	6025	52T	-2.99	-3.05	0.119	-3.59	-3.41	0.119	-5.34	-4.80	0.119	4.28	4.39
		6185		-4.45	-3.99	0.119	-4.92	-4.59	0.119	-6.25	-6.30	0.119	4.28	3.20
		6345		-4.57	-4.28	0.119	-5.09	-4.71	0.119	-6.96	-6.27	0.119	4.28	2.99
	6	6505		-4.95	-4.96	0.119	-5.92	-5.48	0.119	-7.40	-7.15	0.119	0.11	-1.72
	7	6665		-5.87	-6.33	0.119	-6.26	-6.72	0.119	-7.51	-8.10	0.119	2.24	-0.72
		6825		-5.17	-5.91	0.119	-5.91	-6.40	0.119	-7.51	-8.03	0.119	2.24	-0.15
	8	6985		-4.62	-5.15	0.119	-5.43	-5.56	0.119	-7.14	-7.13	0.119	1.26	-0.49

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = 10 log[$(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}$] dBi
Directional gain:
5925-6425MHz: Directional gain = 10 log[$(10^{3.70/10} + 10^{4.80/10})/2$]= 4.28dBi
6425-6525MHz: Directional gain = 10 log[$(10^{-1.0/10} + 10^{1.0/10})/2$]= 0.11dBi
6525-6875MHz: Directional gain = 10 log[$(10^{2.86/10} + 10^{1.60/10})/2$]= 0.24dBi
6875-7125MHz: Directional gain = 10 log[$(10^{-1.40/10} + 10^{2.90/10})/2$]= 1.26dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.
6. We did spot check for output power and all output power values keep identical thus other conducted items is exempt.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Tones: 106T

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 53			RU Index 54				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE20	5	5955	106T	0.24	0.33	N/A	0.10	0.22	N/A	4.28	7.58
		6175		-0.77	-1.14	N/A	-0.96	-1.27	N/A	4.28	6.34
		6415		-1.25	-1.92	N/A	-1.40	-1.94	N/A	4.28	5.72
	6	6435		-1.59	-1.69	N/A	-1.41	-1.58	N/A	0.11	1.63
		6475		-1.51	-1.83	N/A	-1.78	-1.81	N/A	0.11	1.45
		6515		-1.66	-1.92	N/A	-1.67	-2.07	N/A	0.11	1.33
	7	6535		-2.59	-2.94	N/A	-2.74	-3.02	N/A	2.24	2.49
		6695		-3.27	-2.88	N/A	-3.05	-2.75	N/A	2.24	2.35
		6855		-2.61	-2.23	N/A	-2.84	-2.35	N/A	2.24	2.83
	8	6875		-2.75	-2.54	N/A	-2.83	-2.59	N/A	2.24	2.61
		6995		-1.75	-1.72	N/A	-1.89	-1.71	N/A	1.26	2.54
		7115		-1.59	-1.45	N/A	-8.63	-8.16	N/A	1.26	2.75

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 53			RU Index 54			RU Index 56				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE40	5	5965	106T	0.06	0.12	N/A	0.00	0.24	N/A	0.22	0.03	N/A	4.28	7.42
		6165		-1.04	-1.32	N/A	-1.14	-1.41	N/A	-1.24	-1.44	N/A	4.28	6.11
		6405		-1.33	-1.99	N/A	-1.43	-1.93	N/A	-1.64	-2.03	N/A	4.28	5.64
	6	6445		-1.71	-1.89	N/A	-1.42	-1.71	N/A	-1.50	-1.92	N/A	0.11	1.56
		6485		-1.76	-1.91	N/A	-1.71	-1.96	N/A	-1.94	-2.11	N/A	0.11	1.29
	7	6525		-1.79	-2.16	N/A	-1.85	-2.21	N/A	-1.93	-2.42	N/A	2.24	3.28
		6685		-3.25	-2.90	N/A	-3.31	-2.71	N/A	-3.14	-2.78	N/A	2.24	2.29
		6845		-2.68	-2.35	N/A	-2.89	-2.36	N/A	-3.07	-2.50	N/A	2.24	2.74
	8	6885		-3.05	-2.62	N/A	-2.97	-2.56	N/A	-3.28	-2.83	N/A	1.26	1.51
		7005		-1.99	-1.85	N/A	-1.79	-1.89	N/A	-2.19	-2.02	N/A	1.26	2.43
		7085		-1.57	-1.34	N/A	-1.66	-1.42	N/A	-1.76	-1.44	N/A	1.26	2.82

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = 10 log[($10^{G1/10}$ + $10^{G2/10}$ + … + $10^{GN/10}$)/N_{ANT}] dBi
Directional gain:
5925-6425MHz: Directional gain = 10 log[($10^{3.70/10}$ +$10^{4.80/10}$)/2]= 4.28dBi
6425-6525MHz: Directional gain = 10 log[($10^{-1.0/10}$ +$10^{1.0/10}$)/2]= 0.11dBi
6525-6875MHz: Directional gain = 10 log[($10^{2.86/10}$ +$10^{1.60/10}$)/2]= 0.24dBi
6875-7125MHz: Directional gain = 10 log[($10^{-1.40/10}$ +$10^{2.90/10}$)/2]= 1.26dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.
6. We did spot check for output power and all output power values keep identical thus other conducted items is exempt.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan

Tel: +886 2 26099301
Fax: +886 2 26099303

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 53			RU Index 56			RU Index 60				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	106T	0.00	-0.20	N/A	0.51	0.16	N/A	-0.33	-0.32	N/A	4.28	7.63
		6145		-1.35	-1.20	N/A	-1.19	-0.93	N/A	-1.55	-1.61	N/A	4.28	6.23
		6385		-2.01	-1.91	N/A	-1.83	-1.52	N/A	-2.36	-2.27	N/A	4.28	5.62
	6	6465		-2.07	-2.42	N/A	-1.64	-2.21	N/A	-2.17	-2.61	N/A	0.11	1.20
		6545		-2.16	-2.76	N/A	-2.13	-2.53	N/A	-2.85	-3.12	N/A	2.24	2.92
	7	6625		-3.12	-3.92	N/A	-2.65	-3.58	N/A	-3.00	-4.13	N/A	2.24	2.16
		6705		-2.95	-4.14	N/A	-2.51	-3.76	N/A	-2.96	-4.25	N/A	2.24	2.16
		6785		-1.87	-2.86	N/A	-1.63	-2.65	N/A	-2.37	-3.30	N/A	2.24	3.14
	8	6865		-2.29	-3.28	N/A	-2.21	-3.17	N/A	-2.72	-3.78	N/A	2.24	2.59
		6945		-1.44	-2.05	N/A	-1.11	-1.79	N/A	-2.08	-2.43	N/A	1.26	2.83
		7025		-2.03	-2.38	N/A	-1.61	-2.39	N/A	-2.48	-2.82	N/A	1.26	2.29

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 53			RU Index 56			RU Index 60				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80L)	5	6025	106T	-1.36	-1.34	N/A	-0.38	-0.31	N/A	0.03	0.23	N/A	4.28	7.42
		6185		-2.52	-2.17	N/A	-1.51	-1.43	N/A	-1.30	-1.14	N/A	4.28	6.07
		6345		-3.32	-2.37	N/A	-2.18	-1.42	N/A	-1.64	-1.17	N/A	4.28	5.89
	6	6505		-3.23	-3.23	N/A	-2.24	-2.22	N/A	-1.99	-1.82	N/A	0.11	1.22
	7	6665		-4.37	-4.55	N/A	-3.56	-3.56	N/A	-2.77	-3.05	N/A	2.24	2.34
		6825		-3.81	-3.88	N/A	-3.13	-3.01	N/A	-2.46	-2.42	N/A	2.24	2.81
	8	6985		-2.79	-2.88	N/A	-1.94	-2.03	N/A	-1.64	-1.70	N/A	1.26	2.60

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index S53			RU Index S56			RU Index S60				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80H)	5	6025	106T	0.10	0.19	N/A	-0.60	-0.21	N/A	-2.24	-1.80	N/A	4.28	7.44
		6185		-1.37	-0.87	N/A	-1.67	-1.55	N/A	-3.23	-3.07	N/A	4.28	6.18
		6345		-1.51	-1.10	N/A	-2.02	-1.66	N/A	-3.51	-3.08	N/A	4.28	5.99
	6	6505		-2.08	-1.83	N/A	-2.47	-2.41	N/A	-3.99	-4.00	N/A	0.11	1.17
	7	6665		-3.04	-3.28	N/A	-3.65	-3.70	N/A	-5.02	-4.96	N/A	2.24	2.09
		6825		-2.47	-2.29	N/A	-3.14	-2.98	N/A	-4.45	-4.62	N/A	2.24	2.87
	8	6985		-1.71	-1.57	N/A	-2.35	-2.16	N/A	-3.86	-3.62	N/A	1.26	2.63

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925-6425MHz: Directional gain = $10 \log[(10^{3.70/10} + 10^{4.80/10})/2]$= 4.28dBi
6425-6525MHz: Directional gain = $10 \log[(10^{-1.0/10} + 10^{1.0/10})/2]$= 0.11dBi
6525-6875MHz: Directional gain = $10 \log[(10^{2.86/10} + 10^{1.60/10})/2]$= 0.24dBi
6875-7125MHz: Directional gain = $10 \log[(10^{-1.40/10} + 10^{2.90/10})/2]$= 1.26dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.
6. We did spot check for output power and all output power values keep identical thus other conducted items is exempt..

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Tones: 242T

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)			Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 61				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE20	5	5955	242T	1.95	2.4	0.15	4.28	9.62
		6175		1.88	2.28	0.15	4.28	9.52
		6415		1.83	2.37	0.15	4.28	9.55
	6	6435		1.18	1.72	0.15	0.11	4.73
		6475		1.43	1.68	0.15	0.11	4.83
		6515		1.67	1.72	0.15	0.11	4.97
	7	6535		1.38	1.43	0.15	2.24	6.81
		6695		1.62	1.52	0.15	2.24	6.97
		6855		1.53	1.67	0.15	2.24	7.00
	8	6875		0.88	0.99	0.15	2.24	6.34
		6995		0.76	0.8	0.15	1.26	5.20
		7115		-2.98	-2.8	0.15	1.26	1.53

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 61			RU Index 62				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE40	5	5965	242T	1.92	1.17	0.15	1.72	1.07	0.15	4.28	9.00
		6165		1.56	1.24	0.15	1.47	0.97	0.15	4.28	8.84
		6405		1.62	1.25	0.15	1.63	1.35	0.15	4.28	8.93
	6	6445		1.02	0.95	0.15	1.22	0.96	0.15	0.11	4.36
		6485		1.17	0.77	0.15	1.02	1.33	0.15	0.11	4.45
	7	6525		1.39	0.82	0.15	2.05	1.34	0.15	2.24	7.11
		6685		1.04	0.13	0.15	1.25	0.17	0.15	2.24	6.14
		6845		1.04	-0.02	0.15	1.16	0.09	0.15	2.24	6.06
	8	6885		0.81	-0.22	0.15	0.65	-0.17	0.15	1.26	4.75
		7005		0.64	-0.46	0.15	0.69	-0.27	0.15	1.26	4.66
		7085		0.85	-0.12	0.15	0.96	0.47	0.15	1.26	5.14

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925-6425MHz: Directional gain = $10 \log[(10^{3.70/10} + 10^{4.80/10})/2]$= 4.28dBi
6425-6525MHz: Directional gain = $10 \log[(10^{-1.0/10} + 10^{1.0/10})/2]$= 0.11dBi
6525-6875MHz: Directional gain = $10 \log[(10^{2.86/10} + 10^{1.60/10})/2]$= 0.24dBi
6875-7125MHz: Directional gain = $10 \log[(10^{-1.40/10} + 10^{2.90/10})/2]$= 1.26dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.
6. We did spot check for output power and all output power values keep identical thus other conducted items is exempt.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 61			RU Index 62			RU Index 64				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	242T	2.19	2.58	0.15	2.24	2.8	0.15	2.25	2.37	0.15	4.28	9.97
		6145		2.4	2.37	0.15	2.37	2.41	0.15	1.99	2.24	0.15	4.28	9.83
		6385		1.94	2.08	0.15	2.27	2.28	0.15	2.09	2.26	0.15	4.28	9.72
	6	6465		1.76	1.5	0.15	2.57	2.52	0.15	1.65	1.52	0.15	0.11	5.82
		6545		1.28	1.86	0.15	2.23	2.86	0.15	1.87	2.3	0.15	2.24	7.96
	7	6625		0.86	1.61	0.15	1.07	1.64	0.15	0.82	1.47	0.15	2.24	6.76
		6705		1.02	1.57	0.15	1.12	1.67	0.15	0.7	1.5	0.15	2.24	6.80
		6785		0.93	1.4	0.15	0.98	1.63	0.15	0.75	1.57	0.15	2.24	6.72
	8	6865		0.67	1.25	0.15	1.14	1.81	0.15	0.25	0.7	0.15	2.24	6.89
		6945		0.35	0.77	0.15	1.23	1.92	0.15	0.25	0.69	0.15	1.26	6.01
		7025		0.03	0.77	0.15	1.1	1.7	0.15	-0.15	1.06	0.15	1.26	5.83

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 61			RU Index 62			RU Index 64				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80L)	5	6025	242T	1.75	2.56	0.15	2.3	2.89	0.15	1.6	2.47	0.15	4.28	10.05
		6185		1.86	2.32	0.15	2.03	2.85	0.15	1.66	2.31	0.15	4.28	9.90
		6345		1.8	2.33	0.15	2.18	2.57	0.15	1.81	2.34	0.15	4.28	9.82
	6	6505		1.48	1.79	0.15	2.37	2.84	0.15	1.3	1.81	0.15	0.11	5.88
	7	6665		-0.1	1.33	0.15	0.43	1.78	0.15	0.17	1.72	0.15	2.24	6.56
		6825		-0.17	1.26	0.15	0.22	1.51	0.15	-0.35	1.16	0.15	2.24	6.31
	8	6985		-0.67	0.6	0.15	0.59	1.92	0.15	-0.8	0.78	0.15	1.26	5.73

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)									Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index S61			RU Index S62			RU Index S64				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80H)	5	6025	242T	1.39	2.55	0.15	1.3	2.52	0.15	1.68	2.39	0.15	4.28	9.49
		6185		1.61	2.32	0.15	1.4	2.46	0.15	1.76	2.44	0.15	4.28	9.55
		6345		1.61	2.22	0.15	1.55	2.31	0.15	1.85	2.43	0.15	4.28	9.59
	6	6505		1.48	1.78	0.15	1.98	2.49	0.15	1.74	2.33	0.15	0.11	5.51
	7	6665		-0.28	1.39	0.15	-0.52	1.19	0.15	-0.48	1.5	0.15	2.24	6.04
		6825		-0.66	1.31	0.15	0.23	1.25	0.15	-0.38	0.75	0.15	2.24	6.17
	8	6985		-0.76	0.54	0.15	0.07	1.44	0.15	-0.44	0.97	0.15	1.26	5.23

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925-6425MHz: Directional gain = $10 \log[(10^{3.70/10} + 10^{4.80/10})/2]$= 4.28dBi
6425-6525MHz: Directional gain = $10 \log[(10^{-1.0/10} + 10^{1.0/10})/2]$= 0.11dBi
6525-6875MHz: Directional gain = $10 \log[(10^{2.86/10} + 10^{1.60/10})/2]$= 0.24dBi
6875-7125MHz: Directional gain = $10 \log[(10^{-1.40/10} + 10^{2.90/10})/2]$= 1.26dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.
6. We did spot check for output power and all output power values keep identical thus other conducted items is exempt.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Tones: 484T

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)			Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 65				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE40	5	5965	484T	5.13	5.37	N/A	4.28	12.54
		6165		5.11	5.35	N/A	4.28	12.52
		6405		5.05	5.19	N/A	4.28	12.41
	6	6445		5.16	5.37	N/A	0.11	8.39
		6485		5.17	5.53	N/A	0.11	8.47
	7	6525		5.32	5.32	N/A	2.24	10.57
		6685		4.62	4.68	N/A	2.24	9.90
		6845		4.53	4.46	N/A	2.24	9.75
	8	6885		4.69	4.7	N/A	1.26	8.97
		7005		4.45	4.39	N/A	1.26	8.69
		7085		4.58	4.78	N/A	1.26	8.95

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 65			RU Index 66				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	484T	5.13	5.22	N/A	5.19	5.26	N/A	4.28	12.52
		6145		5.26	5.15	N/A	5.33	5.09	N/A	4.28	12.50
		6385		4.9	4.93	N/A	5.31	5.04	N/A	4.28	12.47
	6	6465		5.33	4.91	N/A	5.17	5.36	N/A	0.11	8.39
		6545		5.04	5.41	N/A	5.07	5.15	N/A	2.24	10.48
	7	6625		4.27	4.34	N/A	4.2	4.38	N/A	2.24	9.56
		6705		4.3	4.33	N/A	4.22	4.56	N/A	2.24	9.64
		6785		4.1	4.43	N/A	4.17	4.63	N/A	2.24	9.66
	8	6865		4.2	4.51	N/A	4.38	4.35	N/A	2.24	9.62
		6945		4.45	4.19	N/A	4.12	4.5	N/A	1.26	8.59
		7025		4.12	4.42	N/A	4.28	4.37	N/A	1.26	8.60

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925-6425MHz: Directional gain = $10 \log[(10^{3.70/10} + 10^{4.80/10})/2]$= 4.28dBi
6425-6525MHz: Directional gain = $10 \log[(10^{-1.0/10} + 10^{1.0/10})/2]$= 0.11dBi
6525-6875MHz: Directional gain = $10 \log[(10^{2.86/10} + 10^{1.60/10})/2]$= 0.24dBi
6875-7125MHz: Directional gain = $10 \log[(10^{-1.40/10} + 10^{2.90/10})/2]$= 1.26dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.
6. We did spot check for output power and all output power values keep identical thus other conducted items is exempt.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 65			RU Index 66				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80L)	5	6025	484T	4.83	5.33	N/A	4.58	5.31	N/A	4.28	12.38
		6185		4.85	5.17	N/A	4.93	5.13	N/A	4.28	12.32
		6345		4.77	5.05	N/A	4.85	5.12	N/A	4.28	12.28
	6	6505		5.17	5.05	N/A	5.15	5.22	N/A	0.11	8.31
	7	6665		3.76	4.41	N/A	3.45	4.3	N/A	2.24	9.35
		6825		3.83	4.35	N/A	3.53	4.53	N/A	2.24	9.35
	8	6985		4.19	4.3	N/A	4.01	4.57	N/A	1.26	8.57

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index S65			RU Index S66				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160 (80H)	5	6025	484T	4.76	5.3	N/A	4.65	5.28	N/A	4.28	12.33
		6185		4.72	5.18	N/A	4.77	4.94	N/A	4.28	12.25
		6345		4.53	5.08	N/A	4.81	5.01	N/A	4.28	12.20
	6	6505		4.97	5.28	N/A	4.84	5.16	N/A	0.11	8.25
	7	6665		3.85	4.4	N/A	3.79	4.46	N/A	2.24	9.39
		6825		3.9	4.5	N/A	3.88	4.51	N/A	2.24	9.46
	8	6985		3.89	4.23	N/A	3.96	4.61	N/A	1.26	8.57

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925-6425MHz: Directional gain = $10 \log[(10^{3.70/10} + 10^{4.80/10})/2]$= 4.28dBi
6425-6525MHz: Directional gain = $10 \log[(10^{-1.0/10} + 10^{1.0/10})/2]$= 0.11dBi
6525-6875MHz: Directional gain = $10 \log[(10^{2.86/10} + 10^{1.60/10})/2]$= 0.24dBi
6875-7125MHz: Directional gain = $10 \log[(10^{-1.40/10} + 10^{2.90/10})/2]$= 1.26dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.
6. We did spot check for output power and all output power values keep identical thus other conducted items is exempt.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.

Audix Technology Corp.
No. 491, Zhongfu Rd., Linkou Dist.,
New Taipei City244, Taiwan
Tel: +886 2 26099301
Fax: +886 2 26099303

Tones: 996T

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)			Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 67				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE80	5	5985	996T	6.76	6.38	0.159	4.28	14.02
		6145		6.86	5.96	0.159	4.28	13.88
		6385		7.08	6.32	0.159	4.28	14.17
	6	6465		6.99	6.08	0.159	0.11	9.84
		6545		7.02	5.87	0.159	2.24	11.89
	7	6625		6.3	5.13	0.159	2.24	11.16
		6705		6.2	5.03	0.159	2.24	11.06
		6785		6.08	4.91	0.159	2.24	10.94
	8	6865		5.84	5.13	0.159	2.24	10.91
		6945		6	5.08	0.159	1.26	9.99
		7025		6.07	5.42	0.159	1.26	10.19

Mode	U-NII Band	Centre Frequency (MHz)	Tones	Average Conducted Output power (dBm)						Directional Antenna Gain (dBi) Note 4	Max EIRP (dBm) Note 5
				RU Index 67			RU Index S67				
				AUX	Main	Duty Cycle Factor 10log(1/X) Note 3	AUX	Main	Duty Cycle Factor 10log(1/X) Note 3		
802.11ax-HE160	5	6025	996T	7.05	6.26	0.159	6.94	6.11	0.159	4.28	14.12
		6185		6.93	6.15	0.159	7.04	6.153	0.159	4.28	14.07
		6345		7.22	6.51	0.159	7.14	6.14	0.159	4.28	14.33
	6	6505		6.91	5.69	0.159	6.88	5.84	0.159	0.11	9.67
	7	6665		6.79	5.47	0.159	6.47	5.12	0.159	2.24	11.59
		6825		6.33	5.3	0.159	6.05	4.88	0.159	2.24	11.25
	8	6985		6.12	5.27	0.159	6	5.27	0.159	1.26	10.15

Note: 1. All results have been included cable loss [Please refer to KDB 662911 E 2) c)]
2. EIRP limit is 24dBm
3. Duty cycle factor is not applicable for duty cycle > 98%.
4. According to KDB 662911 D01 d) ii), transmit signals are completely uncorrelated, then
Directional gain = $10 \log[(10^{G1/10} + 10^{G2/10} + \ldots + 10^{GN/10})/N_{ANT}]$ dBi
Directional gain:
5925-6425MHz: Directional gain = $10 \log[(10^{3.70/10} + 10^{4.80/10})/2]$= 4.28dBi
6425-6525MHz: Directional gain = $10 \log[(10^{-1.0/10} + 10^{1.0/10})/2]$= 0.11dBi
6525-6875MHz: Directional gain = $10 \log[(10^{2.86/10} + 10^{1.60/10})/2]$= 0.24dBi
6875-7125MHz: Directional gain = $10 \log[(10^{-1.40/10} + 10^{2.90/10})/2]$= 1.26dBi
The MIMO is uncorrelated and supported SDM(Spatial Division Multiplexing) mode only. This radio device doesn't support beamforming and Cyclic Delay Diversity (CDD).
5. Max EIRP = Max of Average Conducted Output Power [ANT A (AUX)+ ANT B (Main)+ Duty Cycle Factor]+ Directional gain.
6. We did spot check for output power and all output power values keep identical thus other conducted items is exempt.

This test report may be reproduced in full only. The document may only be updated by Audix Technology Corp. personnel. Any changes will be noted in the Document History section of the report.