

4 inches

5 inches

**ESTeem Model 192M RS-232C/422/485  
SETUP SWITCH CONFIGURATION TABLES**

| Baud Rate Configuration Table |      |      | Auto Connect Feature |      |
|-------------------------------|------|------|----------------------|------|
|                               | Bt 1 | Bt 2 | Bt 3                 | Bt 8 |
| 19,200                        | OFF  | OFF  | OFF                  | ON   |
| 9,600                         | ON   | OFF  | OFF                  | ON   |
| 4,800                         | OFF  | ON   | OFF                  | OFF  |
| 2,400                         | ON   | ON   | OFF                  |      |
| 1,200                         | OFF  | OFF  | ON                   |      |
| 600                           | ON   | OFF  | ON                   |      |
| 300                           | OFF  | ON   | ON                   |      |

**Restoring Factory Defaults**  
1. Set Bt 8 ON  
2. Reset ESTeem  
3. Type FA (Enter)

| Parity/Stop Bt Configuration Table      |      |      |      |      |  |  |
|-----------------------------------------|------|------|------|------|--|--|
|                                         | Bt 4 | Bt 5 | Bt 6 | Bt 7 |  |  |
| 7 data bits + No parity + 1 stop bits   | OFF  | OFF  | OFF  | OFF  |  |  |
| 7 data bits + No parity + 2 stop bits   | ON   | OFF  | OFF  | OFF  |  |  |
| 7 data bits + Odd parity + 1 stop bits  | OFF  | ON   | OFF  | ON   |  |  |
| 7 data bits + Odd parity + 2 stop bits  | ON   | ON   | OFF  | ON   |  |  |
| 7 data bits + Even parity + 1 stop bits | OFF  | ON   | OFF  | OFF  |  |  |
| 7 data bits + Even parity + 2 stop bits | ON   | ON   | OFF  | OFF  |  |  |
| 8 data bits + No parity + 1 stop bits   | OFF  | OFF  | ON   | OFF  |  |  |
| 8 data bits + No parity + 2 stop bits   | ON   | OFF  | ON   | OFF  |  |  |
| 8 data bits + Odd parity + 1 stop bits  | OFF  | ON   | ON   | ON   |  |  |
| 8 data bits + Odd parity + 2 stop bits  | ON   | ON   | ON   | ON   |  |  |
| 8 data bits + Even parity + 1 stop bits | OFF  | ON   | ON   | OFF  |  |  |
| 8 data bits + Even parity + 2 stop bits | ON   | ON   | ON   | OFF  |  |  |

FCC ID: ENPESTEEM192M      CANADA: XXXX XXX XXXX

**Est** Electronic Systems Technology, Inc.

**ESTeem Model 192M Label**  
**12.5 KHz Channel Spacing**  
**4 in. x 5 in.**

FCC ID: ENPESTEEM192M

Rear

Bottom View

**ES Teem Model 192V RS-232C/422/485  
SETUP SWITCH CONFIGURATION TABLES**

|        | Bit 1 | Bit 2 | Bit 3 |
|--------|-------|-------|-------|
| 19,200 | OFF   | OFF   | OFF   |
| 9,600  | ON    | OFF   | OFF   |
| 4,800  | OFF   | ON    | OFF   |
| 2,400  | ON    | ON    | OFF   |
| 1,200  | OFF   | OFF   | ON    |
| 600    | ON    | OFF   | ON    |
| 300    | OFF   | ON    | ON    |

|          | Bit 8 |
|----------|-------|
| Enabled  | ON    |
| Disabled | OFF   |

**Restoring Factory Defaults**

1. Set Bit 8 Off
2. Reset ES Teem
3. Type FA (Enter)

|                                         | Bit 4 | Bit 5 | Bit 6 | Bit 7 |
|-----------------------------------------|-------|-------|-------|-------|
| 7 data bits + No parity + 1 stop bits   | OFF   | OFF   | OFF   | OFF   |
| 7 data bits + No parity + 2 stop bits   | ON    | OFF   | OFF   | OFF   |
| 7 data bits + Odd parity + 1 stop bits  | OFF   | ON    | OFF   | ON    |
| 7 data bits + Odd parity + 2 stop bits  | ON    | ON    | OFF   | ON    |
| 7 data bits + Even parity + 1 stop bits | OFF   | ON    | OFF   | OFF   |
| 7 data bits + Even parity + 2 stop bits | ON    | ON    | OFF   | OFF   |
| 8 data bits + No parity + 1 stop bits   | OFF   | OFF   | ON    | OFF   |
| 8 data bits + No parity + 2 stop bits   | ON    | OFF   | ON    | OFF   |
| 8 data bits + Odd parity + 1 stop bits  | OFF   | ON    | ON    | ON    |
| 8 data bits + Odd parity + 2 stop bits  | ON    | ON    | ON    | ON    |
| 8 data bits + Even parity + 1 stop bits | OFF   | ON    | ON    | OFF   |
| 8 data bits + Even parity + 2 stop bits | ON    | ON    | ON    | OFF   |

FCC ID: ENPESTEEM192M

CANADA: A000000000



Electronic Systems Technology, Inc.