



ScanPal™ EDA5S

Mobile Computer
powered by Android™

User Guide

Disclaimer

Honeywell International Inc. ("HII") reserves the right to make changes in specifications and other information contained in this document without prior notice, and the reader should in all cases consult HII to determine whether any such changes have been made. The information in this publication does not represent a commitment on the part of HII.

HII shall not be liable for technical or editorial errors or omissions contained herein; nor for incidental or consequential damages resulting from the furnishing, performance, or use of this material. HII disclaims all responsibility for the selection and use of software and/or hardware to achieve intended results.

This document contains proprietary information that is protected by copyright. All rights are reserved. No part of this document may be photocopied, reproduced, or translated into another language without the prior written consent of HII.

Copyright © 2021 Honeywell International Inc. All rights reserved.

Web Address: www.honeywellaidc.com

Trademarks

Google, Android, Google Play, Google Pay and other marks are trademarks of Google LLC

Bluetooth trademarks are owned by Bluetooth SIG, Inc., U.S.A. and licensed to Honeywell.

microSD is a registered trademark of SD-3C, LLC.

Qualcomm and Snapdragon are registered trademarks or trademarks of Qualcomm Incorporated in the United States and/or other countries.

Other product names or marks mentioned in this document may be trademarks or registered trademarks of other companies and are the property of their respective owners.

Patents

For patent information, refer to www.hsmpats.com.

TABLE OF CONTENTS

Customer Support	ix
Technical Assistance	ix
Product Service and Repair	ix
Limited Warranty	ix
Chapter 1 - About the Computer Features.....	1
About the Mobile Computer.....	1
EDA5S Model Overview.....	2
Mobile Computer Features	3
About the Battery	4
Battery Part Numbers	5
Charge the Battery Before Use.....	5
Battery Replacement.....	5
Replace the Battery.....	5
About the Battery Status.....	8
About the Battery Status LED Setting.....	8
Check the Battery Level and Usage	9
About Battery Life and Conservation	10
Battery Recommendations and Safety Precautions	11
Power On the Computer	11
Welcome Screen.....	12
Unlock the Screen	12
Change the Screen Lock to Protect the Computer	12
Configure the Screen Backlight	13
About the Good Read LED	13

About the Audio Features	14
Adjust Speaker Volume	14
Enable Vibrate Mode.....	15
Audio Settings	15
Insert a microSD Card.....	16
How to Transfer Files.....	17
Configure USB Connection and Transfer Files	17
Accessories for the Computer.....	18

Chapter 2 - About the User Interface and Applications 19

About the User Interface.....	19
Navigation and Function Buttons	20
Remap a Button	21
Restore Default Button Action	22
About Status Bar Icons	22
View and Manage Notifications	23
Open Quick Settings	23
Customize the Home Screen	23
Customize the Favorites Tray	24
Use Google™ Search.....	24
About Screen Gestures	24
Set the Time Zone.....	25
About Honeywell Applications.....	26
Applications You Can Download to the Mobile Computer	27
Unlock Developer Options	29

Chapter 3 - Use the Imager 31

About the Imager	31
About the Scan Wedge Feature	31
Change the Scanner Settings	32
Change the Bluetooth Scanner Settings	32
Restore Default Scan Settings	33
Default Scan Settings.....	33

Add a Scan Setting Profile.....	39
Delete a Scan Setting Profile	40
About ScanHandle Settings.....	40
About the Optional Digital Scan Button	40
Enable and Configure the Digital Scan Button	40
Scan Barcodes.....	41
About Scanning Configuration Barcodes.....	41
Use the Scan Demo App	42
Change the Scan Demo Symbology Settings	42
Chapter 4 - Use the Phone.....	43
About the Phone	43
Activate the Phone	43
Make a Phone Call	45
Answer the Phone	45
Switch Apps During a Phone Call.....	46
Make an Emergency Phone Call	46
Configure Phone Settings	46
Chapter 5 - Use the Camera	47
About the Color Camera	47
How to Zoom	47
Take a Photo.....	47
Record a Video.....	48
Change Camera Settings	49
Use the Camera as a Flashlight	49
Chapter 6 - Configure the Computer	51
How to Configure the Computer	51
Start the Settings App.....	51
About the Structure of the Settings App	51
About Network Communications	62
Connect to a Wi-Fi Network.....	62

Honeywell Wi-Fi Settings	63
How to Connect to Virtual Private Networks	64
About Wireless Security.....	65
About Certificates	65
About Bluetooth Communications.....	67
Connect a Bluetooth Device	67
Rename the Computer and View File History	68
Rename or Unpair a Paired Device.....	68
About USB Communications	68
USB Troubleshooting.....	69
USB, Bluetooth, or Ethernet Tethering for Data Connection Sharing	69
Minimum requirements for USB Tethering	69
Set up and Connection	69
Minimum requirements for Bluetooth Tethering	69
Set up and Connection	70
Minimum requirements for Ethernet Tethering	70
Set up and Connection	70
About Near Field Communication (NFC)	70
Developer Information.....	71
About Provisioning Mode	71
Enable or Disable Provisioning Mode.....	72

Chapter 7 - Manage and Maintain the Computer..... 73

About Software Updates	73
Software Downloads	73
About Transferring Files via USB Connection	74
Install Software Apps with AutoInstall	74
Optional microSD Card Method.....	75
About the Honeywell Upgrader	75
Install OTA Updates	75
Restart (Reboot) the Computer.....	77
About an Enterprise Data Reset.....	77
Before You Begin	77

Enterprise Data Reset the Computer.....78

About a Full Factory Reset.....78

 Before You Begin.....78

 Full Factory Reset the Computer.....79

Repairs.....79

Maintenance79

 Clean the Computer80

Appendix A - Specifications81

Computer Agency Information81

 Label Locations.....81

Physical and Environmental Specifications82

Imager Specifications82

Barcode Symbolologies.....82

S0703 Imager83

 S0703 Imager Field of View/Resolution84

Customer Support

Technical Assistance

To search our knowledge base for a solution or to log in to the Technical Support portal and report a problem, go to www.hsmcontactsupport.com.

For our latest contact information, see www.honeywellaidc.com/locations.

Product Service and Repair

Honeywell International Inc. provides service for all of its products through service centers throughout the world. To find your service center, go to www.honeywellaidc.com and select Support. Contact your service center to obtain a Return Material Authorization number (RMA #) before you return the product.

To obtain warranty or non-warranty service, return your product to Honeywell (postage paid) with a copy of the dated purchase record. To learn more, go to www.honeywellaidc.com and select **Service & Repair** at the bottom of the page.

For ongoing and future product quality improvement initiatives, the mobile computer comes equipped with an embedded device lifetime counter function. Honeywell may use the lifetime counter data for future statistical reliability analysis as well as ongoing quality, repair and service purposes.

Limited Warranty

For warranty information, go to www.honeywellaidc.com and click **Resources > Product Warranty**.

ABOUT THE COMPUTER FEATURES

This chapter introduces the ScanPal™ EDA5S mobile computer. Use this chapter to learn about the basic computer features, functions, and accessories.

Note: *Throughout this manual, all versions of the mobile computer are referred to as the EDA5S unless information is specific to a particular model. The device applications and settings vary by computer model and OS version. Your computer may not include all the features shown in the manual.*

About the Mobile Computer

ScanPal EDA5S mobile computers deliver real-time connectivity, advanced data capture, and future-proof investment protection. All EDA5S models come equipped for fast Wi-Fi connectivity with a WLAN 802.11 a/b/g/n/ac radio and Bluetooth (v5.1) technology that includes Bluetooth Low Energy (BLE) support. EDA5S-1 models provide additional connectivity with a Wireless Wide Area Network (WWAN) radio for high speed data and quality voice support across all network technologies. EDA5S WWAN models also include an integrated global positioning satellite (GPS) receiver that supports GPS protocols including simultaneous GNSS Receiver Support for GPS, GLONASS, Galileo and Beidou.


To learn more about the EDA5S mobile computer, refer to the [EDA5S Model Overview](#) on page 2.

EDA5S Model Overview


Available Features	Model EDA5S-0	Model EDA5S-1
Android operating system*	x	x
Qualcomm® SM6115, 2.0 GHz processor	x	x
Memory options are dependent on model and scan engine type. 3GB DDR4 RAM, 32 GB flash memory 4GB DDR4 RAM, 64 GB flash memory	x	x
Choice of Honeywell high performance 2D imager	x	x
USB Type C connector for communication/charging/headset	x	x
High-tier rugged specifications with IP67 sealing	x	x
WLAN IEEE 802.11 a/b/g/n/ac radio; Wi-Fi certified	x	x
Bluetooth™ V5.0 and Bluetooth Low Energy wireless technology support	x	x
NFC technology for short-range wireless data exchange	x	x
WWAN radio for high speed data and quality voice support across all network technologies		x
Integrated GPS receiver; GPS protocol support for L1 bands that include Simultaneous GNSS Receiver Support for GPS, GLONASS, Galileo and Beidou, Assisted GPS		x
Customer-accessible microSD™ slot for removable memory cards up to 128 GB (SDXC/SDHC/SDIO-compliant)	x	x
13-megapixel color camera with video, image stabilization and advanced software features for enhanced exposure control	x	x
5-megapixel front-facing camera	x	x
Value-added software components supporting specialized imaging and OCR functions	x	x
Large, high definition (1440 x 720) resolution, bright color, outdoor-readable display with responsive multi-touch capacitive touch panel**	x	x
Integrated Ambient light sensor, proximity sensor, accelerometer, hall sensor.	x	x
* For information on supported Android OS versions, see the EDA5S Data Sheet, available at www.honeywellaidc.com. ** Use of a screen protector may have a small effect on the capacitive touch panel performance.		


Note: To learn more, see [Appendix A: Specifications](#) beginning on page 81.

Mobile Computer Features



Note: Wrist strap not shown.





About the Battery

The computer uses a rechargeable Li-ion battery as its main power source. Several factors determine the life of the battery, such as display brightness, display timeout, input device, extreme temperature, and battery usage. Honeywell recommends that you keep the battery charged at all times to prevent data loss.

EDA5S computers are designed for use with battery model BAT-EDA5S manufactured for Honeywell International Inc. **When ordering a replacement battery, it is important to order by part number and not only by model number.** See [Battery Part Numbers](#) on page 5 for guidance on the correct battery part number for your unit configuration.

For a list of compatible accessories, see the *EDA5S Accessory Guide*, available for download from the product device pages at www.honeywellaidc.com. Contact your local sales representative for replacement battery ordering information.



Caution: Improper battery replacement or incompatible device usage may result in risk of burns, fire, explosion, or other hazard. Dispose of lithium-ion batteries according to local regulations. Risk of fire and burns if improperly handled. Do not open, crush, heat above 60°C (140°F), or incinerate.

Battery Part Numbers

EDA5S Models

Battery Model Number	Battery Part Number
BAT-EDA5S	50177747-001



Caution: Read [Enable Airplane Mode](#) on page 10 and all cautionary markings on the battery, charging peripheral, and device using the battery before attempting to install, use, or charge the battery.

Charge the Battery Before Use

The mobile computer ships with a partially charged battery. Charge the battery with an EDA5S charging device for a minimum of **3 hours**.

Note: Using the computer while charging the battery increases the time required to reach a full charge.

About the USB Type C Connector

You can use a USB cable to charge the mobile computer from a host device (e.g., laptop or desktop computer). The connected host device must supply a minimum power output of 5V, 0.5A to the mobile computer.

Note: If the mobile computer is drawing more current than supplied by the charging source, charging will not take place.

Battery Replacement

If your battery power is low, you need to either charge the battery in the computer or replace it with a charged battery.

Replace the Battery




Caution: Improper battery replacement or incompatible device usage may result in risk of burns, fire, explosion, or other hazard. Dispose of lithium-ion batteries according to local regulations. Risk of fire and burns if improperly handled. Do not open, crush, heat above 60°C (140°F), or incinerate.


Remove the Battery

1. Press and hold the **Power** button until the options menu appears.
2. Tap **Power off**.

3. Lift the battery cover and remove it.




4. Pull up the tab on the back of the battery to lift and remove it from the computer.




Install the Battery

1. Insert the charged battery into the computer. The top of the battery must go in first to connect the pins. See [Battery Part Numbers](#) on page 5.



2. Insert the battery cover into the computer.



3. Press the **Power** button.


About the Battery Status

Use the battery icon in the Status bar at the top of the screen to see the charge level of your battery. If you want more detailed information on your battery, such as usage time or charge remaining on the battery, open the **Settings**  app and tap **Battery**.

Battery Status Icons

Icon	Status
	The battery charge is at 100%.
	The battery charge is at 50%.
	The battery charge is low. You need to charge or replace the battery soon.
	The battery is critically low. You need to replace the battery now or connect the computer to a charging accessory.
	The computer is connected to external power and the battery is charging.
	There is a battery error. Install another battery. If the problem persists, call Honeywell Technical Support.

The Battery status LED color and behavior (e.g., steady on, blinking, or off) indicates the charging status of the battery. To view status descriptions and to learn how to modify the Battery LED behavior, see [About the Battery Status LED Setting](#) on page 8.



About the Battery Status LED Setting

You can change the behavior of the Battery status LED if the out-of-box behavior for a charging battery (blinking green) is not acceptable to your environment.

You can choose one of three options:

- **Default Battery LED** (optional Android OS configuration)
- **Honeywell Battery LED** (factory default, out-of-box configuration)
- **No Battery LED**

Honeywell Battery LED Behavior (Factory Default/Out-of-Box Configuration)

Connected to Power	LED State	Description
No	Blinking amber	Battery level is below 15%
No	Off	Battery level is more than 15%

Connected to Power	LED State	Description
Yes	Steady amber	Battery level is between 0% and 60%
Yes	Blinking green	Battery level is between 60% and 95%
Yes	Steady green	Battery level is above 95%
Either	Blinking red	Battery error

Default Battery LED Behavior (Optional Android OS Configuration)

Connected to Power	LED State	Description
No	Blinking red	Battery level is below 15%
No	Off	Battery level is 15% or more
Yes	Steady red	Battery level is below 15%
Yes	Steady amber	Battery level is between 15% and 90%
Yes	Steady green	Battery level is 90% or more

Select the No Battery LED setting if you want to use the LED as a notification LED for applications or device management solutions. For more information on how to use the LED as a notification LED, see <http://developer.android.com/guide/topics/ui/notifiers/notifications.html>.

Change the Battery Status LED Behavior

To change the battery status LED behavior:

1. Swipe up from the bottom of the Home screen to access all apps.
2. Tap **Settings**  > **Honeywell Settings** > **Battery LED**.
3. Choose one of the options:
 - **Default Battery LED** (optional Android OS configuration)
 - **Honeywell Battery LED** (factory default/out-of-box configuration)
 - **No Battery LED** (disable the battery LED)

Check the Battery Level and Usage

In addition to the Battery status icon and LED, you can monitor the battery status from the Settings app.

1. Swipe up from the bottom of the Home screen to access all apps.
2. Tap **Settings**  > **Battery**.

The current percentage of battery power remaining and the amount of usage time left on the battery appears on the screen when the computer is not connected to an external power supply. When connected to an external power source, battery charge information is provided. A list shows the battery usage

for individual apps and services. For usage details, select one of the apps or services in the list. You can also access the Battery saver feature from the battery screen.

About Battery Life and Conservation

It is important to remember that the battery slowly discharges when stored over a long period of time even when the computer is turned off or the battery is stored outside the computer. Use the reference table below to learn about how to conserve battery power.

When you want to:	Do this to save battery power:
Use the computer but the low battery status icon appears or the battery light turns on.	Do one of the following: - Connect the computer to a charging accessory. Replace the Battery (see page 5).
Stop using the computer for 5 minutes or more.	Make sure that the low battery status icon is not on the screen and that the battery status LED is not on. Press and release the Power button to suspend the computer.
Store the computer for more than a day.	- If you are storing the computer for a few days (such as over the weekend), install a fully charged battery or connect the computer to a power source. - If you are storing the computer for a longer period of time, remove and charge the battery. When the battery is done charging, store both the battery and the computer in a cool location. - If you store the battery for several months, recharge the battery periodically to keep it at peak performance.
Store the battery outside of the computer.	Store battery in charger or periodically recharge it to keep it at peak performance.

Enable Airplane Mode

If you do not need to connect to any wireless networks, you can enable Airplane mode to turn off the radios and save battery power.

1. Swipe up from the bottom of the Home screen to access all apps.
2. Tap **Settings**  > **Network & internet**.
3. Tap the toggle button next to **Airplane mode**. An airplane icon appears in the status bar to indicate Airplane mode is turned on.

Battery Recommendations and Safety Precautions



Caution: Improper battery replacement or incompatible device usage may result in risk of burns, fire, explosion, or other hazard. Dispose of lithium-ion batteries according to local regulations. Risk of fire and burns if improperly handled. Do not open, crush, heat above 60°C (140°F), or incinerate.

- For maximum battery life, charge the battery at 20 °C (68 °F) to 25 °C (77 °F) and store at 20 °C (68°F) with a 30%-50% charge.
- Do not store the battery at temperatures above 60 °C (140 °F). Storage above 60 °C (140 °F) may damage the battery.
- Charge the battery before use. Battery ships with only a partial charge.
- See [Charge the Battery Before Use](#) on page 5 for approved charging methods. Use of this battery in other devices could result in damage to the device or battery.
- Avoid dropping the battery or computer. If you suspect that the battery or computer is damaged, send it to Honeywell service center for inspection.
- Replace the battery only with another BAT-EDA5S model battery that matches the part number noted in the [Battery Part Numbers](#) (see page 5) section of this guide. These batteries have been tested in accordance with applicable safety standards. Contact your Honeywell sales representative or distributor if this battery is no longer available.
- Discarded batteries may create a safety hazard. Before disposal, cover the battery contacts with electrical insulating tape.
- Do not modify the battery or attempt to insert foreign objects into it.
- Do not solder directly to the battery contacts.
- Do not drop the battery or apply mechanical shocks or pressure to it.
- Do not immerse batteries into, or expose them to, water or seawater.
- Do not incinerate, microwave, throw into a fire, or expose batteries to temperatures above the maximum rating.
- Do not disassemble a battery or try to open or penetrate its housing.

Power On the Computer

After you have fully charged and installed a battery, power on the computer for the first time:

- Press and hold the **Power** button for approximately 3 seconds, and then release the button.

Welcome Screen

The first time you power on the computer, a Welcome screen appears. You can either scan a configuration barcode or use the Wizard to manually set up the computer. To learn more about how to [Scan Barcodes](#), see [page 41](#).

During the manual setup process, follow the prompts on the screen as the wizard has you:

- Set the default language.
- Set up the Wi-Fi network connections.
- Set the time, date, and time zone.
- Personalize (name) the computer.
- Set up security and privacy options.

Once you complete the initial setup, the Welcome screen no longer appears when you power on the computer and **Provisioning mode** is automatically turned Off (disabled). Scanning a barcode to install applications, certificates, configuration files, and licenses on the computer is restricted when **Provisioning mode** is turned Off. To learn more [About Provisioning Mode](#) see [page 71](#).

Unlock the Screen

The screen lock automatically activates every time the computer is turned On or when the computer wakes from Screen Timeout mode (sleep mode).

- Swipe up from the bottom of screen to open.

The level of security provided depends on the type of lock set (e.g., Swipe, Pattern, PIN, or Password). The default setting (Swipe) provides no protection against unauthorized access to your computer.

Change the Screen Lock to Protect the Computer

After you start using the computer, you should change the screen lock to prevent unauthorized persons from accessing the computer after the screen lock activates, unless they input the correct password, pin, or pattern.

The recommended setting for the Screen Lock is to enable a Password lock. Use a strong password value (e.g., include numbers, characters, special characters, and mixed character case).

1. Swipe up from the bottom of the Home screen to access all apps.
2. Tap **Settings**  > **Security** > **Screen lock**.

3. Choose one of the following options:
 - **None**
 - **Swipe**
 - **Pattern**
 - **PIN**
 - **Password**
4. Follow the on-screen prompts to complete the setup.
5. Exit the Settings app.


Configure the Screen Backlight

The display has an ambient light sensor that automatically adjusts the backlight intensity to conserve power and ensure the display is readable. You can also manually set the backlight intensity if you do not want to use the automated adaptive brightness feature.

1. Swipe up from the bottom of the Home screen to access all apps.
2. Tap **Settings** > **Display**.
3. Choose one of the following options:
 - To have the computer automatically adjust the brightness for your work environment, turn On the **Adaptive brightness** setting. You can tap **Adaptive brightness** to toggle the feature On or Off.
 - To set the brightness level manually, verify the Adaptive brightness feature is turned Off, and tap **Brightness level**. Adjust the slider to set the brightness level.

About the Good Read LED

The Scan Status LED indicates the read status of the imager when scanning a barcode. When active, the LED illuminates below the front speaker. To learn more about how to use and configure the imager for scanning, see [Chapter 3: Use the Imager](#) beginning on page 31.



Good Read LED Descriptions

LED Color	Description
Green	Good read of a barcode.
Blinking green	The data collection imager is processing or starting up.
Red	Failure to scan barcode. Check to make sure you have the correct symbology enabled.

About the Audio Features

The EDA5S has multiple speakers, three microphones, and several software settings to configure sound volume or enable vibration feedback.

Adjust Speaker Volume

Use the Volume buttons on the left side of the computer to adjust the volume of ringtones, media, notifications, and alarms.

Note: *The volume setting varies by OS version.*

To quickly change the active speaker volume level:

- Press the top of the Volume button (+) to raise the volume of the active speaker.
- Press the bottom of the Volume button (-) to lower the volume of the active speaker.

To access the volume quick set menu:

1. Press the Volume button.
2. Adjust the volume level using the on-screen menu.
 - Tap the icon at the top to toggle the media volume between Sound On  , Vibrate Only  , or Silent  .

- Use the slider to adjust the media volume.
- Tap  to turn toggle media volume off.
- Select  at the bottom to adjust Media, Call, Ring, or Alarm volume levels.

Enable Vibrate Mode

Simultaneously press the **Volume up (+)** and **Power** button to quickly enable Vibrate mode so the computer vibrates instead of emitting sound for notifications and rings.

If you need quiet time without interruptions, enable Do Not Disturb to mute sound, stop vibration, and block notifications. Under the full settings menu, you can set a schedule for when you want Do Not Disturb to automatically turn on and off.

To enable Do Not Disturb manually:

1. Swipe down from the top of the screen to view quick set menu.
2. Tap the **Do Not Disturb** icon  to toggle feature On/Off.

Audio Settings

This section describes the audio and sound settings you can configure in the Settings app.

- To change audio settings, open the **Settings**  app and then tap **Sound**.

Sound Settings

Setting	Description
Media volume	Use the sliders to set the volume for media (e.g., music, videos, and games), calls, alarms and rings (notifications and ringtones).
Call volume	
Ring & notification volume	
Alarm volume	
Vibrate for calls	Select to enable vibrate mode when the phone is ringing.
Do not disturb	Select to set which notifications to let through when you have Do Not Disturb turned On and when you want to be left alone.
Shortcut to prevent ringing	Set what happens when you simultaneously press the Power and Volume up button. Options include: Vibrate, Mute or turn the shortcut Off.
Phone ringtone	Select a default ringtone.
Advanced	
Default notification sound	Select a notification sound.
Default alarm sound	Select an alarm sound.


Setting	Description
Other sounds and Vibrations	Turn sounds On or Off for: • Dial pad tones • Screen locking sounds • Charging sounds and vibration • Touch sounds • Touch vibration

Insert a microSD Card

You can use a microSD card to increase file storage capacity or to install software. Honeywell recommends the use of Single Level Cell (SLC) industrial grade microSD or microSDHC memory cards with the computer for maximum performance and durability.


Note: *Format the memory card before initial use.*

1. Save your files and close any open applications.
2. Press and hold the **Power** button until the options menu appears.
3. Tap **Power Off**.
4. Remove the battery from the computer, refer to [page 5](#).
5. Slide the card holder tray out of the slot.



6. Insert the microSD card into the card holder tray with the contacts facing down.

Note: *For WWAN models, the card holder tray has a microSD card slot and a nanoSIM card slot. WLAN models only have a microSD card slot.*



7. Slide the card holder tray back into the slot.
8. Install the battery. Refer to [page 7](#).

How to Transfer Files

To transfer files you can physically connect the mobile computer to your workstation (e.g., laptop or desktop computer) through a USB connection. When the mobile computer is connected and USB is configured for file or photo transfer, use a file browser (e.g., Windows® File Explorer) on your workstation to transfer files between the two computers. If you are transferring files to and from a Mac, use the Android File Transfer application (available from www.android.com/filetransfer).

Note: File transfer through a USB connection is disabled by default. You need to configure the USB connection for transferring files or photos.

You can use these accessories to connect your mobile computer to your workstation:

- A standard USB communication cable with Type C connector.

Configure USB Connection and Transfer Files

Note: The EDA5S supports Hi-Speed USB communications (USB 2.0) with theoretical maximum data transfer rate of 480Mbps. USB on-the-go (OTG) supported.

1. Connect the mobile computer to your workstation.
2. On the mobile computer, swipe down from the top of the screen to see the notifications.
3. Tap the **Android System** notification twice to open the options menu. You may need to scroll down to the bottom of your notifications to find it.

4. Select either **File Transfer** or **PTP** (picture transfer protocol).
5. Open the file browser on your workstation.
6. Browse to the mobile computer. You can now copy, delete, or move files between the EDA5S and your workstation.

Accessories for the Computer

The EDA5S ships with a partially discharged battery. All other accessories are ordered and shipped separately.

For a complete list of compatible accessories for your mobile computer and their part numbers see the *EDA5S Accessory Guide* available for download at www.honeywellaidc.com.

Contact your local sales representative for ordering information.


Accessory	Description
Single Charging Dock (EDA50-HB-R)	Charging cradle for charging ScanPal EDA5S (Compatible with EDA51 scan handle when used with Backwards Adapter: EDA52-ADC). Does not include charging cable; cable and power adapter plugs must be ordered separately.
Single Charging Dock (EDA52-HB-1, EDA52-HB-2, EDA52-HB-3, EDA52-HB-5)	Charging cradle for charging ScanPal EDA5S mobile computer and battery (Compatible with EDA5S scan handle).
Quad Battery Charger (EDA52-QBC-1, EDA52-QBC-2, EDA52-QBC-3, EDA52-QBC-5)	Quad battery charger for charging ScanPal EDA5S batteries. Kit contains power supply and power cord.
Quad Bay Charging Base (EDA50-CB-1, EDA50-CB-2, EDA50-CB-3)	Quad bay charging base for ScanPal EDA5S. Kit contains power supply and power cord. (Compatible with EDA51 scan handle).
Wrist strap (EDA5S-WS-10PK)	Wrist strap attaches to EDA5S mobile computer.
Screen film (EDA52-SP-10PK)	Screen film for EDA5S mobile computer.
Backwards adapter (EDA52-ADC)	Backwards adapter (2pin cup) to work with EDA50/51 accessories.
Power Adapter and Plugs (50130570-001)	Power adapter and plugs for ScanPal EDA50/EDA50hc/EDA50K/EDA51/EDA52/EDA5S. Includes US, EU, UK, and India plugs.

ABOUT THE USER INTERFACE AND APPLICATIONS

Use this chapter to learn about the user interface and how to interact with the screen. You can also use this chapter to learn about the Honeywell applications on the computer.

About the User Interface

The Android operating system provides a touch-friendly and easy-to-navigate user interface. When you turn on the mobile computer, the Home screen is the first screen that appears after language provisioning and the startup wizard is complete.



—— Notification /Status Bar

—— Home Screen Panel

—— Favorites Tray

—— Search Bar

—— Virtual Navigation Buttons

Home Screen Features

Item	Description
Notifications panel / Status bar	Status icons to the left tell you when an app has sent notifications, such as an arriving message. System icons to the right display the current wireless and network connection state and battery level.
Search bar	Search the Internet or the computer using Google™. Tap the microphone icon in the search box to initiate a voice search or command.
Home Screen Panel	You can create more than one custom Home screen panel. Swipe left or right on the Home screen to switch between your custom panels.
Favorites tray	App icons in the customizable tray are visible on all Home screen panels.



Navigation and Function Buttons

Your mobile computer has virtual buttons on the front panel below the Favorites tray and hardware buttons located on the sides for easy navigation and quick feature access when using the computer.

For button locations, see [Mobile Computer Features](#) on page 3.

To learn how to [Remap a Button](#), see [page 21](#).

Navigation and Function Button

Button	Description	
	Back	Tap to return to the previous screen.
	Home	Tap to return to the Home screen.
	Recent Apps	Tap to view and switch between recently used apps. The Screenshot button also appears when selected.
	Volume	Press the top of the Volume button to raise the speaker volume. Press the bottom of Volume button to lower the speaker volume.
	Scan	Press the right or left Scan button to trigger the scanner.
	Power	Press and release the Power button to activate or exit Screen Timeout mode (see page 55). Press and hold the button for approximately 3 seconds, and then release to view the options menu. • Power off (see page 11) • Restart • Emergency Perform a manual restart if touchscreen is unresponsive (see page 77).

Remap a Button

You can change the default function of the Left Scan, Right Scan, Volume Up and Volume Down buttons.

1. Swipe up from the bottom of the Home screen to access all apps.
2. Tap **Settings**  > **Honeywell Settings** > **Keyremap**.
3. Tap the plus sign (+).
4. Press the button you want to remap or select one of the virtual buttons.
5. Tap **OK**.
6. Select one of the following options:
 - Tap **Keys** to view available functions. Select the function you want assigned to the button.
 - Tap **Apps** to view available applications. Select the application you want assigned to the button.
 - Tap **Actions** to enter an Intent or Broadcast. Tap **OK** to assign the action to the button. For example, to start an Intent, type `com.android.settings/com.android.settings.wifi.WifiSettings`.
 - Tap **Command** to enter a command that will be executed when the button is pressed. This option supports all ADB shell commands. For example, if you choose a button to remap and enter the command “input keyevent 64”, pressing the selected button will open the web browser on the device.
 - Tap **Text** to type characters to display when the remapped key is pressed. Use a comma “,” to separate the characters. Tap **OK** to assign the text to the button. Examples are listed below:

Input Text	Button Press
A,A,B	aab
SHIFT_LEFT,A,SHIFT_LEFT,B or CAPS_LOCK,A,CAPS_LOCK,B	AB
SHIFT_LEFT,1	!
CTRL_LEFT,A	(Select All)
VOLUME_UP	(Volume Up)

Note: Lower case text is not supported in the **Text** field. Text must be entered in upper case. For example, “H,e,l,l,o” will display as “h”, whereas “H.E.L.L.O” will display as “hello”.

7. Tap **Keys** or **Applications** to view the available functions.
8. The function you selected now appears next to the button name.

Restore Default Button Action

To restore the button default action:

1. Swipe up from the bottom of the Home screen to access all apps.
2. Tap **Settings**  > **Honeywell Settings** > **Key Remap**.
3. Tap the clean icon .
4. Choose the remapped button(s) you want restored to the default setting.
 - Tap the check box next to the button.
- OR
- Tap **All Select** to choose all the buttons.
5. Tap **Delete**.

About Status Bar Icons

Status and notification icons show you the current status of your network, the battery, notifications, and sounds. Use the table below to understand some of the most common icons.

Status and Notification Icons

Icon	Description	Icon	Description
	Pending alarm and Alarm is set.		Vibrate mode is turned on.
	New text message or multimedia message.		Airplane mode is turned on.
	Error with text or multimedia message delivery.		Bluetooth is turned on.
	New email		SD card is full.
	Computer is connected to a PC with a USB cable.		Wi-Fi network connected with full signal strength.
	Synchronizing data.		Wi-Fi network connected but no signal strength.
	Error with sync or sign-in.		Phone connected with full amount of bars.
	Computer is connected with Ethernet.		Phone connected with full amount of bars but no Internet connection.

View and Manage Notifications

You can view recent events on the computer, manage system notifications, change a setting or quickly respond to an app notification by opening the notifications panel.

When a notification icon appears in the status bar at the top of the screen:

1. Swipe down from the top of the screen to open the notifications panel.
2. Respond to the notification. You can take one of the following actions:
 - Tap the notification to open the associated app.
 - Tap a quick-reply or action command (e.g., Reply, Archive) if available.
 - Swipe the notification sideways, off the screen to dismiss it. Note that some notifications cannot be dismissed.
 - Slide the notification left or right to reveal the settings icon . Choose between **Stop notifications** or **Keep showing**.

To close the notification panel, swipe up from the bottom of the screen, or tap the **Back** or **Home** buttons.

Open Quick Settings

Use the Quick Settings screen to quickly access common settings. Tap an icon to toggle the feature On/Off or to open additional settings.

- To open Quick Settings swipe down once from the top of the screen. The most common settings are at the top of the screen. Swipe down again to expand Quick Settings. Once expanded, you can swipe right to left to view additional settings.
- To close Quick Settings, swipe up on the screen.

Customize the Home Screen

You can add application icons to any Home screen for easier access.

1. Swipe up from the bottom of the Home screen to access all apps.
2. Tap and hold the app you want to add, and then move it slightly. The computer switches to a smaller view of the Home screen panels.
3. Drag and drop the app icon into place.
 - If you want to add another home screen, drag the icon to the right edge of the screen before releasing the icon.
 - If you want to create a folder, drag and drop the icon on top of another icon.

To add widgets or customize the look of the Home screen:

1. Tap and hold an empty section of the Home screen.
2. Select either **Wallpapers**, **Widgets**, or **Home Settings**.

Customize the Favorites Tray

Modify the Favorites tray to contain the apps you use the most.

1. Tap and hold the app you want to replace on the Favorites tray, and then move it slightly.
2. Drag and drop the app on “**X Remove**” at the top of the screen if you want to discard it or simply move it out of the favorites tray to an empty section on the Home screen.
3. Swipe up from the bottom of the screen to access all apps.
4. Tap and hold the icon of the app you want to add, and then move it slightly.
5. Drag and drop the icon into position on the Favorites tray.

Use Google™ Search

Use the Google Search field on the Home screen to help you find anything you need on the computer or on the web.

1. On the Home screen, tap inside the Google Search box and begin to type your search term.

As you type, suggestions from Google web search appear below the Search box, and results from the computer (such as apps or contacts) appear below the web search results.

2. Tap a suggestion to search for it immediately, or tap the arrow to add the term to the search field without starting to search.

About Screen Gestures

Use your fingers or the stylus to manipulate icons, buttons, menus, the on-screen keyboard, and other items on the screen.

- **Tap**

Tap to select something, toggle a setting on or off, or activate a field for text entry. An on-screen keyboard automatically appears for text entry.

- **Tap and hold**

Tap and hold an item but do not lift your finger or stylus until an action occurs.

- **Drag and drop**

Tap and hold an item, and then slide your stylus or finger across the screen until you reach the target position. Lift your finger or stylus off the screen to drop the item in place.

- **Swipe**

Quickly move your finger across the screen, without pausing when you first touch the screen. For example, you can swipe a Home screen left or right to view the other Home screens.

- **Slide**

Slowly move your finger across the screen, without pausing when you first touch the screen. For example, you can slide a notification to the left until the Settings gear is revealed.

- **Double-tap**

Tap quickly twice on a web page, map, or other screen to zoom in. Double-tap again to zoom out.

- **Pinch**

In some apps, you can zoom in and out by placing two fingers on the screen at once and pinching them together (to zoom out) or spreading them apart (to zoom in).

Set the Time Zone

The computer gets the current date and time from its network connection. If preferred, you can change this behavior and manually set the time zone for your location.

1. Swipe up from the bottom of the Home screen to access all apps.
2. Tap **Settings**  > **System** > **Date & time**.
3. To change the time, tap **Use network-provided time** to turn off the feature.
 - a. Tap **Date** then select a date from the calendar and click **OK**.
 - b. Tap **Time** then use the clock to select a new time and click **OK**.
4. To change the time zone, tap **Use network-provided time zone** to turn off the feature.
 - a. Tap **Time zone** and choose the time zone for your location.
 - b. Press the back arrow to return to the Date & time screen.
5. The Time Format defaults to **Use locale default**. Tap **Use 24-hour format** to change the time display.

About Honeywell Applications

Honeywell applications help you troubleshoot and connect your computer to other devices and networks. Some of the applications in this table are located in the Power Tools app. To learn more about Honeywell Power Tools, go to www.honeywellaidc.com to download the *Power Tools User Guide*.

Honeywell Applications Available on the Computer

Icon	Application	Description
	AutoInstall Settings	Enable the AutoInstall feature, to automatically install *.zip or *.apk files containing applications saved in the Internal shared storage\honeywell\autoinstall folder and IPSM card\honeywell\autoinstall folder on the computer during the power-up boot or reboot process.
	Demos	Honeywell Demo apps demonstrate the basic capabilities of the computer and are not intended as functional business solutions. The demos included, demonstrate scanning, signature capture, NFC functionality, and printing via Bluetooth technology. Information on how to create custom applications for your Honeywell mobile computer can be found in the Honeywell Software Development Kit (SDK) for Android, available from the Technical Support Downloads Portal .
	Enterprise Settings	Enterprise Settings can help customers achieve some common customized needs. Support UI interface, SDK and Broadcast way. Scan Settings • Scan result broadcast action • Scan result broadcast key • Scan button key down broadcast • Scan button key up broadcast General Settings • Function Control • Function Restriction • Custom bootanimation • Grant/Revoke runtime permissions • Set default launcher
	HUpgrader	Use to the HUpgrader app to view the current OTA version on the computer, check for updates, or initiate an OTA upgrade from storage.
	HQ Config	HQConfig is used for offline rapid deployment. Synchronize content: common settings, scan settings, applications and firmware upgrades.

Icon	Application	Description
	HonRfid	When the EDA5S is connected to a Honeywell RFID product, the HonRfid app is used to demonstrate the functions of Honeywell RFID products (e.g., inventory, RFID tag reading, writing and locking, power adjustment, frequency adjustment, etc.)
Power Tools		
	BattMon	BattMon provides information on the charge status and health of the battery, and provides access to activate battery status notifications and battery charging history logs.
	ConfigApps	The ConfigApps Power Tool gives you the ability to enable or disable apps installed on the computer and to uninstall app updates that may be causing storage or performance issues. You can also view the total number of apps on the computer and the total number of apps currently disabled.
	Configure Autorun	Configure Autorun provides the ability to set applications to automatically run after a reboot.
	Diagnostic Information	Diagnostic Information provides access to system statistics, notifications and version information about the computer.
	EZConfig	EZConfig supports advanced customization and configuration of the hand held computer. EZConfig includes a standard XML editor and configuration barcode scanner feature.
	WiFi Diagnostic	Use application to: • View Wi-Fi radio status information about a connected access point or a list of other available access points in range of the Wi-Fi radio. • Use the Route utility to view packet destination gateway information across the subnets. • Use the IPConfig utility to view IP parameters for the on-board network adapters. • Use the Ping utility to verify communication links or to make sure a specific IP address is working.
	Wireless Tether	Use to enable range tracking and customize out-of-range alerts for Bluetooth devices paired and tethered to your hand held computer.

Applications You Can Download to the Mobile Computer

You can download Honeywell applications to extend the capabilities of the computer. You may need to purchase a license to run some applications. To learn more about the applications described in this section and other Honeywell software solutions, go to www.honeywellaidc.com > **Products** > **Software**.

About Honeywell Enterprise Browser

Enterprise Browser for Microsoft® Internet Explorer® is a locked-down enterprise Web client application designed for Honeywell computers. It provides a controlled Web application environment that helps enterprises increase productivity and reduce IT management expenses. You can configure Enterprise Browser for your specific application requirements and design custom web applications that run through the Enterprise Browser to provide your users with an easy-to-use yet controlled experience.

If Enterprise Browser is not included on your computer model, you can download a trial version for evaluation. After the evaluation period expires, you need to purchase a license. For more information about Enterprise Browser, visit www.honeywellaidc.com.

About Terminal Emulators

Honeywell offers several terminal emulator solutions that allow users to manage their mobile devices by providing reliable data transfer between the host mobile device and terminal. Terminal emulators can be used for remote management and configuration of devices, data collection and analysis, and session management.

Depending on the computer model, a terminal emulator may come preinstalled on the device. If a terminal emulator is not included on your model, you can download a trial version for evaluation. After the evaluation period expires, you need to purchase a license. For more information, visit www.honeywellaidc.com.

About Honeywell Launcher

Launcher is a configurable locked-down menu program designed for Honeywell computers that prevents end-users from accessing the start menu and other non-authorized applications. Use Launcher to provide a platform where your mobile computer users are limited to running only company-approved applications and prevent them from initiating unauthorized configuration changes. You can also use Honeywell Launcher together with Honeywell Enterprise Browser to create a single-purpose device configuration.

If Launcher is not included on your computer model, you can download a trial version of the software for evaluation. After the evaluation period expires, you need to purchase a license. For more information about Launcher, visit www.honeywellaidc.com.

Unlock Developer Options

Developer options only appear in the Settings app if you unlock the feature. If you are a developer working with the computer, you can easily unlock the additional settings to use for testing and debugging applications under development for the computer.

1. Swipe up from the bottom of the Home screen to access all apps.
2. Tap **Settings**  > **About phone**.
3. Tap **Build number** seven times. A message appears informing you that you are now a developer.
4. Open **Settings** > **System** and scroll to the bottom of the list.
5. Tap **Advanced**.
6. Tap **Developer options**.

USE THE IMAGER

Use this chapter to understand how to scan barcodes, configure the scan settings, and capture images using the integrated image engine in the computer.

About the Imager

The EDA5S mobile computer features the following Honeywell high-performance imager:

- S0703 Imager

You can use the imager in the computer as a scanner or camera.

Use the imager as a scanner to read 1D and 2D barcode symbologies, composite symbologies, and postal codes. It also supports omni-directional scanning for greater flexibility in real-world settings. By default, the scanner feature is enabled and uses the default scan profile. You can modify the **Default Profile** or create new

profiles for custom applications from **Settings**  **Honeywell Settings** > **Scanning**.

Use the imager as a camera to capture black and white images, such as signatures or pictures of damaged inventory.

Note: *Instead of using the internal imager, you can also use Bluetooth communications to connect the computer to an external scanner, such as the Granit™ 1990i and 1991i.*

About the Scan Wedge Feature

The scan wedge feature sends scanned barcode data to an active application as Android keypad input. To scan a barcode as keyboard input, open an application that accepts text input and then scan a barcode. You can use applications that are coded to use the scanner or applications that receive data through the scan wedge feature. If an application claims the scanner through the BarcodeReader API, the scan wedge feature is temporarily disabled.

You can find information on how to create custom applications for the computer in the *Software Development Kit (SDK)* available for download from the *Technical Support Downloads Portal* at <https://hsmftp.honeywell.com>. Once you create an account and enter the portal, navigate to **Software > Software and Tools > Developer Library > SDKs for Android**.

Change the Scanner Settings

Changes you make to the Default profile apply to all applications with no profile assigned.

1. Swipe up from the bottom of the Home screen to access all apps.
2. Tap **Settings**  > **Honeywell Settings** > **Scanning**.
3. Tap **Internal Scanner** > **Default profile**.
4. Select from the following:
 - **Data Processing Settings**,
 - **Symbology Settings**,
 - **Decode Settings**,
 - **Imager Settings**,
 - **Trigger Settings**, or
 - **Notification Settings**.
5. Modify the settings to meet your application needs.

To learn more about the scanner settings, [Default Scan Settings](#) on page 33.

Change the Bluetooth Scanner Settings

When the Bluetooth scanner is paired, changes can be made to the Default profile for the scanner.

1. Swipe up from the bottom of the Home screen to access all apps.
2. Tap **Settings**  > **Honeywell Settings** > **Scanning**.
3. Tap **Bluetooth Scanner** > **Default Profile** > **Data Processing Settings**.
4. Modify the settings to meet your application needs.

To learn more about the scanner settings, see [Data Processing Settings](#) on page 33.

Restore Default Scan Settings

You can easily discard all changes you made to the Default profile and restore the default values.

Note: When you choose the *Restore all defaults* option from a settings screen in a profile, all the settings in that profile return to their default values.

1. Open the **Default profile**.
2. Tap  in the upper right corner of any of the scan settings screens for the profile.
3. Tap **Restore all defaults**.

Default Scan Settings

Use the following sections to understand the scan settings available for scanner profiles. To learn how to create a new profile, see page [39](#).

Data Processing Settings

Use the Data Processing Settings to specify how barcode data is processed by the computer.

Data Processing Settings

Setting	Description	Default										
Wedge	Enable or Disable the scan wedge feature.	Enabled										
Wedge Method	Specify wedge method: Standard or Keyboard	Standard										
Charset	Select the character set to use when interpreting the barcode data into a string.	ISO-8859-1										
Prefix	Defines the string added before the decoded barcode data. Substitutions occur within the Prefix string values. <table><tr><th>Substring</th><th>Replacement Character Code</th></tr><tr><td>\r</td><td>13</td></tr><tr><td>\n</td><td>10</td></tr><tr><td>\t</td><td>9</td></tr><tr><td>\\</td><td>\'</td></tr></table>	Substring	Replacement Character Code	\r	13	\n	10	\t	9	\\	\'	None
Substring	Replacement Character Code											
\r	13											
\n	10											
\t	9											
\\	\'											

Setting	Description	Default										
Suffix	Defines the string added after the decoded barcode data. Substitutions occur within the Suffix string values.	None										
	<table><tr><th>Substring</th><th>Replacement Character Code</th></tr><tr><td>\r</td><td>13</td></tr><tr><td>\n</td><td>10</td></tr><tr><td>\t</td><td>9</td></tr><tr><td>\\</td><td>'\'</td></tr></table>		Substring	Replacement Character Code	\r	13	\n	10	\t	9	\\	'\'
	Substring		Replacement Character Code									
	\r		13									
	\n		10									
	\t		9									
\\	'\'											
Wedge as Keys	List of character values to wedge as keys, represented as a comma-separated list of decimal values.	9,10,13										
Data Editing Plugin	Specify a Total Freedom data editing plug-in and edit plug-in settings.	None										
Symbology Prefix	Specify a symbology identifier prefix to the barcode data. Options include: - None - Honeywell - AIM	None										
Launch Browser	Enable or disable URL barcode handling. If a barcode starts with http:// or https://, the browser opens using the barcode data as a URL. Corresponds to BarcodeReader property: PROPERTY_DATA_PROCESSOR_LAUNCH-BROWSER	Enabled										
Scan to Intent	Enable or disable special handling of scan-to-intent barcodes. Applies to barcodes in one of the following formats: '/' ACTION '/' ACTION '\$' extra-data Where: ACTION and extra-data are any string of characters. Launches an application listening for the intent. Intent action: "com.honeywell.scantointent.intent.action." + ACTION Intent extra: "com.honeywell.scantointent.intent.extra.DATA" contains the remainder of the barcode data after the first '\$' character. Corresponds to BarcodeReader property: PROPERTY_DATA_PROCESSOR_SCAN_TO_INTENT	Enabled										
Launch EZConfig	Enable or disable special handling of EZConfig barcodes. Applies to EZConfig barcodes that are encoded with the Aztec symbology and contain specific header data. Corresponds to BarcodeReader property: PROPERTY_DATA_PROCESSOR_LAUNCH_EZ_CONFIG	Enabled										

Setting	Description	Default
Data Intent	Enables the reception and processing of barcode data without using an SDK or library.	Disabled

Symbology Settings

Use the Symbology Settings to enable or disable barcode symbologies for the selected scan setting profile.

- Tap the check box next to a symbology name to enable (check mark) or disable (no check mark) decoding for that symbology.
- Tap the symbology name to view and modify additional configuration parameters for the symbology selected.

To view a list of default settings for supported symbologies, see [page 82](#).

Decode Settings

Adjust the Decode Settings when scanning barcodes that are densely packed or poor quality.

Decode Settings

Setting	Description	Default
Center Decode	When enabled, the imager scans and decodes a barcode only if part of the barcode is at the center of the aimer window. This is useful in situations where several barcodes may be very close together in the imager field-of-view. • Tap the check box to toggle the feature On or Off. • Select Center Decode to adjust the feature parameters. Honeywell recommends leaving the window size settings at 50 (default) to define the “center” area for the barcode. Configurable parameters: • Center Decode Timeout (ms) • Window top • Window bottom • Window left • Window Right	Disabled
Decode Security	Use this setting to control the reading tolerance of the decoder. Lower settings are more lenient when reading low quality barcodes while higher values are more strict.	2
Decoder timeout	Set the amount of time in milliseconds that the scanner will timeout if a readable barcode is not found.	150

Setting	Description	Default
Decode Filter	Use these settings to modify or reject data strings. - Decode filter script The Decode Filter Script is used to configure a filter for decode results during scanning. For example, a filter could be used to reject barcodes that don't begin with certain characters, remove leading characters (like "00") from the beginning of a barcode, or only scan barcodes that begin with certain characters. - Decode filter timeout (ms) The decode filter timeout option can be used to disable the logic inside the filter script after a given amount of time. - Debug level Set the filter information level. The default level is 0, no information. Higher levels emit more information. Level 4 emits the most information.	none
Poor Quality 1D Reading	Enable this setting when scanning damaged or badly printed 1-D barcodes to improve barcode read success.	Disabled
Video mode	Use this setting to specify whether normal or inverse decoding for linear symbologies is enabled during the execution of Decode. By default normal video is enabled. Options include: - Normal - Inverse - Normal and Inverse	Normal
DPM mode	Use this setting when scanning Direct Part Marking (DPM) barcodes that are etched or imprinted directly into the surfaces of materials including metal and plastic. Options include: - No DPM optimization - Dotpeen DPM decoding - Reflective DPM decoding	No optimization

Setting	Description	Default
Region of Interest	Set the ROI for decoding. Options include: • Disable ROI is disabled and the entire original image is sent to the decoder. • Standard Use the aimer position to weight activity. Activity calculated on the row and the column in the middle of each cell. The ROI window may not include the aimer. • Standard, aimer centered Activity calculated on the row and the column in the middle of each cell. The ROI window will always include the aimer. • DPM, aimer centered Activity calculated on 4 rows and 2 columns in each cell. The ROI window will always include the aimer. • Kiosk/presentation application Ignore aimer position, no weight activity. Activity calculated on the row and the column in the middle of each cell. The ROI window may not include the aimer. • Learning Engine When selected, the computer will receive continuous updates to improve the decoder software based on your specific environment. The Staging Hub Agent must also be enabled.	Disabled
Multicode Scan	When you enable Multicode Scan, each barcode is checked to see whether it satisfies the defined multicode rules before the results are transmitted. Options include: • Enable or disable multicode scanning. • Set the number of barcodes. • Specify a separator to be used between barcodes. • Define up to 10 barcodes to be included in the multicode. • Set a timeout in milliseconds. If set with a non-zero value, the timeout starts after the scan button is pressed. Once the timeout occurs, scanning will return to standard (single) barcode mode. • Enable or disable the transmission of an incomplete multicode. When enabled, the incomplete multicode is transmitted when the incomplete transmission timeout expires. • Set a timeout in milliseconds to use when incomplete transmission is enabled. If set with a non-zero value, the timeout starts after the scan button is pressed. Once the timeout occurs, the results that were collected before the timeout happened will be transmitted if they satisfy the defined multicode rules.	Disabled

Setting	Description	Default
Preferred Symbology Settings	Use this setting to establish which barcode has priority if more than one barcode appears on the same label. - Tap the check box to toggle the feature On or Off. - Select Preferred Symbology Settings to adjust the feature parameters. Options include: Preferred Timeout (ms) The length of time the scanner will ignore a low priority barcode while it searches for a high priority barcode. If a high priority symbology is located during this period, then that data is read immediately. If the time-out period expires before a high priority symbology is read, the scanner will read any barcode in its view. The default is 500ms. Symbology Set the priority level (High or Low) for symbology codes. This is used when you want to specify one symbology as a higher priority over other symbologies in situations where both barcode symbologies appear on the same label, but the lower priority symbology cannot be disabled. If a code is set as a High Priority, the decode of that symbology is accepted immediately. If a code is set as a Low Priority, the decode is buffered to see if a decode of a preferred High Priority symbology can be found within a given timeout period.	Disabled

Imager Settings

You should not need to modify the Imager Settings. The **Override Recommended Values** setting is disabled by default. The recommended Imager Settings are designed to work in a wide range of environments and should only be modified if you have an advanced understanding of imagers.

Trigger Settings

Use the Trigger Settings to configure how the scan buttons work.

Trigger Settings

Setting	Description	Default
Enable Scan Trigger	Enable or Disable activating the imager by pressing the side scan buttons or the virtual Scan button in the Scan Demo app.	Enabled
Scan delay	Set the minimum amount of time in seconds before the scanner can read another barcode.	0
Decode Timeout	Set the number of seconds before the scanner automatically turns off if the scan button is pressed and nothing has successfully decoded.	20

Setting	Description	Default
Trigger Scan Mode	Set read behavior on scan button press. Options available: - One Shot - Continuous - Read on release - Read on second trigger press	One Shot
Same symbol timeout	Set the minimum buffer time in seconds before the scanner reads the same barcode. This can be adjusted to prevent inadvertent scans of the same barcode if the code is left in the scan field longer than the Decode Timeout limit. The default same symbol timeout is 1000 seconds.	Disabled

Notification Settings

Use the Notification Settings to configure how your computer responds when you scan a barcode.

Notification Settings

Setting	Description	Default
Good Read Notification	Enables or disables a good read notification. The notification consists of a green blink of the Good Read LED, a short beep, and an optional short vibration.	Enabled
Bad Read Notification	Enables or disables notification of a failed scan. The notification consists of a red blink of the Good Read LED, an error beep, and an optional short vibration.	Disabled
Vibrate On Notification	Enables or disables whether the computer vibrates when there is a good or bad read.	Disabled

Add a Scan Setting Profile

To create a scan setting profile for a custom app on the computer:

1. Swipe up from the bottom of the Home screen to access all apps.
2. Tap **Settings**  > **Honeywell Settings** > **Scanning** > **Internal Scanner**.
3. Tap  in the upper right corner of the app screen.
4. Take one of the following actions:
 - Tap the **Profile name** field, and then add a new name.
OR
 - Tap the **select an application** option, and then choose an app from the list.

The new profile appears on the Internal Scanner profile list. You can now select and modify the scan settings for the new profile.

Delete a Scan Setting Profile

1. Swipe up from the bottom of the Home screen to access all apps.
2. Tap **Settings**  > **Honeywell Settings** > **Scanning** > **Internal Scanner**.
3. Tap and hold the profile you want to delete, select **Delete** and then click **OK**.

About ScanHandle Settings

1. Swipe up from the bottom of the Home screen to access all apps.
2. Tap **Settings**  > **Honeywell Settings** > **ScanHandle Settings**.
3. Tap **Enable ScanHandle** to turn the feature on.

A preview of the button appears at the bottom of the screen. Attach the scan handle to the EAD5S mobile computer for easier grip and trigger action when scanning labels.

About the Optional Digital Scan Button

By default, the imager is enabled for scanning with the left and right Scan buttons configured to trigger the imager. If your application environment requires use of an on-screen Scan button, enable the Digital Scan Button feature in the Settings app. Once enable, you can then modify the appearance of the on-screen Scan button and select the apps the button appears in.

Enable and Configure the Digital Scan Button

1. Swipe up from the bottom of the Home screen to access all apps.
2. Tap **Settings**  > **Honeywell Settings** > **Digital Scan Button**.
3. Tap **Enable Digital Scan Button** to turn the feature on. A preview of the button appears at the bottom of the screen.
4. Configure the button appearance. As you adjust the settings, the preview of the button updates.
 - Tap **Select Button Size**, and then choose Small, Medium or Large.
 - Tap **Select Button Color** and then choose from seven color options. Default color is black. Tap a dot to select the color, and then select **OK** to confirm.
 - Use the slider under **Transparency Level** to adjust how transparent the button appears on the application screen.

5. Drag the preview of the Scan button to the location where you want it to appear on the screen. Once you have positioned the button, tap the **Set Button Location** toggle button to lock it into position.
6. Tap **Choose Application**.
7. Check the box next to all the applications where you want the digital scan button to be available.
8. Select **OK**.
9. Tap the **Back** arrow to return to the Settings screen.


The digital scan button appears on the screen when you open any of the apps you selected during the button setup. Tap and hold the button to activate the imager and scan a barcode.

Scan Barcodes

By default, the integrated imager is enabled for scanning. It supports omni-directional (360°) barcode scanning, and an aiming beam is provided to help assist with targeting barcodes.

Before you start scanning barcodes, go into **Settings**  > **Honeywell Settings** > **Scanning** > **Internal Scanner** and modify the scan profile to enable only the barcode symbologies that you need. By reducing the active symbology list, you can increase scan speed.

1. Point the imager window at the barcode. For optimum performance, avoid reflections by scanning the barcode at a slight angle.
2. Press and hold any **Scan** button.
3. Center the aiming beam over the barcode. Make sure the entire barcode is inside of the illumination frame.
4. Release the **Scan** button when the computer beeps, and the Good Read LED briefly turns on. The barcode information is entered into the application in use.



Note: Not all barcode symbologies are enabled by default. If a barcode does not scan, the correct symbology may not be enabled.

About Scanning Configuration Barcodes

After completing the out-of-box set up process, Provisioning mode is automatically turned off. Scanning a barcode to install applications, certificates, configuration files, and licenses on the computer is restricted unless you enable Provisioning mode in the Settings app.

To learn more [About Provisioning Mode](#), see page 71.

Use the Scan Demo App

Use the Scan Demo app to read barcodes or to test your symbology decode settings.

1. Swipe up from the bottom of the Home screen to access all apps.
2. Tap the **Demos** app.
3. Swipe left or right on the screen until **Scan Demo** appears under the turntable. Tap the center of the box image to open the app.
4. Point the imager window at the barcode.
5. Press and hold either side **Scan** button or tap **SCAN** on the computer screen.
6. Center the aiming beam over the barcode. Make sure the entire barcode is inside of the illumination frame.
7. Release the **Scan** button when the computer beeps, and the Good Read LED briefly turns on. Barcode information appears on the screen.

Note: *In the Scan Demo app, not all barcode symbologies are enabled by default. If a barcode does not scan, the correct symbology may not be enabled.*

Change the Scan Demo Symbology Settings

1. In the Scan Demo app, tap  in the upper right corner of the screen.
2. Select **Symbology Settings**.
3. Modify the symbology parameters.
 - Tap the check box next to a symbology name to enable (check mark) or disable (no check mark) decoding for that symbology.
 - Tap the symbology name to view and modify additional configuration parameters for the symbology selected.
4. Tap **Back** arrow to return to the Scan Demo app.

USE THE PHONE

You can use the phone feature to make and receive phone calls as well as transmit data through wireless wide-area networks (WWANs).

Note: Phone features are only supported on EDA5S WWAN models

About the Phone

Phone features on the computer include dual speakers and three microphones for noise cancellation. You can also use a hands-free kit or headset that supports Bluetooth® wireless technology.

On WWAN models the phone feature is enabled by default and supports all cellular radio access technologies (2G, 3G, etc.) for voice and data connections around the globe. These features are certified by PTCRB, GCF, and all major US carriers.

After you turn on the phone and activate service with your wireless carrier, you can customize the phone features and network settings in the Network & internet section of the Settings app.

Note: WWAN radios support Network Information and Time Zone (NITZ) messages to automatically set the system time.

Activate the Phone

You use either a nano-SIM card or embedded SIM (eSIM) to activate the phone and connect to a mobile network. Available SIM options are model and mobile carrier dependent. Contact your mobile service provider to obtain a nano-SIM card and/or for additional details on phone network activation.


Available Configurations:

- EDA5S WWAN models include one nano-SIM card socket and eSIM.


Install nano-SIM Card

Note: On EDA5S WWAN models with an eSIM, you do not need to install a nano-SIM card unless you want a dual carrier setup.

1. Press and hold the **Power** button until the options menu appears.
2. Tap **Power Off**.
3. Remove the battery from the computer. Refer to [page 5](#).
4. Slide the card holder tray out of the slot.



5. Place the nanoSIM card into the card holder tray with contacts facing down.



6. Slide the card holder tray back into the card holder slot.
7. Install the battery. Refer to [page 7](#).

Make a Phone Call

Once the phone is activated, you can make a phone call.

1. Tap  in the favorites tray to open the phone app.
2. Use one of the methods below to enter the telephone number you want to call.
 - Tap  and use the on-screen dialer.
 - Select a person on your saved contact list .
 - Select a favorite on your speed dial list .
 - Select a number from the recent calls list .
3. Tap call .
4. To end the call, tap .

Answer the Phone

When you receive a phone call, the Incoming Call screen opens. If the caller's telephone number is available, it appears on the screen. Depending on your calling plan, you may also see a Caller ID information. All incoming calls are recorded in the Call log. If you miss a call, you receive a notification.

1. On the Incoming Call screen, tap and hold the white call icon.
2. Three icons appear:
 - To answer the call, drag the icon to .
 - To send the caller directly to voice mail, drag the icon to .
 - To send a text message back to the caller instead of answering, drag the icon to .

Switch Apps During a Phone Call

You can multitask while a phone call is in progress. For example, you can use the Calendar app to check your schedule during a call.

Note: Depending on your WWAN connection and carrier, apps that need a data connection may be unable to access online data while the phone call is in progress. If simultaneous phone calls and data connections are not possible due to provider limitations, voice calls receive priority. Check with your provider for more information.

1. During a phone call the screen goes dark. Take the phone away from your ear to wake the screen. Tap the **Home** button.
2. Select another app (e.g., Calendar, Contacts). The phone icon appears in the status bar at the top of the screen while the call is connected.
3. To return to the call screen, swipe down from the top of the screen and select ongoing call notification or select **Hang up** if you want to end the call.

Make an Emergency Phone Call

You can use the phone to make an emergency phone call even if the SIM card is missing from your phone. The phone shows no service but the call still goes through if you dial certain emergency numbers (e.g., 112, 911, 000, 08, 118, 119, and 999).

Configure Phone Settings

You can customize settings for the phone, including the ringtone, voicemail options, keypad tones, Internet call settings, and other options.

1. Open the phone app .
2. Tap  next to the microphone icon at the top of the screen.
3. Select **Settings**. The Call settings menu appears.
4. Change phone settings as necessary.

Note: Available settings vary depending on your cellular carrier and phone plan.

USE THE CAMERA

Use this chapter to learn how to take pictures and record videos with the color camera(s).

About the Color Camera

The EDA5S mobile computer comes equipped with two cameras, a 13-megapixel color camera on the back of the computer and a 5-megapixel camera located on the front. Both include 4K video support with image stabilization and advanced software features for enhanced exposure control when taking pictures and videos.

Use the **photos** app  to view photos and videos stored on the mobile computer. By default the photos and videos captured with the Camera app are saved on the computer under Internal shared storage\DCIM\Camera.

How to Zoom

The camera zoom is controlled using a pinching motion on the touch screen. Place two fingers on the screen at the same time, and then:

- spread your fingers apart to zoom in (enlarge an object), or
- pinch them together to zoom out.

Take a Photo

1. Tap the **Camera** icon  in the favorites tray on the Home screen.
2. Select  to switch between the front and rear camera. The front camera does not include a Flash feature.
3. Using the screen as a viewfinder, move the computer until you see the image you want to capture.

4. The camera automatically adjusts the focus but you can tap the screen to modify the focal point. By default, the camera senses the lighting in the environment and turns the flash on, if needed.
5. Tap  or the Volume button to take a photo.
 - To view the picture, tap the preview near the bottom of the screen.
 - To return to the Camera app, tap the **Back** navigation button.

Record a Video


This section explains how to record video with the camera in the computer.

1. Tap the **Camera** icon  in the favorites tray.
2. Tap  to start recording video.
 - To zoom in or out, pinch or spread your fingers apart.
 - To toggle sound recording on or off, tap the microphone icon at the top of the screen.
 - To pause recording, select . To resume recording, tap .
 - To capture a still picture during recording, tap the **Camera** icon .
 - To add light while recording, tap the flash icon. Flash is only available with the rear camera on the back of the computer.
3. When you are done recording, tap .

Change Camera Settings

You can change the camera settings for best results when taking pictures. The camera settings are adjustable from within the Camera app.

1. Open the **Camera** app .
2. At the top of the screen, select any of the following to adjust the settings. The options vary depending on camera mode selected.



- **More Settings**
Select to access HDR, Automatic and Advanced settings.

HDR

Tap to quickly toggle HDR mode on or off. When enabled, the computer automatically captures multiple photos and combines them into one photo creating the best quality image possible.

Automatic

Select Automatic to have the camera automatically adjust the settings and focus for you.

- **Advanced Settings**

Select the gear  to access settings that allow you to modify the camera setting defaults and to configure how the camera app functions (i.e., General, Still camera, Video camera, System).

Use the Camera as a Flashlight

To use the rear camera as a flashlight.

1. Open Quick Settings (see page [23](#)).
2. Tap the Flashlight icon to toggle the flashlight On or Off.

Note: The flashlight feature only works if the camera app is closed.

CONFIGURE THE COMPUTER

Use this chapter to learn about the available methods for configuring your mobile computer. You can also use this chapter to learn how to configure network communications and wireless security.

How to Configure the Computer

You can configure many parameters on the computer such as the bar code symbologies it decodes or the network settings. The values you set for these parameters determine how the computer operates. You configure the computer using the Settings app.

Start the Settings App

The Settings app is available from the all apps menu and the notification panel.

- Swipe up from the bottom of the Home screen, and then tap **Settings** .

OR

- Swipe down twice from the top of the Home screen, and then select .

About the Structure of the Settings App

Use this section to learn about the structure of the Settings app so you can find parameters quickly. A search field appears at the top of the screen when you open the Settings app to help you locate settings quickly.

Note: *The Settings app varies by computer model and OS version. Your computer may not include all the features outlined in this section.*

Network & internet

In the Settings app, select **Network & internet** to access the following settings.

Setting	Description
Wi-Fi	• Turn Wi-Fi radio on or off. • Lists available Wi-Fi networks in range and the connection status when the radio is turned on. • Add a network Wi-Fi connection and view saved networks. • Tap Wi-Fi preferences to access advanced Wi-Fi options, view MAC and IP address information, access Honeywell Wi-Fi settings (see page 63), and import and export Wi-Fi configurations.
Mobile network (WWAN models)	Modify mobile network settings, including enabling data access and roaming over mobile networks, selecting access points and network operators, or selecting only 2G networks (to save battery life). • Turn Mobile data On or Off. • Turn Roaming On or Off. • View Data use information. • Access advanced options, including: • 4G LTE Mode On/Off setting • Preferred network settings • CDMA roaming settings and subscription settings (i.e, RUIM/SIM, NV) • Access point name and selection • Network selection settings
Airplane mode	Turn Airplane mode on or off.
Ethernet	• Turn Ethernet connection on and off. • View last Ethernet connection information.
Mobile plan	Provides information on your cell phone plan.
Hotspot & Tethering	• Enable or disable Bluetooth or Ethernet tethering for sharing mobile data connections. • Enable or Disable using the computer as a portable Wi-Fi hotspot. • Configure Wi-Fi hotspot.
Advanced	
Data Saver	Turn the Data saver feature On or Off. Specify which apps can use unrestricted data.
VPN	Set the password parameters for a virtual private network (VPN) connection.
Private DNS	Select Private DNS Mode.

Connected devices

In the Settings app, select **Connected devices** to view current, connected devices and to access the following settings.

Setting	Description
Pair new device	- Connect to a Bluetooth Device. - Lists Bluetooth enabled devices in range. - View and rename the computer. - View the computer Bluetooth address.
USB	Select the type of communication: - File Transfer - USB tethering - PTP - No data transfer Note: This setting only appears when the unit is connected via USB.
Previously connected devices	View previously connected devices. Note: This setting only appears once the computer has been paired with another device.
Connection Preferences	
Bluetooth	- Turn the Bluetooth radio On or Off. - Lists Bluetooth enabled devices in range when the radio is turned On. - Connect to a Bluetooth Device. - View and rename the computer. - View the computer Bluetooth address.
NFC	Turn Near Field Communication (NFC) On or Off. When the NFC radio is enabled, data exchanges are allowed when the computer touches another NFC enabled device.
Cast	Set up a Cast connection. Cast (project) audio and screen content to a secondary device such as a television.
Android Beam	Turn the Android Beam feature On or Off. When NFC is enabled, this feature is accessible. You can beam app content to another NFC capable device by holding the devices close together. The app determines what content is transmitted to the other device.
Printing	Set up a printer connection with the EDA5S. Connection options include cloud print services, Wi-Fi printing via a router or printing via NFC.
Files received via Bluetooth	View statistics and received files.
Chromebook	Set up connection from the mobile computer to a Chromebook.
Nearby Share	Set up file sharing with nearby devices. The device location setting needs to be turned on for Bluetooth and Wi-Fi radios to detect nearby devices.
Android Auto	Use apps on your phone screen or car display. To learn more, go to Android Auto Help at https://support.google.com .

Apps & Notification

In the Settings app, select **Apps & Notifications** to access the following settings.

Setting	Description
Apps info	View a list of recently opened apps or select "See all . ." to view a list of installed apps on the computer and system services running.
Notifications	Set rules for notifications.
Screen time	- Shows Screen time, Notifications received, Times opened. - Allows to set app timer.
Default apps	View and manage default app use.
Advanced	
Permission manager	View and manage individual app permissions.
Wireless Emergency alerts	Manage Emergency alert notifications.
Special app access	Manage apps with special unrestricted access.

Battery

In the Settings app, select **Battery** to view battery status, use statistics and adjust features that conserve battery charge.

Note: Some settings in previous OS versions can be found in Display.

Setting	Description
Battery	View current battery charge or charging status.
Battery saver	Turn the Battery saver feature On or Off manually. Set a schedule, based on the battery charge percentage (%) remaining that automatically activates the Battery saver feature. Use the slider to set the battery percentage level. Slider adjusts from 5% to 7% and is only available once schedule is selected. When charging, set the battery saver feature to turn Off when the battery reaches 90%. Default setting.
Battery Manager	Turn the Battery Manager On or Off. Battery manager detects when apps drain the battery.
Battery percentage	Set to show or do not show battery percentage in status bar.
Last full charge	View time since the battery was fully charged.
Screen usage since last full charge	View amount of time when the screen was used since the battery was fully charged.

Display

In the Settings app, select **Display** to access the following settings.

Setting	Description
Brightness level	Set the Brightness level manually if Adaptive brightness feature is turned Off.
Dark theme	Enable dark mode to switch app backgrounds to a black color.
Night light	Activate the Night light feature to adjust the screen tint to a light amber for easier viewing and reading in dim light or for the hours you use the device before going to sleep. Set the feature to stay on or define a schedule to turn the feature On/Off. You can manually adjust the intensity of the amber hue once the feature is activated.
Adaptive brightness	Set how the screen in sleep mode responds when new notifications are received (e.g., wake or do not wake).
Wallpaper	Set the wallpaper.
Advanced	
Screen timeout	Set the inactivity time limit before the unit automatically turns of the screen to save battery power (seconds or minutes).
Auto-rotate screen	Set the screen to switch from portrait to landscape when the unit is rotated. When Off the screen does not automatically rotate.
Colors	Adjust the screen color settings (e.g, Natural, Boosted, Adaptive).
Font size	Set the default on-screen text size.
Display size	Set the default size of items on your screen.
Screen saver	Set the default screen saver as well as when to display it. Tap Settings to select screen saver style or to turn Night mode on.
Lock screen	Select what to show on the lock screen and when to display new notifications.

Sound

In the Settings app, select **Sound** to modify the audio and sound settings. To learn more, see [Audio Settings](#) on page 15.

Storage

In the Settings app, select **Storage** to view statistics on available and used storage space on the device and on any portable storage cards installed.

Privacy

In the Settings app, select **Privacy** to define privacy settings for the device.

Setting	Description
Permission manager	Define which apps have access to features on the device, such as the camera or microphone.
Show passwords	Briefly displays the characters in a password as you type before hiding them.
Notifications on lock screen	Select whether or not to show all notification content on the lock screen.

Setting	Description
Autofill service from Google	Automatically fill fields using saved data from your Google account.
Advanced	
Google location history	Enable or disable location history and manage or delete activity. A Google account must be associated with the device to use this feature.
Activity controls	Choose what type of activities are saved in your Google account. A Google account must be associated with the device to use this feature.
Ads	Opt in or out of ad personalization features. When this is on, ads are personalized with the activity and information from your Google Account.
Usage & diagnostics	Automatically send diagnostic, device, and app usage data to Google. By default, this setting is turned off.

Location

In the Settings app, select **Location** to define which apps have access to the device's location.

Setting	Description
Use Location	Turn location services (Google and GPS satellite data) On or Off. Set location mode accuracy and view location request history.
App access to location	View and manage app-level location service permissions.
Wi-Fi and Bluetooth scanning	Turn Wi-Fi and/or Bluetooth scanning On or Off. When enabled system apps and services are allowed to detect Wi-Fi networks or Bluetooth devices at any time to improve location services.
Advanced	
Emergency Location Service	Allows the device to automatically send its location to emergency locations.
Google Location Accuracy	Improves location accuracy by using Wi-Fi, mobile networks, and sensors to help estimate the device location.
Google Location History	Allows the device to report Location History to Google. A Google account must be associated with the device to use this feature.
Google Location Sharing	Allows the device to share its location with anyone in the contacts list.

Security

In the Settings app, select **Security** to view latest Security scan results, security updates and phone encryption status. Access additional settings related to device security.

Setting	Description
Google Play Protect	Manually initiate a scan of the apps on the device to check for problems.
Find My Device	Allows users to locate, ring, or wipe a device remotely.
Security update	Displays the last date security was updated on the device.

Setting	Description
Screen Lock	Activate and configure a screen lock (i.e., None, Swipe, Pattern, Pin, Password).
Smart Lock	Define safe conditions or locations where your phone will stay unlocked (e.g. On-body, Trusted places, Trusted devices, Voice Match).
Device admin apps	Manage administrator privileges.
Encryption & credentials	View encryption status and manage trusted credentials (e.g., view, install, clear, and edit).
Trust agents	View and enable/disable trusted agent apps such as, Smart Lock by Google on the device. Trusted agents bypass security based on set parameters.
App pinning	Enable or disable the screen pinning feature. When enabled you can pin the device screen to a recently used app where it stays until you unpin the app via the security method chosen.
Confirm SIM deletion	Require a password to delete an eSIM.

Accounts

In the Settings app, select **Accounts** to access the following settings.

Note: Some settings in previous OS versions can be found in System.

Setting	Description
Add account	Select to add and manage Corporate or Email account on the computer.
Automatically sync app data	Turn auto-sync On or Off for accounts. Turning the feature On allows apps to refresh data automatically.

Accessibility

In the Settings app, select **Accessibility** to access screen readers, display settings, interaction controls, and audio & on-screen text features to improve accessibility levels.

Setting	Description
Screen Readers	
Select to Speak	When turned on, you can tap specific items on the screen to hear them read aloud.
TalkBack	When turned on, the feature provides spoken feedback so you can use the computer without always looking at the screen. TalkBack describes your actions and tells you about alerts and notifications
Text-to-speech output	Select and configure the preferred TTS, set language, speech rate and pitch of synthesized voice.

Setting	Description
Display	Configure display features that may aid visual accessibility levels. • Adjust Font size • Adjust Display size • Turn Dark theme On/Off • Turn the Magnification feature On/Off • Set Color correction • Turn Color inversion On/Off • Turn Large mouse pointer On/Off • Turn Remove Animations On/Off
Interaction controls	Set interaction controls that may aid physical accessibility levels. • Accessibility Menu provides large on-screen menus. • Configure Switch Access. You can use a switch or keyboard to control your device. • Set the Dwell timing (Click after pointer stops moving) delay. • Turn the Power button ends call feature On/Off. • Turn Auto-rotate screen On/Off. • Adjust the Touch & hold delay. • Time to take action (Accessibility timeout) • Vibration & haptic strength • Set System navigation (e.g., Gesture navigation or 3-button navigation).
Audio & on-screen text	• Turn Mono audio On/Off. • Set Audio balance if using headphones or hearing aids. • Turn Captions On/Off.
Experimental	• Turn High contrast text On/Off. • Turn Shortcut from lock screen On/Off.

Honeywell Settings

In the Settings app, select **Honeywell Settings** to access the following settings.

Setting	Description
Battery LED	Configures the battery LED behavior. To learn more, see Change the Battery Status LED Behavior on page 9.

Setting	Description
Battery Optimizer	View battery status and app usage information. Tap Optimize Battery to create and enable or disable a battery optimization profile that implements a group of settings to conserve power. Options include: • None When selected, no battery optimization profile is active. • Energy Saver This pre-defined profile implements UI settings that optimize battery conservation. • Cold Storage This pre-defined profile implements UI settings that optimize battery savings in cold storage environments. • Custom Profile Tap to create a custom battery profile that balances your application needs with energy saving settings. You can turn location services on or Off, configure sound and vibration options, modify brightness and timeout display options, turn UI transition animations on or off and background services on or off.
Digital Scan Button	Enable and configure the optional digital scan button. To learn more, see About the Optional Digital Scan Button on page 40.
DisplayDockService	
Glove Mode	Enable or disable Glove Mode.
HXLogger	The HXLogger is an advanced diagnostic log service that provides a basic log service, plug-ins for modified log services, and a log manager. • Tap HXLogger to turn the basic log service On/Off. When enabled the service records app and system diagnostic troubleshooting information into four basic log files: main log file, radio log, event log, and kernel dynamic log. • Tap Kernel dynamic log to toggle feature On or Off and to set the Input file name and Input function name. This log is typically used by advanced software application developers. • Tap Plugin to view and enable additional log services and custom plug-ins. • Tap Manager, to change the default log path, delete logs or upload logs for technical support troubleshooting. Select the more icon  to Select the max bootset count or to manually Sync Log.
Key WakeUp	Set the buttons you want to use to wake the computer from sleep mode. Options include: Left Scan, Right Scan, Volume Up, Volume Down. By default the Left and Right Scan buttons are enabled for wake up.
Keyremap	Change (remap) a button or key function. To learn more, see Remap a Button on page 21.
Provisioning Mode	Enable or disable unrestricted installation of applications, certificates, configuration files, and licenses. Provisioning mode is turned off by default. To learn more About Provisioning Mode , see page 71.
ScanHandle Settings	Enable or Disable Scan handle, see About ScanHandle Settings on page 40.

Setting	Description
Scanning	Configure the computer imager. To learn more, see Change the Scanner Settings on page 32.
Smart sensor	Configures the integrated motion detection sensors for advanced power management. Options include: Keep awake on motion, Wake on motion, Face down suspend.
Staging Hub Agent	Use this agent and settings to connect the computer to the Honeywell Staging Hub Foundation software platform; a centralized software platform IT integrators and administrators can use as a solution for managing, monitoring and deploying Honeywell devices in a connected workspace environment.
Web Applications	Enables access for the Honeywell Mobility SDK for Web apps and port selection.

Digital Wellbeing & parental controls

In the Settings app, select **Digital Wellbeing** to access the following settings. See <https://wellbeing.google/>.

Google

In the Settings app, select **Google** to set up and manage your Google accounts and services.

System

In the Settings app, select **System** to access the following settings.

Setting	Description
Language & input	- Set the active language. - Set and manage Virtual and Physical Keyboard input methods. - Configure auto-typing features such as capitalization, punctuation, spell check, and the personal dictionary. - Adjusts the pointer speed. - Set text-to-speech output.
Gestures	- Turn Jump to Camera On/Off. - Turn Swipe Up on Home Button On/Off. - Set the Prevent ringing option. Options: Vibrate, Mute, Do Nothing.
Date & time	Configure all date and time settings. See page 25 .
Backup	Turn the Google Drive backup feature On or Off. When enabled, phone data (e.g., apps, apps data, call history, contacts, device settings, SMS, Wi-Fi passwords and permissions) is automatically backed up to the Google Drive.
Advanced	

Setting	Description
Reset Options	Select from the following reset options: - Reset Wi-Fi, Mobile & Bluetooth. Use to reset all network settings, including Wi-Fi, Mobile data and Bluetooth. - Reset app preferences. Use to reset app preference back to defaults. This includes apps you disabled, notification changes, default app actions set, background data restrictions for apps and permission restrictions. - Enterprise data reset. To learn more, see About an Enterprise Data Reset on page 77. - Erase all data (factory reset). To learn more, see About a Full Factory Reset on page 78.
Multiple Users	- Modify the owner profile name and add profiles for other people who use the computer. - Activate a different user profile. - Enable or disable allowing users to be added from the lock screen.
Developer options	Enable developer-specific options such as USB debugging and SD card protection. This option only appears under System settings if you enable the feature. To learn more, see Unlock Developer Options on page 29.
System update	Check for Android system updates.

About Phone

In the Settings app, select **About Phone** to access the following information.

Setting	Description
Device name	A nickname to identify the device. To change, tap Device name and enter a new name.
Phone number*	The phone number(s) assigned to the device.
Emergency information	Emergency medical and contact information that will be displayed on the lock screen in an emergency.
Legal information	Provides links to third-party licenses and other legal information.
Compliance information	Displays certification and compliance information.
SIM status*	Displays information on the SIM card in the device that can be used for diagnostic purposes.
Model	Displays the model number and serial number of the device.
IMEI*	Displays the International Mobile Equipment Identify number.
Android version	The version of Android on the device. Tap to view additional details.
Asset number	Asset tag assigned to the device.
IP address	IP address associated with the device.
Wi-Fi MAC address	Wi-Fi Mac address associated with the device.
Bluetooth address	Bluetooth address associated with the device.
Up time	Amount of time the mobile computer has been running since the last power up or restart.

Setting	Description
Build number	Kernel number installed.
* If your WWAN model supports a dual SIM card setup, both sim slot 1 and sim slot 2 will be listed.	

About Network Communications

You can easily add the mobile computer to your wireless or wired network. Connect the EDA5S to your computer using:

- 802.11 a/b/g/n/ac/ax radio communication technology
- Ethernet communication technology
- Bluetooth communication technology
- USB communication technology

Connect to a Wi-Fi Network

The computer contains an 802.11 a/b/g/n/ac/ax radio to transfer data using wireless communications. Before you connect to a Wi-Fi network, you need to know about your network security protocol and its required credentials.

By default, the 802.11 radio is disabled.

1. Swipe up from the bottom of the Home screen to access all apps.
2. Tap **Settings**  > **Network & internet** > **Wi-Fi**.
3. Tap  the toggle button to turn the Wi-Fi radio **On** . A list of discovered networks appears.
4. On the list, tap a network name to initiate a connection.

To add a network if it does not appear on the list:

- a. Navigate to the end of the discovered network list, and then tap **Add network**.
 - b. Type the Wi-Fi network name (SSID).
 - c. Choose a security protocol and add any required information.
 - d. Tap **Save**.
5. Enter any required information if the network is secured (e.g., password, key or certificate name).
 6. Tap **Connect**.

Once you connect to a saved Wi-Fi network:

- Tap the network name on the list to view details (e.g., status, signal strength, speed, frequency, security type). Select **Cancel** to close details screen.

- The computer automatically connects to the same network when the network is in range and the Wi-Fi radio is turned on.
- To remove a network from your saved list, tap and hold the network name and select **Forget**. You can do this for networks you no longer use.
- To view a list of only your saved networks, tap **Saved networks**.

Configure Proxy Settings for a Wi-Fi Network

If you need to connect to network resources through a proxy server, you can configure settings for the proxy server for each Wi-Fi network you add. By default, the Wi-Fi networks you add are not configured to connect through a proxy server.

Note: Proxy settings apply only to the Wi-Fi network you modify. You must change proxy settings for each network requiring a proxy server.

1. Swipe up from the bottom of the Home screen to access all apps.
2. Tap **Settings**  > **Network & internet** > **Wi-Fi**. The list of available Wi-Fi networks appears.
3. Tap the  icon next to a connected network.
4. Tap the  icon to edit network details.
5. Tap **Advanced options**.
6. Expand the Proxy menu, then select **Manual**.
7. Enter the proxy settings for the network.
8. Tap **Save**.

Disable Wi-Fi Notifications

By default, when Wi-Fi is enabled, you receive notifications in the Status bar when the computer discovers a wireless network. You can disable these notifications.

1. Swipe up from the bottom of the Home screen to access all apps.
2. Tap **Settings**  > **Network & internet** > **Wi-Fi**. Verify the Wi-Fi radio is turned On.
3. Tap **Wi-Fi preferences**. The Configure Wi-Fi menu appears.
4. Tap **Notify for public networks** to toggle the setting On or Off.

Honeywell Wi-Fi Settings

To access Wi-Fi preference settings for advanced configuration of the wireless 802.11 radio in the mobile computer:

1. Swipe up from the bottom of the Home screen to access all apps.
2. Tap **Settings**  > **Network & internet** > **Wi-Fi**.
3. Tap **Wi-Fi preferences**. The Configure Wi-Fi menu appears.
4. Tap **Advanced** > **Honeywell Wi-Fi Settings**.
5. Tap a setting to enable or disable the option or to access additional parameters that configure the Wi-Fi radio.

How to Connect to Virtual Private Networks

The computer supports connecting to virtual private networks (VPNs). This section describes how to add and connect to VPNs. To configure VPN access, you must obtain details from your network administrator. You view and change VPN settings in the Settings app.

Note: Before you can add or connect to a VPN, you must enable a screen lock method.

Add a VPN

Before you can connect to a VPN, you must create a VPN profile.

1. Swipe up from the bottom of the Home screen to access all apps.
2. Tap **Settings**  > **Network & internet** > **Advanced** > **VPN**.
3. Tap **+** to add a new VPN profile.
4. Enter the required information for the VPN connection. If needed, swipe up on the screen to access all the required information fields.
5. Tap **Save**. The VPN name appears in the VPN list.

Connect to a VPN

Once a VPN profile is created, you can connect to the VPN at any time.

1. Swipe up from the bottom of the Home screen to access all apps.
2. Tap **Settings**  > **Network & internet** > **Advanced** > **VPN**.
3. Tap the name of the VPN in the list.
4. Enter any necessary credentials when prompted.
5. Tap **Connect**.

A  appears in the status bar and a notification is received. To disconnect from the VPN, tap the notification.

Edit VPN Information

Editing an existing VPN profile is done from the VPN screen.

1. Swipe up from the bottom of the Home screen to access all apps.
2. Tap **Settings**  > **Network & Internet** > **Advanced** > **VPN**.
3. Tap and hold the name of the VPN in the list.
4. Tap  to the right of the VPN profile you want to edit.
5. Edit the VPN settings as necessary.
6. When you are done, tap **Save**.

About Wireless Security

The computer provides these security solutions for your wireless network:

- Wi-Fi Protected Access 2 (WPA2™)
- Wi-Fi Protected Access (WPA)
- 802.1x
- LEAP
- WEP

Honeywell recommends WPA2 security with PSK (Personal) or 802.1x (Enterprise) key management.

Before you set security, you need to enable the radio, set the date, and set the SSID on your computer. To use 802.1x security, you need to load a root certificate on your computer. To use transport layer security (TLS) with 802.1x security, you also need to load a user certificate.

Use the Settings app to access and configure all wireless security settings.

About Certificates

You can use digital certificates to identify the computer for network access or authentication to servers. To use a certificate to identify your device, you must install it in the trusted credential storage on the computer.

Android supports DER-encoded X.509 certificates saved in files with a .crt or .cer file extension. To install a valid certificate with a .der or other extension, you must change the extension to .crt or .cer to install it.

Android also supports X.509 certificates saved in PKCS#12 key store files with a .p12 or .pfx extension. To install a valid key store file with another extension, you must change the extension to .p12 or .pfx to install it. When you install a certificate from a PKCS#12 key store, Android also installs any accompanying private key or certificate authority certificates.

Load a Certificate

To use a certificate, you must install it in the trusted credential storage on the computer.

Note: Apps such as email and browsers that support certificates allow you to install certificates directly from within the app. For more information, see the help that comes with the app.

1. Copy the certificate or key store from your PC to the mobile computer.
2. Swipe up from the bottom of the Home screen to access all apps.
3. Tap **Settings**  > **Security** > **Encryption & credentials**.
4. Tap **Install a certificate**.
5. Select either **CA certificate**, **VPN & app user certificate** or **Wi-Fi certificate**.
6. Tap the Menu icon , and then navigate to the location where you saved the certificate.
7. Tap the certificate or key store to install it. If prompted, enter the key store password and tap **OK**.
8. Enter a name for the certificate and tap **OK**.

Disable or Remove Certificates

If a user or system certificate is compromised, or your organization chooses not to trust it, you can disable or remove the certificate.

1. Swipe up from the bottom of the Home screen to access all apps.
2. Tap **Settings**  > **Security** > **Encryption & credentials**.
3. Tap **Trusted Credentials**.

The trusted credentials screen has two tabs:

- **System** shows Certificate Authorities (CA) certificates permanently installed on the computer. They can only be disabled.
 - **User** shows CA certificates you have installed yourself. You can remove these certificates.
4. Tap the name of the certificate that you want to disable or remove. The Security certificate screen appears.

5. Scroll to the bottom of the screen and tap **Disable** (for System certificates) or **Remove** (for User certificates).
6. Tap **OK**.

Note: You can enable a disabled System certificate, but if you remove a User certificate, you must install it again to enable it.

About Bluetooth Communications

Your mobile computer is equipped to communicate with other devices using Bluetooth technology. The Bluetooth radio must be turned on to discover, pair and connect to other devices using Bluetooth wireless technology. System bar icons indicate Bluetooth radio status.

Connect a Bluetooth Device

To connect to a Bluetooth device, you must turn on the Bluetooth radio and then select the device from a list of discovered devices.

1. Swipe up from the bottom of the Home screen to access all apps.
2. Tap **Settings**  > **Connected devices**.
3. Tap **+** Pair new device. A list of Bluetooth devices appears.
4. Select a device on the list to initiate a pairing request.
5. When the pairing request message appears:
 - Verify the pairing PIN is the same on both devices, and then tap **Pair**.

OR

- If the pairing request requires a PIN, enter the **PIN**, and then tap **Pair**.

When the device is successfully paired with the computer, the device name appears under Previously Connected Devices.

6. (Optional) Once paired to a device, you can connect manually to the device. Tap the device under Paired devices. The word “Connecting” appears under the paired device name. When a connection is established, the device appears under Other Devices.

Note: To delete a paired device, tap  next to the name of the paired device and then tap **Forget**.

Rename the Computer and View File History

You can change the name of the computer to make it easier to identify when pairing with other Bluetooth enabled devices and view statistics about received files.

1. Swipe up from the bottom of the Home screen to access all apps.
2. Tap **Settings**  > **Connected devices** > **Connection preferences** > **Bluetooth**.
3. Tap **Device Name** to change the device name. Type the new name and then tap **Rename**.

Rename or Unpair a Paired Device

You can rename a paired device to make it easier to identify on the list or unpair the device to remove it from the paired list.

1. Swipe up from the bottom of the Home screen to access all apps.
2. Tap **Settings**  > **Connected devices** > **Previously connected devices**.
3. Tap  next to the **paired device**.
4. Take one of the following actions:
 - To rename the device, tap the  icon, type the new name, and then tap **RENAME**.
 - To allow **Contact Sharing**, tap the check box next to the settings.
 - To unpair the device, tap **Forget**.

About USB Communications

You can use these optional EDA5S accessories to transmit data to and receive data from another device using an Ethernet or USB cable connection:

- Home Bases
- Ethernet Home Bases
- Display Docks
- Snap-on Cup (USB)

Accessory documentation is available for download from the EDA5S product pages at www.honeywellaidc.com.

For a complete list of compatible accessories for your mobile computer and their part numbers see the EDA5S *Accessory Guide* available for download at www.honeywellaidc.com.

Contact your local sales representative for ordering information.

USB Troubleshooting

- If you have a problem with your workstation computer recognizing the USB device, try downloading and installing the Honeywell-aidc-usb-driver. The driver is part of the Honeywell_Mobility SDK_Android software.zip file. To learn where to get the software, see [Developer Information](#) on page 71.
- Check to make sure you have enabled the USB for file transfer. To learn more, see [Configure USB Connection and Transfer Files](#) on page 17.

USB, Bluetooth, or Ethernet Tethering for Data Connection Sharing

You can share your mobile computer data connection with another device through a USB, Bluetooth, or Ethernet tethering.

Minimum requirements for USB Tethering

- Mobile computer minimum operating system version of Android 9 or later.
- A compatible USB communication accessory and/or cable.

Set up and Connection

1. Connect the devices using a USB accessories and/or cable.
2. On the mobile computer, tap **Settings**  > **Connected devices** > **USB**.
3. Select **USB tethering**, and then tap the back arrow twice.
4. Tap **Network & Internet** > **Hotspot & tethering**.
5. Select **USB tethering** to initiate the shared data connection.

Note: To stop sharing the connection, tap **USB tethering** again to turn Off the feature or disconnect the USB accessory.

Minimum requirements for Bluetooth Tethering

All devices must support Bluetooth communication.

Set up and Connection

1. Pair the mobile computer with another Bluetooth enabled device.
2. Verify the other device is set to use a network connection using Bluetooth technology.
3. Swipe up from the bottom of the Home screen to access all apps.
4. Tap **Settings**  > **Network & internet** > **Hotspot & tethering**.
5. Select **Bluetooth tethering** to initiate the shared data connection.

Note: To stop sharing the connection, tap **Bluetooth tethering** again to turn Off the feature.

Minimum requirements for Ethernet Tethering

- Mobile computer minimum operating system version of Android 11 or later.
- A compatible USB-to-Ethernet adapter.
- Ethernet cable

Set up and Connection

1. Plug the Ethernet cable into a router or modem, connect the Ethernet adapter to the cable, then plug the adapter into the mobile computer.
2. Swipe up from the bottom of the Home screen to access all apps.
3. Tap **Settings**  > **Network & internet** > **Hotspot & tethering**.
4. Select **Ethernet tethering** to initiate the shared data connection.

Note: To stop sharing the connection, tap **Ethernet tethering** again to turn Off the feature or disconnect the USB accessory.

About Near Field Communication (NFC)

NFC technology provides the ability for short-range, wireless data transfer between the EDA5S and NFC tags or other NFC enabled devices placed in close proximity to the back of the computer. All EDA5S mobile computers support the following modes of operation:

- NFC tag reader/writer mode: The computer reads and/or writes digital information from or to an NFC tag.
- Peer-to-Peer (P2P) mode: The computer uses Bluetooth technology to transfer screen content (e.g., a picture, contact information, Web page URL, or file) between NFC enabled devices.

- NFC card emulation mode: The computer emulates an NFC card (smart card) that an external card reader can access. You can download and install apps for card emulation mode from the Google Play™ store. Some examples include digital wallets (e-wallets) offered by your bank or credit card company and Google Pay™. The app you install determines the type of emulation mode used: Card Emulation with a Secure Element or Host-based Card Emulation. Secure element use is common for financial transactions that require a high level of security in order to provide a secure memory and execution environment for running custom smart card applets and storing your personal information (e.g., account information and credentials).

Note: When using a Universal Integrated Circuit (UICC) card for NFC Secure Element NFC link encryption, install the card in SIM slot 1.

Developer Information

To download the Honeywell Mobility SDK for Android and EZConfig for Mobility:

1. Go to the *Technical Support Downloads Portal* at <https://hsmftp.honeywell.com>.
2. Create an account if you have not already created one. You must login to download the software.
3. Install the *Honeywell Download Manager* tool on your workstation (e.g., laptop or desktop computer) prior to trying to download any files.
4. Navigate to the software:
 - *Honeywell Mobility SDK for Android*
Click on **Software** > **Software and Tools** > **Developer Library** > **SDKs for Android**.
 - *EZConfig for Mobility*
Click on **Software** > **Software and Tools** > **EZConfig for Mobility**.
5. Select **Download** next to the software zip file.

About Provisioning Mode

Once you complete the out-of-box initial setup process, Provisioning mode is automatically turned off to improve device security against unwanted modifications to the system.

When Provisioning mode is turned off (disabled):

- Configuration barcodes do not scan and process.
- \honeywell\autoinstall folders are inaccessible.

Note: To learn more about network and security for Honeywell mobile computers with Android operating systems, go to www.honeywellaidc.com.

Enable or Disable Provisioning Mode

1. Swipe up from the bottom of the Home screen to access all apps.
2. Tap **Settings**  > **Honeywell Settings** > **Provisioning mode**.
3. Tap the button to toggle the provisioning **On** or **Off**.

MANAGE AND MAINTAIN THE COMPUTER

Use this chapter to understand how to upgrade software, reset and maintain the computer.

About Software Updates

Cyber security best practices include keeping your device apps and OS up to date. To help, Honeywell offers maintenance patches, security updates and operating system upgrades through our Honeywell Edge services.

Availability and cost depend on the following:

- Date of purchase of the device or software app.
- Warranty status.
- Service agreement status (devices) or Maintenance plan status (apps).

To learn more about Honeywell Edge Services, go to <https://sps.honeywell.com/us/en/services/productivity/support-services>.

Software Downloads

Product support is available online through [Technical Support](#). Software updates can be accessed through the [Software Downloads](#) portal. You will need to create a login account for portal access. Additional information such as purchased date, service agreement number, maintenance plan number, or software license number may be required for downloads.

1. Go to <https://hsmftp.honeywell.com>.
2. Create a login account if you have not already created one.
3. Install the Honeywell Download Manager tool. See “Note” on the portal page. This tool is required for downloads.
4. Locate the app or upgrade you want to download in the Software directory.
5. If prompted, enter additional information, and click **Submit**.

6. Select **Download**. Follow the prompts to download the file.

About Transferring Files via USB Connection

If you plan on using a USB connection to transfer files to the mobile computer, make sure you set the USB connection to allow file transfers. To learn more, see [Configure USB Connection and Transfer Files](#) on page 17.

Install Software Apps with AutoInstall

Important: *The mobile computer must have power for the entire length of the install process or it could become unstable. Do not attempt to remove the battery during the process.*

1. Swipe up from the bottom of the Home screen to access all apps.
2. Tap **Settings**  > **Honeywell Settings** > **Provisioning mode**.
3. Tap the toggle button to turn Provisioning mode **On**.
4. Save the Android application file (*.zip or *.apk) in one of the following folders on the EDA5S mobile computer:
 - **Internal shared storage\honeywell\autoinstall**
Files saved to this folder for installation do not persist when a Full factory reset or Enterprise data reset is performed.
 - **IPSM card\honeywell\autoinstall**
Files saved to this folder for installation do not persist when a Full factory reset is performed. However, the software does persist if an Enterprise data reset is performed.
5. Swipe up from the bottom of the Home screen to access all apps.
6. Tap **AutoInstall Settings**  and verify **Enable Autoinstall** is enabled ☒.
7. Tap **Packages Update** from the AutoInstall Settings screen.

If required by the app, the computer may automatically initiate a reboot before starting the installation process. When the installation is finished, a message appears or the unit finishes rebooting and the lock screen appears.
8. Once installation is complete, turn Provisioning mode **Off**.

Note: *Some updates do not require the computer to reboot before installation.*

Optional microSD Card Method

The mobile computer comes equipped with a microSD card socket. You can install an upgrade from a microSD card you insert in the computer.

Important: *The EDA5S must have power for the entire length of the install process or it could become unstable. Do not attempt to remove the battery during the process.*

1. On the EDA5S, swipe up from the bottom of the Home screen to access all apps.
2. Tap **Settings**  > **Honeywell Settings** > **Provisioning mode**.
3. Tap the toggle button to turn Provisioning mode **On**.
4. Tap **AutoInstall Settings** . Verify **Autoinstall** is enabled ☒.
5. Press and hold the **Power** button, and then tap **Power off**.
6. On your workstation (e.g., laptop, desktop computer), format the microSD card and create a **\honeywell\autoinstall** folder on the root of the card.
7. Save the upgrade file in the **autoinstall** folder.
8. Install the microSD card in the EDA5S, and then press the **Power** button.

The computer automatically runs the upgrade found in the autoinstall folder on the card. The system update screen appears during the upgrade process. When the upgrade is finished, the lock screen appears.

9. Once installation is complete, turn Provisioning mode **Off**.

About the Honeywell Upgrader


Use the Honeywell Upgrader app (HUpgrader) to check for and install OTA updates, and view the current OTA version installed on the computer.

Install OTA Updates



To use the HUpgrader to install an OTA update file downloaded from the [Technical Support Downloads Portal](#):

1. Save the OTA file (*.zip) the following folder on the EDA5S computer:
 - **Internal shared storage\Download**

2. Tap **HUpgrader**  to open the Honeywell Upgrader app.



3. Tap , and then tap **Choose OTA from storage**.
4. Select the storage location (i.e., Internal Storage) where you saved the file.
5. Tap the OTA update file. The computer examines the file, and then starts the installation.



6. Once the installation is complete (100%), select **OK** when prompted to **Reboot** the computer. The computer reboots and finishes the update.

Restart (Reboot) the Computer

You may need to reboot the computer to correct conditions where an application stops responding to the system.

1. Save your files and close any open applications.
2. Press and hold the **Power** button until the options screen appears.
3. Tap **Restart**. The computer restarts.

If the touch panel display is unresponsive:

- Press and hold the **Power** button for approximately 8 seconds until the computer reboots.

About an Enterprise Data Reset

You can perform an Enterprise data reset if a Reboot did not improve the condition and all other troubleshooting methods have not resolved the issue. This method provides a clean configuration for troubleshooting by erasing all data from the Internal shared storage location on the computer. Data is not erased from the IPSM Card location.



Caution: An Enterprise data reset results in data loss, only perform this procedure if all other recovery methods have failed. All personal content is erased including, but not limited to emails, pictures, contacts, Google account information, system settings and app settings.

Note: *This method of recovery may not be available if your system administrator has set policies to prevent the reset use.*

Before You Begin

- If you recently reset your Google Account password, wait 24 hours before performing an Enterprise data reset.
- Make sure you have your screen lock password, PIN or pattern if you activated one. You will need this to reset the computer.
- If you have a Google Account, back up your data and settings to your Google Account so you can restore them if needed.
- Connect the computer to an external power source or make sure you have a full battery charge.

- Make sure you have an Internet connection.

Enterprise Data Reset the Computer

1. Swipe up from the bottom of the Home screen to access all apps.
2. Select **Settings**  > **System** > **Advanced** > **Reset options**.
3. Tap **Reset enterprise data**.
4. Tap **Erase all data**
5. If prompted, type your screen lock security pattern, PIN, or password and tap next ().
6. Tap **Erase all data**. A message appears informing you an Enterprise data reset is being performed.

About a Full Factory Reset

A full factory reset should only be performed if you have exhausted all other troubleshooting options. This method reverts the computer back to the factory state by erasing all data in Internal shared storage and the IPSM Card storage locations on the computer.



Caution: A Full factory reset results in data loss. Perform this procedure only if all other recovery methods have failed and have no other option. All personal content is erased including, but not limited to emails, pictures, contacts, Google account information, system settings and app settings.

Note: *This method of recovery may not be available if your system administrator has set policies to prevent the reset use.*

Before You Begin

- If you added a Google Account to the EDA5S computer, make sure you have your Google username and password associated with the computer. If you do not have the username and password, you will not be able to use the computer after the reset. This is a security measure that prevents unauthorized users from using the device if they try a Full factory reset.
- If you did not add a Google Account to the computer, the extra security level is not enabled and you will not need a Google username and password.
- If you recently reset your Google Account password, wait 24 hours before performing a Full factory reset.
- Connect the computer to an external power source or make sure you have a full battery charge.
- Make sure you have an Internet connection.

Full Factory Reset the Computer

1. Swipe up from the bottom of the Home screen to access all apps.
2. Select **Settings**  > **System** > **Advanced** > **Reset options**.
3. Tap **Erase all data (factory reset)**.
4. Tap **Erase all data**.
5. If prompted, type your screen lock security pattern, PIN, or password and tap next ().
6. Tap **Erase all data**. A message appears informing you an Enterprise data reset is being performed.

Repairs

Repairs and/or upgrades are not to be performed on this product. These services are to be performed only by an authorized service center (see [Customer Support](#) on page ix).

Maintenance

Your device provides reliable and efficient operation with a minimum of care. Although specific maintenance is not required, the following sections describe periodic checks to ensure dependable operation.

Clean the Computer

The computer housing, scanner window, camera window and touch screen may be cleaned with a soft cloth dampened with water or a mild detergent-water solution. If a mild detergent solution is used, wipe the computer with a clean cloth dampened only with water to remove any detergent residue.

Note: *Reading performance may degrade if the scanner window is not clean. If the window is visibly dirty, or if the scanner is not operating well, clean the window.*



Caution: Do not submerge the EDA5S in water or cleaning solution.

Caution: Do not use abrasive wipes or cloths on the windows or touch screen. Abrasive wipes may scratch the windows and touch screen. Never use solvents (e.g., acetone) on the housing or window. Solvents may damage the computer finish, the windows or touch screen.

Caution: Ensure all components are dry prior to mating the computer with charging accessories or other peripheral devices. Mating wet components may cause damage not covered by the warranty.

SPECIFICATIONS

Computer Agency Information


EDA5S mobile computers meet or exceed the requirements of all applicable standards organizations for safe operation. The best way to ensure safe operation is to use the mobile computer according to the agency guidelines on the product regulatory sheet, quick start guide, battery insert and in this user guide. Read all guidelines before using your computer.

Product documentation is available for download from www.honeywellaidc.com.

Public certificates are available for download from www.honeywellaidc.com/compliance.

Label Locations

Labels inside the battery compartment contain information about the computer including, compliance information, model number, serial number, IMEI number and MAC address. Laser safety labeling is located on the back of the computer.



Physical and Environmental Specifications

1. Go to www.honeywellaidc.com.
2. Type **EDA5S** in the Search box, and then press **Enter**.
3. Click on the product link in the search results.
4. Select one of the following tabs:
 - **Specifications**
View System Architecture, Wireless Connectivity, Mechanical, and Environmental specifications.
 - **Resources or Documents**
View and download available product documentation. For example, Data Sheet, Accessory Guide, Quick Start Guide, User Guide, Regulatory Information, Battery Information.

Imager Specifications

The EDA5S is equipped with the following Honeywell high-performance imager:

- S0703 Imager

Barcode Symbolologies

The computer supports the following barcode symbolologies:

1D Symbolologies		2D Symbolologies		Postal Codes	
	Default		Default		Default
Codabar	Enabled	Aztec Code	Enabled	China Post	Disabled
Code 39	Enabled	Codablock A	Disabled	Korean Post	Disabled
Code 11	Disabled	Codablock F	Disabled	2D Postal	Disabled
Code 93	Disabled	DataMatrix	Enabled		
Code 128	Enabled	DotCode	Disabled		
Composite	Disabled	Grid Matrix	Disabled		
EAN-8	Enabled	HanXin	Disabled		
EAN-13	Enabled	Maxicode	Disabled		
GS1-128	Enabled	Micro PDF 417	Disabled		
GS1 DataBar	Disabled	PDF 417	Enabled		
IATA 2 of 5	Disabled	QR Code	Enabled		
Standard 2 of 5	Disable	OCR	Disabled		
Interleaved 2 of 5	Enable	Digimarc	Disabled		
Matrix 2 of 5	Disable	TLC 39	Disabled		

1D Symbologies		2D Symbologies		Postal Codes	
	Default		Default		Default
MSI	Disable				
Telepen	Disable				
Trioptic	Disable				
UPC/EAN	Enabled				
UPC-A	Enabled				
UPC-E	Enabled				

Note: To learn about changing the symbology settings, see [Change the Scanner Settings](#) on page 32.

S0703 Imager

The depth of field measurements used the following parameters:

- Distances are measured from the front of the Imager.
- +23°C (+73°F), 0 lux for guaranteed, 200 lux for typical.
- Photographic quality codes

Note: Time to Read and Depth of Field are impacted if the barcode symbol is at the edge of the image.

Guaranteed Specs

Focus		Standard Range	
Symbology		Near Distance	Far Distance
5 mils Code 39	mm	79	270
	in.	3.11	10.63
10 mils Code 39	mm	40	450
	in.	1.57	17.72
20 mils Code 39	mm	44	674
	in.	1.73	26.53
13 mils 100% UPC-A	mm	44	515
	in.	1.73	20.27
15 mils Code 128	mm	42	572
	in.	1.65	22.52
10 mils Data Matrix	mm	83.1	236
	in.	3.27	9.29
5 mils PDF 417	mm	119	177.04
	in.	4.68	6.97

Focus		Standard Range	
Symbology		Near Distance	Far Distance
6.7 mils PDF 417	mm	96.01	236
	in.	3.78	9.29
15 mils QR	mm	39	390
	in.	1.54	15.35

Typical Specs

Focus		Standard Range	
Symbology		Near Distance	Far Distance
5 mils Code 39	mm	70	301
	in.	2.75	11.85
10 mils Code 39	mm	40	517
	in.	1.57	20.35
20 mils Code 39	mm	44	800
	in.	1.73	31.5
13 mils 100% UPC-A	mm	44	573
	in.	1.73	22.56
15 mils Code 128	mm	42	650
	in.	1.65	25.59
10 mils Data Matrix	mm	72	297
	in.	2.83	11.69
6.7 mils PDF 417	mm	84	244
	in.	3.31	9.61
15 mils QR	mm	39	414
	in.	1.54	16.30

S0703 Imager Field of View/Resolution

Focus	Standard Range (SR)
Horizontal Field Angle (degrees)	48 ± 2°
Vertical Field Angle (degrees)	31 ± 2°

DPI can be calculated based on the following formula:

Horizontal DPI = 1280 pixels/width of horizontal field of view (inches)

Vertical DPI = 800 pixels/width of vertical field of view (inches)

Honeywell
9680 Old Bailes Road
Fort Mill, SC 29707

www.honeywellaidc.com



Agency Models: EDA5S-0, EDA5S-1

Publicly downloadable certificates are available at www.honeywellaidc.com/compliance .	Les certificats téléchargeables accessibles au public sont disponibles à www.honeywellaidc.com/compliance .	Les certificats téléchargeables accessibles au public sont disponibles sur www.honeywellaidc.com/compliance .	I certificati pubblicamente scaricabili sono disponibili sul sito Web www.honeywellaidc.com/compliance .	Zertifikate stehen unter www.honeywellaidc.com/compliance öffentlich zum Download zur Verfügung.	Hay certificados descargables disponibles públicamente en www.honeywellaidc.com/compliance .	Puede descargar los certificados de acceso público en www.honeywellaidc.com/compliance .
Certificados disponíveis ao público para download em: www.honeywellaidc.com/compliance .	如需公开下载证书，请访问 www.honeywellaidc.com/compliance 。	如需公開下載證書，請造訪 www.honeywellaidc.com/compliance 。	一般にダウンロード可能な証明書は、 www.honeywellaidc.com/compliance で利用可能です。	공개적으로 다운로드 가능한 인증서는 www.honeywellaidc.com/compliance 에서 구할 수 있습니다.	Публичные сертификаты доступны на странице www.honeywellaidc.com/compliance .	الشهادات القابلة للتحميل متاحة العامة على الموقع www.honeywellaidc.com/compliance
Product documentation is available at www.honeywellaidc.com .	La documentation sur le produit est disponible à www.honeywellaidc.com .	La documentation du produit est disponible sur le site www.honeywellaidc.com .	La documentazione sul prodotto è disponibile sul sito www.honeywellaidc.com .	Die Produktdokumentation ist unter www.honeywellaidc.com verfügbar.	La documentación del producto está disponible en www.honeywellaidc.com .	La documentación del producto está disponible en www.honeywellaidc.com .
A documentação do produto está disponível em www.honeywellaidc.com .	产品文档请参见 www.honeywellaidc.com 。	產品文件集請參見 www.honeywellaidc.com 。	製品ドキュメントは www.honeywellaidc.com で利用可能です。	제품 설명서는 www.honeywellaidc.com 에서 확인할 수 있습니다.	Документацию по изделию можно найти на сайте www.honeywellaidc.com .	توفّر وثائق المنتج على الموقع التالي www.honeywellaidc.com .
Caution: Any changes or modifications made to this equipment not expressly approved by Honeywell International Inc. may void the authorization to operate this equipment.	MISE EN GARDE: Tout changement ou modification apportée(s) à cet équipement qui n'est pas expressément approuvée(e) par Honeywell International Inc. peut annuler l'autorisation d'utiliser cet équipement.	Mise en garde: tous les changements ou les modifications apportés à cet équipement non expressément approuvés par Honeywell International Inc. peuvent annuler l'autorisation d'utiliser cet équipement.	Attenzione: qualsiasi variazione o modifica apportata a questa apparecchiatura, non espressamente approvata da Honeywell International Inc., potrebbe annullare l'autorizzazione concessa all'utente per utilizzare l'apparecchiatura.	Vorsicht: Von Honeywell International Inc. nicht ausdrücklich genehmigte Veränderungen an diesem Gerät können dazu führen, dass die Betriebsgenehmigung für dieses Gerät erlischt.	Precaución: Cualquier modificación o cambio realizado en este equipo, no expresamente aprobado por Honeywell International Inc., puede anular la autorización para utilizar este equipo.	Precaución: cualquier cambio o modificación a este equipo que no esté expresamente aprobado por Honeywell International Inc. puede invalidar la autorización para usarlo.
Atenção: qualquer alteração ou modificação não aprovada expressamente pela Honeywell International Inc. neste equipamento poderá invalidar a autorização de operação.	注意: 对本设备进行任何未经 Honeywell International Inc. 明确准许的更改或修改, 可能会使操作本设备的授权失效。	注意: 凡未經 Honeywell International Inc. 明確准許即擅自變更或改造本設備者, 可能無權再操作本設備。	警告: Honeywell International Inc. の明示的な承認なしに、この機器を変更または改造すると、この機器を操作する権限が無効になる場合があります。	주의: Honeywell International Inc. 에 의해 확실한 승인을 받지 않은 방법으로 본 장비를 변경 또는 개조하는 경우 장비를 작동할 수 있는 승인이 취소될 수 있습니다.	Внимание! Любые изменения или модификации данного оборудования без одобрения компании Honeywell International Inc. могут привести к запрету эксплуатации данного оборудования.	تحذير: قد تؤدي أي تغييرات أو تعديلات على هذا الجهاز غير مصرح بها من Honeywell International Inc. شركة إلى إلغاء ترخيص تشغيل هذا الجهاز.

For body worn operation, this device has been tested and meets the limits regarding human exposure to electromagnetic radiation set forth in related CE rules, guidelines and standards for use with the following body worn accessory: holster. Use of other accessories may not ensure compliance with the mentioned rules.

Fonctionnement près du corps: ce dispositif a été testé et s'avère conforme aux règles et lignes directrices des normes EC, relatives aux limites d'une exposition humaine sécuritaire au rayonnement électromagnétique pour une utilisation près du corps de l'accessoire suivant: holster. L'utilisation d'autres accessoires peut ne pas assurer la conformité avec les règles mentionnées.

802.11 Caution: A Wireless Network Administrator should review the operating restrictions and use with a properly configured access point.						
Use only shielded data cables with this system.	Utiliser uniquement des câbles de données blindés avec ce système.	Utilisez uniquement des câbles de données blindés avec ce système.	Utilizzare solo cavi dati schermati con questo sistema.	Für dieses System nur abgeschirmte Datenkabel verwenden.	Utilice sólo cables de datos blindados con este sistema.	Use únicamente cables protegidos para datos con este sistema.
Use somente cabos de dados blindados com este sistema.	此系统仅能使用屏蔽数据电缆。	此系統只能使用包覆的資料傳輸線。	このシステムにはシールド付きデータケーブルのみを使用してください。	이 시스템에는 차폐된 데이터 케이블만 사용하십시오.	Используйте с этой системой только экранированные кабели передачи данных.	استخدم فقط كابلات البيانات المصحح مع هذا النظام.

Honeywell International Inc. hereby declares that the radio equipment types, non-specific SRD (Models: EDA5S-0, EDA5S-1) and cellular (Model: EDA5S-1), are in compliance with the following directives: • 2014/53/EU Radio Equipment • 2011/65/EU RoHS (Recast) The full text of the EU declaration of conformity is available at the following internet address: www.honeywellaidc.com/compliance. European contact: Honeywell Productivity Solutions BV Lagelandseweg 70 6545CG Nijmegen The Netherlands	Honeywell International Inc. déclare par la présente que les types d'équipement radio, SRD non spécifiques (modèles : EDA5S-0, EDA5S-1) et cellulaires (modèle : EDA5S-1) sont conformes aux directives suivantes : • Equipement radio 2014/53/UE • 2011/65/UE – RoHS (Refonte) Le texte intégral de la déclaration de conformité de l'UE est disponible à l'adresse Internet suivante : www.honeywellaidc.com/compliance. Personne-ressource en Europe : Honeywell Productivity Solutions BV Lagelandseweg 70 6545CG Nijmegen Les Pays-Bas	Honeywell International Inc. dichiara che i tipi di apparecchiature radio, SRD (dispositivi a corto raggio) non portee non specifiche (Modelli : EDA5S-0, EDA5S-1) e portabiles (Modello : EDA5S-1) sono conformi alle seguenti direttive: • 2014/53/UE - Apparecchiature radio • RoHS 2011/65/UE (rifusione) Il testo completo della Dichiarazione di conformità UE è disponibile al seguente indirizzo Internet: www.honeywellaidc.com/compliance. Contatto in Europa: Honeywell Productivity Solutions BV Lagelandseweg 70 6545CG Nijmegen Paesi Bassi	Honeywell International Inc. erklärt hiermit, dass das nicht näher spezifizierte SRD (Modelle: EDA5S-0, EDA5S-1) bzw. Mobilfunkgerät (Modell: EDA5S-1) folgende Richtlinien erfüllt: • Richtlinie 2014/53/UE (Funkanlagen) • 2011/65/UE RoHS (Recast) Die vollständige EU Konformitätserklärung finden Sie im Internet unter: www.honeywellaidc.com/compliance. Ansprechpartner Europa: Honeywell Productivity Solutions BV Lagelandseweg 70 6545CG Nijmegen Niederlande	Honeywell International Inc. declara que los tipos de equipo de radio, dispositivos de corto alcance (SRD) no específicos (modelos: EDA5S-0, EDA5S-1) y móviles (modelo: EDA5S-1), cumplen con las directivas siguientes: • 2014/53/UE sobre equipos de radio • 2011/65/UE RoHS (Refundida) El texto completo de la declaración de conformidad de la UE está disponible en la siguiente dirección de internet: www.honeywellaidc.com/compliance. Contacto europeo: Honeywell Productivity Solutions BV Lagelandseweg 70 6545CG Nijmegen Países Bajos	Honeywell International Inc. declara que los tipos de equipo de radio, SRD no específicos (modelos: EDA5S-0, EDA5S-1), son conforme a las siguientes directivas: • Normativa 2014/53/UE sobre equipos radioeléctricos • 2011/65/UE RoHS (Reformulada) El texto completo de la declaración de conformidad UE está disponible en la siguiente dirección de internet: www.honeywellaidc.com/compliance. Contacto europeo: Honeywell Productivity Solutions BV Lagelandseweg 70 6545CG Nijmegen Países Bajos
Por meio deste documento, a Honeywell International Inc. declara que os tipos de equipamento de rádio, sem SRD específico (modelos: EDA5S-0, EDA5S-1) e celular (modelo: EDA5S-1), estão em conformidade com as seguintes diretivas: • Equipamento de rádio 2014/53/UE • 2011/65/UE RoHS (Reformulação) O texto completo da declaração de conformidade da União Europeia está disponível em www.honeywellaidc.com/compliance. Contato na Europa: Honeywell Productivity Solutions BV Lagelandseweg 70 6545CG Nijmegen Holanda	Honeywell International Inc. 特此聲明，無線電設備類型「非特定 SRD」（型號：EDA5S-0, EDA5S-1）和「蜂窩式」（型號：EDA5S-1）符合以下指令的規範： • 2014/53/UE 無線電設備（新版） • 2011/65/UE RoHS（重訂） 关于欧盟符合性声明的全文，请访问以下网址：www.honeywellaidc.com/compliance。 欧洲联络信息： Honeywell Productivity Solutions BV Lagelandseweg 70 6545CG Nijmegen The Netherlands	Honeywell International Inc. 此聲明，無線電設備類型「非特定 SRD」（型號：EDA5S-0, EDA5S-1）および移動体通信（モデル：EDA5S-1）が、以下の指令に準拠することをここに宣言します。 • 2014/53/UE 無線電機器 • 2011/65/UE RoHS（重訂） 如需欧盟符合性聲明的全文，請造訪下列網址：www.honeywellaidc.com/compliance。 歐洲聯絡資訊： Honeywell Productivity Solutions BV Lagelandseweg 70 6545CG Nijmegen The Netherlands	Honeywell International Inc. 는 무선 장비 유형, 일반 SRD (모델: EDA5S-0, EDA5S-1) 및 셀룰러 (모델: EDA5S-1) 가 다음 지침을 준수함을 선언합니다. • 2014/53/UE 무선 장비 • 2011/65/UE RoHS (Recast) EU 준수 선언문의 전문은 인터넷 주소 www.honeywellaidc.com/compliance 에서 참조할 수 있습니다. 유럽 연락처: Honeywell Productivity Solutions BV Lagelandseweg 70 6545CG Nijmegen The Netherlands	Настоящим компания Honeywell International Inc. заявляет, что радиосистемы ближнего действия (модели EDA5S-0, EDA5S-1) и мобильные системы (модель EDA5S-1) соответствуют следующим директивам: • Директива 2014/53/ЕС по радиооборудованию • 2011/65/ЕС Директива RoHS (исправленная) Полный текст декларации соответствия стандартам ЕС доступен на странице www.honeywellaidc.com/compliance. Контактное лицо в Европе: Honeywell Productivity Solutions BV Lagelandseweg 70 6545CG Nijmegen The Netherlands	هoneywell شركة International أن أنواع المعدات الأسلاك، والهجرة القصيرة المدى (SRD) (النموذج: EDA5S-0, EDA5S-1، EDA5S-1) متوافقة مع التوجيهات التالية: • جهاز الإرسال الأسلكي وفقا للوائح الاتحاد الأوروبي: 2014/53 (المعاد) • توجيهات الاتحاد الأوروبي: 2011/65 (المعاد) يمكنك الاطلاع على النص الكامل لإعلان المطابقة وفقا للوائح الاتحاد الأوروبي بزيارة الموقع التالي: www.honeywellaidc.com/compliance جهات الاتصال الأوروبية: Honeywell Productivity Solutions BV Lagelandseweg 70 6545CG Nijmegen هولندا

United Kingdom Contact: United Kingdom Honeywell Scanning and Mobility, Honeywell House, Skimped Hill Lane, Bracknell, Berkshire, RG12 1EB Phone: +44 (0)1344921052

The equipment is intended for use throughout the European Community.

Operating Frequency Ranges

- Model: EDA5S-1
- 13-14 MHz (NFC): -19.56 dBµA/m @10 m EIRP
 - 2400-2483.5 MHz (PAN Bluetooth): 6.80 dBm EIRP
 - 2400-2483.5 MHz (Bluetooth Low Energy): 6.73 dBm EIRP
 - 2400-2483.5 MHz (WLAN IEEE 802.11b/g/n): 17.40 dBm EIRP
 - 5150-5350 MHz, 5470-5725 MHz and 5725-5875 MHz (WLAN/RLAN IEEE 802.11a/n/ac): 17.12 dBm, 17.01 dBm, and 13.10 dBm (5G B4) EIRP
 - 1710-1785 / 1805-1880 MHz (LTE Band 3, Tx/Rx): 23.21 dBm
 - 2500-2570 / 2620-2690 MHz (LTE Band 7, Tx/Rx): 22.33 dBm
 - 832-862 / 791-821 MHz (LTE Band 20, Tx/Rx): 24.27 dBm
 - 1920-1980 / 2110-2170 MHz (LTE Band 1, Tx/Rx): 22.73 dBm
 - 880-915 / 925-960 MHz (LTE Band 8, Tx/Rx): 23.15 dBm
 - 703-748 / 758-803 MHz (LTE Band 28, Tx/Rx): 23.85 dBm
 - 2570-2620 MHz (LTE Band 38): 22.92 dBm
 - 2300-2400 MHz (LTE Band 40): 22.64 dBm
 - 880-915 / 925-960 MHz (UMTS 900 Band, Tx/Rx): 23.90 dBm
 - 1920-1980 / 2110-2170 MHz (UMTS 2100 Band, Tx/Rx): 24.99 dBm
 - 880-915 / 925-960 MHz (GSM/EGPRS GSM 900 Band, Tx/Rx): 33.71 dBm
 - 1710-1785 / 1805-1880 MHz (GSM/EGPRS DCS 1800 Band, Tx/Rx): 30.89 dBm

Restrictions (Revision ERC/REC 70-03 E 2017-02, Annex 3 Band A: 2400-2483.5 MHz):	
AZ	No license needed if used indoor and power not exceeding 30 mW.
IT	The public use is subject to general authorization by the respective service provider.
RU	SRD with FHSS modulation • Maximum 2.5 mW EIRP. • Maximum 100 mW EIRP. Permitted for use SRD for outdoor applications without restriction on installation height only for purposes of gathering telemetry information for automated monitoring and resources accounting systems. Permitted to use SRD for other purposes for outdoor applications only when the installation height is not exceeding 10 m above the ground surface. • Maximum 100 mW EIRP. Indoor applications SRD with DSSS and other than FHSS wideband modulation • Maximum mean EIRP density is 2 mW/MHz. Maximum 100 mW EIRP. • Maximum mean EIRP density is 20 mW/MHz. Maximum 100 mW EIRP. It is permitted to use SRD for outdoor applications only for purposes of gathering telemetry information for automated monitoring and resources accounting systems or security systems. • Maximum mean EIRP density is 10 mW/MHz. Maximum 100 mW EIRP. Indoor applications
UA	EIRP =100 mW with built-in antenna with amplification factor up to 6 dBi

L'équipement est prévu pour une utilisation dans les pays de la Communauté européenne.

Plages de fréquences de fonctionnement :

- Modèle: EDA5S-0
- 13 à 14 MHz (NFC): PIRE -19.56 dBµA/m @10 m
 - 2 400 à 2 483.5 MHz (PAN Bluetooth) : PIRE 6.80 dBm
 - 2 400 à 2 483.5 MHz (Bluetooth à basse énergie) : PIRE 6.73 dBm
 - 2 400 à 2 483.5 MHz (WLAN IEEE 802.11b/g/n) : PIRE 17.40 dBm
 - 5 150 à 5 350 MHz, 5 470 à 5 725 MHz et 5 725 à 5 850 MHz (WLAN/RLAN IEEE 802.11a/n/ac) : PIRE 17.12 dBm et 17.01 dBm et 13.10 dBm (5G B4)
- Modèle: EDA5S-1
- 13 à 14 MHz (NFC): PIRE -19.56 dBµA/m @10 m
 - 2 400 à 2 483.5 MHz (PAN Bluetooth) : PIRE 6.80 dBm
 - 2 400 à 2 483.5 MHz (Bluetooth à basse énergie) : PIRE 6.73 dBm
 - 2 400 à 2 483.5 MHz (WLAN IEEE 802.11b/g/n) : PIRE 17.40 dBm
 - 5 150 à 5 350 MHz, 5 470 à 5 725 MHz et 5 725 à 5 850 MHz (WLAN/RLAN IEEE 802.11a/n/ac) : PIRE 17.12 dBm et 17.01 dBm et 13.10 dBm (5G B4)
 - 1 710 à 1 785 / 1 805-1 880 MHz (LTE bande 3, Tx/Rx): 23.21 dBm
 - 2 500 à 2 570 / 2 620 à 2 690 MHz (LTE bande 7, Tx/Rx): 22.33 dBm
 - 832 à 862 / 791 à 821 MHz (LTE bande 20, Tx/Rx): 24.27 dBm
 - 1 920 à 1 980 / 2 110 à 2 170 MHz (LTE bande 1, Tx/Rx): 22.73 dBm
 - 880 à 915 / 925 à 960 MHz (LTE bande 8, Tx/Rx): 23.15 dBm
 - 703 à 748 / 758 à 803 MHz (LTE bande 28, Tx/Rx): 23.85 dBm
 - 2 570 à 2 620 MHz (LTE bande 38): 22.92 dBm
 - 2 300 à 2 400 MHz (LTE bande 40): 22.64 dBm
 - 880 à 915 / 925 à 960 MHz (bande de 900 MHz pour UMTS, Tx/Rx): 23.90 dBm
 - 1 920 à 1 980 / 2 110 à 2 170 MHz (bande de 2100 MHz pour UMTS, Tx/Rx): 24.99 dBm
 - 880 à 915 / 925 à 960 MHz (bande de 900 MHz pour GSM/EGPRS GSM, Tx/Rx): 33.71 dBm
 - 1 710 à 1 785 / 1 805 à 1 880 MHz (bande de 1800 MHz pour GSM/EGPRS DCS, Tx/Rx): 30.89 dBm

Restrictions (révision ERC/REC 70-03 E 2017-02, Annexe 3 bande A : 2 400 à 2 483.5 MHz)	
AZ	Aucune licence nécessaire pour une utilisation à l'intérieur et une puissance ne dépassant pas 30 mW.
IT	L'usage public est soumis à une autorisation générale du fournisseur de service respectif.
RU	Appareil de faible portée (SRD) avec modulation FHSS • Puissance isotrope rayonnée équivalente (PIRE) maximale 2,5 mW. • Puissance isotrope rayonnée équivalente (PIRE) maximale 100 mW. L'usage du SRD est autorisé pour les applications extérieures sans restriction de hauteur d'installation et uniquement à des fins de collecte de données de télémétrie pour la surveillance automatisée et les systèmes de comptabilité des ressources. L'usage du SRD est autorisé à d'autres fins pour les applications extérieures uniquement lorsque la hauteur d'installation ne dépasse pas les 10 m au-dessus de la surface du sol. • Puissance isotrope rayonnée équivalente (PIRE) maximale 100 mW. Applications à l'intérieur SRD avec DSSS et une technique autre que la modulation FHSS à large bande • La densité de PIRE moyenne maximale est de 2 mW/MHz. Puissance isotrope rayonnée équivalente (PIRE) maximale 100 mW. • La densité de PIRE moyenne maximale est de 20 mW/MHz. Puissance isotrope rayonnée équivalente (PIRE) maximale 100 mW. Il est permis d'utiliser le SRD pour les applications extérieures uniquement aux fins de la collecte de données de télémétrie pour la surveillance automatisée et les systèmes de comptabilité des ressources ou les systèmes de sécurité. • La densité de PIRE moyenne maximale est de 10 mW/MHz. Puissance isotrope rayonnée équivalente (PIRE) maximale 100 mW. Applications à l'intérieur
UA	PIRE = 100 mW avec une antenne intégrée dotée d'un facteur d'amplification jusqu'à 6 dBi

Models: EDA5S-0

- 13-14 MHz (NFC): -19.56 dBµA/m @10 m EIRP
- 2400-2483.5 MHz (PAN Bluetooth): 6.80 dBm EIRP
- 2400-2483.5 MHz (Bluetooth Low Energy): 6.73 dBm EIRP
- 2400-2483.5 MHz (WLAN IEEE 802.11b/g/n): 17.40 dBm EIRP
- 5150-5350 MHz, 5470-5725 MHz and 5725-5875 MHz (WLAN/RLAN IEEE 802.11a/n/ac): 17.12 dBm, 17.01 dBm, and 13.10 dBm (5G B4) EIRP

802.11a/b/g/n/ac, Bluetooth and NFC

European Community Restrictions: 5150-5350 MHz is for indoor use only.

	AT	BE	BG	HR	CY	CZ	DK	EE	FI	FR	DE	GR
	HU	IS	IE	IT	LV	LI	LT	LU	MT	NL	NO	PL
	PT	RO	SK	SI	ES	SE	CH	RU	RS	TR	UK	UK(NI)

Restrictions (Revision ERC/REC 70-03 E 2017-02, Annex 13 Band E1: 5150-5350 MHz, Band E2: 5470-5725 MHz):	
AZ	No license needed if used indoor and power not exceeding 30 mW

Restrictions (Revision ERC/REC 70-03 E 2017-02, Annex 9 Band J2: 13553-13567 kHz):	
AZ	Not implemented or no information.
BY	Not implemented.
GE	Not implemented.
RU	Maximum magnetic field strength is +42 dBµA/m at 10 m.
UA	The maximal strength of magnetic field on the distance of 10 m from a construction where the radiator is placed is 42 dBµA/m.

802.11a/b/g/n/ac, Bluetooth et NFC

Restrictions : la bande de fréquences 5 150-5 350 MHz est limitée à une utilisation à l'intérieur uniquement.

	AT	BE	BG	HR	CY	CZ	DK	EE	FI	FR	DE	GR
	HU	IS	IE	IT	LV	LI	LT	LU	MT	NL	NO	PL
	PT	RO	SK	SI	ES	SE	CH	RU	RS	TR	UK	UK(NI)

Restrictions (révision ERC/REC 70-03 E 2017-02, Annexe 13 bande E1 : 5 150 à 5 350 MHz, bande E2 : 5 470 à 5 725 MHz)	
AZ	Aucune licence nécessaire pour une utilisation à l'intérieur et une puissance ne dépassant pas30 mW.

Restrictions (révision ERC/REC 70-03 E 2017-02, Annexe 9 bande J2 : 13 553 à 13 567 KHz) :	
AZ	Non applicable ou aucune information.
BY	Non applicable.
GE	Non applicable.
RU	L'intensité maximale du champ magnétique est +42 dBµA/m à 10 m.
UA	L'intensité maximale du champ magnétique à une distance de 10 m d'une construction dans laquelle le radiateur est placé est de 42 dBµA/m.

<

Оборудование предназначено для эксплуатации на всей территории Европейского сообщества.

Рабочий диапазон частот:

Модели: EDA5S-0

- 13–14 МГц (NFC): EIRP -19.56 дБмкА/м @10 м
- 2402–2480 МГц (Bluetooth-PAN): EIRP 6.80 дБм
- 2402–2480 МГц (технология Bluetooth с низким энергопотреблением): EIRP 6.73 дБм
- 2412–2472 МГц (WLAN 2.4G IEEE 802.11b/g/n): EIRP 17.40 дБм
- 5150–5350 МГц, 5470–5725 МГц и 5725–5850 МГц (WLAN/RLAN IEEE 802.11a/n/ac): EIRP 17.12 дБм 17.01 дБм и 13.10 дБм

Модели: EDA5S-1

- 13–14 МГц (NFC): EIRP -19.56 дБмкА/м @10 м
- 2402–2480 МГц (Bluetooth-PAN): EIRP 6.80 дБм
- 2402–2480 МГц (технология Bluetooth с низким энергопотреблением): EIRP 6.73 дБм
- 2412–2472 МГц (WLAN 2.4G IEEE 802.11b/g/n): EIRP 17.40 дБм
- 5150–5350 МГц, 5470–5725 МГц и 5725–5850 МГц (WLAN/RLAN IEEE 802.11a/n/ac): EIRP 17.12 дБм 17.01 дБм и 13.10 дБм
- 1710–1785 / 1805–1880 МГц (LTE Band 3, Tx/Rx): 23.21 дБм
- 2500–2570 / 2620–2690 МГц (LTE Band 7, Tx/Rx): 22.33 дБм
- 832–862 / 791–821 МГц (LTE Band 20, Tx/Rx): 24.27 дБм
- 1920–1980 / 2110–2170 МГц (LTE Band 1,Tx/Rx): 22.73 дБм
- 880–915 / 925–960 МГц (LTE Band 8, Tx/Rx): 23.15 дБм
- 703–748 / 758–803 МГц (LTE Band 28, Tx/Rx): 23.85 дБм
- 2570–2620 МГц (LTE Band 38): 22.92 дБм
- 2300–2400 МГц (LTE Band 40): 22.64 дБм
- 880–915 / 925–960 МГц (диапазон UMTS 900, Tx/Rx): 23.90 дБм
- 1920–1980 / 2110–2170 МГц (диапазон UMTS 2100, Tx/Rx): 24.99 дБм
- 880–915 / 925–960 МГц (диапазон GSM/EGPRS GSM 900, Tx/Rx): 33.71 дБм
- 1710–1785 / 1805–1880 МГц (диапазон GSM/EGPRS DCS 1800, Tx/Rx): 30.89 дБм

Ограничения (проверка ERC/REC 70-03 E 2017-02, приложение 3, диапазон A: 2400–2483,5 МГц)

AZ

При эксплуатации в помещении с мощностью не более 30 мВт разрешение не требуется.

IT

Общественное использование оборудования возможно с разрешения соответствующего поставщика услуг.

RU

Устройство малого радиуса действия (SRD) с модуляцией FHSSMaximum 2.5 mW EIRP.

- Максимальная эффективная изотропно излучаемая мощность (EIRP) 2,5 мВт.
- Максимальная эффективная изотропно излучаемая мощность (EIRP) 100 мВт. Эксплуатация SRD разрешена только вне помещений без ограничений по высоте установки и для сбора данных телеметрии для систем автоматического управления и учета ресурсов. Разрешается эксплуатировать SRD в других целях только вне помещений, если высота установки не превышает 1,0 м над уровнем земли.
- Максимальная эффективная изотропно излучаемая мощность (EIRP) 100 мВт. Эксплуатация **внутри помещений.SRD with DSSS and other than FHSS wideband modulation**
- Максимальная средняя плотность EIRP 2 мВт/МГц. Максимальная эффективная изотропно излучаемая мощность (EIRP) 100 мВт
- Максимальная средняя плотность EIRP 20 мВт/МГц. Максимальная эффективная изотропно излучаемая мощность (EIRP) 100 мВт. Эксплуатация SRD разрешена только вне помещений для сбора данных телеметрии для систем автоматического управления, учета ресурсов или безопасности.
- Максимальная средняя плотность EIRP 10 мВт/МГц. Максимальная эффективная изотропно излучаемая мощность (EIRP) 100 мВт. Эксплуатация внутри помещений.

UA

EIRP = 100 мВт со встроенной антенной с коэффициентом усиления до 6 дБи.

802.11a/b/g/n/ac, Bluetooth и NFC

Ограничения : полосы радиочастот 5150–5350 МГц предназначены для использования только в помещениях.

AT

BE

IS

BG

IE

HR

IT

CY

LV

CZ

LI

DK

LT

EE

LU

FI

MT

FR

NL

DE

NO

GR

PL

PT

RO

SK

SI

ES

SE

CH

RU

RS

TR

UK

UK(NI)

Ограничения (проверка ERC/REC 70-03 E 2017-02, приложение 13, диапазон E1: 5150–5350 МГц, диапазон E2: 5470–5725 МГц)

AZ

При эксплуатации в помещении с мощностью не более 30 мВт разрешение не требуется.

Ограничения (проверка ERC/REC 70-03 E 2017-02, приложение 9 диапазон J2: 13553–13567 кГц):
Примечание. Это ограничение распространяется только на модели NFC.

AZ

Не используется или нет данных.

BY

Не используется .

GE

Не используется .

RU

Максимальная сила магнитного поля составляет +42 дБмкА/м на расстоянии 10 м.

UA

Максимальная сила магнитного поля на расстоянии 10 м от места установки радиатора составляет 42 дБмкА/м.

Bu donanım, Avrupa Birliği ülkelerinin tümünde kullanılabilir.

Çalışma Frekans Aralıkları:

Modeller: EDA5S-0

- 13 – 14 MHz (NFC): -19.56 dBµA/m @10 m EIRP
- 2400 – 2483.5 MHz (PAN Bluetooth): 6.80 dBm EIRP
- 2400 – 2483.5 MHz (Bluetooth Düşük Enerji): 6.73dBm EIRP
- 2400 – 2483.5 MHz (WLAN IEEE 802.11b/g/n): 17.40 dBm EIRP
- 5150 – 5350 MHz, 5470 – 5725 MHz ve 5725 – 5850 MHz (WLAN/RLAN IEEE 802.11a/n/ac): 17.12 dBm 17.01 dBm ve 13.10 dBm (5G B4) EIRP

Modeller: EDA5S-1

- 13 – 14 MHz (NFC): -19.56 dBµA/m @10 m EIRP
- 2400 – 2483.5 MHz (PAN Bluetooth): 6.80 dBm EIRP
- 2400 – 2483.5 MHz (Bluetooth Düşük Enerji): 6.73 dBm EIRP
- 2400 – 2483.5 MHz (WLAN IEEE 802.11b/g/n): 17.40 dBm EIRP
- 5150 – 5350 MHz, 5470 – 5725 MHz ve 5725 – 5850 MHz (WLAN/RLAN IEEE 802.11a/n/ac): 17.12 dBm 17.01 dBm ve 13.10 dBm (5G B4) EIRP
- 1710 – 1785 / 1805 – 1880 MHz (LTE Bant 3, Tx/Rx): 23.21 dBm
- 2500 – 2570 / 2620 – 2690 MHz (LTE Bant 7, Tx/Rx): 22.33 dBm
- 832 – 862 / 791 – 821 MHz (LTE Bant 20, Tx/Rx): 24.27 dBm
- 1920 – 1980 / 2110 – 2170 MHz (LTE Bant 1,Tx/Rx): 22.73 dBm
- 880 – 915 / 925 – 960 MHz (LTE Bant 8, Tx/Rx): 23.15 dBm
- 703 – 748 / 758 – 803 MHz (LTE Bant 28, Tx/Rx): 23.85 dBm
- 2570 – 2620 MHz (LTE Bant 38): 22.92 dBm
- 2300 – 2400 MHz (LTE Bant 40): 22.64 dBm
- 880 – 915 / 925 – 960 MHz (UMTS 900 Bant, Tx/Rx): 23.90 dBm
- 1920 – 1980 / 2110 – 2170 MHz (UMTS 2100 Bant, Tx/Rx): 24.99 dBm
- 880 – 915 / 925 – 960 MHz (GSM/EGPRS GSM 900 Bant, Tx/Rx): 33.71 dBm
- 1710 – 1785 / 1805 – 1880 MHz (GSM/EGPRS DCS 1800 Bant, Tx/Rx): 30.89 dBm

Kısıtlamalar (Revizyon ERC / REC 70-03 E 2017-02, Ek 3 Bant A: 2400 – 2483,5 MHz)

AZ

İç mekanlarda ve 30 mW'ı aşmayan güç kullanıldığında lisans gerekli değildir.

IT

Kamu kullanımı, ilgili hizmet sağlayıcısı tarafından genel izne tabidir.

RU

FHSS modülasyonlu SRD

- Maksimum 2,5 mW EIRP.
- Maksimum 100 mW EIRP. Kurulum yüksekliğinde kısıtlama olmaksızın dış mekan uygulamaları için SRD kullanımına yalnızca otomatik izleme ve kaynak hesaplama sistemleri için telemetri bilgileri toplamak amacıyla izin verilir. Yalnızca kurulum yüksekliği zemin yüzeyinden maksimum 10 m yukarıda olduğunda dış mekan uygulamalarında diğer amaçlar için SRD kullanımına izin verilir.
- Maksimum 100 mW EIRP. İç mekan uygulamaları.

FHSS geniş bant modülasyonu dışında DSSS'li SRD

- Maksimum ortalama EIRP yoğunluğu 2 mW/MHz'dir. Maksimum 100 mW EIRP.
- Maksimum ortalama EIRP yoğunluğu 20 mW/MHz'dir. Maksimum 100 mW EIRP. Dış mekan uygulamaları için yalnızca otomatik izleme ve kaynak hesaplama sistemleri veya güvenlik sistemleri için telemetri bilgileri toplamak amacıyla SRD kullanımına izin verilir.
- Maksimum ortalama EIRP yoğunluğu 10 mW/MHz'dir. Maksimum 100 mW EIRP. İç mekan uygulamaları.

UA

EIRP = 100 mW, amplifikasyon faktörü 6 dBi'ye kadar olan dahili anten ile.

802.11a/b/g/n/ac, Bluetooth ve NFC

Kısıtlamalar: 5150–5350 MHz sadece kapalı alanda kullanım içindir.

AT

BE

BG

HR

CY

CZ

DK

EE

FI

FR

DE

GR

HU

IS

IE

IT

LV

LI

LT

LU

MT

NL

NO

PL

PT

RO

SK

SI

ES

SE

CH

RU

RS

TR

UK

UK(NI)

Kısıtlamalar (Revizyon ERC / REC 70-03 E 2017-02, Ek 13 Bant E1: 5150 – 5350 MHz, Bant E2: 5470 – 5725 MHz)

AZ

İç mekanlarda ve 30 mW'ı aşmayan güç kullanıldığında lisans gerekli değildir.

Kısıtlamalar (Revizyon ERC / REC 70-03 E 2017-02, Ek 9 Bant J2: 13553–13567 kHz):

AZ

Uygulanmadı veya bilgi yok.

BY

Uygulanmadı.

GE

Uygulanmadı.

RU

Maksimum manyetik alan kuvveti 10 m'de +42 dBµA/m'dir.

UA

Radyatörün yerleştirildiği bir yapıdan 10 m mesafedeki manyetik alanın azamı gücü 42 dBµA/m'dir.

Product Environmental Information Refer to www.honeywellaidc.com/environmental for the RoHS / REACH / WEEE information.	Renseignements relatifs à l'environnement à propos des produits Reportez-vous à la page www.honeywellaidc.com/environmental pour obtenir des renseignements concernant les directives RoHS/REACH/ WEEE.	Informazioni ambientali relative al prodotto Consultare il sito web www.honeywellaidc.com/environmental per informazioni su RoHS/REACH/ RAEE.	Informazioni zur Umweltverträglichkeit von Produkten Unter www.honeywellaidc.com/environmental finden Sie Informationen über RoHS/ REACH/WEEE.	Información ambiental del producto Consulte www.honeywellaidc.com/environmental para obtener información sobre RoHS/ REACH/WEEE.	Información ambiental de producto Consulte la información RoHS/REACH/ WEEE en www.honeywellaidc.com/environmental .
Informações ambientais sobre produtos Consulte a página www.honeywellaidc.com/environmental para obter informações sobre as normas RoHS/REACH/WEEE.	产品信息信息 有关 RoHS / REACH / WEEE 信息，请参阅 www.honeywellaidc.com/environmental 。	產品環境資訊 請參閱 www.honeywellaidc.com/environmental 以瞭解 RoHS / REACH / WEEE 資訊。	製品の環境情報 RoHS / REACH / WEEE に関する情報については、 www.honeywellaidc.com/environmental を参照してください。	제품 환경 정보 RoHS / REACH / WEEE 정보는 www.honeywellaidc.com/environmental 에서 참조하십시오.	Экологическая информация о продукции Информация о соответствии требованиям RoHS / REACH / WEEE приведена на сайте www.honeywellaidc.com/environmental .
					المواصفات البيئية للمنتج يُرجى الرجوع إلى www.honeywellaidc.com/environmental

CUIDADO: a substituição incorreta da bateria ou o uso de um dispositivo incompatível pode resultar em riscos de queimaduras, incêndio, explosão ou outros perigos. Descarte as baterias de ion de lítio de acordo com as regulamentações locais.	注意：電池更換不當或者用于不兼容的设备可能导致燃烧、起火、爆炸或其他危险。请按照当地规定处置锂电池。	注意：不適當的電池更換或者與不相容的裝置搭配使用，可能導致燃燒、火災、爆炸或其他危險。請依照當地法規處置锂电池。	注意：誤った電池交換または互換性の無いデバイス使用により、やけど、発火、爆発などの危険をお引きこす可能性があります。リチウムイオン電池の廃棄については、地域の規則に従ってください。	주의：배터리를 부적절하게 교체하거나 호환되지 않는 장비를 사용하게 되면, 화상, 화재, 폭발, 기타 위험이 발생할 수 있습니다. 지역 규정에 따라 리튬 이온 배터리를 처리하십시오.	ВНИМАНИЕ: В случае неправильной замены аккумулятора или использования несовместимого устройства существует опасность ожога, пожара, взрыва, а также других несчастных случаев. Утилизация литий-ионных аккумуляторов должна производиться в соответствии с местными нормативами.	تحذير: قد يتسبب استخدام بطارية غير صحيحة أو الاستعمال غير المتوافق للجهاز في الإصابة بحروق أو اندلاع حريق أو حدوث انفجارات أو التسبب بمخاطر أخرى. يجب التخلص من البطاريات وفقاً للوائح المحلية.
RF Exposure Information (SAR) This mobile phone meets the government's requirements for exposure to radio waves. The exposure standard for wireless mobile phones employs a unit of measurement known as the Specific Absorption Rate, or SAR. The SAR limit set by the government for Europe is 2 W/Kg. Although the SAR is determined at the highest certified power level, the actual SAR level of the phone while operating can be well below the maximum value. This is because the phone is designed to operate at multiple power levels so as to use only the power required to reach the network. In general, the closer you are to a wireless base station antenna, the lower the power output. Model EDA5S-0 CE SAR The highest reported CE SAR value for head and body-worn accessory use conditions are: 0.21 W/kg (10 g) and 1.54 W/kg (10g). Model EDA5S-1 CE SAR The highest reported CE SAR values for head, body-worn accessory and simultaneous transmission use conditions are: 0.30 W/kg (10g), 1.07 W/kg (10g), and 3.35 W/kg (10g). For body-worn operation, this device has been tested and meets the ICNIRP guidelines and the European Standard EN62209-2, for use with dedicated accessories. SAR is measured with this device at a separation of 5mm to the body. While there may be differences between the SAR levels of various phones and at various positions, they all meet the government requirement. Caution: If a body worn accessory is not purchased from Honeywell, the accessory must contain no metal and provide a 1.5 cm (0.6 in) space between the device and the body. Use of antennas and accessories not authorized may void the compliance of this product and may result in RF exposures beyond the limits established for this equipment.				Informations sur l'exposition RF Ce téléphone mobile respecte les exigences du gouvernement en matière d'exposition aux ondes radio. Ce téléphone est conçu et fabriqué de manière à ne pas dépasser les limites d'émission pour l'exposition à l'énergie de radiofréquence (RF) établies par la Commission fédérale des communications des gouvernements américain et canadien. La norme d'exposition pour les téléphones mobiles sans fil utilise une unité de mesure connue sous le nom de débit d'absorption spécifique ou DAS. La limite du DAS établie et de 2W/kg pour l'Europe. Bien que le DAS soit déterminé en fonction du plus haut niveau de puissance certifié, le niveau réel du DAS du téléphone en cours d'utilisation peut être nettement inférieur à la valeur maximale. Ceci s'explique par le fait que le téléphone est conçu pour fonctionner à plusieurs niveaux de puissance ainsi que pour utiliser uniquement le puissance requis pour atteindre le réseau. En général, plus vous vous trouvez à proximité d'une antenne de station de base sans fil, plus la puissance de sortie sera faible. Modèle EDA5S-0 DAS IC Les valeurs DAS IC les plus élevées pour les conditions d'utilisation des accessoires portés sur la tête et le corps sont les suivantes: 0.21 W/kg (10g) et 1.54 W/kg (10g). Mise en garde : Si un accessoire de corps n'est pas acheté auprès d'Intermec, cet accessoire ne doit contenir aucun métal et garantir un espace de 1,5 cm entre l'appareil et le corps. L'utilisation d'antennes et d'accessoires non autorisés peut annuler la conformité de cet appareil et peut causer une exposition aux RF au-delà des limites établies pour cet équipement.		
Patents For patent information, refer to www.hsmpts.com. Patentes Para obter informações sobre patente, consulte www.hsmpts.com.	Brevets Veuillez consulter le site www.hsmpts.com pour obtenir des renseignements au sujet du brevet. 專利 有关专利信息，请参阅 www.hsmpts.com。	Brevets Pour plus d'informations sur les brevets, visitez la page www.hsmpts.com. 專利 相關專利資訊請參閱 www.hsmpts.com 中的說明。	Brevetti Per i dettagli sui brevetti, fare riferimento al sito Web www.hsmpts.com. 特許 特許情報については、 www.hsmpts.com を参照してください。	Patente Patentinformationen sind unter www.hsmpts.com erhältlich. 특허 특허 정보는 www.hsmpts.com 를 참조하십시오 .	Patentes Para obtener información sobre las patentes, visite www.hsmpts.com. Патенты Информация о патентах приведена на веб-странице www.hsmpts.com.	Patentes Para obtener información sobre la garantía, visite el sitio www.honeywellaidc.com y haga clic en Recursos > Garantía del producto. براءات الاختراع للحصول على معلومات براءة الاختراع، قم بزيارة الموقع التالي: www.hsmpts.com.
For warranty information, go to www.honeywellaidc.com and click Resources > Product Warranty. Para ver informações sobre a garantia, acesse www.honeywellaidc.com e clique em Recursos > Garantia do produto.	Pour obtenir des renseignements sur la garantie, rendez-vous sur www.honeywellaidc.com et cliquez sur Ressources > Garantie du produit. 有关保修信息，请访问 www.honeywellaidc.com， 辦理 资源 > 产品质量保证书。	Pour obtenir des informations sur la garantie, rendez-vous sur www.honeywellaidc.com et cliquez sur Ressources > Garantie du produit. 如需瞭解產品資訊，請前往 www.honeywellaidc.com，然後按保修資源 > 產品諮詢按	Per informazioni sulla garanzia, visitare www.honeywellaidc.com e fare clic su Risorse > Garanzia prodotto. 保証情報については、 www.honeywellaidc.com に移動し、リソース > 製品保証をクリックしてください。	Informationen zur Garantie finden Sie auf unserer Website www.honeywellaidc.com unter Ressourcen > Produkt garantie. 보증 정보는 www.honeywellaidc.com 을 방문하여 자료 > 제품 보증 를 선택하십시오 .	Para obtener información sobre la garantía, vaya a www.honeywellaidc.com y haga clic en Recursos > Garantía del producto. Для получения гарантийной информации перейдите на сайт www.honeywellaidc.com и выберите Доступ к ресурсам > Гарантия на продукт.	Para obtener información sobre la garantía, visite el sitio www.honeywellaidc.com y haga clic en Recursos > Garantía del producto. للحصول على معلومات الضمان، انتقل إلى www.honeywellaidc.com وانقر فوق الموارد > ضمان المنتج
This document was prepared and executed in the English language. In the event this document is translated into another language and a conflict arises between the English version and a non-English version, the English version shall prevail, it being recognized and acknowledged that the English language version most clearly expresses the intent of the parties. Any notice or communication given in connection with this document must include a version in the English language. Este documento foi preparado e feito em lingua inglesa. Se este documento for traduzido para outro idioma e surgirem conflitos entre a versão em inglês e a versão no outro idioma, a versão em inglês prevalecerá, sendo reconhecido e atestado que a versão em língua inglesa expressa mais claramente a intenção das partes. Qualquer comunicação ou aviso relacionado a este documento deve conter a versão em inglês.	Ce document a été préparé et exécuté dans la langue anglaise. Dans l'éventualité où le document serait traduit dans une autre langue et qu'un litige survient entre la version en anglais et la version autre qu'en anglais, la version en anglais prévaudra, étant confirmé et reconnu que la version en anglais exprime de façon plus précise l'intention des parties. Tout avis ou toute communication relatif à ce document doit inclure une version en anglais. 本文档以英文撰写。如果本文档的其他语言版本与英文版存在冲突，则以英文版为基准，各方一致认可和同意英文版最清楚地表达了各自的意图。任何与本文档相关的声明或沟通，都应包括英文版本。	Ce document a été préparé et finalisé en anglais. Si ce document est traduit dans une autre langue et si un conflit survient entre la version en anglais et la version traduite, la version en anglais prévaudra tant il est reconnu et établi qu'elle exprime le plus clairement les intentions des parties. Tout avis ou communication produit en relation avec ce document doit comporter une version en anglais. 本文件的原稿是以英文撰寫。如果本文件翻譯為其他語言，而英文版和非英文版之間產生衝突，應以英文版為準，並且各方一致認同並確認英文版最能夠清楚地表達各方的意圖。凡是所有與本文件有關之公告或通訊，都必須包含英文的版本。	Questo documento è stato preparato e redatto in lingua inglese. In caso di traduzione in altre lingue, nell'eventualità sorgano conflitti fra la versione non inglese e quella inglese, prevarrà quest'ultima in quanto viene riconosciuto e accettato che la versione in lingua inglese esprime più chiaramente gli accordi fra le parti. Qualsiasi notifica o comunicazione inviata in rapporto a questo documento deve includere una versione in lingua inglese. 本書は英語で作成され発行されています。本書を他の言語に翻訳し、英語版と英語以外の版に矛盾が生じた場合は、関係者の意図を最も明確に表すものが英語版であることを認識および承認し、英語版が優先するものとします。さらに、本書に関連して与えられる告知や通知は、すべて英語版を含むものとしす。	Dieses Dokument wurde in englischer Sprache erstellt und ausgefertigt. Wenn dieses Dokument in eine andere Sprache übersetzt wird, und ein Konflikt zwischen der englischen und nicht-englischen Fassung auftritt, hat die englische Fassung Vorrang, da die Parteien anerkennen, dass die Fassung in englischer Sprache ihren Absichten am deutlichsten Ausdruck verleiht. Alle Hinweise oder Mitteilungen in Zusammenhang mit diesem Dokument müssen auch in einer Fassung in englischer Sprache erfolgen. 본 문서는 영어로 준비되어 작성된 것입니다. 본 문서를 다른 언어로 번역했는데 영문본과 번역본 사이에 상충하는 부분이 발생하는 경우에는 영문본이 우선하며, 영문본이 양쪽 당사자의 의도를 가장 명확하게 표현하고 있음을 인식하고 확인합니다. 본 문서와 관련한 모든 고지 또는 전달 사항에는 영문본이 동봉되어야 합니다.	Originalmente, este documento se creó y redactó en inglés. En caso de que se traduzca a otro idioma y surja algún conflicto entre la versión en inglés y la del idioma extranjero, prevalecerá la versión en inglés, dado que se reconoce y admite que, en la versión en inglés, expresa la intención de las partes con más claridad. Cualquier aviso o comunicación proporcionada en relación con este documento debe incluir una versión en inglés. Данный документ был подготовлен и выполнен на английском языке. При переводе данного документа на другой язык, в случае возникновения противоречий между английской версией и версией на другом языке английский версия имеет преимущественную силу. Данным признается, что версия документа на английском языке наиболее четко выражает намерения сторон. Любые уведомления или письма направляемые в связи с данным документом, должны включать в себя версию на английском языке	Este documento se preparó y redactó en inglés. En caso de que se traduzca a otro idioma y surja algún conflicto entre la versión en inglés y la del idioma extranjero, prevalecerá la versión en inglés, dado que se reconoce y admite que la versión en inglés expresa más claramente la intención de las partes. Cualquier aviso o comunicación proporcionada en relación con este documento deberá incluir una versión en inglés. لحورت هذه الوثيقة وكُتبت باللغة الإنجليزية. تسمى النسخة الإنجليزية الوثيقة ويعترف بها وتر بأنها النسخة التي تعبر صراحة عن مقصد أطراف العقد في حال ترجمتها لأي لغة أخرى ونشئ بذلك نزاعاً بين النسخة المترجمة والنسخة الإنجليزية. ترفي نسخة باللغة الإنجليزية لأي إخطارات أو الاتصالات مرسلة تنطبق بهذه الوثيقة.

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Caution: Any changes or modifications not expressly approved by Grantee Name for compliance could void the user's authority to operate this equipment.

RF Exposure Statement

1, For body worn operation, this device has been tested and meets FCC RF exposure guidelines. When used with an accessory that contains metal may not ensure compliance with FCC RF exposure guidelines.

2, This device and its antenna must not be co-located or operating in conjunction with any other antenna or transmitter.

EDA5S-0

The highest reported FCC SAR values for head and body-worn accessory use conditions are: 0.80 W/kg (1g) and 0.66 W/kg (1g)

EDA5S-1

The highest reported FCC SAR values for head and body-worn accessory use conditions are: 0.84 W/kg (1g) and 1.23 W/kg (1g)