

Giant Electronics Ltd.,

Level	Description	Qty	Reqd. U/M	Schema	Alt A
Parent	T8230 FRS RADIO			EA	
1	BASE UNIT (ALL)		1 EA		
0.2	BASE CASING (ALL)		1 EA		
..3	BASE CASING COMMON		1 EA		
...4	BATT PLATE "-"		1 EA		
...4	ANTENNA WIRE		1 EA		
...4	BATT PLATE "+" "-" (A)		1 EA		
...4	BATT PLATE "-" "+" (B)		1 EA		
...4	CHARGING CONTACT		2 EA		
...4	KEYPAD		1 EA		
...4	PTT BUTTON		1 EA		
...4	LCD TAPE PAPER		1 EA	E:	
...4	SPEAKER NET		1 EA	E:	
...4	PROTECTIVE PAPER - DISPLAY LENS		1 EA		
...4	MIC CUSHION COVER		1 EA		
...4	SPEAKER CUSHION		1 EA	E:	
...4	SPEAKER SPONGE		1 EA		
...4	SPONGE CUSHION		2 EA		
...4	FRONT HOUSING SILVER		1 EA		
...4	REAR HOUSING SILVER		1 EA		
...4	BATTERY DOOR SILVER		1 EA		
...4	LENS W/O PRINT		1 EA		
...4	LED LIGHT GUIDE		1 EA		
...4	FACEPLATE PLATED CHROME		1 EA		
...4	ANTENNA SHROUD		1 EA		
...4	VOLUME KNOB		1 EA		
...4	BELT CLIP COVER SILVER		1 EA		
...4	PTT INSERT		1 EA		
...4	ANTENNA INSERT		1 EA		
...4	DUST CAP GREY		1 EA		
...4	TAPTITE SCREW X/HD T2.3X8		4 EA		
0.2	BASE RF & MAIN PCB (ALL)		1 EA		
..3	BASE CASING COMMON PARTS		1 EA		
...4	STRAND WIRE UL1007 #28 BLACK	0.038 M		JW201	
...4	STRAND WIRE UL1007 #28 RED	0.037 M		JW202	
...4	SPEAKER 32 OHM 0.5W 3632A505		1 EA	SPK101	
...4	MIC DB MIC C9745 42dB		0 EA	*	
...4	MIC HORN EM9745PA-42		1 EA	MIC101	
..3	BASE RF & MAIN COMMON PART		1 EA		
...4	CAP ELECT 6.3V M 10UF 3X5MM		3 EA	C109, C235, C275, E:	
...4	CAP. ELECT 6.3V M 10UF 4X5MM		1 EA	C172	
...4	CAP. ELECT. 6.3V M% 100UF		1 EA	C266, E:	
...4	CAP. ELECT 6.3V M 100UF 5X5MM		1 EA	C242, E:	
...4	CAP. ELECT 6.3V M 470UF 6X8MM		2 EA	C237, C248, E:	
...4	SAW FILTER 465MHZ SF465 AEI		1 EA	BPF101	
...4	CRYSTAL FILTER 21.4M AEI 21.4N7.5A UM-5		0 EA	*	
...4	FILTER CRYSTAL 21.4MHZ CMT MU-5		1 EA	BPF102	
...4	CERAMIC FILTER CFT450HT-1 HUATAO		1 EA	BPF105	
...4	LCD TB3198E O/P 3V 1/2 BIAS 1/4 DUTY		1 EA	LCD101	
...4	4 DIGIT WITH ICON 22X20X1.7MM 9 3492TF/E		0 EA	*	

Giant Electronics Ltd.,

...4	DIA 2.5mm EARPHONE JACK ST-101	1 EA	J101
...4	HEAT SEAL CABLE P=0.6MM L=10MM 12PINS K&K	1 EA	JW203
...4	COIL FIXED 2U2H 5%	1 EA	L112
...4	SHIELD CAN A	1 EA	
...4	LCD BRACKET FOR 1W	1 EA	E:
...4	BATT PLATE "+'	1 EA	
...4	SHEET STEEL	1 EA	
...4	METAL DOME	1 EA	
...4	WHITE SHEET FOR RUBBER	1 EA	
...4	LCD CUSHION	2 EA	
...4	CUSHION FOR FILTER	1 EA	
...4	LCD LIGHT GUIDE	1 EA	
...4	JTB 450KHZ CERAMIC DISCRIMINATOR	1 EA	L114, E:
...4	RES. SEMI. F-09115SA A5KB L14. 6FCX7	1 EA	VR103
...4	RES. SEMI. RD901S-20-146F-A53-0038 (A5K)	0 EA	*
...4	SLIDE TACT SWITCH TS-37-BH-DG	1 EA	
...4	CERAMIC RESONATOR 4MHZ +/-0.2%	1 EA	X102
...4	BASE RF & MAIN PCB SMT COMMON PARTS	1 EA	
....5	PCB RF 95.5X46X1.2MM DS USA	1 EA	E:
....5	BASE RF & MAIN PCB SMT BOTTOM COMMON PART	1 EA	
....6	CAP. CER. CHIP 50V CH J% 100PF MURATA	6 EA	C231, C251, C210, C19, C142, C178
....6	CAP. CER. CHIP 50V B K% 0.001UF MURATA	4 EA	C113, C148, C164, C214
....6	CAP. CER. CHIP 16V X7R K 0.01UF	4 EA	C192, C194, C257, R11
....6	CAP. CER. CHIP 16V F Z% 0.1UF MURATA	9 EA	C170, C173, C175, C204, C207, C222, C264, C205, C10
....6	CAP. CER. CHIP 16V F Z% 1UF	1 EA	C147
....6	CAP. CER. CHIP 50V CH C% 1PF MURATA	0.3 EA	C179 FOR MATCH YELLOW/B3 CRYSTAL
....6	CAP. CER. CHIP 50V CH J% 12PF MURATA	0.3 EA	C180 FOR MATCH WHITE/B1 CRYSTAL
....6	CAP. CER. CHIP 16V B K% 0.012UF MURATA	1 EA	C184
....6	CAP. CER. CHIP 50V CH J% 15PF MURATA	0.75 EA	C180 MATCH BLACK/YELLOW/B3 CRYSTAL C171 FOR MATCH GREEN/B4 CRYSTAL
....6	CAP. CER. CHIP 50V B K% 0.0015UF	1 EA	C163
....6	CAP. CER. CHIP 16V B K 0.015UF MURATA	1 EA	C162
....6	CAP. CER. CHIP 50V CH C% 1.5PF MURATA	1 EA	C123
....6	CAP. CER. CHIP 50V CH J% 18PF MURATA	0.15 EA	C180 FOR MATCH B4 CRYSTAL
....6	CAP. CER. CHIP 50V CH J% 20PF MURATA	0.45 EA	C180 FOR MATCH GREEN CRYSTAL C171 FOR MATCH BLACK/B1 CRYSTAL
....6	CAP. CER. CHIP 50V CH C% 2PF MURATA	0.6 EA	C165 MATCH BLACK/WHITE/GREEN C179 FOR MATCH WHITE CRYSTAL
....6	CAP. CER. CHIP 50V CH J% 22PF MURATA	0.45 EA	C171 MATCH YELLOW/WHITE/B3 CRYSTAL
....6	CAP. CER. CHIP 50V B K% 0.0022UF MURATA	1 EA	C161
....6	CAP. CER. CHIP 16V B K% 22NF MURATA	7 EA	C196, C228, C239, C258, C203, C6, C7
....6	CAP. CER. CHIP 50V NPO J 27P 0402	2 EA	C190, C155
....6	CAP. CER. CHIP 50V NPO J% 30pF	1 EA	C133
....6	CAP. CER. CHIP 50V CH C% 3PF MURATA	1 EA	C114
....6	CAP. CER. CHIP 16V B K% 0.33UF	1 EA	C186
....6	CAP CER CHIP 50V NPO J% 39PF MURATA	1 EA	C202
....6	CAP. CER. CHIP 50V CH C% 4PF MURATA	0.15 EA	C165 FOR MATCH B4 CRYSTAL
....6	CAP CER CHIP 50V NPO J% 47PF MURATA	1 EA	C201
....6	CAP. CER. CHIP 50V NPO J% 470PF	1 EA	C274, E:
....6	CAP. CER. CHIP 10V X7R K 0.047UF	2 EA	C188, C256
....6	CAP. CER. CHIP 50V CH C% 5PF MURATA	0.15 EA	C165 FOR MATCH B1 CRYSTAL

Giant Electronics Ltd.,

.....6 CAP. CER. CHIP 50V NPO J% 56pF
6 CAP. CER. CHIP 50V X7R K 560PF
6 CAP. CER. CHIP 25V B K% 0.0056UF MURATA
6 CAP. CER. CHIP 10V X7R K 0.056UF
6 CAP. CER. CHIP 50V U2J J% 62PF
6 CAP. CER. CHIP 50V CH C% 7PF MURATA
6 CAP. CER. CHIP 50V CH C% 8PF MURATA
6 CAP. CER. CHIP 50V B K 820PF 0603 MURATA
6 LED CHIP KPA-3010EC RED
6 LED CHIP KPT-2012EC RED
6 DIODE PIN 1SS314
6 INDUCTOR CHIP 27NH +-5% LQG18HN27NJ00D
6 INDUCTOR CHIP 27NH +-5% SDCL1608C27NJ
6 THER. NTCM10053EH220JC TDK 0402 TYPE
6 RES. CHIP 1/16W 0 OHM
6 RES. CHIP 1/16W 1K
6 RES. CHIP 1/16W 10K
6 RES. CHIP 1/16W 100K
6 RES. CHIP 1/16W 1M
6 RES CHIP 1/16W 1.1M 5%
6 RES. CHIP 1/16W 1.2K
6 RES CHIP 1/16W 5% 120K 0402
6 RES. CHIP 1/16W 13K 0402
6 RES. CHIP 1/16W 130K
6 RES CHIP 1/16S 5% 1.3M 0402
6 RES. CHIP 1/16W 15K
6 RES. CHIP 1/16W 5% 150K 0402
6 RES. CHIP 1/16W 180 0402
6 RES CHIP 1/16W 5% 180K 0402
6 RES. CHIP 1/16W 220
6 RES. CHIP 1/16W 2.2K
6 RES. CHIP 1/16W 22K
6 RES. CHIP 1/16W 220K
6 RES. CHIP 1/16W 270 OHM 0402
6 RES CHIP 1/16W 5% 27K 0402
6 RES. CHIP 1/16W 270K 0402
6 RES. CHIP 1/16W 3K
6 RES. CHIP 1/16W 33
6 RES. CHIP 1/16W 330 OHM 0402
6 RES. CHIP 1/16W 3.3K
6 RES. CHIP 1/16W 3.3K 0402
6 RES. CHIP 1/16W 33K
6 RES. CHIP 1/16W 5% 330K 0402
6 RES. CHIP 1/16W 390
6 RES. CHIP 1/16W 3.9K
6 RES. CHIP 1/16W 4.7K 0402
6 RES. CHIP 1/16W 47K
6 RES. CHIP 1/16W 470K 0402

6 RES. CHIP 1/16W 51K
6 RES. CHIP 1/16W 6.8K 0402

1 EA C199
 1 EA C185
 2 EA C241, C5
 1 EA C191
 1 EA C176
 1 EA C131
 1 EA C130
 1 EA C225, E:
 2 EA D2, D108
 1 EA D109
 1 EA D106
 1 EA L110
 1 EA L107
 1 EA TR102
 1 EA C168, E:
 3 EA R270, R176, R147, E:
 2 EA R168, R187
 2 EA R102, R241
 1 EA R206
 1 EA R167
 1 EA R123
 1 EA R145
 2 EA R156, R161
 1 EA R148
 1 EA R186
 1 EA R195
 3 EA R146, R213, R30
 1 EA R189
 1 EA R141
 1 EA R127
 2 EA R259, R199
 1 EA R243, E:
 2 EA R154, R196
 1 EA R188
 1 EA R198
 5 EA R155, R185, R12, R14, R214
 1 EA R151
 1 EA R231
 1 EA R262
 1 EA R13
 2 EA R107, R1
 2 EA R160, R244
 2 EA R153, R172
 1 EA R297, E:
 1 EA R131
 3 EA R211, R224, R296, E:
 2 EA R144, R200
 12 EA R117, R132, R157, R192, R208, R209, R210, R221, R222, R223
 R10, R4, E:
 1 EA R158
 1 EA R140, E:

.....6 TR.CHIP PNP 2SA1980UF SOT-323F
6 TR.CHIP PNP 2SA1586GR 4862830A05
6 TR.CHIP NPN 2SC5090
6 TR.CHIP NPN 2SC5343UF SOT-323F
6 TR.CHIP NPN 2SC4116GR
6 DIE MCU JT5J80-XXXX FOR E8230
6 CRYSTAL 20.95MHZ ZHENFENG
6 CRYSTAL 20M95HZ A CL=15PF UM-5 NDK BLACK
6 CRYSTAL 20M95HZ B CL=15PF UM-5 NDK WHITE
6 CRYSTAL 20M95HZ C CL=15PF UM-5 NDK YELLOW
6 CRYSTAL 20M95HZ D CL=15PF UM-5 NDK GREEN
6 CRYSTAL 20.95MHZ CL=15PF CM-1 ZHENFENG BLACK
6 CRYSTAL 20.95MHZ CL=15PF UM-1 ZHENFENG YELLOW
6 CRYSTAL 20.95MHZ CL=15PF UM-1 ZHENFENG GREEN
6 CRYSTAL
5 BASE RF & MAIN PCB SMT TOP COMMON PART
6 CAP. CHIP TRIMMER 10PF TZBX4100AA110
6 CAP.CER.CHIP 50V D% 10PF NPO MURATA
6 CAP.CER.CHIP 50V CH J% 100PF MURATA
6 CAP. CER. CHIP 50V CH J% 100PF
6 CAP.CER.CHIP 50V B K% 0.001UF MURATA
6 CAP. CER. CHIP 50V B K% 0.001UF
6 CAP. CER. CHIP 16V X7R K 0.01UF
6 CAP. CER. CHIP 16V F Z% 0.1UF
6 CAP.CER.CHIP 16V F Z% 0.1UF MURATA
6 CAP. CER. CHIP 25V B K% 0.1UF
6 CAP CER CHIP 6.3V Y5V 1uF Z 0402 MURATA
6 CAP. CER. CHIP 16V F Z% 1UF
6 CAP.CER.CHIP 50V CH J% 12PF MURATA
6 CAP.CER.CHIP 50V CH J% 15PF MURATA
6 CAP. CER. CHIP 50V CH J% 20PF MURATA
6 CAP.CER.CHIP 50V B K% 0.0022UF MURATA
6 CAP. CER. CHIP 50V B K% 0.0022UF
6 CAP.CER.CHIP 16V B K% 22NF MURATA
6 CAP. CER. CHIP 50V CH J% 24PF
6 CAP.CER.CHIP 50V CH J% 270PF MURATA
6 CAP.CER.CHIP 50V CH C% 3PF MURATA
6 CAP. CER. CHIP 16V B K% 0.33UF
6 CAP. CHIP 50V COG +/-0.1P 3.3PF 0402
6 CAP CER CHIP 50V NPO J 390PF
6 CAP.CER.CHIP 50V CH C% 4PF MURATA
6 CAP. CER. CHIP 50V CH J% 470PF
6 CAP CER CHIP 50V B 5P 0402
6 CAP. CER. CHIP 50V CH C% 5PF MURATA
6 CAP. CER. CHIP 50V X7R K 560PF
6 CAP. CER. CHIP 25V B K% 0.0056UF MURATA
6 CAP.CER. CHIP 50V NPO J% 68pF
6 CAP CER CHIP 50V X7R K 680PF MURATA
6 CAP. CER. CHIP 25V B K 0.0068UF
6 CAP. CER. CHIP 50V X7R K 0.068UF

1 EA Q111
 0 EA *
 2 EA Q102, Q107
 3 EA Q115, Q116, Q3
 0 EA *
 1 EA IC105, E:
 1 EA X101
 0 EA *
 0 EA *
 0 EA *
 0 EA *
 0 EA *
 0 EA *
 0 EA *
 0 EA *
 1 EA
 1 EA C159
 1 EA C140
 21 EA C116, C128, C129, C135, C139, C158, C174, C224, C227, C238
 C245, C259, C262, C263, C2, C8, C182, C183, C189, C4, C153
 1 EA C3
 2 EA C206, R121
 1 EA C250
 3 EA C118, C246, C276, E:
 1 EA C167
 6 EA C126, C221, C234, C244, C249, C121, E:
 1 EA C232
 1 EA C145
 2 EA C157, C177
 2 EA C137, C151
 1 EA C15
 1 EA C18
 1 EA C12
 1 EA C209
 1 EA C156
 2 EA C169, C105, E:
 1 EA C223
 1 EA C115
 1 EA C166
 3 EA C144, C141, C270, E:
 1 EA C187
 3 EA C138, C150, C146, E:
 1 EA C132
 2 EA C134, C119
 2 EA C104, C14, E:
 1 EA C122
 1 EA C1
 1 EA C236
 1 EA C219
 2 EA C11, C13
 2 EA C226, C229

Giant Electronics Ltd.,

.....6 CAP. CER. CHIP 25V B K 0.068UF
6 CAP. CER. CHIP 50V B K 820PF 0603 MURATA
6 CAP CER CHIP 50V COG +/-0.1PF 9PF EYANG
6 DIODE CHIP SCHOTTKY BARRIER RB715F
6 DIODE PIN ISS314
6 DIODE VARACTOR 1SV214
6 INDUCTOR CHIP 15NH LQG11A15N
6 INDUCTOR CHIP 22NH +-5% SDCL1608C22NJ
6 INDUCTOR CHIP 27NH +-5% LQG18HN27NJ00D
6 LQG18HN5N6S00 5.6NH 5% 0603 49744-09
6 INDUCTOR CHIP 68NH CCSP0805 68NG
6 THERMISTOR CHIP NTH5G10P40B473K08TH
6 THERMISTOR CHIP ECTH100505473J4100HT
6 RES. CHIP 1/16W 0 OHM
6 RES. CHIP 1/16W 10 OHM
6 RES. CHIP 1/16W 1K
6 RES. CHIP 1/16W 10K
6 RES. CHIP 1/16W 10K
6 CHIP VOLUME 103POZ3AN1 10KB
6 RES. CHIP 1/16W 100K
6 RES. CHIP 1/16W 1M
6 RES CHIP 1/16W 5% 12K 0402
6 RES. CHIP 1/16W 180 0402
6 RES CHIP 1/16W 5% 18K 0402
6 RES CHIP 1/16W 5% 180K 0402
6 RES. CHIP 1/16W 2.2K
6 RES. CHIP 1/16W 22K
6 RES. CHIP 1/16W 1% 22K 0402
6 RES. CHIP 1/16W 220K
6 RES CHIP 1/16W 5% 24K 0402
6 RES. CHIP 1/16W 2.7K
6 RES. CHIP 1/16W 3K
6 RES. CHIP 1/16W 30K 0402
6 RES. CHIP 1/16W 5% 330K 0402
6 RES. CHIP 1/16W 3.9K
6 RES. CHIP 1/16W 39K 0402
6 RES. CHIP 1/16W 470
6 RES. CHIP 1/16W 4.7K 0402
6 RES. CHIP 1/10W 47K
6 RES. CHIP 1/16W 47K

6 RES. CHIP 1/16W 470K 0402
6 CHIP VOLUME POZ3AN-1-502N 5K
6 RES. CHIP 1/16W 5.6K 0402
6 RES. CHIP 1/16W 6.8K 0402
6 RES CHIP 1/16W 5% 68K 0402
6 RES. CHIP 1/16W 8.2K 0402
6 RES CHIP 1/16W 5% 820K 0402
6 RES CHIP 1/16W 1% 9.1K 0402

1 EA C160
 1 EA C230
 1 EA C102
 1 EA D110
 3 EA D101, D105, D102
 1 EA D104
 1 EA L109
 1 EA L2, E:
 2 EA L111, L103, E:
 1 EA L1
 1 EA L3
 1 EA TR101
 0 EA *
 1 EA C269, E:
 2 EA R139, R7
 3 EA R124, R248, R245
 1 EA R266, E:
 10 EA R125, R143, R150, R17, R173, R19, R228, R129, R18, R114, E:
 2 EA VR1, VR102, E:
 2 EA R205, R229
 3 EA R232, R234, R239
 1 EA R130
 1 EA R116
 1 EA R236
 2 EA R32, R33
 3 EA R119, R128, R133
 9 EA R126, R230, R249, R251, R164, R204, R118, R268, R138
 1 EA R169
 4 EA R31, R37, R27, R28, E:
 1 EA R235
 2 EA R109, R34, E:
 1 EA R295
 1 EA R294
 1 EA R135
 2 EA R183, R184, E:
 1 EA R182
 2 EA R112, R103
 6 EA R122, R142, R247, R250, R113, R298, E:
 1 EA R159
 6 EA R202, R242, R174, R261, R201 FOR MATCH BLACK CRYSTAL
 R291 FOR MATCH WHITE CRYSTAL
 R292 FOR MATCH YELLOW CRYSTAL
 R293 FOR MATCH GREEN CRYSTAL, , R149, E:
 7 EA R24, R29, R36, R203, R23, R163, R299, E:
 1 EA VR101
 1 EA R8
 1 EA R152
 1 EA R35
 1 EA R134
 1 EA R220
 1 EA R255

Giant Electronics Ltd.,

.....6 TR CHIP PNP KSA1182-Y
6 TR.CHIP PNP 2SA1980UF SOT-323F
6 TR CHIP PNP 2SA1586GR 4862830A05
6 TR. CHIP NPN 2SC4901
6 TR.CHIP NPN 2SC5090
6 TR CHIP NPN 2SC5087-O (TE85L) TOSTHIBA
6 TR.CHIP NPN 2SC5343UF SOT-323F

6 TR CHIP NPN 2SC4116GR
6 TR CHIP FET 2SK3756 TOSHIBA
6 IC LOW POWER CS34119
6 IC LM324D 14SOP ON
6 IC LOW POWER NARROW BAND FM IF S1T3361D
6 IC S1T8825B PLL SAMSUNG
6 IC UTC34119 LOW POWER AUDIO AMP SOP-8
6 RESET IC S-80820 CNNB-B8F-T2
6 IC XC6201T302PR 3V REGULATOR SOT-89
6 SPRING COIL 0.4X1.0X4T QJ WFD
6 COIL SPRING 0.4X1.3X4TS WFD
 ..3 BASE RF & MAIN UNIQUE PART
 ...4 BASE RF & MAIN SMT UNIQUE PART
5 BASE RF & MAIN SMT BOTTOM UNIQUE PART
6 RES. CHIP 1/16W 10K
6 RES CHIP 1/16W 5% 120K 0402
5 BASE RF & MAIN SMT TOP UNIQUE PART
6 CAP.CER.CHIP 50V CH J% 100PF MURATA
6 CAP.CER.CHIP 16V F Z% 0.1UF MURATA
6 CAP. CER. CHIP 16V F Z% 1UF
6 CAP. CER. CHIP 25V B K% 560PF
6 DIODE ARRAY CHIP DA204U
6 RES. CHIP 1/16W 0 OHM
6 RES. CHIP 1/16W 10K
6 RES. CHIP 1/16W 10K
6 RES. CHIP 1/16W 100K
6 RES. CHIP 1/16W 1M
6 RES. CHIP 1/16W 1.5K
6 RES CHIP 1/16W 5% 1.8K 0402
6 RES. CHIP 1/16W 220K
6 RES. CHIP 1/16W 330
6 RES. CHIP 1/16W 330 OHM 0402
6 RES. CHIP 1/16W 3.3K 0402
6 RES. CHIP 1/16W 47K
6 RES. CHIP 82K 1/16W 0402
6 TR CHIP NPN 2SC4116GR
 1 PACKING ALL
 0.2 PACKING COMMON
 ..3 BELT CLIP ASSEMBLY

1 EA Q131, E:
 3 EA Q108, Q119, Q122
 0 EA *
 2 EA Q105, Q106
 0 EA *
 1 EA Q130
 12 EA Q110, Q118, Q120, Q123, Q125, Q13, Q4, Q5, Q6, Q127, Q128
 Q129
 0 EA *
 1 EA IC1
 1 EA IC107
 2 EA IC102, IC104
 1 EA IC101
 1 EA IC103
 0 EA *
 1 EA IC109
 1 EA IC108
 3 EA L101, L102, L106
 1 EA L113
 1 EA
 1 EA
 1 EA
 1 EA R254
 1 EA R136
 1 EA
 1 EA C255
 2 EA C108, C124
 2 EA C136, C149
 1 EA C111
 1 EA D103
 2 EA R253, R252
 1 EA R3
 3 EA R2, R5, R6
 1 EA R166, E:
 1 EA R115
 1 EA R110
 1 EA R101
 1 EA R105
 1 EA TR105
 1 EA R104
 1 EA R106
 1 EA R120
 1 EA R16
 4 EA Q1, Q2, Q103, Q109
 1 EA
 1 EA
 1 EA

>>>> End of B.O.M. <<<<