

(10)

THE ADJUSTMENT OF MODULATION LEVEL:

THE FIRST PIN OF MEASURING IC101 IS $400\text{mV} \pm 30\text{mV}$.ADJUST VR101 TO MAKE THE MODULATION METER APPEAR
TO $18 \pm 1\text{KHz}$.

(11) THE ADJUSTMENT OF TONE LEVEL:

CHANGE THE AF FILTERS OF MODULATION METER TO 60
KHz, AND ADJUST VR102 TO MAKE THE MODULATION METER
APPEAR TO $10 \pm 2\text{KHz}$. (OR ADJUST SPAN=100KHz FROM
SPECTRUM ANALYZER TO MAKE THE DIFFERENCE
BETWEEN LEVEL AND MAIN FREQUENCY BE $16\text{dB} \pm 2$).