



General Document

User Manual Cobra Module

OPTION NV, Kolonel Begaultlaan 45, B-3012 Leuven
Tel +32 16 317 411 Fax +32 16 207 164 <http://www.option.com>

Option Confidential



About this document

Overview and Purpose

This document describes how to register an Option Cobra Module on a CMU200.

Confidentiality

All data and information contained or disclosed by this document is confidential and proprietary of Option NV, and all rights therein are expressly reserved. By accepting this document, the recipient agrees that this information is held in confidence and in trust and will not be used, copied, reproduced in whole or in part, nor its contents revealed in any manner to others without prior and written permission of Option NV.

Version History

Date	Version	Author(s)	Revision(s)	Remarks
Apr 26, 2006	V01 – F1	R. Biesemans		Initial version
July 31, 2006		J. Boeckx		Review

Author:**Creation Date:** Jul 31, 2006**Version:** V01 – F1**Page:** 1 of 6**Option Confidential:**

This document is Option Confidential - it may not be duplicated, neither distributed externally without prior and written permission of Option NV.




Table of contents

1 INTRODUCTION 3

2 Registering the module to the CMU200 3

 2.1 Settings on CMU200 3

 2.2 Settings on the module 4

3 References..... 6



1 INTRODUCTION

This document describes how to register an Option Cobra Module on a CMU 200. This manual will guide you through the steps so you can do some tests on the CMU 200.

2 REGISTERING THE MODULE TO THE CMU200

*Note: When mentioned switch off, AT+CFUN should be set to: AT+CFUN=0
When mentioned switch on, AT+CFUN should be set to: AT+CFUN=1*

Use RF2 connection of CMU200 to connect the module. Select GSM or WCDMA on CMU. When the card is properly configured, and the preferred band is selected, the card will register automatically on the system.

When the card does not register on the CMU with the default setting of the CMU, please check the settings in the following paragraphs.

If the CMU has the integrity check enabled, you can use the card without any security setting changes (AT_OSEC=4). If not, please change the OSEC setting of the card: set OSEC to 3 (AT_OSEC=3) using a terminal program (for ex. HyperTerminal). For life networks, integrity checks are default enabled, so the OSEC setting needs to be set on 4.

2.1 Settings on CMU200

1. RF connector compensation:

Look if compensation settings are right: AF/RF. In normal use, meaning when your cables are all very well isolated, you have to compensate both directions for a minimum of +0,5 dB. You can choose higher values when you think the cables are not isolated enough.

2. BS signal too low:

When at first try, the card doesn't seem to register, try to increase the BS signal levels. Normal operation would be around 65 dBm. Try this value and switch the card off and on again.

After checking these settings. Switch off and switch on the card again. (at+cfun=0 and at+cfun=1)
It is also recommended to safe remove the card.



2.2 Settings on the module

When previous steps didn't do the trick, please check the settings on the card.

All steps mentioned next, should be evaluated in this order.

After each step, perform a safe removal of the card.

1. At_opbm

When not working in a shielded environment, all life networks could interfere with the signal coming from the CMU. When the simulated network is not in the same band as the surrounding life networks, this problem can be avoided by deselecting all other basebands but the one you are working in.

This could be done using the at_opbm command:

Extract from datasheet:

Preferred Band Mode _OPBM

Command	Possible response(s)
_OPBM=<band>,<n>	OK
_ OPBM =?	_OPBM: (list of supported <band>s)
_ OPBM?	<band>: <n>[<CR><LF><band>: <n>[...]]

Description

This command is used to disable/enable specific frequency bands.

Defined Values

<band>	
"ANY"	: any band
"EGSM"	: EGSM (900MHz) band
"DCS"	: DCS (1800MHz) band
"PCS"	: PCS (1900MHz) band
"G850"	: GSM 850MHz band
"U2100"	: WCDMA 2100MHz band
"U1900"	: WCDMA 1900MHz band
"U1700"	
"U17IV"	
"U850"	: WCDMA 1900MHz band

<n>	
0	: disable
1	: enable

Eg: if you use GSM1900 (PCS) band, select only this band. All other bands have to be deselected. It is also very important to deselect EVERY UMTS band when trying to connect to a GSM network and vice versa:



At_opbm = "PCS",1 (selection of PCS band)
 At_opbm = "DCS",0 (deselection of DCS band)
Same for the other bands, also the UMTS bands!!!

To check if the band is really (de)selected, use "at_opbm?" The bands showing 0 are deselected, the bands showing 1 are selected.

2. AT_OP SYS

When the band settings did not work, try the OPSYS command: this command selects the UTRAN and the packet and/or circuit switched domain.

Extract from datasheet:

Preferred SYStem "AT_OP SYS"

Command	Possible Response(s)
_OP SYS=[<mode>[,<domain>]]	OK
_OP SYS?	_OP SYS: <mode>,<domain>
_OP SYS=?	_OP SYS: (0-5),(0-6)

Description

This command changes the preferred system, GSM/WCDMA, the acquisition order and the service domain preference PS/CS.

Defined values

<mode>:

- 0 GSM only
- 1 WDMA only
- 2 GSM first
- 3 WCDMA first
- 4 No change
- 5 Auto

<domain>:

- 0 Acquire only circuit-switched systems
- 1 Acquire only packet-switched systems
- 2 Acquire circuit-and/or packet-switched systems
- 3 Any domain will do; no preference

Eg: at_opsys=0,2 selects options:
 GSM only and CS & PS domains

Author:

Creation Date: Jul 31, 2006

Option Confidential:

This document is Option Confidential - it may not be duplicated, neither distributed externally without prior and written permission of Option NV.

Version: V01 – F1

Page: 5 of 6



3 REFERENCES

Ref	Document	