

[Peak Power Meters/Analyzers](#)
[RF Power Meters](#)
[6-Channel RF Power Meter](#)
[VXI](#)
[RF Voltmeters](#)
[RF Millivoltmeter](#)
[Capacitance Meters](#)
[Modulation Analyzers & Meters](#)
[Audio Analyzers](#)
[CW Sensors](#)
[Peak Power Sensors](#)
[Request Quote](#)
[:products: Peak Power Sensors](#)

Product Show

Model Impedance RF Connector	Frequency Range (Low Bandwidth)	Dynamic Range Peak Pwr Rng CW Pwr Rng(1) Int Trigger Range	Overload Rating Pulse / Continuous	Sensor Response	
				Fast Risetime (Bandwidth)	Slow Risetime (Bandwidth)

DUAL DIODE PEAK POWER SENSORS

For use with models 4400, 4500, 4400A, and 4500A RF Peak Power Me
4530 Series RF Power Meter when combined with Model 2530 1 GHz calibrat

56218 50 ohm N (M)	0.03 to 18 GHz	-24 to +20 dBm -34 to +20 dBm -10 to +20 dBm	1 W for 1μs 200 mW	<150 ns (2 MHz)	<500 ns (700 kHz)
56318 50 ohm N (M)	0.5 to 18 GHz	-24 to +20 dBm -34 to +20 dBm -10 to +20 dBm	1 W for 1μs 200 mW	<15 ns (2) (35 MHz)	<200 ns (1.75 MHz)
56326 50 ohm K (M)	0.5 to 26.5 GHz	-24 to +20 dBm -34 to +20 dBm -10 to +20 dBm	1 W for 1μs 200 mW	<15 ns(2) (35 MHz)	<200 ns (1.75 MHz)
56418 50 ohm N (M)	0.5 to 18 GHz	-34 to +5 dBm -40 to +5 dBm -18 to +5 dBm	1 W for 1μs 200 mW	<30 ns (15 MHz)	<100 ns (6 MHz)
56518 50 ohm N (M)	0.5 to 18 GHz	-40 to +20 dBm -50 to +20 dBm -27 to +20 dBm	1 W for 1μs 200 mW	<100 ns (6 MHz)	<300 ns (1.16 MHz)

For use with models 4400, 4500, 4400A, 4500A, and 4530.
Compatible with 4530 Series internal 50 MHz calibrator.

57318 50 ohm N (M)	0.5 to 18 GHz (0.05 to 18 GHz)	-24 to +20 dBm -34 to +20 dBm -10 to +20 dBm	1 W for 1μs 200 mW	<15 ns(2) (35 MHz)	<10 μs (35 kHz)
57340 50 ohm K (M)	0.5 to 40 GHz (0.05 to 40 GHz)	-24 to +20 dBm -34 to +20 dBm -10 to +20 dBm	1 W for 1μs 200 mW	<15 ns(2) (35 MHz)	<10 μs (35 kHz)

57540 50 ohm K (M)	0.1 to 40 GHz (0.05 to 40 GHz)	-40 to +20 dBm -50 to +20 dBm -27 to +20 dBm	1 W for 1µs 200 mW	<100 ns (6 MHz)	<10 µs (35 kHz)
--------------------------	--------------------------------------	--	-----------------------	--------------------	--------------------