

802.11b Wireless Router

User Manual

FCC Certifications



This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. The equipment version marketed in US is restricted to usage of the channels 1-11 only. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

FCC Caution: Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.

IMPORTANT NOTE:

FCC Radiation Exposure Statement:

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. End users must follow the specific operating instructions for satisfying RF exposure compliance.

This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

The equipment version marketed in US is restricted to usage of the channels 1-11 only

CE Mark Warning



This equipment complies with the requirements relating to electromagnetic compatibility, EN55022 class B for ITE, the essential protection requirement of Council Directive 89/336/EEC on the approximation of the laws of the Member States relating to electromagnetic compatibility.

Company has an on-going policy of upgrading its products and it may be possible that information in this document is not up-to-date. Please check with your local distributors for the latest information. No part of this document can be copied or reproduced in any form without written consent from the company.

Trademarks:

All trade names and trademarks are the properties of their respective companies.

Copyright © 2003, All Rights Reserved.

Document Version: 2.0


Table of Contents

Unpacking Information	1
Introduction To Wireless Router	2
General Description	2
Key Features	3
The Front Panel	4
System LEDs	4
Port LEDs (WAN)	4
Port LEDs (LAN)	4
Port LEDs (Wireless)	5
Factory Setting button	5
The Rear Panel	6
Power Connection	6
Placement (Optional)	6
Installing And Using Wireless Router	8
Network configuration setup	8
Computer configuration setup	9
Wireless Router configuration setup	14
Status	15
Wireless	17
TCP/IP Setting	24
Firewall Configuration	29
Syslog	33
Statistics	34
Upgrade Firmware	34
Save and Reload	35
Password	35
Product Specifications	36
Appendix	37

Unpacking Information

Thank you for purchasing the Wireless Router. Before you start, please check all the contents of this package.

The product package should include the following:



1. One Wireless Router
2. One power adapter
3. One User Manual (CD)
4. One QIG
5. Stand and Screws (Optional)

Introduction To Wireless Router

General Description

The Wireless Router built-in with 4-port 10/100Mbps Fast Ethernet Switch is the latest generation of Wireless router product for Home/Office and SOHO users who are thirsting high speed Internet access. This full-feature and self-contained compact Wireless Router will be fully for broadband access in both of LAN and Wireless environment. This device has been specifically designed to provide LAN and Wireless users the most cost-effective method with multiple accesses to the Internet at the cost of a single public IP address (IP Sharing) and enjoy the true Plug-and-Play installation. Moreover, the built-in 4-port 10/100Mbps switch lets users plug the network cable into the device without buying additional switch.

This device is also an Access Point. It has a built-in wireless LAN. Users can connect to Internet using wireless network interfaces anywhere within the range of its radio transmission. It's idea for SOHO users who require instant and convenient access to Internet without the restriction of connecting cables.

The friendly WEB-based graphics interface for setup makes any inexperienced users soon enter plug-and-play operation. Embedded DHCP server simplified IP address management and no MIS people needed for daily technical services. What is more, NAT/firewall is also implemented on this compact Router Box for protecting whole LAN from outside attack.

Key Features

The switch provides the following key features:

- Complies with 10BASE-T specifications of IEEE802.3 standard
- Complies with 100BASE-TX specifications of IEEE802.3u standard
- Complies with IEEE802.3x full duplex operation and flow control
- 4 * RJ-45 ports for 100BASE-TX and 10BASE-T connectivity on LAN side
- 1 * WAN port on WAN side
- Friendly GUI offers painless setup and management
- LAN/WAN management via WEB-Based management interface
- Supports DHCP client/server function
- Supports N-Way Auto-Negotiation on each LAN and WAN port
- Supports PPPoE protocol
- Supports NAT/NAPT function
- Supports Port, IP and MAC filtering, Port Forwarding and Virtual DMZ (Firewall); WEP and WPA (Wireless)
- Supports extensive LED indicators for network diagnostics
- External power adapter
- FCC CLASS B, CE
- Built-in 11Mbps IEEE802.11b wireless LAN Access Point
- An instant LAN with an integrated 4 ports 10/100Mbps switch

The Front Panel

The front panel of the Wireless Router is shown below.



System LEDs

System LED indicators locate on the front panel for showing the operating status of the whole device.

- **PWR (Power) LED**
This indicator lights green when the Wireless Router is receiving power; otherwise, it is off.
- **Status LED**
The LED will be dark for a few seconds when the system is started. After that, the LED will blink periodically to show the Wireless Router is working normally. If the LED stays green/dark that means the system failed, you need to contact your agent or try to reboot the system.

Port LEDs (WAN)

Port LED (WAN) indicators locate on the front panel for showing the operating status of WAN port.

- **Act/Link LED**
The LED stays light (green) means the port has good linkage to its associated devices.
The LED will blink green when there is traffic transverse the port.

Port LEDs (LAN)

Port LEDs (LAN) indicators locate on the front panel for showing the operating status of 10/100Mbps Fast Ethernet switching ports.

- **Act/Link LED**
Every port has a Act/Link LED. Steady green (link state) indicates that the port has good linkage to its associated devices. Flashing green indicates that the port is receiving or transmitting data between its associated devices.

Port LEDs (Wireless)

- **Act LED**
 - I. When Wireless AP is ready for data transmitting and receiving, it is steady green.
 - II. When the data is transmitting or receiving, it is blinking green.


Factory Setting button

1. Push the button for more than 5 seconds and then release it, the system will return to factory default setting. In the meantime, system rewrites flash to default value and Status LED halts for a while. Approximately 60 seconds later, the Status LED blinks green periodically, now the whole system parameters have returned to factory default value. If the process has been interrupted by any reason (power off...), the system will fail. Before performing the process, ensure a safe operating environment please !
2. To reboot the Router, Press the button for 2-5 seconds and then release it, and all the setting won't be erased. Wait for the Router to complete the reboot, and then you can start to use it.

Warning : Incomplete factory setting recovery procedure will cause the Wireless Router malfunction ! If you are unfortunately in this situation, do not try to repair it by yourself. Consult your local distributor for help !

The Rear Panel

The rear panel of the Wireless Router is shown below



Power Connection

Plug the circle end of the power adapter firmly into the rear panel of the Wireless Router, and the other end put into an electric service outlet then the system is ready.

Placement (Optional)

There are three ways to place the Router. The first way is to place the Router horizontally on a surface. The second way is to attach the router to the wall. The third way is to stand the Router vertically on a surface. These options are explained in further detail below.

Desktop Option

1. The Router has one plastic stand that can be divided into two parts.
2. Combine one part of stand with the side of router.
3. Do the same with the second part.
4. Place the Router

Wall-mount option

Before attach this router on the wall, you have to finish the desktop option steps first.

1. Select a location with access for cables and a power outlet.
2. Unplug the unit. Place it upside down on a flat surface and mark the two holes for anchors.
3. Installing the Wall mount anchor (plastic) into the wall with tools such as drill or hammer.

4. Insert the provided screws in each hole of the stand parts.
5. Attaches the unit to the anchors on the wall.

Stand Option

1. The Router includes two stand parts.
2. Combine two parts into one stand. Combine it with the side of router near the power port. Push the stand up to snap it into place.
3. Place the Router.

Installing And Using Wireless Router

This Chapter provides a step-by-step guide to the installation and configuration of the Wireless Router. It assumes that your computers use the Windows 95/98 or newer version and a WEB browser is installed for configuration purposes. We suggest you go over the whole chapter and then do more advanced operation.

Network configuration setup


Steps to build up the network:

- Connect the ADSL or Cable modem to the Ethernet WAN port on the back of the Wireless Router by using the UTP cable.
- Connect the phone line from the wall socket to the line-in port on the ADSL modem, or the coaxial cable to the line-in port on the Cable modem.
- Plug-in the power adapter to the modem and turn on the power. Install the Ethernet card into the computer by referring to the User Guide that came with the card.
- Connect the computer to the Wireless Router by using standard twisted-pair Ethernet cable from the computer's Ethernet card to an 10/100Mbps Ethernet port on the back of the Wireless Router.
- Plug-in the power adapter to the Router and the other side to the wall outlet.


Computer configuration setup

In order to communicate with Wireless Router, the connected computer needs to install the TCP/IP protocol and setup the related address information.


1. Double click the "My Computer" icon on the desktop screen




2. Double click the "Control Panel" icon on the My Computer window




- Double click the "Network" icon on the Control Panel window




- Click the "Configuration" tab and check the TCP/IP protocol is available or not. If yes, skip the procedures 5 ~ 6. If no, click the "Add" button.



- Select "Protocol" item on the Select Network Component Type window. After that, click "Add" button




- Select "Microsoft" item on the left side of Select Network Protocol window. After that, select "TCP/IP" protocol on the Network Protocols block and click "OK" button.



- Select the "TCP/IP" component in the Configuration tab of the Network window. Click "Properties" button.

8. The screen will show up the TCP/IP Properties window then start the setting. First of all, you need to choose the IP address is dynamically assigned by a DHCP server or fixed.



Dynamically assigned:

- Select the **"IP Address"** tab and select **"Obtain an IP address automatically"** (default setting)
- Select the **"Gateway"** tab and click **"Remove"** to clear any existing entry of gateway IP address
- Select the **"DNS Configuration"** tab and click **"Disable DNS"**
- Click **"OK"** button

Fixed:

If there are some clients who need to get fixed IP addresses for some reasons and the nodes also need to access Internet through the Wireless Router then the following steps used to configure system

- Select **"Specify an IP address"** in the IP Address Tab of the TCP/IP Properties window and enter 192.168.1.*** in the IP Address field (the *** is a number between 2 and 254 used by the Wireless Router to identify individual computers)
- Select the **"Subnet Mask"** field and enter 255.255.255.0
- Select the **"DNS Configuration"** tab and click **"Enable DNS"**
- Enter the DNS IP Address obtained from your ISP in the **"Server Search Order"** location. Click **"OK"** button.

NOTE : 1. The default IP address of Wireless Router is 192.168.1.1 and subnet mask is 255.255.255.0
2. For the new network computers to use dynamic IP addresses provided by the Wireless Router DHCP server, they should not use the range of fixed IP addresses. For example, If the fixed IP addresses already use 192.168.1.2 to 192.168.1.68 the DHCP server must be setup to allocate the dynamic addresses out of this range.

9. The screen will return back to Network window then click "OK" button. At this moment, the system will prompt you for restarting the Windows. Click "Yes"

Wireless Router configuration setup

In order to make the whole network operate successfully, it is necessary to configure the Wireless Router through your computer has a WEB browser installed. Please follow up the steps listed below.

1. Double click the Internet WEB browser icon on your desktop screen (Netscape Communicator 4.0 and Internet Explorer 3.0 or update version)
2. Type 192.168.1.1 into the URL WEB address location and press Enter.



3. The Username and Password Required window appears.
 - Enter **admin** in the User Name location (default value).
 - Enter **admin** in the Password location (default value).
 - Click "OK" button¹



¹ Don't forget to change the Username and Password in configuration's Authentication to ensure the security.

Status

In the home page of the Wireless Router, the left navigation bar shows the options to configure the system. In the right navigation screen is the summary of system status for viewing the configurations.

Site contents:

Status

Wireless

TCP/IP Settings

LAN Interface

WAN Interface

Firewall

SysLog

Statistics

Upgrade Firmware

Save/Reload Settings

Password

Wireless Router Status

This page shows the current status and some basic settings of the device.

System

Alias Name

Wireless-Gateway

Up-time

0day.1h:51m:41s

Firmware Version

v1.4 11/21/2003

Wireless Configuration

SSID

WLAN-11b-GW

Channel Number

Encryption

Disabled

Associated Clients

0

BSSID

00:e0:7d:c0:c5:00

LAN Configuration

IP Address

10.10.13.196

Subnet Mask

255.255.0.0

DHCP Server

Disabled

MAC Address

00:e0:7d:c0:c5:00

WAN Configuration

Attain IP Protocol

Fixed IP

IP Address

11.0.0.1

Subnet Mask

255.255.255.0

Default Gateway

11.0.0.254

MAC Address

00:e0:7d:c0:c5:01

System

Alias Name	Name of Router
Up-time	Total of operation time
Firmware version	Version of Firmware

Wireless Configuration

SSID	This is the name of the wireless LAN. All the devices in the same wireless LAN should have the same SSID.
Channel Number	The channel used by the wireless LAN. All devices in the same wireless LAN should use the same channel.
Encryption	Type of Encryption

Associate Clients	Number of all active wireless stations that are connecting to the access point.
BSSID	Basic Service Set Identification of AP

- LAN Configuration

IP Address	IP Address of Router
Subnet Mask	Subnet Mask
DHCP Server	Enabled or Disable of DHCP
MAC Address	MAC Address of LAN-port

- WAN Configuration

Attain IP Protocol	Static IP address
IP Address	IP address of WAN-port
Subnet Mask	Subnet Mask of WAN-port
Default Gateway	Default Gateway of WAN-port
MAC Address	MAC Address of WAN-port

Wireless

Wireless Access Point builds a wireless LAN and can let all PCs equipped with IEEE802.11b wireless network adaptor connect to your Intranet. It supports WEP encryption and MAC address filter to enhance the security of your wireless network.

- Basic Setting

You can set up the configuration of your Wireless and monitor the Wireless Clients associate with your AP.

Wireless Basic Settings

This page is used to configure the parameters for wireless LAN clients which may connect to your Access Point. Here you may change wireless encryption settings as well as wireless network parameters.

Alias Name:	Wireless-Gateway
☐ Disable Wireless LAN Interface	
SSID:	WLAN-11b-GW
Country:	Germany
Channel Number:	1
Associated Clients:	Show Active Clients
Apply Changes	Reset

Configuration

Alias Name	The name of Router
☐ Disable Wireless LAN Interface	To Disable interface of Wireless LAN
SSID	The name of Wireless
Country	Select the country where you are to decide the Channel number
Channel Number	The channel used by the wireless LAN. All devices in the same wireless LAN should use the same channel.
Associated Clients	Click "Show Active Clients" button, then an "Active Wireless Client Table" will pop up. You can see the status of all active wireless stations that are connecting to the access point.

Click <Apply> at the bottom of the screen to save the above configurations. You can now configure other advance sections or start using the router (with the advance settings in place)

Active Wireless Client Table

MAC Address	MAC address of this active wireless station.
Tx Packet	The number of transmitted packets that are sent out from this active wireless station.
Rx Packet	The number of received packets that are received by this active wireless station.
TX Rate	The transmission rate
Power Saving	Shows if the wireless client is in Power Saving mode
Expired Time	This is the time in second before dissociation. If the wireless keeps idle longer than the expired time, this wireless router will dissociate it. The wireless client station has to associate again when it is active.
Refresh	Refresh the "Active Wireless Client Table".
Close	Close the "Active Wireless Client Table".

Advanced Settings

You can set advanced wireless LAN parameters of this router. The parameters include Authentication Type, Fragment Threshold, RTS Threshold, Beacon Interval, Tx Operation Rate, Tx Basic Rate, Preamble Type, and Broadcast SSID. You should not change these parameters unless you know what effect the changes will have on this router.

Configuration

Authentication Type	Open System mode	Wireless AP can associate with this wireless router without WEP encryption.
	Shared Key mode	You should also setup WEP key in the "Security" page and wireless AP associating with this wireless router should use WEP encryption in the authentication phase.
	Auto	The wireless client can associate with this wireless router by using any one of these two Modes.
Fragment Threshold	To specifies the maximum size of packet during the data transition. The lower values you set, the worst performance it will be.	

RTS Threshold	If the packet size is smaller the RTS threshold, the wireless router will not send this packet by using the RTS/CTS mechanism.
Beacon Interval	The period of time how long a beacon is broadcasted.
Data Rate	The "Data Rate" is the data packets limitation this wireless router can transmit. The wireless router will use the highest possible selected transmission rate to transmit the data packets.
Preamble Type	It defines the length of CRC block in the frames during the wireless communication. "Short Preamble" is suitable for heavy traffic wireless network. "Long Preamble" provides much communication reliability.
Broadcast SSID	If you enable "Broadcast SSID", every wireless station located within the coverage of this wireless router can discover this wireless router easily. If you are building a public wireless network, enabling this feature is recommended. Disabling "Broadcast SSID" can provide better security.
IAPP	To enables multiple AP to communicate and pass information regarding the location of associated Stations.

Click <Apply> at the bottom of the screen to save the above configurations. You can now configure other advance sections or start using the router.

● Wireless Security Setup

At the page, you can set up the WEP, WPA Encryption to ensure the security of your Wireless.

Configuration

Encryption	To enable WEP or WPA encryption, select the option in the drop list. If you select none, any data will be transmitted without Encryption and any station can access the router.
Use 802.1x Authentication	To enable the 802.1x, Click the check box of the item.
WPA Authentication Mode	There are two items, "WPA-Radius" and "pre-shared key". You can select the mode by clicking the item.
WPA Unicast Cipher Suite	To enable "TKIP", click the check box.
Pre-Shared key Format	To decide the format, select what you need in the drop list.

Authentication RADIUS Sever	If you use RADIUS Sever to ensure your security, you have to set up the parameters in the item. To set up the Port, IP address and Password of your RADIUS, Enter the Port Number, IP and Password.
--------------------------------	---

Click <Apply Change> at the bottom of the screen to save the above configurations. You can now configure other advance sections or start using the router.

- Access Control

To restrict the Number of Access authentication of Stations, Set up the control list in this page.

Configuration

Enable Wireless Access control	To enable it, click the check box.
MAC Address & Comment	To set up the Value of MAC Address & Comment; enter the MAC Address and Comment of station and click Apply Changes to save.
Current Access Control list	To Delete the station on the list, Click the check box in the select item and click the "Delete Selected". If you want to delete all stations on the list, click "Delete All" to remove all of them.

Click <Apply Change> at the bottom of the screen to save the above configurations. You can now configure other advance sections or start using the router.

WDS Setting

Wireless Distribution System allows the router to communicate with other APs wirelessly. To make it work, you must ensure that these APs and the Router are in the same Channel and add these APs MAC Address and Comment values into the WDS list. Don't Forget to Enable the WDS by click the check box of "Enable WDS" and press "Apply Changes" button to save.

To Delete the AP on the list, Click the check box in the select item and click the "Delete Selected". If you want to delete all APs on the list, click "Delete All" to remove all of them.

TCP/IP Setting

- LAN Interface Setup

To set up the configuration of LAN interface, Private IP of your router LAN Port and Subnet mask for your LAN segment.

Site contents:

- Status
- Wireless
- Basic Settings
- Advanced Settings
- Security
- Access Control
- WDS setting
- TCP/IP Settings
- LAN Interface
- WAN Interface
- Firewall
- Port Filtering
- IP Filtering
- MAC Filtering
- Port Forwarding
- Virtual DMZ
- SysLog
- Statistics
- Upgrade Firmware
- Save/Reload Settings
- Password

LAN Interface Setup

This page is used to configure the parameters for local area network which connects to the LAN port of your Access Point. Here you may change the setting for IP address, subnet mask, DHCP, etc..

IP Address: 10.10.13.196

Subnet Mask: 255.255.0.0

DHCP Server: Disabled

DHCP Client Range: 192.168.1.100 - 192.168.1.200 [Show Client](#)

802.1d Spanning Tree: Disabled

[Apply Changes](#) [Reset](#)

DHCP Static Assignment:

MAC: - IP:

Comment: [Apply Changes](#)

Current DHCP Static Assignment Table:

MAC Address	IP	Comment	Select
Delete Selected	Delete All	Reset	

Configuration

IP address	The IP of your Router LAN port (Default 192.168.1.1)
Subnet Mask	Subnet Mask of you LAN (Default 255.255.255.0)
802.1d Spanning tree	To prevent from network loops and preserve the quality of bridged network
Default Gateway	To set up the Default Gateway, enter the IP Value.
DHCP	To give your LAN Client an IP, you have to enable "DHCP". If not, manual setting up your client IP is necessary when you want to use the router as your client's default gateway.
DHCP Static Assignment	To assign an IP for a specified MAC-address, Enter the MAC-address, IP, Comment name in the Text-box and Click "Apply Changes" to save.

- WAN Interface Setup

In the page, you can set up the three types of Internet Access, PPPoE, DHCP, and Fixed IP.

WAN Interface Setup

This page is used to configure the parameters for Internet network which connects to the WAN port of your Access Point. Here you may change the setting for IP address, PPPoE, DNS, etc..

☐ Enable WAN ACCESS

WAN ACCESS IP: 0.0.0.0

WAN ACCESS PORT: 80

☒ Attain IP Automatically (DHCP)

☐ Fixed IP

IP Address: 172.1.1.1

Subnet Mask: 255.255.0.0

Default Gateway: 172.1.1.254

☐ PPPoE

User Name:

Password:

Connection Type: Continuous [Connect](#) [Disconnect](#)

Idle Time: 5 (1-1000 minutes)

☐ Enable MTU setup

MTU SIZE: 1500

Normal MTU range: 512 - 1500

PPPoE MTU range: 512 - 1492

☒ **Attain DNS Automatically**
☐ **Set DNS Manually**
 DNS 1:
 DNS 2:
 DNS 3:
 Clone MAC Address:

☐ **Enable DDNS**
 Service Provider:
 Host Name:
 Username:
 Password:
 Mail Exchanger (*):
☐ **Enable Wildcard (*)**
* available in selective Service Provider

Configuration	
DHCP	If your connection type is DHCP; select "Attain IP automatically (DHCP)".
Fixed IP	When you ISP use Static IP, you have to select "Fixed IP" and enter the IP address, Subnet Mask and Default Gateway provided by Your ISP.
PPPoE	When your connection type is PPPoE, You need to enter the information provided by your ISP, Such as User name, Password, Connection type (continuous, connect on demand and manual), and Idle Time.
	Username EX. Peter
	Password EX. 12345
	Connection Type
	Continuous is for Always keep connection

	Connect on demand is for bill by connection time. You can set up the Idle time for the value specifies the number of time that elapses before the system automatically disconnects the PPPoE session. Manual To connect to ISP, click "Connect" manually from the WEB user interface. The WAN connection will not disconnected due to the idle timeout. If the WAN line breaks down and latter links again, the router will not auto-connect to the ISP. Idle time (Minute) The value specifies the number of idle time that elapses before the system automatically disconnects the PPPoE session.
DNS	If your DNS provide by ISP is dynamic, choose "Attain DNS automatically" To specify the DNS, and enter the DNS provided by your ISP in DNS 1 2 3.
Clone Mac Address	When ISP use MAC address authentication (with DHCP), then the MAC address of the Ethernet card attached to your Cable modem must be registered with the ISP before connecting to the WAN (Internet). If the Ethernet card is changed, the new MAC address must be registered with the ISP. MAC cloning feature allows the MAC address reported by WAN side network interface card to be set to the MAC address already registered with the ISP eliminating the need to register the new MAC address with the ISP. This feature does not change the actual MAC address on the NIC, but instead changes the MAC address reported by Wireless Router to client requests. To Change the MAC address, enter it in the text box.
Enable WAN Access	To Enable the user to access this Router through Internet, Enter the specific IP and the port number

Enable DDNS	The Dynamic DNS feature allows you to dynamically register your assigned IP address to an Internet resolvable Fully Qualified Domain Name (FQDN). This is especially useful if you have a dynamically assigned IP address and you want to maintain a constantly resolvable web address. To enable Dynamic DNS, select Enable in the Dynamic DNS checkbox control, select a dynamic DNS service provider from the Service Provider drop list, and enter the host name, username and password in the Host Name, Username and Password fields. Note: You must create an account with the selected provider before using this feature. Note. Wildcard and Mail Exchanger service depend on the service providers.
Enable MTU Setup	To Enable the Maximum Transmission Unit of Router setup. Any packet over this number will be chopped up into suitable size before sending. Larger number will enhance the transmission performance. Enter your MTU number in the text-box to set the limitation. Default is 1500.

Firewall Configuration

The firewall could not only obstruct outside intruders from intruding your system, but also restricting the LAN users.

Port Filtering To restrict certain type of data packets from your LAN to Internet through the Router, add them on the Current Filtering Table.

Configuration

- | | |
|-------|---|
| STEPS | 1. Click the check box of "Enable Port Filtering" to enable the function. |
| | 2. Enter the Port range (EX 25-110), Protocol (UDP/TCP), and comment (EX. E-Mail) |
| | 3. To Delete the Port range on the list, Click the check box in the select item and click the "Delete Selected". If you want to delete all entries on the list, click "Delete All" to remove all of them. |

Click <Apply Change> at the bottom of the screen to save the above configurations. You can now configure other advance sections or start using the router.

- IP filtering

The Wireless Router could filter the outgoing packets for security or management consideration. You can set up the filter against the IP addresses to block specific internal users from accessing the Internet.

Configuration

- | STEPS | |
|-------|--|
| 1. | Click the check box of "Enable IP Filtering" to enable the function. |
| 2. | Enter the specific Local IP address (EX 10.10.3.9), Protocol (UDP/TCP), and comment (EX. Peter) |
| 3. | To Delete the IP address on the list, Click the check box in the select item and click the "Delete Selected". If you want to delete all entries on the list, click "Delete All" to remove all of them. |

Click <Apply Change> at the bottom of the screen to save the above configurations. You can now configure other advance sections or start using the router.

- MAC filtering

The Wireless Router could filter the outgoing packets for security or management consideration. You can set up the filter against the MAC addresses to block specific internal users from accessing the Internet.

Configuration

- | STEPS | |
|-------|---|
| 1. | Click the check box of "Enable MAC Filtering" to enable the function. |
| 2. | Enter the specific MAC address (EX 00:0e:b6:a8:72), and comment (EX. Peter) |
| 3. | To Delete the Mac address on the list, Click the check box in the select item and click the "Delete Selected". If you want to delete all Entries on the list, click "Delete All" to remove all of them. |

Click <Apply Change> at the bottom of the screen to save the above configurations. You can now configure other advance sections or start using the router.

- Port forwarding

The Port Forwarding allows you to re-direct a particular range of service port numbers (from the Internet/WAN Ports) to a particular LAN IP address. It helps you to host some servers behind the router NAT firewall.

Configuration

- | STEPS | |
|-------|--|
| 1. | Click the check box of "Enable port forwarding" to enable the function. |
| 2. | Enter the specific IP address (EX 10.10.10.10), Protocol (UDP/TCP), Port range (EX 25-110), and comment (EX. E-Mail) |
| 3. | To Delete the IP address on the table, Click the check box in the select item and click the "Delete Selected". If you want to delete all Entries on the table, click "Delete All" to remove all of them. |

Click <Apply Change> at the bottom of the screen to save the above configurations.

- Virtual DMZ

The virtual DMZ is used to enable protocols, which need to open ports on the router. The router will forward all unspecified incoming traffic to the host specified in this page.

To configure it, enter the Host IP (private IP address) and Click "Apply changes" to enact the setting.

Syslog

View and save the log in remote machine on the page.

To enable the system log,


1. Click the check box
2. Click show log to monitor.

To enable the Remote system log,

1. Click the check box
2. Enter the remote machine IP address

Statistics

On this page, you can monitor the sent & received packets counters of wireless, Ethernet LAN, and Ethernet WAN. To see the latest report, click refresh button.




The screenshot shows the 'Wireless Router' 'Statistics' page. It includes a description: 'This page shows the packet counters for transmission and reception regarding to wireless and Ethernet networks.' Below this is a table with three sections: Wireless LAN, Ethernet LAN, and Ethernet WAN. Each section has two rows: 'Sent Packets' and 'Received Packets'. A 'Refresh' button is at the bottom.

Wireless Router		
Statistics		
This page shows the packet counters for transmission and reception regarding to wireless and Ethernet networks.		
Wireless LAN	Sent Packets	57
	Received Packets	0
Ethernet LAN	Sent Packets	736
	Received Packets	739
Ethernet WAN	Sent Packets	216
	Received Packets	8598
Refresh		

Upgrade Firmware

To Upgrade Firmware,

- STEPS
1. Click "browse..." button to select the firmware you want to upgrade.
 2. Click Upload to start the upgrade process. Please don't close the WEB-browser and wait for process to complete. When Upgrade is completed, you can start to use the router.



The screenshot shows the 'Wireless Router' 'Upgrade Firmware' page. It includes a note: 'This page allows you upgrade the Access Point firmware to new version. Please note, do not power off the device during the upload because it may crash the system.' Below this is a 'Select File:' label with a text input field and a '浏览...' (Browse) button. At the bottom are 'Upload' and 'Reset' buttons.


Save and Reload

To save setting to file, click "Save..." button.

To load setting from file,

1. Click "Browse..." on the to select the file
2. Click upload to start the process and wait for it to complete

To reset setting to Default, click reset to start the process and it will be completed till the status LED start blinking.



The screenshot shows the 'Wireless Router' 'Save/Reload Settings' page. It includes a description: 'This page allows you save current settings to a file or reload the settings from the file which was saved previously. Besides, you could reset the current configuration to factory default.' Below this are three sections: 'Save Settings to File:' with a 'Save...' button; 'Load Settings from File:' with a text input field, a '浏览...' (Browse) button, and an 'Upload' button; and 'Reset Settings to Default:' with a 'Reset' button.

Password

To set up the Administrator Account information, enter the Username, New password, and reenter the password on the text box. Don't forget to click the "Apply Changes" to save the configuration.



The screenshot shows the 'Wireless Router' 'Password Setup' page. It includes a description: 'This page is used to set the account to access the web server of Access Point. Empty user name and password will disable the protection.' Below this are three labels: 'User Name:', 'New Password:', and 'Confirmed Password:', each followed by a text input field. At the bottom are 'Apply Changes' and 'Reset' buttons.

Product Specifications

Standard	IEEE802.3, 10BASE-T IEEE802.3u, 100BASE-TX IEEE802.3x full duplex operation and flow control IEEE802.11b wireless LAN infrastructure
Interface	1 * WAN port 4 * 10/100 RJ-45 Fast Ethernet switching ports One wireless LAN comply with IEEE 802.11b
WAN Connection	Ethernet 10/100 Mbps
Cable Connections	RJ-45 (10BASE-T): Category 3,4,5 UTP RJ-45 (100BASE-TX): Category 5 UTP
Network Data Rate	LAN: Auto-Negotiation (10Mbps, 100Mbps) Wireless: 11Mbps, 5.5Mbps, 2Mbps, 1Mbps data rated and auto-fallback support
Transmission Mode	Auto-Negotiation (Full-duplex, Half-duplex)
LED indications	System Power Status Port (WAN) ACT/LINK Port (LAN) ACT/LINK Port(Wireless) ACT
Software Support	Embedded WEB based management interface LAN/WAN management via WEB-based management interface DHCP client / server function Firmware upgradeable PPPoE protocol NAT / NAPT function Port filtering IP filtering MAC filtering Virtual DMZ
Wireless Access Point	Built-in 11Mbps wireless Access Point Direct Sequence Spread Spectrum (DSSS) operating at unlicensed 2.4 GHz ISM band 64/128bit Wired Equivalent Privacy (WEP) data encryption
Emission	FCC CLASS B, CE
Operating Temperature	0° ~ 50°C (32° ~ 122°F)
Operating Humidity	10% - 90%
Power Supply	External Power Adapter, 12VDC/500mA

Appendix

Service Name, Protocol and Port number

Service	Protocol	Port	Service	Protocol	Port
ANY	Any	Any	AOL	TCP	5190-5194
BGP	TCP	179	Finger	TCP	79
FTP	TCP	20-21	Gopher	TCP	70
HTTP	TCP	80	HTTPS	TCP	443
IMAP	TCP	143	InterLocator	TCP	389
IRC	TCP	6660-6669	L2TP	TCP	1701
VDOLive	TCP	7000-7010	WAIS	TCP	210
WINFRAME	TCP	1494	X-WIN	TCP	6000-6030
DNS	UDP	53	IKE	UDP	500
NFS	UDP	111	NTP	UDP	123
PC-Anywhere	UDP	123	RIP	UDP	520
SNMP	UDP	161	SYSLOG	UDP	514
TALK	UDP	517-518	TFTP	UDP	69
UDP-Any	UDP	Any	UUCP	UDP	540
PING	ICMP	ANY	TRACEROUTE	ICMP	Any