

Process C256 Process H30255 Process H30255 Process H30255	GE Lighting A SAVANT COMPANY	GRAPHICS APPROVAL Approvals designate all items on checked new items reviewed & are correct in addition to other organizational responsibilities.	SKU LISTING INFO: 9331476 NPI CYNQ Sam's reveal RS Can LED 2pk 7302489
REVIEWED DATE SIGNATURE	PACKAGING GRAPHICS	REVISION (DATE) PK: 4 (04-20-23) CN	BAK CODE 3MPC: ☐ 100% No HWK ☐ 80% No HWK ☒ N/A
Proof Reading - Spelling Proof against IDS request	Website Graphics Printability	INSERT OF SHARED: None	SUPPLIER PROJECT: N/A
PRINT METHOD: ☐ Offset/Litho ☐ Flexo (direct)	GE DIE: DL-90859	PK (VERSION): DL-00119101-1	

PC93131476 ING

THIS ART IS SUPPLIED AT 100% SCALE
DO NOT RESIZE, RESHAPE OR ALTER

Recessed Downlight Installation Guide

Getting Started

Download the CYNQ App, powered by Savant

Determine location and complete installation

Add your Recessed Downlight to the CYNQ App

Set up your Amazon Alexa voice assistant (optional)

For set up help, visit cyncsupport.gelighting.com or call 1-844-302-2943

Specifications

Model	Input Voltage (Vac, Hz)	Current (mA)	Wattage (W)
Full Color RS Can 4" CTR5C8CRVD	120	100	13

Dimming Capability

NOT FOR USE WITH DIMMER SWITCHES.
Compatible with only CYNQ smart dimmers that provide dimming at the switch or through the CYNQ App.

Before you begin: Read these instructions completely and carefully.

WARNING: RISK OF ELECTRIC SHOCK

Risk of fire or electric shock. Install this kit only in locations that have the construction features and dimensions shown in the photographs and/or drawings and where the input rating of the retrofit kit does not exceed the input rating of the luminaire.

Do not make or alter any open holes in an enclosure or wiring or electrical components during kit installation.

Let's Do It

Included:

You'll need:

GE is a trademark of General Electric Company. Used under trademark license. Amazon, Alexa, and brand logos are trademarks of Amazon.com, Inc. or its affiliates. Google and other related marks and logos are trademarks of Google LLC.

You Got This!

And we're here to help. For in-depth instructional videos and a guided tour through the installation, go to: cyncsupport.gelighting.com or call 1-844-302-2943

Step 3 Determine the Mounting Method

The Recessed Downlight is designed to install in most 6 in. and 5 in. recessed can fixtures. Use either the torsion spring or flip clip.

Torsion bracket

BEFORE YOU DO ANYTHING: Step 1 Turn Off The Power!

Turn off power at the source to the recessed housing(s) that you are installing the fixture(s) in.

Step 2 Remove Existing Trim and Bulb

Remove existing trim and bulb, revealing the housing and the existing socket inside.

1. Housing with torsion bracket.

Use the manufacturer installed torsion springs for installation.

2. Housing without torsion bracket.

Replace the torsion springs with the flip clips included in the packaging using a screwdriver.

Recessed Downlight Installation Guide

Step 4 Installing the Base

Medium Base Sockets
Screw the medium (E26) base into the socket and then connect the base to the fixture using the plug connector.

Plug-In Connection
Insert the plug connector from the ceiling into the plug connector on the fixture.

Step 5 Finish Installation

1. Housing with torsion bracket. Check that the "torsion springs" are firmly attached. Compress the torsion springs and insert into the bracket inside the housing. Release springs and gently push up until flush with the ceiling.

2. Housing without torsion bracket. Check that the "flip clips" are firmly attached. Center the fixture in the housing opening and gently push up until flush with the ceiling.

Congratulations!

You've completed the Recessed Downlight installation.

Next...

Download the CYNQ App

Add your Recessed Downlight to the CYNQ App

Set up your Alexa or Hey Google voice assistant (optional)

Enable Your Voice Assistant

Connect to your Amazon Alexa or Hey Google voice assistants in the CYNQ App.

Then try this:

Alexa, turn off the living room.

Alexa, turn on the bedroom.

Alexa, set kitchen to 50%.

Hey Google, turn on the lights.

Hey Google, good morning.

Hey Google, I'm leaving.

Recessed Downlight Installation Guide

Additional Information and Warnings

FCC Compliance Statement Compliance Notice:
Warning: Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

The device must not be co-located or operating in conjunction with any other antenna or transmitter.

This device complies with part 15 of FCC rules. Operation is subject to the following two conditions:
(1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

RF Exposure Information:
Caution: To maintain compliance with the FCC's RF exposure guidelines, place the product at least 20cm from nearby persons.

IC Statement

This device complies with RSS247 of Industry Canada. Cet appareil se conforme à RSS247 de Canada d'Industrie.

This device complies with Industry Canada license-exempt RSS standard(s).

Operation is subject to the following two conditions:
(1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device. Appareil radio exempt de licence.

Son fonctionnement est sujet aux deux conditions suivantes:
(1) le dispositif ne doit pas produire de brouillage préjudiciable, et (2) ce dispositif doit accepter tout brouillage reçu, y compris un brouillage susceptible de provoquer un fonctionnement indésirable.

This equipment complies with IC RSS-302 radiation exposure limits set forth for an uncontrolled environment.

This transmitter must be installed to provide a separation distance of at least 20cm from all persons and must not be co-located or operating in conjunction with any other antenna or transmitter.

Cet équipement est conforme aux limites d'exposition aux rayonnements IC RSS-302 définies pour un environnement non contrôlé.

Cet émetteur doit être installé pour fournir une distance de séparation d'au moins 20 cm de toutes les personnes et ne doit pas être colocalisé ou fonctionner en conjonction avec une autre antenne ou émetteur.

Like your new Recessed Downlight? Share your experience!

Leave a review where you purchased the product.

★★★★★