



3301 E. Deseret Drive, St. George, UT 84790  
www.wilsonelectronics.com • info@wilsonelectronics.com  
phone 1-800-204-4104 • fax 1-435-656-2432

March 3, 2017

To: Whom it May Concern

Subject: Calculated Mobile Station Coupling Losses (MSCL) For FCCID: PWO460030IL

The following formulas were used to calculate MSCL with a 6' foot path loss and a 45 degree polarity mismatch between the inside antenna and the mobile device:

Path Loss dB = 36.6 dB + 20Log(F MHz) dB + 20Log(D<sub>miles</sub>) dB


Polarity Loss dB = 10Log(E<sub>1</sub>/E<sub>2</sub>)<sup>2</sup> dB = P<sub>L</sub> dB

P<sub>L</sub> dB = 10Log(E<sub>1</sub><sup>2</sup>/(E<sub>1</sub>Sin(45<sub>deg</sub>))<sup>2</sup>) dB = 20Log(1/Sin(45<sub>deg</sub>)) dB = 3.01dB

Where:

E<sub>1</sub> = Maximum Possible Magnitude of the Electric Field from the Mobile Device

E<sub>2</sub> = Magnitude of the electric field from the Mobile device with a 45deg polarity mismatch = E<sub>1</sub>Sin(τ).



MSCL dB = Path Loss dB + Polarity Loss dB - Antenna Gain dB

The results of the calculations are shown in the following table:

| Uplink Center Frequency MHz | 707-710      | 782          | 836.5        | 1732.5       | 1880-1882.5  |
|-----------------------------|--------------|--------------|--------------|--------------|--------------|
| Path Loss (dB)              | 34.70        | 35.57        | 36.16        | 42.48        | 43.21        |
| Polarity Loss (dB)          | 3            | 3            | 3            | 3            | 3            |
| Antenna Gain with Coax Loss | -0.80        | -1.35        | -0.77        | -0.01        | 1.47         |
| <b>MSCL (dB)</b>            | <b>38.50</b> | <b>39.92</b> | <b>39.93</b> | <b>45.49</b> | <b>44.74</b> |

Note: Antenna Gain with Coax Loss as measured.

Sincerely

Patrick L. Cook  
Senior Electrical Engineer