

Giant Telecom Limited

Application
For
Permissive Change

900MHz/ 5.8GHz Analog Modulation Cordless Phone with Caller ID
(Handset Unit)

(FCC ID: RAQOL5800H)

05084602
TL/Ann Choy
August 31, 2005

- The test results reported in this test report shall refer only to the sample actually tested and shall not refer or be deemed to refer to bulk from which such a sample may be said to have been obtained.
- This report shall not be reproduced except in full without prior authorization from Intertek Testing Services Hong Kong Limited.
- For Terms And Conditions of the services, it can be provided upon request.
- The evaluation data of the report will be kept for 3 years from the date of issuance.

Intertek Testing Services Hong Kong Ltd.

2/F., Garment Centre, 576 Castle Peak Road, Kowloon, Hong Kong.
Tel: (852) 2173 8888 Fax: (852) 2741 1693 Website: www.hk.intertek-etlsemko.com

INTERTEK TESTING SERVICES

LIST OF EXHIBITS

INTRODUCTION

<i>EXHIBIT 1:</i>	General Description
<i>EXHIBIT 2:</i>	System Test Configuration
<i>EXHIBIT 3:</i>	Emission Results
<i>EXHIBIT 4:</i>	Equipment Photographs
<i>EXHIBIT 5:</i>	Product Labelling
<i>EXHIBIT 6:</i>	Technical Specifications
<i>EXHIBIT 7:</i>	Instruction Manual
<i>EXHIBIT 8:</i>	Security Code Information
<i>EXHIBIT 9:</i>	Confidentiality Request

INTERTEK TESTING SERVICES

MEASUREMENT/TECHNICAL REPORT

Giant Telecom Limited - MODEL: OL6813
OL6811, OL6814,
OL6817, OL6818
FCC ID: RAQOL5800H

This report concerns (check one:) Original Grant ____ Class II Change X

Equipment Type : DXT - Cordless Telephone

Deferred grant requested per 47 CFR 0.457(d)(1)(ii)? Yes ____ No X

If yes, defer until : ____
date

Company Name agrees to notify the Commission
by: _____

date

of the intended date of announcement of the product so that the grant can be issued
on that date.

Transition Rules Request per 15.37 ? Yes ____ No X

If no, assumed Part 15, Subpart C for intentional radiator - the new 47 CFR [10-01-04
Edition] Provision.

Report prepared by:

Tommy Leung
Intertek Testing Services Hong Kong Ltd.
2/F., Garment Centre,
576 Castle Peak Road,
Kowloon, Hong Kong.
Phone : 852-2173-8538
Fax: 852-2741-1693

INTERTEK TESTING SERVICES

Table of Contents

1.0	<u>General Description</u>	2
1.1	Product Description	2
1.2	Purpose of Application	2
1.3	Test Methodology	3
1.4	Test Facility	3
2.0	<u>System Test Configuration</u>	5
2.1	Justification	5
2.2	EUT Exercising Software	5
2.3	Support Equipment List and Description	6
2.4	Measurement Uncertainty	7
2.5	Equipment Modification	7
3.0	<u>Emission Results</u>	9
3.1	Field Strength Calculation	10
3.2	Radiated Emission Configuration Photograph - Handset	11
3.3	Radiated Emission Data - Handset	12
3.4	Radiated Emission on the bandedge	15
4.0	<u>Equipment Photographs</u>	18
5.0	<u>Product Labelling</u>	20
6.0	<u>Technical Specifications</u>	22
7.0	<u>Instruction Manual</u>	24
8.0	<u>Security Code Information</u>	26
9.0	<u>Confidentiality Request</u>	28

INTERTEK TESTING SERVICES

List of attached file

Exhibit type	File Description	filename
Cover Page	Purpose of Application	product change.pdf
Confidentiality Request	Confidentiality Request	request.pdf
Test Report	Test Report	report.pdf
Operation Description	Technical Description	descri.pdf
Test Setup Photo	Radiated Emission for Handset	config photos.doc
Test Report	Emission Plot	emission.pdf
External Photo	External Photo	external photos.doc
Internal Photo	Internal Photo	internal photos.doc
Block Diagram	Block Diagram	block.pdf
Schematics	Circuit Diagram	circuit.pdf
ID Label/Location	Label Artwork and Location	label.pdf
User Manual	User Manual	manual.pdf
User Manual	FCC Information	fcc information.pdf

INTERTEK TESTING SERVICES

EXHIBIT 1 GENERAL DESCRIPTION

INTERTEK TESTING SERVICES

1.0 General Description

1.1 Product Description

The OL6813 is a 900MHz/ 5.8GHz Analog Modulation Cordless Phone with Caller ID. Base Unit and handset operate at frequency of 902.100MHz to 904.000MHz with 20 channels and 5863.800MHz to 5871.600MHz with 40 channels respectively. The unit is capable of either tone or pulse dialing. The internal power supply's isolation is accomplished through a power transformer having an adequate dielectric rating. The circuit wiring is consistent under the requirement of part 68.

The handset unit consists of a keypad with twelve standard keys (0,...9,*,#), six function keys (Calls, Delete, Flash, Redial, Mute, Mem), and one channel switch key. A Talk key is provided to control pick/release telephone line in a toggle base.

The base unit has a page key, which is used to page the handset unit.

The antennas used in base unit and handset are integral, and the tested sample is a prototype.

The Models: OL6811, OL6814, and OL6818 are the same as the Model: OL6813 in hardware aspect except different packaging. The model OL6817 is an additional identical handset with a charger for selling a handset standalone. The difference in model number serves as marketing strategy.

The circuit description is saved with filename: descri.pdf

Connection between the device and the telephone network is accomplished through the use of USOC RJ11C in the 2-wire loop calling central office line.

1.2 Purpose of Application

The purpose of application is saved with filename: product change.pdf.

This is a single application for Permissive Change Class II of Handset Unit of a cordless telephone system. The FCC ID of the associated base unit is RAQOL5800B, and it was subjected to Permissive Change Class I.

INTERTEK TESTING SERVICES

1.3 Test Methodology

Radiated emission measurements were performed according to the procedures in ANSI C63.4 (2003). All measurements were performed in Open Area Test Sites. Preliminary scans were performed in the Open Area Test Sites only to determine worst case modes. All Radiated tests were performed at an antenna to EUT distance of 3 meters, unless stated otherwise in the "**Justification Section**" of this Application.

1.4 Test Facility

The open area test site and conducted measurement facility used to collect the radiated data is located at Garment Centre, 576 Castle Peak Road, Kowloon, Hong Kong. This test facility and site measurement data have been fully placed on file with the FCC.

INTERTEK TESTING SERVICES

**EXHIBIT 2
SYSTEM TEST CONFIGURATION**

INTERTEK TESTING SERVICES

2.0 System Test Configuration

2.1 Justification

For emissions testing, the equipment under test (EUT) was setup to transmit continuously to simplify the measurement methodology. Care was taken to ensure proper power supply voltages during testing. During testing, all cables were manipulated to produce worst case emissions. The handset was powered by a fully charged battery.

For the measurements, the EUT is attached to a plastic stand if necessary and placed on the wooden turntable. If the handset attaches to peripherals, they are connected and operational (as typical as possible). The base unit is remotely located as far from the antenna and the handset as possible to ensure full power transmission from the handset. Else, the handset is wired to transmit full power without modulation.

The signal is maximized through rotation and placement in the three orthogonal axes. The antenna height and polarization are varied during the search for maximum signal level. The antenna height is varied from 1 to 4 meters. Radiated emissions are taken at three meters unless the signal level is too low for measurement at that distance. If necessary, a pre-amplifier is used and/or the test is conducted at a closer distance.

All readings are extrapolated back to the equivalent three meter reading using inverse scaling with distance. Analyzer resolution is 100 kHz or greater. The spurious emissions more than 20 dB below the permissible value are not reported.

2.2 EUT Exercising Software

The EUT exercise program used during radiated testing was designed to exercise the various system components in a manner similar to a typical use.

INTERTEK TESTING SERVICES

2.3 Support Equipment List and Description

The FCC ID's for all equipment, plus descriptions of all cables used in the tested system (included inserted cards, which have grants) are:

HARDWARE:

The unit was operated standalone. A battery (provided with the unit) was used to power the device. Its description is listed below.

- (1) A "Ni-MH" type rechargeable battery (3.6V 600mAh)

CABLES:

There are no cables necessary for compliance of this product.

OTHERS:

There are no special accessories necessary for compliance of this product.

INTERTEK TESTING SERVICES

2.4 Measurement Uncertainty

When determining of the test conclusion, the Measurement Uncertainty of test has been considered.

2.5 Equipment Modification


Any modifications installed previous to testing by Giant Telecom Limited will be incorporated in each production model sold/leased in the United States.

No modifications were installed by ETL Division, Intertek Testing Services Hong Kong Ltd.

All the items listed under section 2.0 of this report are confirmed by:

Confirmed by:

*Tommy Leung
Assistant Manager
Intertek Testing Services
Agent for Giant Telecom Limited*



Signature

Sep 1, 2005 Date

INTERTEK TESTING SERVICES

EXHIBIT 3 EMISSION RESULTS

INTERTEK TESTING SERVICES

3.0 **Emission Results**

Data is included of the worst case configuration (the configuration which resulted in the highest emission levels). A sample calculation, configuration photographs and data tables of the emissions are included.

INTERTEK TESTING SERVICES

3.1 Field Strength Calculation

The field strength is calculated by adding the Antenna Factor and Cable Factor, and subtracting the Amplifier Gain (if any) from the measured reading. The basic equation with a sample calculation is as follows:

$$FS = RA + AF + CF - AG$$

where FS = Field Strength in dB μ V/m
 RA = Receiver Amplitude (including preamplifier) in dB μ V
 CF = Cable Attenuation Factor in dB
 AF = Antenna Factor in dB
 AG = Amplifier Gain in dB

In the following table(s), the reading shown on the data table reflects the preamplifier gain. An example for the calculations in the following table is as follows:-

$$FS = RR + LF$$

where FS = Field Strength in dB μ V/m
 RR = RA - AG in dB μ V
 LF = CF + AF in dB

Assume a receiver reading of 52.0 dB μ V is obtained. The antenna factor of 7.4 dB and cable factor of 1.6 dB is added. The amplifier gain of 29 dB is subtracted, giving a field strength of 32 dB μ V/m. This value in dB μ V/m was converted to its corresponding level in μ V/m.

$$RA = 52.0 \text{ dB}\mu\text{V/m}$$

$$AF = 7.4 \text{ dB}$$

$$CF = 1.6 \text{ dB}$$

$$AG = 29.0 \text{ dB}$$

$$FS = RR + LF$$

$$FS = 23 + 9 = 32 \text{ dB}\mu\text{V/m}$$

$$RR = 23.0 \text{ dB}\mu\text{V}$$

$$LF = 9.0 \text{ dB}$$

$$\text{Level in } \mu\text{V/m} = \text{Common Antilogarithm } [(32 \text{ dB}\mu\text{V/m})/20] = 39.8 \mu\text{V/m}$$

INTERTEK TESTING SERVICES

3.2 Radiated Emission Configuration Photograph - Handset

Worst Case Radiated Emission

at 3914.400 MHz

For electronic filing, the worst case radiated emission configuration photographs are saved with filename: config photos.doc


INTERTEK TESTING SERVICES

3.3 Radiated Emission Data - Handset

The data on the following pages list the significant emission frequencies, the limit and the margin of compliance.

Judgement : Passed by 0.1 dB

TEST PERSONNEL:



Tester Signature

Jess Tang, Engineer
Typed/Printed Name

August 31, 2005
Date

INTERTEK TESTING SERVICES

Company: Giant Telecom Limited
Model: OL6813
Mode : TX-Channel 1

Date of Test: June 14-22, 2005

Table 1, Handset unit

Radiated Emissions

Polarization	Frequency (MHz)	Reading (dBμV)	Pre- Amp (dB)	Antenna Factor (dB)	Net at 3m (dBμV/m)	Limit at 3m (dBμV/m)	Margin (dB)
H	5863.800	82.6	34	36.6	85.2	94	-8.8
H	*977.300	19.7	16	33.0	36.7	54	-17.3
H	1954.600	54.8	34	27.2	48.0	54	-6.0
H	2931.900	55.1	34	30.4	51.5	54	-2.5
H	*3909.200	48.7	34	33.3	48.0	54	-6.0
H	*4886.500	46.9	34	34.9	47.8	54	-6.2
H	6841.100	48.5	34	36.9	51.4	54	-2.6
H	7818.400	44.4	34	38.9	49.3	54	-4.7
H	8795.700	42.8	34	39.5	48.3	54	-5.7
H	9773.000	43.9	34	40.4	50.3	54	-3.7
H	*10750.300	42.9	34	40.4	49.3	54	-4.7
H	*11727.600	43.6	34	40.5	50.1	54	-3.9
H	12704.900	42.1	34	41.7	49.8	54	-4.2

- NOTES: 1. Peak detector is used for the emission measurement.
2. All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
3. Negative value in the margin column shows emission below limit.
4. Horn antenna is used for the emission over 1000MHz.
5. Radiated emission measurement were performed the lowest radio frequency signal generated in the device which is greater than 9kHz to 40GHz.
- * Emission within the restricted band meets the requirement of part 15.205.

Test Engineer: Jess Tang

INTERTEK TESTING SERVICES

Company: Giant Telecom Limited
Model: OL6813
Mode : TX-Channel 40

Date of Test: June 14-22, 2005

Table 2, Handset unit

Radiated Emissions

Polarization	Frequency (MHz)	Reading (dB μ V)	Pre- Amp (dB)	Antenna Factor (dB)	Net at 3m (dB μ V/m)	Limit at 3m (dB μ V/m)	Margin (dB)
H	5871.600	83.7	34	36.6	86.3	94	-7.7
H	*978.600	19.9	16	33.0	36.9	54	-17.1
H	1957.200	60.2	34	27.2	53.4	54	-0.6
H	2935.800	57.3	34	30.4	53.7	54	-0.3
H	*3914.400	54.6	34	33.3	53.9	54	-0.1
H	*4893.000	47.5	34	34.9	48.4	54	-5.6
H	6850.200	50.7	34	36.9	53.6	54	-0.4
H	7828.800	45.0	34	38.9	49.9	54	-4.1
H	8807.400	43.1	34	39.5	48.6	54	-5.4
H	9786.000	44.4	34	40.4	50.8	54	-3.2
H	*10764.600	43.5	34	40.4	49.9	54	-4.1
H	*11743.200	43.9	34	40.5	50.4	54	-3.6
H	12721.800	42.2	34	41.7	49.9	54	-4.1

- NOTES: 1. Peak detector is used for the emission measurement.
2. All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
3. Negative value in the margin column shows emission below limit.
4. Horn antenna is used for the emission over 1000MHz.
5. Radiated emission measurement were performed the lowest radio frequency signal generated in the device which is greater than 9kHz to 40GHz.
- * Emission within the restricted band meets the requirement of part 15.205.

Test Engineer: Jess Tang

INTERTEK TESTING SERVICES

3.4 Radiated Emission on the bandedge

From the following table, it shows that the fundamental emissions are confined in the specified band and it meets the general radiated emission limits in Section 15.209 at the frequency bands of 5725MHz and 5875MHz. It is complied with the requirement of section 15.249(d).

INTERTEK TESTING SERVICES

Emission Plot

For electronic filing, the emission plots are saved with filename: emission.pdf

INTERTEK TESTING SERVICES

**EXHIBIT 4
EQUIPMENT PHOTOGRAPHS**

INTERTEK TESTING SERVICES

4.0 **Equipment Photographs**

For electronic filing, the photographs are saved with filename: external photos.doc & internal photos.doc

INTERTEK TESTING SERVICES

EXHIBIT 5 PRODUCT LABELLING

INTERTEK TESTING SERVICES

5.0 **Product Labelling**

For electronic filing, the FCC ID label artwork and location is saved with filename:
label.pdf

INTERTEK TESTING SERVICES

**EXHIBIT 6
TECHNICAL SPECIFICATIONS**

INTERTEK TESTING SERVICES

6.0 Technical Specifications

For electronic filing, the block diagram and circuit diagram are saved with filename: block.pdf and circuit.pdf respectively.

INTERTEK TESTING SERVICES

EXHIBIT 7 INSTRUCTION MANUAL

INTERTEK TESTING SERVICES

7.0 **Instruction Manual**

For electronic filing, a preliminary copy of the Instruction Manual is saved with filename: manual.pdf

Please note that the required FCC Information to the User is saved with filename: fcc information.pdf.

This manual will be provided to the end-user with each unit sold/leased in the United States.

INTERTEK TESTING SERVICES

**EXHIBIT 8
SECURITY CODE INFORMATION**

INTERTEK TESTING SERVICES

8.0 Security code information

The telephone has an internal security code with 65,536 possible combinations. Each time the HANDSET is placed on the BASE UNIT, the code is randomly set to a new combination.