SimpleLink™ Wi-Fi® CC3x20, CC3x3x Network Processor

User's Guide

Literature Number: SWRU455M
FEBRUARY 2017 – REVISED OCTOBER 2020

C.1 Regulatory Domain

Table C-1 lists the country codes that the system supports and the supported channels in the different modes.

Table C-1. Country Codes and Channels

Country Code	Country	Region	STA Supported Channels			AP Supported Channels	
			2.4 GHz	5 GHz	5 GHz DFS	2.4 GHz	5 GHz
"00"	World wide	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13		36,40,44,48,52,56,60,64,100,104,108,112,116,120,124,128,132,136,140,149,153,157,161,165	1,2,3,4,5,6,7,8,9,10,11	
"AD"	Andorra	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"AE"	United Arab Emirates	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"AF"	Afghanistan	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"AI"	Anguilla	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"AL"	Albania	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"AM"	Armenia	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"AN"	Netherlands Antilles	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"AR"	Argentina	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"AS"	American Samoa	FCC	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165

Copyright © 2020 Texas Instruments Incorporated

Table C-1. Country Codes and Channels (continued)

Country Code	Country	Region	STA Supported Channels			AP Supported Channels	
			2.4 GHz	5 GHz	5 GHz DFS	2.4 GHz	5 GHz
"AT"	Austria	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"AU"	Australia	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"AW"	Aruba	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"AZ"	Azerbaijan	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"BA"	Bosnia and Herzegovina	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"BB"	Barbados	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"BD"	Bangladesh	JP	1,2,3,4,5,6,7,8,9,10,11,12,13	149,153,157,161,165		1,2,3,4,5,6,7,8,9,10,11,12,13	
"BE"	Belgium	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"BF"	Burkina Faso	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"BG"	Bulgaria	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"BH"	Bahrain	JP	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"BL"	Saint-Barthélemy	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"BM"	Bermuda	FCC	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165
"BN"	Brunei Darussalam	JP	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,
"BO"	Bolivia	JP	1,2,3,4,5,6,7,8,9,10,11,12,13	149,153,157,161,165	52,56,60,64	1,2,3,4,5,6,7,8,9,10,11,12,13	
"BR"	Brazil	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"BS"	Bahamas	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165

Copyright © 2020 Texas Instruments Incorporated

Table C-1. Country Codes and Channels (continued)

Country Code	Country	Region	STA Supported Channels			AP Supported Channels	
			2.4 GHz	5 GHz	5 GHz DFS	2.4 GHz	5 GHz
"BT"	Bhutan	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"BY"	Belarus	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"BZ"	Belize	JP	1,2,3,4,5,6,7,8,9,10,11,12,13	149,153,157,161,165		1,2,3,4,5,6,7,8,9,10,11,12,13	
"CA"	Canada	FCC	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,132,136,140	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165
"CF"	Central African Republic	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"CH"	Switzerland	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"CI"	Côte d'Ivoire	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"CL"	Chile	JP	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"CN"	China	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"CO"	Colombia	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"CR"	Costa Rica	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"CU"	Cuba	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13			1,2,3,4,5,6,7,8,9,10,11,12,13	
"CX"	Christmas Island	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"CY"	Cyprus	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"CZ"	Czech Republic	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"DE"	Germany	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48

Copyright © 2020 Texas Instruments Incorporated

Table C-1. Country Codes and Channels (continued)

Country Code	Country	Region	STA Supported Channels			AP Supported Channels	
			2.4 GHz	5 GHz	5 GHz DFS	2.4 GHz	5 GHz
"DK"	Denmark	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"DM"	Dominica	FCC	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165	52,56,60,64	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165
"DO"	Dominican Republic	FCC	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165	52,56,60,64	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165
"DZ"	Algeria	JP	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"EC"	Ecuador	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"EE"	Estonia	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"EG"	Egypt	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"ES"	Spain	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"ET"	Ethiopia	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"EU"	Europe	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"FI"	Finland	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"FM"	Micronesia, Federated States of	FCC	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165
"FR"	France	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"GB"	Gabon	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"GD"	Grenada	FCC	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165
"GE"	Georgia	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48

Copyright © 2020 Texas Instruments Incorporated

Table C-1. Country Codes and Channels (continued)

Country Code	Country	Region	STA Supported Channels			AP Supported Channels	
			2.4 GHz	5 GHz	5 GHz DFS	2.4 GHz	5 GHz
"GF"	French Guiana	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"GH"	Ghana	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"GL"	Greenland	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"GP"	Guadeloupe	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"GR"	Greece	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"GT"	Guatemala	FCC	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165	52,56,60,64	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165
"GU"	Guam	FCC	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165
"GY"	Guyana	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	149,153,157,161,165		1,2,3,4,5,6,7,8,9,10,11,12,13	149,153,157,161,165
"HK"	Hong Kong, SAR China	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"HN"	Honduras	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"HR"	Croatia	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"HT"	Haiti	FCC	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165
"HU"	Hungary	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"ID"	Indonesia	JP	1,2,3,4,5,6,7,8,9,10,11,12,13	149,153,157,161		1,2,3,4,5,6,7,8,9,10,11,12,13	
"IE"	Ireland	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"IL"	Israel	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48

Copyright © 2020 Texas Instruments Incorporated

Table C-1. Country Codes and Channels (continued)

Country Code	Country	Region	STA Supported Channels			AP Supported Channels	
			2.4 GHz	5 GHz	5 GHz DFS	2.4 GHz	5 GHz
"IN"	India	JP	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"IR"	Iran, Islamic Republic of	JP	1,2,3,4,5,6,7,8,9,10,11,12,13	149,153,157,161,165		1,2,3,4,5,6,7,8,9,10,11,12,13	
"IS"	Iceland	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"IT"	Italy	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"JM"	Jamaica	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"JO"	Jordan	JP	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165		1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"JP"	Japan	JP	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,184,188,192,196	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,184,188,192,196
"KE"	Kenya	JP	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153	100,104,108,112	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"KH"	Cambodia	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"KN"	Saint Kitts and Nevis	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"KP"	Korea (North)	JP	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161	52,56,60,64,100,104,108,112,116,120,124	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"KR"	Korea (South)	JP	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"KW"	Kuwait	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"KY"	Cayman Islands	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"KZ"	Kazakhstan	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13			1,2,3,4,5,6,7,8,9,10,11,12,13	
"LB"	Lebanon	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"LC"	Saint Lucia	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48

Copyright © 2020 Texas Instruments Incorporated

Table C-1. Country Codes and Channels (continued)

Country Code	Country	Region	STA Supported Channels			AP Supported Channels	
			2.4 GHz	5 GHz	5 GHz DFS	2.4 GHz	5 GHz
"LI"	Liechtenstein	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"LK"	Sri Lanka	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"LS"	Lesotho	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"LT"	Lithuania	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"LU"	Luxembourg	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"LV"	Latvia	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"MA"	Morocco	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"MC"	Monaco	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"MD"	Moldova	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"ME"	Montenegro	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"MF"	Saint-Martin (French part)	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"MH"	Marshall Islands	FCC	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165
"MK"	Macedonia, Republic of	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"MN"	Mongolia	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165

Copyright © 2020 Texas Instruments Incorporated

Table C-1. Country Codes and Channels (continued)

Country Code	Country	Region	STA Supported Channels			AP Supported Channels	
			2.4 GHz	5 GHz	5 GHz DFS	2.4 GHz	5 GHz
"MO"	Macao, SAR China	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"MP"	Northern Mariana Islands	FCC	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165
"MQ"	Martinique	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"MR"	Mauritania	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"MT"	Malta	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"MU"	Mauritius	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"MV"	Maldives	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"MW"	Malawi	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"MX"	Mexico	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"MY"	Malaysia	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"NG"	Nigeria	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	149,153,157,161,165	52,56,60,64	1,2,3,4,5,6,7,8,9,10,11,12,13	
"NI"	Nicaragua	FCC	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165
"NL"	Netherlands	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"NO"	Norway	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140,149,153,157,165	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"NP"	Nepal	JP	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48

Copyright © 2020 Texas Instruments Incorporated

Table C-1. Country Codes and Channels (continued)

Country Code	Country	Region	STA Supported Channels			AP Supported Channels	
			2.4 GHz	5 GHz	5 GHz DFS	2.4 GHz	5 GHz
"NZ"	New Zealand	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"OM"	Oman	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"PA"	Panama	FCC	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165	52,56,60,64	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165
"PE"	Peru	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"PF"	French Polynesia	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"PG"	Papua New Guinea	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"PH"	Philippines	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"PK"	Pakistan	JP	1,2,3,4,5,6,7,8,9,10,11,12,13	149,153,157,161,165		1,2,3,4,5,6,7,8,9,10,11,12,13	
"PL"	Poland	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"PM"	Saint Pierre and Miquelon	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"PR"	Puerto Rico	FCC	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165
"PT"	Portugal	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"PW"	Palau	FCC	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165
"PY"	Paraguay	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"QA"	Qatar	JP	1,2,3,4,5,6,7,8,9,10,11,12,13	149,153,157,161,165		1,2,3,4,5,6,7,8,9,10,11,12,13	

Copyright © 2020 Texas Instruments Incorporated

Table C-1. Country Codes and Channels (continued)

Country Code	Country	Region	STA Supported Channels			AP Supported Channels	
			2.4 GHz	5 GHz	5 GHz DFS	2.4 GHz	5 GHz
"RE"	Réunion	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"RO"	Romania	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"RS"	Serbia	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,52,56,60,64	100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"RU"	Russian Federation	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"RW"	Rwanda	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"SA"	Saudi Arabia	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"SE"	Sweden	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"SG"	Singapore	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"SI"	Slovenia	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"SK"	Slovakia	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"SN"	Senegal	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"SR"	Suriname	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"SV"	El Salvador	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"SY"	Syrian Arab Republic (Syria)	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13			1,2,3,4,5,6,7,8,9,10,11,12,13	
"TC"	Turks and Caicos Islands	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"TD"	Chad	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48

Copyright © 2020 Texas Instruments Incorporated

Table C-1. Country Codes and Channels (continued)

Country Code	Country	Region	STA Supported Channels			AP Supported Channels	
			2.4 GHz	5 GHz	5 GHz DFS	2.4 GHz	5 GHz
"TG"	Togo	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"TH"	Thailand	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"TN"	Tunisia	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"TR"	Turkey	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"TT"	Trinidad and Tobago	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"TW"	Taiwan, Republic of China	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"TZ"	Tanzania, United Republic of	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	149,153,157,161,165		1,2,3,4,5,6,7,8,9,10,11,12,13	149,153,157,161,165
"UA"	Ukraine	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"UG"	Uganda	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"US"	United States of America	FCC	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165
"UY"	Uruguay	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"UZ"	Uzbekistan	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"VC"	Saint Vincent and Grenadines	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"VE"	Venezuela (Bolivarian Republic)	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"VI"	Virgin Islands, US	FCC	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,149,153,157,161,165
"VN"	Viet Nam	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165

Copyright © 2020 Texas Instruments Incorporated

Table C-1. Country Codes and Channels (continued)

Country Code	Country	Region	STA Supported Channels			AP Supported Channels	
			2.4 GHz	5 GHz	5 GHz DFS	2.4 GHz	5 GHz
"VU"	Vanuatu	FCC	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,149,153,157,161,165
"WF"	Wallis and Futuna Islands	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"WS"	Samoa	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"XX"		ETSI	1,2,3,4,5,6,7,8,9,10,11	36,40,44,48,52,56,60,64,100,104,108,112,116,120,124,128,132,136,140,149,153,157,161,165		1,2,3,4,5,6,7,8,9,10,11	36,40,44,48
"YE"	Yemen	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13			1,2,3,4,5,6,7,8,9,10,11,12,13	
"YT"	Mayotte	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"ZA"	South Africa	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48,100,104,108,112,116,120,124,128,132,136,140	52,56,60,64	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48
"ZW"	Zimbabwe	ETSI	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48	52,56,60,64,100,104,108,112,116,120,124,128,132,136,140	1,2,3,4,5,6,7,8,9,10,11,12,13	36,40,44,48

Copyright © 2020 Texas Instruments Incorporated