



Using Avaya J189 IP Phone SIP

Release 4.0.6
Issue 1
May 2020

1 © 2019-2020, Avaya Inc.

2 All Rights Reserved.

3 **Note**

4 Using a cell, mobile, or GSM phone, or a two-way radio in close
5 proximity to an Avaya IP telephone might cause interference.

6 **Documentation disclaimer**

7 "Documentation" means information published in varying mediums
8 which may include product information, operating instructions and
9 performance specifications that are generally made available to users
10 of products. Documentation does not include marketing materials.
11 Avaya shall not be responsible for any modifications, additions, or
12 deletions to the original published version of Documentation unless
13 such modifications, additions, or deletions were performed by or on
14 the express behalf of Avaya. End User agrees to indemnify and hold
15 harmless Avaya, Avaya's agents, servants and employees against all
16 claims, lawsuits, demands and judgments arising out of, or in
17 connection with, subsequent modifications, additions or deletions to
18 this documentation, to the extent made by End User.

19 **Link disclaimer**

20 Avaya is not responsible for the contents or reliability of any linked
21 websites referenced within this site or Documentation provided by
22 Avaya. Avaya is not responsible for the accuracy of any information,
23 statement or content provided on these sites and does not
24 necessarily endorse the products, services, or information described
25 or offered within them. Avaya does not guarantee that these links will
26 work all the time and has no control over the availability of the linked
27 pages.

28 **Warranty**

29 Avaya provides a limited warranty on Avaya hardware and software.
30 Refer to your sales agreement to establish the terms of the limited
31 warranty. In addition, Avaya's standard warranty language, as well as
32 information regarding support for this product while under warranty is
33 available to Avaya customers and other parties through the Avaya
34 Support website: [https://support.avaya.com/helpcenter/
35 getGenericDetails?detailId=C20091120112456651010](https://support.avaya.com/helpcenter/getGenericDetails?detailId=C20091120112456651010) under the link
36 "Warranty & Product Lifecycle" or such successor site as designated
37 by Avaya. Please note that if You acquired the product(s) from an
38 authorized Avaya Channel Partner outside of the United States and
39 Canada, the warranty is provided to You by said Avaya Channel
40 Partner and not by Avaya.

41 "Hosted Service" means an Avaya hosted service subscription that
42 You acquire from either Avaya or an authorized Avaya Channel
43 Partner (as applicable) and which is described further in Hosted SAS
44 or other service description documentation regarding the applicable
45 hosted service. If You purchase a Hosted Service subscription, the
46 foregoing limited warranty may not apply but You may be entitled to
47 support services in connection with the Hosted Service as described
48 further in your service description documents for the applicable
49 Hosted Service. Contact Avaya or Avaya Channel Partner (as
50 applicable) for more information.

51 **Hosted Service**

52 THE FOLLOWING APPLIES ONLY IF YOU PURCHASE AN AVAYA
53 HOSTED SERVICE SUBSCRIPTION FROM AVAYA OR AN AVAYA
54 CHANNEL PARTNER (AS APPLICABLE), THE TERMS OF USE
55 FOR HOSTED SERVICES ARE AVAILABLE ON THE AVAYA
56 WEBSITE, <https://support.avaya.com/LICENSEINFO> UNDER
57 THE LINK "Avaya Terms of Use for Hosted Services" OR SUCH
58 SUCCESSOR SITE AS DESIGNATED BY AVAYA, AND ARE
59 APPLICABLE TO ANYONE WHO ACCESSES OR USES THE
60 HOSTED SERVICE. BY ACCESSING OR USING THE HOSTED
61 SERVICE, OR AUTHORIZING OTHERS TO DO SO, YOU, ON
62 BEHALF OF YOURSELF AND THE ENTITY FOR WHOM YOU ARE
63 DOING SO (HEREINAFTER REFERRED TO INTERCHANGEABLY
64 AS "YOU" AND "END USER"), AGREE TO THE TERMS OF USE. IF
65 YOU ARE ACCEPTING THE TERMS OF USE ON BEHALF A
66 COMPANY OR OTHER LEGAL ENTITY, YOU REPRESENT THAT
67 YOU HAVE THE AUTHORITY TO BIND SUCH ENTITY TO THESE
68 TERMS OF USE. IF YOU DO NOT HAVE SUCH AUTHORITY, OR IF
69 YOU DO NOT WISH TO ACCEPT THESE TERMS OF USE, YOU
70 MUST NOT ACCESS OR USE THE HOSTED SERVICE OR
71 AUTHORIZE ANYONE TO ACCESS OR USE THE HOSTED
72 SERVICE.

73 **Licenses**

74 THE SOFTWARE LICENSE TERMS AVAILABLE ON THE AVAYA
75 WEBSITE, <https://support.avaya.com/LICENSEINFO>,
76 UNDER THE LINK "AVAYA SOFTWARE LICENSE TERMS (Avaya
77 Products)" OR SUCH SUCCESSOR SITE AS DESIGNATED BY
78 AVAYA, ARE APPLICABLE TO ANYONE WHO DOWNLOADS,
79 USES AND/OR INSTALLS AVAYA SOFTWARE, PURCHASED
80 FROM AVAYA INC., ANY AVAYA AFFILIATE, OR AN AVAYA
81 CHANNEL PARTNER (AS APPLICABLE) UNDER A COMMERCIAL
82 AGREEMENT WITH AVAYA OR AN AVAYA CHANNEL PARTNER.
83 UNLESS OTHERWISE AGREED TO BY AVAYA IN WRITING,
84 AVAYA DOES NOT EXTEND THIS LICENSE IF THE SOFTWARE
85 WAS OBTAINED FROM ANYONE OTHER THAN AVAYA, AN AVAYA
86 AFFILIATE OR AN AVAYA CHANNEL PARTNER; AVAYA
87 RESERVES THE RIGHT TO TAKE LEGAL ACTION AGAINST YOU
88 AND ANYONE ELSE USING OR SELLING THE SOFTWARE
89 WITHOUT A LICENSE. BY INSTALLING, DOWNLOADING OR
90 USING THE SOFTWARE, OR AUTHORIZING OTHERS TO DO SO,
91 YOU, ON BEHALF OF YOURSELF AND THE ENTITY FOR WHOM
92 YOU ARE INSTALLING, DOWNLOADING OR USING THE
93 SOFTWARE (HEREINAFTER REFERRED TO
94 INTERCHANGEABLY AS "YOU" AND "END USER"), AGREE TO
95 THESE TERMS AND CONDITIONS AND CREATE A BINDING
96 CONTRACT BETWEEN YOU AND AVAYA INC. OR THE
97 APPLICABLE AVAYA AFFILIATE ("AVAYA").

98 Avaya grants You a license within the scope of the license types
99 described below, with the exception of Heritage Nortel Software, for
100 which the scope of the license is detailed below. Where the order
101 documentation does not expressly identify a license type, the
102 applicable license will be a Designated System License as set forth
103 below in the Designated System(s) License (DS) section as
104 applicable. The applicable number of licenses and units of capacity
105 for which the license is granted will be one (1), unless a different
106 number of licenses or units of capacity is specified in the
107 documentation or other materials available to You. "Software" means
108 computer programs in object code, provided by Avaya or an Avaya
109 Channel Partner, whether as stand-alone products, pre-installed on
110 hardware products, and any upgrades, updates, patches, bug fixes,
111 or modified versions thereto. "Designated Processor" means a single
112 stand-alone computing device. "Server" means a set of Designated
113 Processors that hosts (physically or virtually) a software application
114 to be accessed by multiple users. "Instance" means a single copy of
115 the Software executing at a particular time: (i) on one physical
116 machine; or (ii) on one deployed software virtual machine ("VM") or
117 similar deployment.

118 **License types**

119 Designated System(s) License (DS). End User may install and use
120 each copy or an Instance of the Software only: 1) on a number of
121 Designated Processors up to the number indicated in the order; or 2)
122 up to the number of Instances of the Software as indicated in the
123 order, Documentation, or as authorized by Avaya in writing. Avaya
124 may require the Designated Processor(s) to be identified in the order
125 by type, serial number, feature key, Instance, location or other
126 specific designation, or to be provided by End User to Avaya through
127 electronic means established by Avaya specifically for this purpose.

128 Shrinkwrap License (SR). You may install and use the Software in
129 accordance with the terms and conditions of the applicable license
130 agreements, such as "shrinkwrap" or "clickthrough" license
131 accompanying or applicable to the Software ("Shrinkwrap License").

132 **Heritage Nortel Software**

133 "Heritage Nortel Software" means the software that was acquired by
134 Avaya as part of its purchase of the Nortel Enterprise Solutions
135 Business in December 2009. The Heritage Nortel Software is the
136 software contained within the list of Heritage Nortel Products located
137 at <https://support.avaya.com/LicenseInfo> under the link "Heritage
138 Nortel Products" or such successor site as designated by Avaya. For
139 Heritage Nortel Software, Avaya grants Customer a license to use
140 Heritage Nortel Software provided hereunder solely to the extent of
141 the authorized activation or authorized usage level, solely for the
142 purpose specified in the Documentation, and solely as embedded in,
143 for execution on, or for communication with Avaya equipment.
144 Charges for Heritage Nortel Software may be based on extent of
145 activation or use authorized as specified in an order or invoice.

1 Copyright

2 Except where expressly stated otherwise, no use should be made of
3 materials on this site, the Documentation, Software, Hosted Service,
4 or hardware provided by Avaya. All content on this site, the
5 documentation, Hosted Service, and the product provided by Avaya
6 including the selection, arrangement and design of the content is
7 owned either by Avaya or its licensors and is protected by copyright
8 and other intellectual property laws including the sui generis rights
9 relating to the protection of databases. You may not modify, copy,
10 reproduce, republish, upload, post, transmit or distribute in any way
11 any content, in whole or in part, including any code and software
12 unless expressly authorized by Avaya. Unauthorized reproduction,
13 transmission, dissemination, storage, and or use without the express
14 written consent of Avaya can be a criminal, as well as a civil offense
15 under the applicable law.

16 Virtualization

17 The following applies if the product is deployed on a virtual machine.
18 Each product has its own ordering code and license types. Unless
19 otherwise stated, each Instance of a product must be separately
20 licensed and ordered. For example, if the end user customer or
21 Avaya Channel Partner would like to install two Instances of the
22 same type of products, then two products of that type must be
23 ordered.

24 Third Party Components

25 "Third Party Components" mean certain software programs or
26 portions thereof included in the Software or Hosted Service may
27 contain software (including open source software) distributed under
28 third party agreements ("Third Party Components"), which contain
29 terms regarding the rights to use certain portions of the Software
30 ("Third Party Terms"). As required, information regarding distributed
31 Linux OS source code (for those products that have distributed Linux
32 OS source code) and identifying the copyright holders of the Third
33 Party Components and the Third Party Terms that apply is available
34 in the products, Documentation or on Avaya's website at: [https://
35 support.avaya.com/Copyright](https://support.avaya.com/Copyright) or such successor site as designated
36 by Avaya. The open source software license terms provided as Third
37 Party Terms are consistent with the license rights granted in these
38 Software License Terms, and may contain additional rights benefiting
39 You, such as modification and distribution of the open source
40 software. The Third Party Terms shall take precedence over these
41 Software License Terms, solely with respect to the applicable Third
42 Party Components to the extent that these Software License Terms
43 impose greater restrictions on You than the applicable Third Party
44 Terms.

45 The following applies only if the H.264 (AVC) codec is distributed with
46 the product. THIS PRODUCT IS LICENSED UNDER THE AVC
47 PATENT PORTFOLIO LICENSE FOR THE PERSONAL USE OF A
48 CONSUMER OR OTHER USES IN WHICH IT DOES NOT RECEIVE
49 REMUNERATION TO (i) ENCODE VIDEO IN COMPLIANCE WITH
50 THE AVC STANDARD ("AVC VIDEO") AND/OR (ii) DECODE AVC
51 VIDEO THAT WAS ENCODED BY A CONSUMER ENGAGED IN A
52 PERSONAL ACTIVITY AND/OR WAS OBTAINED FROM A VIDEO
53 PROVIDER LICENSED TO PROVIDE AVC VIDEO. NO LICENSE IS
54 GRANTED OR SHALL BE IMPLIED FOR ANY OTHER USE.
55 ADDITIONAL INFORMATION MAY BE OBTAINED FROM MPEG LA,
56 L.L.C. SEE [HTTP://WWW.MPEGLA.COM](http://www.mpegla.com).

57 Service Provider

58 THE FOLLOWING APPLIES TO AVAYA CHANNEL PARTNER'S
59 HOSTING OF AVAYA PRODUCTS OR SERVICES. THE PRODUCT
60 OR HOSTED SERVICE MAY USE THIRD PARTY COMPONENTS
61 SUBJECT TO THIRD PARTY TERMS AND REQUIRE A SERVICE
62 PROVIDER TO BE INDEPENDENTLY LICENSED DIRECTLY FROM
63 THE THIRD PARTY SUPPLIER. AN AVAYA CHANNEL PARTNER'S
64 HOSTING OF AVAYA PRODUCTS MUST BE AUTHORIZED IN
65 WRITING BY AVAYA AND IF THOSE HOSTED PRODUCTS USE
66 OR EMBED CERTAIN THIRD PARTY SOFTWARE, INCLUDING
67 BUT NOT LIMITED TO MICROSOFT SOFTWARE OR CODECS,
68 THE AVAYA CHANNEL PARTNER IS REQUIRED TO
69 INDEPENDENTLY OBTAIN ANY APPLICABLE LICENSE
70 AGREEMENTS, AT THE AVAYA CHANNEL PARTNER'S EXPENSE,
71 DIRECTLY FROM THE APPLICABLE THIRD PARTY SUPPLIER.

72 WITH RESPECT TO CODECS, IF THE AVAYA CHANNEL
73 PARTNER IS HOSTING ANY PRODUCTS THAT USE OR EMBED
74 THE H.264 CODEC OR H.265 CODEC, THE AVAYA CHANNEL

75 PARTNER ACKNOWLEDGES AND AGREES THE AVAYA
76 CHANNEL PARTNER IS RESPONSIBLE FOR ANY AND ALL
77 RELATED FEES AND/OR ROYALTIES. THE H.264 (AVC) CODEC
78 IS LICENSED UNDER THE AVC PATENT PORTFOLIO LICENSE
79 FOR THE PERSONAL USE OF A CONSUMER OR OTHER USES
80 IN WHICH IT DOES NOT RECEIVE REMUNERATION TO: (I)
81 ENCODE VIDEO IN COMPLIANCE WITH THE AVC STANDARD
82 ("AVC VIDEO") AND/OR (II) DECODE AVC VIDEO THAT WAS
83 ENCODED BY A CONSUMER ENGAGED IN A PERSONAL
84 ACTIVITY AND/OR WAS OBTAINED FROM A VIDEO PROVIDER
85 LICENSED TO PROVIDE AVC VIDEO. NO LICENSE IS GRANTED
86 OR SHALL BE IMPLIED FOR ANY OTHER USE. ADDITIONAL
87 INFORMATION FOR H.264 (AVC) AND H.265 (HEVC) CODECS
88 MAY BE OBTAINED FROM MPEG LA, L.L.C. SEE [HTTP://
89 WWW.MPEGLA.COM](http://www.mpegla.com).

90 Compliance with Laws

91 You acknowledge and agree that it is Your responsibility for
92 complying with any applicable laws and regulations, including, but not
93 limited to laws and regulations related to call recording, data privacy,
94 intellectual property, trade secret, fraud, and music performance
95 rights, in the country or territory where the Avaya product is used.

96 Preventing Toll Fraud

97 "Toll Fraud" is the unauthorized use of your telecommunications
98 system by an unauthorized party (for example, a person who is not a
99 corporate employee, agent, subcontractor, or is not working on your
100 company's behalf). Be aware that there can be a risk of Toll Fraud
101 associated with your system and that, if Toll Fraud occurs, it can
102 result in substantial additional charges for your telecommunications
103 services.

104 Avaya Toll Fraud intervention

105 If You suspect that You are being victimized by Toll Fraud and You
106 need technical assistance or support, call Technical Service Center
107 Toll Fraud Intervention Hotline at +1-800-643-2353 for the United
108 States and Canada. For additional support telephone numbers, see
109 the Avaya Support website: <https://support.avaya.com> or such
110 successor site as designated by Avaya.

111 Security Vulnerabilities

112 Information about Avaya's security support policies can be found in
113 the Security Policies and Support section of [https://
114 support.avaya.com/security](https://support.avaya.com/security).

115 Suspected Avaya product security vulnerabilities are handled per the
116 Avaya Product Security Support Flow ([https://
117 support.avaya.com/css/P8/documents/100161515](https://support.avaya.com/css/P8/documents/100161515)).

118 Downloading Documentation

119 For the most current versions of Documentation, see the Avaya
120 Support website: <https://support.avaya.com>, or such successor site
121 as designated by Avaya.

122 Contact Avaya Support

123 See the Avaya Support website: <https://support.avaya.com> for
124 product or Hosted Service notices and articles, or to report a problem
125 with your Avaya product or Hosted Service. For a list of support
126 telephone numbers and contact addresses, go to the Avaya Support
127 website: <https://support.avaya.com> (or such successor site as
128 designated by Avaya), scroll to the bottom of the page, and select
129 Contact Avaya Support.

130 Regulatory Statements

131 Australia Statements

132 Handset Magnets Statement:



Danger:

133 The handset receiver contains magnetic devices that can
134 attract small metallic objects. Care should be taken to avoid
135 personal injury.

136 Industry Canada (IC) Statements

137 RSS Standards Statement

1 This device complies with Industry Canada licence-exempt RSS
2 standard(s). Operation is subject to the following two conditions:

- 3 1. This device may not cause interference, and
- 4 2. This device must accept any interference, including
5 interference that may cause undesired operation of the
6 device.

7 Le présent appareil est conforme aux CNR d'Industrie Canada
8 applicables aux appareils radio exempts de licence. L'exploitation est
9 autorisée aux deux conditions suivantes:

- 10 1. L'appareil ne doit pas produire de brouillage, et
- 11 2. L'utilisateur de l'appareil doit accepter tout brouillage
12 radioélectrique subi, même si le brouillage est susceptible
13 d'en compromettre le fonctionnement.

14 *Radio Transmitter Statement*

15 Under Industry Canada regulations, this radio transmitter may only
16 operate using an antenna of a type and maximum (or lesser) gain
17 approved for the transmitter by Industry Canada. To reduce potential
18 radio interference to other users, the antenna type and its gain
19 should be so chosen that the equivalent isotropically radiated power
20 (EIRP) is not more than that necessary for successful
21 communication.

22 Conformément à la réglementation d'Industrie Canada, le présent
23 émetteur radio peut fonctionner avec une antenne d'un type et d'un
24 gain maximal (ou inférieur) approuvé pour l'émetteur par Industrie
25 Canada. Dans le but de réduire les risques de brouillage
26 radioélectrique à l'intention des autres utilisateurs, il faut choisir le
27 type d'antenne et son gain de sorte que la puissance isotrope
28 rayonnée équivalente ne dépasse pas l'intensité nécessaire à
29 l'établissement d'une communication satisfaisante.

30 This Class B digital apparatus complies with Canadian ICES-003.
31 Cet appareil numérique de la classe B est conforme à la norme
32 NMB-003 du Canada.

33 *Radiation Exposure Statement*

34 This equipment complies with FCC & IC RSS102 radiation exposure
35 limits set forth for an uncontrolled environment. This equipment
36 should be installed and operated with minimum distance 20cm
37 between the radiator & your body. This transmitter must not be co-
38 located or operating in conjunction with any other antenna or
39 transmitter.

40 Cet équipement est conforme aux limites d'exposition aux
41 rayonnements ISÉ établies pour un environnement non contrôlé.
42 Cet équipement doit être installé et utilisé avec un minimum de 20
43 cm de distance entre la source de rayonnement et votre corps.

44 This product meets the applicable Innovation, Science and Economic
45 Development Canada technical specifications.

46 *Japan Statements*

47 *Class B Statement*

48 This is a Class B product based on the standard of the VCCI Council.
49 If this is used near a radio or television receiver in a domestic
50 environment, it may cause radio interference. Install and use the
51 equipment according to the instruction manual.

この装置は、クラスB情報技術装置です。この装置は、家庭環境で使用
することを目的としていますが、この装置がラジオやテレビジョン受信機に
近接して使用されると、受信障害を引き起こすことがあります。

52 取扱説明書に従って正しい取り扱いをして下さい。 VCCI-B

53 *Denan Power Cord Statement*



Danger:

54 Please be careful of the following while installing the
55 equipment:

- 56 • Please only use the connecting cables, power cord, and
57 AC adapters shipped with the equipment or specified by
58 Avaya to be used with the equipment. If you use any
59 other equipment, it may cause failures, malfunctioning,
60 or fire.

- 61 • Power cords shipped with this equipment must not be
62 used with any other equipment. In case the above
63 guidelines are not followed, it may lead to death or
64 severe injury.



警告

65 本製品を安全にご使用頂くため、以下のことにご注意ください。

- 67 • 接続ケーブル、電源コード、ACアダプタなどの部品は、必ず
68 製品に同梱されております添付品または指定品をご使用くだ
69 さい。添付品指定品以外の部品をご使用になると故障や動作
70 不良、火災の原因となることがあります。
- 71 • 同梱されております付属の電源コードを他の機器には使用し
72 ないでください。上記注意事項を守らないと、死亡や大怪我
73 など人身事故の原因となることがあります。

74 *México Statement*

75 The operation of this equipment is subject to the following two
76 conditions:

- 77 1. It is possible that this equipment or device may not cause
78 harmful interference, and
- 79 2. This equipment or device must accept any interference,
80 including interference that may cause undesired operation.

81 La operación de este equipo está sujeta a las siguientes dos
82 condiciones:

- 83 1. Es posible que este equipo o dispositivo no cause
84 interferencia perjudicial y
- 85 2. Este equipo o dispositivo debe aceptar cualquier
86 interferencia, incluyendo la que pueda causar su operación
87 no deseada.

88 *Brazil Statement*

89 Este equipamento não tem direito à proteção contra interferência
90 prejudicial e não pode causar interferência em sistemas devidamente
91 autorizados

92 *Power over Ethernet (PoE) Statement*

93 This equipment must be connected to PoE networks without routing
94 to the outside plant.

95 *U.S. Federal Communications Commission (FCC) Statements*

96 *Compliance Statement*

97 The changes or modifications not expressly approved by the party
98 responsible for compliance could void the user's authority to operate
99 the equipment.

100 To comply with the FCC RF exposure compliance requirements, this
101 device and its antenna must not be co-located or operating to
102 conjunction with any other antenna or transmitter.

103 This device complies with part 15 of the FCC Rules. Operation is
104 subject to the following two conditions:

- 105 1. This device may not cause harmful interference, and
- 106 2. This device must accept any interference received,
107 including interferences that may cause undesired
108 operation.

109 This equipment has been tested and found to comply with the limits
110 for a Class B digital device, pursuant to Part 15 of the FCC Rules.
111 These limits are designated to provide reasonable protection against
112 harmful interferences in a residential installation. This equipment
113 generates, uses and can radiate radio frequency energy and, if not
114 installed and used in accordance with the instructions, may cause
115 harmful interference to radio communications. However, there is no
116 guarantee that interference will not occur in a particular installation. If
117 this equipment does cause harmful interferences to radio or
118 television reception, which can be determined by turning the

- 1 equipment off and on, the user is encouraged to try to correct the
2 interference by one or more of the following measures:
- 3 • Reorient or relocate the receiving antenna.
 - 4 • Increase the separation between the equipment and receiver.
 - 5 • Connect the equipment into an outlet on a circuit different from
6 that to which the receiver is connected.
 - 7 • Consult the dealer or an experienced radio/TV technician for
8 help.

9 *Radiation Exposure Statement*

10 This equipment complies with FCC radiation exposure limits set forth
11 for an uncontrolled environment. This equipment should be installed
12 and operated with minimum distance of 8 in or 20 cm between the
13 radiator and your body. This transmitter must not be co-located or
14 operating in conjunction with any other antenna or transmitter.

15 **ENERGY STAR® compliance statement**



16
17 As an ENERGY STAR partner, Avaya Inc. has determined that this
18 product meets the ENERGY STAR guidelines for energy efficiency.
19 Information on the ENERGY STAR program can be found at
20 www.energystar.gov. ENERGY STAR and the ENERGY STAR mark
21 are registered trademarks owned by the U.S. Environmental
22 Protection Agency.

23 **EU Countries**

24 This device when installed complies with the essential requirements
25 and other relevant provisions of the EMC Directive 2014/30/EU,
26 Safety LV Directive 2014/35/EU, and **Radio Equipment Directive**
27 **2014/53/EU**. A copy of the Declaration may be obtained from [https://](https://support.avaya.com)
28 support.avaya.com or Avaya Inc., 4655 Great America Parkway,
29 Santa Clara, CA 95054–1233 USA.

30 **WiFi transmitter**

- 31 • Frequencies for 2412-2472 MHz, transmit power: 17.8 dBm
- 32 • Frequencies for 5180-5240 MHz, transmit power: 19.14 dBm

33 **BT transmitter**

- 34 • Frequencies for 2402-2480 MHz, transmit power: 5.06 dBm

35 **General Safety Warning**

- 36 • Use only the Avaya approved Limited Power Source power
37 supplies specified for this product.
- 38 • Ensure that you:
 - 39 - Do not operate the device near water.
 - 40 - Do not use the device during a lightning storm.
 - 41 - Do not report a gas leak while in the vicinity of the leak.
 - 42 - **For Accessory Power Supply – Use Only Limited Power**
43 **Supply Pihong Technology Co. Ltd. Model:**
44 **PSAC12R-050, Output: 5VDC, 2.4A.**

45 **Trademarks**

46 The trademarks, logos and service marks (“Marks”) displayed in this
47 site, the Documentation, Hosted Service(s), and product(s) provided
48 by Avaya are the registered or unregistered Marks of Avaya, its
49 affiliates, its licensors, its suppliers, or other third parties. Users are
50 not permitted to use such Marks without prior written consent from
51 Avaya or such third party which may own the Mark. Nothing
52 contained in this site, the Documentation, Hosted Service(s) and
53 product(s) should be construed as granting, by implication, estoppel,
54 or otherwise, any license or right in and to the Marks without the
55 express written permission of Avaya or the applicable third party.

56 Avaya is a registered trademark of Avaya Inc.

57 All non-Avaya trademarks are the property of their respective owners.
58 Linux® is the registered trademark of Linus Torvalds in the U.S. and
59 other countries.

60 **Device Usage Consent**

61 By using the Avaya device you agree that Avaya, from time to time,
62 may collect network and device data from your device and may use
63 such data in order to validate your eligibility to use the device.

Contents

Chapter 1: Introduction	12
Purpose	12
Chapter 2: Phone overview	13
Physical layout	14
Optional components	16
Chapter 3: Getting started	17
Entering the file server address	17
Identifying the device type during phone boot-up	18
Logging in to your phone	18
Logging out of your phone	19
Locking your phone	19
Unlocking your phone	19
Connecting to a WiFi network	20
Chapter 4: Navigation	21
Cursor navigation	21
Navigation cluster	21
Text input	22
Line keys	22
Main menu	23
General phone icons	23
Presence icons	25
Multiple Level Precedence and Preemption icons	26
Wi-Fi icons	27
Chapter 5: Handling incoming calls	28
Answering a call	28
Answering a call when on another call	28
Handling calls and conferences using Multiple Device Access	29
Ignoring a call	29
Declining a call	30
Chapter 6: Handling outgoing calls	31
Making a call by using the dial mode	31
Making a call without using the dial mode	31
Redialing a number	31
Making a call by using speed dial	32
Making a call from the local Contacts list	32
Making a call from the corporate database Contacts list	33
Making an international call	33
Emergency call	33
Making an emergency call	34

Chapter 7: Call-related features	35
Muting and unmuting a call	35
Placing a call on hold and resuming the call	35
Chapter 8: Managing contacts	36
Adding a new contact	36
Adding a contact from the Recents list	37
Editing a contact	37
Doing a quick search for a contact	37
Viewing the contact details	38
Searching for a contact	39
Combining contacts	39
Deleting a contact	40
Creating a local Contacts group	40
Adding a contact to the local group	41
Removing a contact from the local group	41
Assigning a ringtone to a contact	42
LDAP Directory	42
Setting LDAP Directory as the contact search source	43
Searching LDAP contacts	43
Chapter 9: Managing Recents	45
Call log	45
Making a call from Recents	45
Viewing the Recents details	45
Deleting a call record from Recents	46
Clearing the Recents list	47
Chapter 10: Managing conference calls	48
Adding a person to an active call	48
Adding a person on hold to a conference call	48
Putting a conference call on hold and resuming a call	49
Dropping or Disconnecting the last participant from a conference call	49
Viewing the details of a conference	50
Chapter 11: Advanced features	51
Accessing the Features screen	51
Active call shortcut keys	51
Making a call transfer with a shortcut key	52
Making a conference call with a shortcut key	52
Activating the screen saver	53
Activating Send All Calls	53
Automatic Callback	54
Setting up Automatic Callback	54
Autodialing a pre-assigned number	54
Blocking your extension from displaying during calls	55
Bridged Call Appearance	55

Making a call on a bridged line.....	55
Answering a bridged line call.....	56
Joining a call on a bridged line	56
Busy Indicator.....	56
Busy Indicator icons and LED indication.....	57
Busy Indicator call operations.....	57
Call Transfer to a monitored user.....	58
Calendar.....	59
Accessing calendar.....	59
Configuring the Microsoft® Exchange Server calendar.....	60
Reviewing your Calendar event.....	60
Call Forwarding.....	61
Forwarding a call to another extension.....	62
Setting enhanced call forwarding.....	62
Call forwarding to your cell phone using EC500.....	64
Calling in your intercom group.....	65
Call Parking.....	65
Parking a call.....	65
Unparking a call.....	66
Dynamic Park and Page	66
Parking and paging an active call.....	66
Retrieving the parked call.....	67
Call Pickup.....	67
Answering a call for a Call Pickup group member.....	68
Answering a call in the same Call Pickup group.....	68
Answering a call using the extension number.....	69
Call recording.....	69
Recording a call.....	70
Call Transfer.....	70
Making a consultative transfer.....	70
Making a blind transfer.....	71
Crisis alert station.....	71
Acknowledging the crisis alert.....	72
Emergency caller information.....	72
Stopping the crisis alert.....	73
Acknowledging the crisis alert after an error in the first acknowledgment.....	73
Displaying your extension on outgoing calls.....	74
Excluding others from bridging on to your call.....	74
Extending a call to your cell phone.....	75
Retrieving a voice message.....	75
Hunt Group Busy.....	76
Using Hunt Group Busy.....	76
Interrupting a call with a whisper page.....	76

Limit Incoming Calls.....	77
Activating Limit Incoming Calls.....	77
Deactivating Limit Incoming Calls.....	77
Long-term acoustic exposure protection.....	78
Configuring Long term acoustic protection.....	78
Multiple Device Access.....	79
Using URI dialing to make a call.....	80
Making a priority call.....	80
Multicast Paging.....	80
Sending a multicast page.....	81
No Hold Conference.....	81
Adding a participant to no hold conference.....	82
Precedence call.....	82
Making a precedence call by using the Main menu.....	83
Making a precedence call by using dial plan configuration.....	83
Pre-configuration of keys.....	84
Presence.....	84
Viewing the Presence status of your contacts.....	84
Changing your Presence status.....	85
SLA Mon™	85
Shared control	86
Team Button.....	87
Answering an active call on a monitored extension.....	87
Viewing the status of monitored stations.....	87
Speed dialing to a monitored extension.....	88
Transferring a call to a monitored phone.....	88
Monitoring other extensions at a glance.....	89
Tracing a malicious call.....	89
Using a Guest Login.....	90
WML browser.....	90
Accessing the WML browser.....	91
Chapter 12: Customization.....	92
Phone.....	92
Setting the dialing mode.....	92
Displaying call timers.....	92
Setting key repeat delay.....	93
Setting redial options.....	93
Assigning speed dial entries.....	94
Setting Mute alert.....	95
Visual alerting.....	95
Customizing phone keys.....	96
Restoring customized keys to default.....	97
Applications.....	97

Enabling the Away timer.....	97
Enabling phone auto-lock.....	98
Turning call history on and off.....	98
Enabling and disabling Microsoft® Exchange contact integration.....	99
Calendar settings.....	99
Activating Do not disturb.....	101
Redirecting calls when Do Not Disturb is active.....	102
Audio.....	102
Turning automatic gain control on or off.....	102
Enabling and disabling Bluetooth.....	103
Pairing a Bluetooth enabled headset with your phone.....	103
Turning button clicks on and off.....	104
Turning error tones on and off.....	104
Enabling wireless headset bidirectional signaling.....	104
Setting headset mic level.....	105
Configuring hearing aid compatibility.....	106
Setting a headset profile.....	106
Setting a personalized ringtone.....	107
Display.....	108
Changing the background image.....	108
Changing the screen saver.....	108
Setting the screen saver details.....	109
Adjusting the brightness of a phone screen.....	109
Setting the display language.....	110
Setting the backlight timer.....	110
Setting the time format.....	110
Setting the date format.....	111
Setting the time zone.....	111
Setting the text size.....	112
Setting the phone screen width.....	112
Setting the network mode.....	113
Setting the network configuration.....	113
Connecting to a Wi-Fi network.....	115
Chapter 13: Troubleshooting	116
Limited access during failover.....	116
Recording audio parameters	117
Viewing the Product ID.....	117
Viewing the Device type.....	118
Viewing the Server type.....	118
Chapter 14: Resources	119
Documentation.....	119
Finding documents on the Avaya Support website.....	121
Avaya Documentation Center navigation.....	121

Viewing Avaya Mentor videos..... 122

Support..... 123

Chapter 1: Introduction

Purpose

- 3 This document describes the features of the Avaya J189 IP Phone and also provides instructions
- 4 on how to use this phone.
- 5 This document is for end users.

Chapter 2: Phone overview

The Avaya J189 IP Phone is intended to be used in business communications. The phone supports up to ten call appearances with five lines of call display.

The Avaya J189 IP Phone has a secondary display and can support up to three button modules, and each button module provides 24 additional lines.

Physical specifications

- 5 call appearances in Full Screen mode and 10 call appearances in Half Screen mode
- 800 x 480 pixels (main LCD), 240 x 320 pixels (secondary LCD)
- Secondary Display
- 4 softkeys
- 5 Menu navigation buttons and two navigation buttons for Secondary Display
- Dual 10/100/1000 network ports
- Optional 5V DC Power support
- 48Vdc POE support
- J100 wireless card support
- Magnetic Hook Switch
- Button module support

Physical layout



No.	Name	Description
1	Beacon LED	Provides visual alerts for the following: • Incoming call • Voice mail

Table continues...

No.	Name	Description
2	Phone display	Displays two areas: 1. Top Bar: It is always visible, and displays communication status, time and date, and device status. 2. Application area displays the following: • Application header: It displays the context specific application title and subtitles. The header is always empty on the Phone screen. • Application content area: It displays menus, lists, pop-up windows, images, and other application content. • Softkey labels area: It displays labels with information about the state of the soft key button.
3, 16	Line keys	Used to select the corresponding line or feature. Each line key has a combination of red and green LEDs that provide call or feature specific visual alert.  Note: The default action depends on the application and the context.
4	Soft keys	Used to select the corresponding label of context-specific actions. With the Help soft key, you can view a short description of the features available on your phone.
7	Navigation cluster	Used to navigate on the phone screen. • Up and Down arrow keys: To scroll up and down. • Right and Left arrow keys: To move cursor in the text input field, and to toggle values in the selection fields. • OK button: To select the action assigned to the first soft key.
8	Voicemail	Used to dial the configured voice mail number to receive a voice message.
10	Dialpad keys	Used to dial the phone extensions or enter alphanumeric characters and special symbols.
12	End Call	Used to end an active call, including outgoing not answered, transferred, and conference calls. The End Call key ends ongoing direct calls from any screen. In case of adding a participant to a conference or selecting a destination for call transfer, it cancels these operations, and resumes a held call. You can also close the Dialing screen, cancel dialing, and stop audio push by pressing this key.
13	Headset	Used to turn on headset, and also to toggle your call from the speaker to headset.

Table continues...

No.	Name	Description
14	Speaker	Used to turn on the speaker.
15	Secondary display	Provides quick access to line appearances, features, and phone menus.
17	Volume	Used to adjust volume of a handset, speaker, or ringtone. • (+) : To increase the volume. • (-): To decrease the volume.
18	Mute Button	Used to mute and unmute the outgoing audio.
19	Left, Right keys	Used to navigate on the Secondary Display screen.
20	Handset	Used to receive and make calls.

1 Application keys provide direct access to the corresponding applications:

No.	Application keys	Description
5	Main Menu	Displays the list of options, such as Features , Applications , Settings , and Network Information .
6	Phone key	Displays the Phone screen.
9	Contacts	Displays the entries in your Contact list.
11	Recents	Displays the list of all calls.

2 Optional components

3 You can use the following optional components with the phone:

- 4 • PSAC12R-050 – 5V DC Power adapter
- 5 • JBM24 Button Module
- 6 • Avaya J100 Expansion Module
- 7 • PoE power supply
- 8 • J100 wireless card support

Chapter 3: Getting started

Entering the file server address

About this task

Enter the file server address if the phone prompts, for example, when you connect to the network for the first time.

Before you begin

Obtain the file server address from the system administrator.

Procedure

1. When you boot the phone for the first time, the Auto Provisioning screen displays `Do you want to activate Auto Provisioning now?`, press one of the following:

- **Yes:** To connect to the Device Enrollment Services (DES) server to obtain the file server address and ignore the file server address from the DHCP.
- **No:** To obtain the file server address from the DHCP server.

In case of a time out, and the DHCP does not provide the file server address, the phone selects **Yes**.

If the connection to DES is successful, and the phone receives the file server address, the phone continues to boot and not prompt you for the file server address.

If the connection to DES is successful, and the phone does not receive the file server address, the phone prompts you for an Enrollment code. Contact your administrator for an Enrollment code. When you enter the valid Enrollment code, the phone continues to boot and not prompt you for the file server address.

If you do not have an Enrollment code, press Cancel. The phone continues to boot using the DHCP.

If the connection is successful, the phone displays the `Starting` message. If the phone does not receive the file server address from the DES or the DHCP server, the phone displays the Enter the file server address screen.

2. On Enter the file server address screen, press one of the following:

- **Config:** To enter the file server address.
- **Never:** To never prompt for the file server address.
- **Cancel:** To cancel the prompt and display the Login screen.

3. After you have pressed **Config**, enter the file server address in the **Address** field.

The address can be in the form of a numerical IP address or an alphanumeric Fully Qualified Domain Name (FQDN) like `http://myfileservr.com/j100/`.

 Tip:

4 To enter the dot symbol (.) in the field, press the alphanumeric soft key to toggle to the alphanumeric mode.

6 To enter the forward slash symbol (/) in the field, press the / soft key.

4. Press **Save**.

The phone continues to boot and connect to the file server address for provisioning configuration.

Identifying the device type during phone boot-up

About this task

Avaya J100 Series IP Phones screen displays the device type during the phone boot-up. This feature is supported only in the phone software version 4.0.3 and later.

Procedure

1. Set up the phone hardware.

2. Plug the Ethernet cable to the phone.

The phone powers up and starts to initialize.

The phone primary screen displays one of the following as the backplash screen:

- A screen with Avaya text for Avaya SIP phones
- A screen with Open SIP text for Open SIP phones

Logging in to your phone

Before you begin

Your extension and password are provided by your administrator.

Procedure

1. On the Login screen in the **Username** field, type your extension.

2. Press **Enter**.

3. In the **Password** field, type your password.

4. Press **Enter**.

Logging out of your phone

About this task

Use this procedure to log out of your primary or guest user extension.

 Note:

- 5 After a guest user logs out, the primary user will be logged in.

Procedure

1. Press **Main menu**.
2. Scroll to **Applications**, and press **Select**.
3. Scroll to **Log out**, and press **Select**.
4. In the confirmation window, press **Log out**.

Related links

[Using a Guest Login](#) on page 90

Locking your phone

About this task

You can lock your phone to prevent unauthorized use of the phone when you are away. Locking your phone does not log you out, you can still receive all calls and make calls to emergency numbers.

To lock the phone, press **Main menu**, and select **Applications > Lock**.

Unlocking your phone

About this task

You can unlock your phone using a PIN or a password. Depending on the configuration made by your administrator, the phone screen displays the field for entering either a PIN or a password. A PIN is a digit-only value whereas a password can be an alphanumeric value.

If you do not know or remember your PIN or password, contact your administrator.

You cannot unlock the phone if you enter an incorrect PIN or password.

1 Your administrator sets a limit to the number of incorrect attempts. If you exceeded the limit, the
2 phone temporarily blocks you from attempting to unlock the phone for a period that your
3 administrator specifies.

4 To unlock the phone, press **Unlock** and enter the PIN or password.

5 Connecting to a WiFi network

6 About this task

7 Use this procedure to connect your phone to an available WiFi network.

8 Before you begin

9 Make sure your phone is connected to a WiFi module and WiFi connection is enabled by your
10 administrator.

11 Procedure

- 12 1. From the **Main Menu**, navigate to **Settings > Network > Network Mode**.
- 13 2. Toggle WiFi.
- 14 3. Scroll to a WiFi network you want to connect to from the list of available networks and
15 press **Connect**.
- 16 4. Press **Info** to view the selected network details.

17 Next steps

18 Switching back to Ethernet network mode causes the phone to reboot.

Chapter 4: Navigation

Cursor navigation

You can use the navigation cluster for cursor movement or selection of options on the Phone screen or in other menus. The navigation cluster has the following keys on the phone:

- **Left Arrow**
- **Right Arrow**
- **Up Arrow**
- **Down Arrow**
- **OK**

Navigation cluster

The effect of pressing a navigation key depends on the current application and context.

Key name	Description
Left Arrow and Right Arrow	Use these keys in: • Text input fields to move the cursor position. • Selection fields to toggle field values and select options in lists and menus. • Half-width displays to move the selection left or right. • Scrolling between pages when navigating the phone screen, provided that page scrolling mode is switched on by your administrator. The directional keys are context-sensitive.
Up Arrow and Down Arrow	Use these keys to scroll vertically in lists, menus, and pop-up windows.
OK	Unless otherwise specified, use this key for the first or left-most soft key action. If there are two or more pages of soft keys, the OK key is active only when the phone screen displays the first page of soft keys.

1 Text input

2 You can use the dial pad or the text input soft keys to edit and enter text in the text input fields of
3 the phone.

4 Input field

5 Depending on the application and context, a text input field is a text box with a label. The user
6 interface displays labels on the left side of the text box or in the line preceding the text box. An
7 input field can be blank or display a current value that can be modified. The user interface displays
8 input cursors on the right side of the current value or, if the input field is blank, on the left side of
9 the text box.

10 Hint text

11 Depending on the application and context, a text box contains hint text. The user interface
12 displays hint text on the left side of the text box in grey, italic font. The interface replaces the hint
13 text with the actual text that you enter. The interface displays the hint text again when you clear
14 the entered text. The interface does not display the hint text if the field contains a value.

15 Text truncation

16 When the space in the input area cannot display the full current value, the user interface truncates
17 the text. The interface truncates the text from the left side and displays a blank space with a cursor
18 on the right side of the input field for a new entry. When you enter a new character, the interface
19 truncates the existing character from the left side of the display.

20 Active language text direction

21 When the text direction of the active language is right-to-left, the text entry rules are reversed. The
22 user interface:

- 23 • Displays the hint text on the right side of the text box.
- 24 • Displays the input cursor on the left side of the current character or, if the input field is blank,
25 on the right side.
- 26 • Displays the new character on the left side of the current character.
- 27 • Deletes the character on the right side of the cursor when you press **Backspac**.

28 Line keys

29 The line keys are context-sensitive. When you press a line key:

- 30 • In full-width lists, the user interface selects the corresponding line or the object.
- 31 • In half-width lists, the interface selects the list item adjacent to the key.
- 32 • In page scroll mode and then scroll on to the next or previous page, the selected item
33 remains highlighted.

Input line

The following actions take place when you press the line key against the input lines.

- Selects the corresponding line for the line which accepts user input.
- Displays the cursor after the last character of the existing content if the line is an input line. If an input line is selected, the interface performs no action even if the cursor is in the middle of the line.
- Performs the action of the first soft key for the line which does not accept user input even if the line is already selected.

For example, when you press a line key in Contacts, the interface initiates a call to the contact because the first soft key represents the **Call** key.

Main menu

The following table lists the Main menu icons used in Avaya J189 IP Phone:

Icons	Name	Description
	Features	To access administrator activated features.
	Applications	• To access phone applications such as Contacts, Recents, and activate screen saver. • To sign off the phone, to protect your settings, or to let another user log in.
	Settings	To change your phone settings, customize button labels, adjust brightness, audio settings, assign speed dial entries, etc.
	Network information	To check network settings.
	Administration	To access administration settings.
	About	To view the phone model, software version, default device type, and the default server type.

General phone icons

The following table lists the icons used in the Avaya J189 IP Phone:

Icon	Description
	Microphone is muted.
	Missed call on your phone. You can see this icon in the Recents application.
	Incoming call; indicates you have answered this call. You can see this icon in the Recents application.
	Outgoing call; indicates you have made this call. You can see this icon in the Recents application.
	Bridged call; indicates this line is being used for a call on another phone.
	Incoming call is alerting.
	Outgoing call; indicates you have made this call.
	Call is active.
	Call is on hold.
	Call is on hold during a conference or transfer call setup.
	Conference is active.
	Conference is on hold.
	Use the Right or Left navigation arrow to see more pages / screens / options.
	Scroll left for other options.
	Scroll right for other options.
	Team icon indicating this team member is available.
	Team icon indicating this team member is busy on a call and unavailable.
	Team icon indicating this team member is not on a call, but is forwarding incoming calls.
	Team icon indicating this team member is busy on a call and is forwarding incoming calls.

Table continues...

Icon	Description
	Indicates that the phone is not connected to the SIP proxy server and is operating in Failover mode. Some features might not be available or work incorrectly. If the appearance line displays this icon, it indicates that the phone has encountered a failure and has preserved the media session until the user hangs up. This icon can also indicate that the phone is connected to the call server but the features are not available.
	The EC500 feature is on.
	The Do not disturb feature is on.
	The Call forward feature is on.
	Indicates that the call is using a wideband codec for excellent voice quality.
	Indicates a low network performance or presence of local network issues that might result in lower call quality.
	The Limit Number of Concurrent Calls (LNCC) feature is on.
	Indicates that the SLA Mon™ agent has taken control of the phone.
	Indicates that the call is being recorded for SLA Mon™.
	Indicates that the audio of this call is secure.
	Indicates that the audio alert for incoming calls is off.
	Indicates the Bluetooth feature is on.
	Indicates that you have missed a call. The number in the icon indicates the number of missed calls.
	Indicates that you have missed a call. The + in the icon indicates that the number of missed calls are more than 9.
	Autodialing feature

1 Presence icons

2 The following table lists presence icons for the Avaya J189 IP Phone and their description:

Icon	Status	Description
	Available	Contact is available and can communicate.
	On a call	Contact is on a call.
	Busy	Contact is busy.
	Away	Contact is away from the phone.
	Do Not Disturb	Contact does not want to communicate.
	Out of Office / Offline	Out of Office: Contact is out of office. Offline: Contact is offline or wants to appear invisible.
	Unknown	The presence status of the contact is unknown or the phone is not registered.

1 Related links

- 2 [Changing your Presence status](#) on page 85

3 Multiple Level Precedence and Preemption icons

- 4 The following table lists the icons used in Avaya J189 IP Phone.

Icon	Precedence level	Description
	Priority	Priority icon for a priority call.
	Routine	Routine icon for a regular call.
	Immediate	Immediate icon for a priority call with a higher precedence value than Priority.
	Flash	Flash icon for a priority call with a higher precedence value than Immediate.
	Flash Override	Flash override icon for a priority call with the highest precedence.

1 Wi-Fi icons

2 The following table lists the Wi-Fi icons used in the Avaya J189 IP Phone:

Icon	Description
	Non-secure Wi-Fi network is detected.
	Secure Wi-Fi network is detected.
	Wi-Fi network is out of range or offline.

Chapter 5: Handling incoming calls

Answering a call

About this task

Use this procedure to answer a call. When you receive a call, the phone does the following:

- Generates audio-visual alerts.
- Displays the caller's name or number.

* Note:

- When the Incoming call pop-up window is displayed, the only visual alert is the flashing beacon LED. If you press **Ignore**, both the beacon LED and line key LED start flashing.

Procedure

Do one of the following:

- Lift the handset.
- Press **Speaker**.
- Press **OK**.
- Press the **Answer** soft key.
- Press **Headset**.

Answering a call when on another call

About this task

You can receive a call on a secondary call appearance only if the call appearance is free.

Procedure

Press one of the following:

- The **Answer** soft key
- **OK**

The phone puts the first call on hold and moves to the second call.

1 Handling calls and conferences using Multiple Device 2 Access

3 About this task

4 With the Avaya Aura® and Multiple Device Access feature, you can have up to ten devices
5 configured with the same extension number. You can use this extension number to transfer active
6 calls between your devices.

7 Before you begin

8 Ensure that the system administrator has activated the Multiple Device Access feature (MDA) for
9 your extension.

10 Procedure

- 11 1. Initiate a call from your phone.
- 12 2. To transfer the call to another phone, press **Bridge** on your phone.

13 If the MDA phone that is joining the call uses a different signaling mode address family, you
14 might notice the Limited Service icon appear on your device for a brief moment. After the
15 MDA phone that is joining the call switches to using the signaling mode address family of
16 the active call, the icon disappears.

17 Related links

18 [Adding a participant to no hold conference](#) on page 82

19 [Multiple Device Access](#) on page 79

20 Ignoring a call

21 About this task

22 When you do not want to answer a call or you are on another call, you can ignore the new
23 incoming call. When you ignore a call, only the ring alert on your phone stops, you can still answer
24 this call within its ring time by using the Up and Down arrow keys to select the call and answer it.

25 Procedure

26 On the Incoming call screen, press one of the following:

- 27 • **Ignore** soft key
- 28 • **+ volume** button
- 29 • **- volume** button

30 The phone turns off the audio alert.

 Note:

- 1 If you ignore a call using the Bluetooth headset, to answer back the call, press **Answer** or
- 2 **Headset** button on the phone.

3 Declining a call

4 About this task

5 You can decline an incoming call when you do not want to answer a call. The incoming call is
6 declined depending on the Call decline policy set by your administrator. Contact your administrator
7 to enable this feature for your extension and also to know about the Call decline policy.

8 Before you begin

9 Ensure that the feature is activated by the administrator. Contact your administrator for details.

10 Procedure

11 On the incoming call screen, press **Decline** soft key.

12 Result

13 The call is declined. Depending on your Call decline policy, the caller receives one of the following
14 alert:

- 15 • An audio message alert
- 16 • A busy tone alert

Chapter 6: Handling outgoing calls

Making a call by using the dial mode

About this task

Use this procedure to make a call without lifting the handset or pressing **Speaker**.

Set the dial mode on the phone to one of the following:

- **Auto**: Dial the number.

The phone starts the call when the inter digit timer times out.

- **Auto**: Dial the number and press # key.

Pressing # key indicates end of dial, the phone starts the call.

- **Manual**: Dial the number, and press the **Call** soft key.

Related links

[Setting the dialing mode](#) on page 92

Making a call without using the dial mode

Procedure

1. Do one of the following:

- Lift the handset.
- Press **Speaker**.
- Press **Headset**.

2. Dial the number.

Redialing a number

About this task

You can redial the most recently dialed number.

Before you begin

Ensure that the call history is not empty.

Procedure

1. Press **Redial** soft key.

The phone dials the most recently dialed number.

2. **(Optional)** To see the list of dialed numbers:

- a. Scroll to the number you want to redial.
- b. Press **Call**.

Related links

[Setting redial options](#) on page 93

Making a call by using speed dial

Before you begin

Ensure you have speed dial numbers assigned to your contacts.

Procedure

Press and hold the dial pad key assigned to the number you want to call.

Related links

[Assigning speed dial entries](#) on page 94

Making a call from the local Contacts list

Procedure

1. Press **Contacts**.
2. Scroll to the contact you want to call.
3. **(Optional)** Press the digits on the dial pad that correspond to the letters of the name of the person you want to call.
For example, press 76484 to search for someone whose name is Smith.
4. Press **Call**.

1 Making a call from the corporate database Contacts list

2 About this task

3 Depending on the configuration by your administrator you may be able to search and call contacts
4 from other remote contacts lists or directories.

5 Procedure

- 6 1. Press **Contacts**.
- 7 2. Press **Search**.
- 8 3. Enter the digits on the dial pad that correspond to the name of the person you want to call.
9 For example, press 76484 to search for someone whose name is Smith.
- 10 4. Press **Search** again.
11 The phone displays the contact saved in the corporate database.
- 12 5. Press **Call**.

13 Related links

14 [Searching for a contact](#) on page 39

15 Making an international call

16 Procedure

- 17 1. Press and hold the **0** key to enter the plus sign (+).
- 18 2. Dial the number that you want to call.

19 Emergency call

20 Emergency calling is used to connect to a preset emergency services number. The emergency
21 service number is configured by the administrator.

22 You can make an emergency call from the following screens:

- 23 • Login screen
- 24 • Phone screen
- 25 • Lock screen

26 In the IP Office environment, you can make an emergency call only when you are logged in to
27 your phone.

28 If your system administrator configures emergency calling for your phone, the Phone screen
29 displays the **Emerg** soft key.

Using the **Emerg** soft key, you can dial only the number that is given the highest priority by the system administrator. Alternatively, you can dial the emergency numbers by using the dial pad in the following cases:

- The **Emerg** soft key is unavailable.
- The **Emerg** soft key is available, but you want to dial an emergency number that is not set by the system administrator.

In the IP Office environment, the **Emerg** soft key is unavailable. You must dial the emergency number by using the dial pad.

Making an emergency call

Before you begin

Ensure that the **Emerg** soft key is assigned by your administrator.

Procedure

Do one of the following:

- On the Phone screen, press the **Emerg** soft key, and again press **Emerg** when the phone prompts you for confirmation.
- Dial the emergency number by using the dial pad.

Chapter 7: Call-related features

Muting and unmuting a call

About this task

If you mute a call on the phone, you must unmute it using the **Mute** button. If you mute the call on the Bluetooth headset, you must unmute it on the headset.

Procedure

1. To mute an active call, press **Mute**.
The **Mute** button is lit.
2. To unmute the call, press **Mute** again.

Placing a call on hold and resuming the call

About this task

During a call, you can place the call on hold. When you put a call on hold, both you and the caller cannot hear each other on the call. While a call is on hold, you can call other contacts. When multiple calls are held, you can return to the held call by using the up and down arrow keys to scroll to the required call.

Procedure

1. To put an active call on hold, press the **Hold** soft key, or press the line key of the active call.
2. To resume the held call, press the **Resume** soft key, or press the line key of the held call.

Chapter 8: Managing contacts

Adding a new contact

About this task

Use this procedure to add a contact to the phone. You can save up to 250 contacts.

Procedure

1. Press **Contacts**.
2. **(Optional)** To navigate through **Main menu**, do the following:
 - a. Scroll to **Applications**, and press **Select**.
 - b. Scroll to **Contacts**, and press **Select**.
3. Do one of the following:
 - If your Contacts list is empty, press **New**.
 - If your Contacts list is not empty, press **More > New**.
4. Use the dial pad to enter the contact's first and last name in the corresponding fields.
 - Press the number key that corresponds to the letter or number that you want to enter.
 - If the characters are on the same key, pause before entering the next character.
 - To enter a space, press **0**.
 - Enter the remaining letters or numbers.
 - To enter a symbol, press **More > Symbol**. Use the navigation arrows to highlight the symbol that you want to enter and press **Insert**.
 - To delete the last character, press the **Bksp** soft key.
5. Enter the extension.

The contact extension can include uppercase and lowercase letters, numbers 0 - 9, and special symbols, such as comma (,), plus (+), and dot (.).
6. Press **Save**.

Related links

[Adding a contact to the local group](#) on page 41

1 Adding a contact from the Recents list

2 About this task

3 Use this procedure to add a number to your Contacts list from your call history.

4 Procedure

- 5 1. Press **Recents**.
- 6 2. Scroll to the required number, and press **+Contact**.
- 7 3. In the **First name** and **Last name** fields, type the relevant information.
8 The phone assigns the extension number to **Last name**. You can remove the extension
9 number from this field and add other information.
- 10 4. Press **Save**.

11 Editing a contact

12 Procedure

- 13 1. Press **Contacts**.
- 14 2. **(Optional)** To navigate through **Main menu**, do the following:
 - 15 a. Scroll to **Applications**, and press **Select**.
 - 16 b. Scroll to **Contacts**, and press **Select**.
- 17 3. Select the contact.
- 18 4. Press **Details > Edit**.
- 19 5. Scroll to the field to edit.
- 20 6. Use the dial pad and soft keys to change the contact information.
- 21 7. Press **Save**.

22 Doing a quick search for a contact

23 About this task

24 Using the Quick Search feature of the phone, you can quickly search for a saved contact from the
25 Contacts list without entering the entire name of the contact.

26 Before you begin

27 Ensure that at least one contact is available in the Contacts list.

Procedure

1. Press **Contacts**.
2. **(Optional)** To navigate through **Main menu**, do the following:
 - a. Scroll to **Applications**, and press **Select**.
 - b. Scroll to **Contacts**, and press **Select**.
3. Press the key corresponding to the first letter of the first or last name of the contact on the dial pad.

Result

The phone displays all the contacts whose first or last name begins with the letter associated with the pressed key.

Viewing the contact details

About this task

Use this procedure to view the details of a contact. You can call, edit, or delete a contact from the Details window.

Before you begin

You must have at least one contact in the Contacts list.

Procedure

1. Press **Contacts**.
2. **(Optional)** To navigate through **Main menu**, do the following:
 - a. Scroll to **Applications**, and press **Select**.
 - b. Scroll to **Contacts**, and press **Select**.
3. Select the contact that you want to view.
4. Press **Details**.
 - To call the contact, press **Call**.
 - To edit the contact, press **Edit**.
 - To delete the contact, press **Delete**.
 - To view more options, press **More**.

1 Searching for a contact

2 About this task

3 Use this procedure to search contacts from the following:

- 4 • My contacts: J100 local contact entries
- 5 • My Exchange: exchange integration, My contacts
- 6 • Global Exchange: exchange integration, global contacts
- 7 • System contacts: Avaya Aura contacts
- 8 • LDAP: LDAP directory

9 Procedure

- 10 1. Press **Contacts**.
- 11 2. **(Optional)** To navigate through **Main menu**, do the following:
 - 12 a. Scroll to **Applications**, and press **Select**.
 - 13 b. Scroll to **Contacts**, and press **Select**.
- 14 3. Press **Search > More > Sources**.
- 15 4. In **Contact sources**, press **Toggle** for the required directory.
- 16 5. Press **Save**.
- 17 6. Use the dial pad to enter the name, and press **Search**.
- 18 7. **(Optional)** To add the contact to the local Contacts list, press **+Contact**.

19 Related links

20 [Making a call from the corporate database Contacts list](#) on page 33

21 Combining contacts

22 About this task

23 Use this procedure to merge the phone number of the current contact with the existing local
24 contact.

25 Before you begin

26 Ensure the Contacts list is not empty.

27 Procedure

- 28 1. Press **Contacts**.
- 29 2. **(Optional)** To navigate through **Main menu**, do the following:
 - 30 a. Scroll to **Applications**, and press **Select**.

- b. Scroll to **Contacts**, and press **Select**.
3. Scroll to the contact that you want to combine, and press **Details > More > Combine**.
The select mode displays the Contacts list without the current content.
4. To combine the current contact, scroll to the existing contact, and press **Select**.
The current contact will be deleted from the Contacts list and merged with the local contact.

Deleting a contact

Procedure

1. Press **Contacts**.
2. **(Optional)** To navigate through **Main menu**, do the following:
 - a. Scroll to **Applications**, and press **Select**.
 - b. Scroll to **Contacts**, and press **Select**.
3. Select the contact to delete.
4. Press **Details > More > Delete**.
5. Press one of the following:
 - **Delete**: To delete the contact.
 - **Cancel**: To cancel the action.

Creating a local Contacts group

Procedure

1. Press **Contacts**.
2. **(Optional)** To navigate through **Main menu**, do the following:
 - a. Scroll to **Applications**, and press **Select**.
 - b. Scroll to **Contacts**, and press **Select**.
3. Press **Groups**.
4. Press **NewGroup**.
5. In the **Enter group name** field, type your group name.
6. Press **Save**.

1 Adding a contact to the local group

2 Before you begin

- 3 • Ensure that your Contacts list is not empty.
- 4 • Create minimum one local group to add your contacts.

5 Procedure

- 6 1. Press **Contacts**.
- 7 2. **(Optional)** To navigate through **Main menu**, do the following:
 - 8 a. Scroll to **Applications**, and press **Select**.
 - 9 b. Scroll to **Contacts**, and press **Select**.
- 10 3. Press **Groups**.
- 11 4. Select the group, and press **+Members**.
- 12 5. Scroll to the contact you want to add, and press **Add**.
- 13 6. **(Optional)** To add more contacts, repeat Steps 4 and 5.

14 Related links

- 15 [Adding a new contact](#) on page 36

16 Removing a contact from the local group

17 Before you begin

- 18 Ensure that you have at least one user added to your Contacts list group.

19 Procedure

- 20 1. Press **Contacts**.
- 21 2. **(Optional)** To navigate through **Main menu**, do the following:
 - 22 a. Scroll to **Applications**, and press **Select**.
 - 23 b. Scroll to **Contacts**, and press **Select**.
- 24 3. Press **Groups**.
- 25 4. Scroll to the group, and press **Members**.

26 The phone displays the list of contacts in the group.
- 27 5. Select a contact, and press **Remove**.

28 The contact will be removed from your Contacts list.

1 Assigning a ringtone to a contact

2 About this task

3 Use this procedure to assign a ringtone to a contact. You can assign a ringtone only to a contact
4 that is saved in the Contacts list.

5 Procedure

- 6 1. Press **Contacts**.
- 7 2. **(Optional)** To navigate through **Main menu**, do the following:
 - 8 a. Scroll to **Applications**, and press **Select**.
 - 9 b. Scroll to **Contacts**, and press **Select**.
- 10 3. Select the contact, and press **Details**.
- 11 4. Scroll to the active ringtone, and press **Edit**.

12 The Phone screen displays the Select ringtone window.
- 13 5. Scroll down to the ringtone that you want to assign, and press **Select**.
- 14 6. **(Optional)** To play the ringtone, press **Play**.
- 15 7. Press **Save**.

16 LDAP Directory

17 With the LDAP Directory feature, you can search contacts in available Lightweight Directory
18 Access Protocol (LDAP) directories. An LDAP directory option appears at the top of the **Contacts**
19 application list.

20 You can also select an LDAP directory as your contact search source. This selection disables
21 other search sources. When LDAP directory is an active search source, if you select another
22 search source, this selection disables LDAP directory search.

23 You can enter multiple search keywords and view up to 49 attributes for each match, such as
24 personal names, addresses, job titles and telephone numbers.

25 You can add frequently used LDAP contacts to your local **Contacts** with the help of the **+Contact**
26 soft key.

27 You can combine any found LDAP contact with an existing local contact with the help of the
28 **Combine** soft key.

Setting LDAP Directory as the contact search source

About this task

You can select an LDAP directory as your contact search source to enable searching from the **Contacts** application. This selection disables other available search sources for the **Contacts** application.

Before you begin

Ensure that the feature is activated by the administrator. Contact your administrator for details.

Procedure

1. Press **Contacts**.
2. **(Optional)** To navigate through **Main menu**, do the following:
 - a. Scroll to **Applications**, and press **Select**.
 - b. Scroll to **Contacts**, and press **Select**.
3. To select LDAP Directory as a source for contact search, press **Search > More > Sources**.
4. Scroll to **LDAP contacts**, and press **Toggle**.
 LDAP Directory is now your contact search source. Other sources are disabled. The phone displays the following message: LDAP selected — other search sources disabled.
5. Press **Save**.

Searching LDAP contacts

About this task

You can search LDAP directory using **Contacts** application on your phone or directly. You can use multiple search attributes and display up to 20 matches for each search.

Do not use the backslash symbol in your search queries. If your query contains a backslash, enter \5c instead of it. Commas and blank spaces separate search keywords. If your keyword contains a comma or a space, enter \2c for commas and \2p for spaces.

Before you begin

Set LDAP directory as the contacts search source.

Procedure

1. Press **Contacts**.
2. **(Optional)** To navigate through **Main Menu** list, do one of the following:
 - Scroll to **Applications**, and press **Select**.

- Scroll to **Contacts**, and press **Select**.

3. If you are searching from a LDAP Directory, scroll to **LDAP Directory**, and press **Select**.

The phone displays the list of up to 1000 LDAP contacts. You can use **Up** and **Down** line keys to scroll through the list. If the phone cannot retrieve the contacts from a LDAP server, the phone displays the following message:

No contacts in the group.

4. Press **Search**.

5. Use the dial pad to enter multiple keywords, separated by a blank space or a comma, into the **Search** field, and press **Search**.

The phone displays the list of matches. If no matches are found in the LDAP directory, the phone displays the following message: No match found.

If more than 20 matches are found in the LDAP directory, the phone displays the following message: We found too many matches. Select from the list or press Back to refine your search.

6. (Optional) Press **Details** to view contact information for a selected match.

7. (Optional) Press **+Contact** from the **Details** view to add an LDAP contact to the list of your local contacts.

8. (Optional) Press **Combine** from the **Details** view to select an existing local contact and merge it with the selected LDAP contact.

Chapter 9: Managing Recents

Call log

Depending on the call type, call log provides the following information about the last 100 calls on your phone:

- Caller name
- Caller number
- Call time-stamp
- Call duration

Avaya J100 Series IP Phones software version 4.0.3 and later always encrypts the content of the call log file.

When the offline call log feature is disabled in System Manager, if you downgrade the software of your phone to a version earlier than 4.0.3, you will lose the call log details. Contact your administrator for information on retaining the call log details.

Making a call from Recents

Procedure

1. Press **Recents**.
2. Use the **Up** and **Down Arrow** keys to select the contact that you want to call.
3. Press **Call**.

Viewing the Recents details

About this task

In the Recents screen, depending upon the call type, you can view the following details of each call:

- Incoming call icon

- Outgoing call icon
- Missed call icon
- Name
- Extension number
- Time
- Date
- Duration

 Note:

Duration is not available for a missed call.

Procedure

1. Press **Recents**.
2. **(Optional)** To navigate through **Main menu**, scroll to the following:
 - a. **Applications**, and press **Select**.
 - b. **Recents**, and press **Select**.
3. Select the call that you want to view.
4. Press **Details**.

The phone displays the details of the selected call.

Deleting a call record from Recents

Procedure

1. Press **Recents**.
2. **(Optional)** To navigate through **Main menu**, scroll to the following:
 - a. **Applications**, and press **Select**.
 - b. **Recents**, and press **Select**.
3. Select a number that you want to delete.
4. Press **Details**.
5. Press **Delete**.
6. Select one of the following when the phone prompts for confirmation:
 - **Delete**: To delete the entry.The phone deletes the number from the call history list.
 - **Cancel**: To cancel and return to the previous menu.

Clearing the Recents list

Procedure

1. Press **Recents**.
2. **(Optional)** To navigate through **Main menu**, scroll to the following:
 - a. **Applications**, and press **Select**.
 - b. **Recents**, and press **Select**.
3. Press **Delete**.
4. Select one of the following when the phone prompts for confirmation:
 - **Delete**: To delete all entries.
 - **Cancel**: To cancel and return to the previous menu.

Chapter 10: Managing conference calls

Adding a person to an active call

About this task

You can add participants to an active call to set up a conference call.

Before you begin

Start a call.

Procedure

1. During a call, on the Phone screen, press **More > Conf**.
The phone puts the existing call on hold.
2. To make a call to a participant, do one of the following:
 - Dial the phone extension by using the dial pad.
 - Call the person from the Contacts list or the Recents list.
3. When the third participant answers the call, press the **Join** soft key.
4. To add another person, press **Add** and repeat Steps 2 and 3.

Adding a person on hold to a conference call

About this task

You can add a held call to a conference call.

Procedure

1. On the Phone screen, select your active call.
2. Press **Conf** or **Add** button if you are already in a conference.
3. Press **Held call** soft key to see a list of held calls.
4. Select the call on hold that you want to add to the conference.
5. Press one of the following:
 - **Join**

1 • **Conf**

2 The held call is added to the conference call.

3 **Putting a conference call on hold and resuming a call**

4 **About this task**

5 Use this procedure to put a conference participant on hold, while other participants continue the
6 conference call.

7 **Procedure**

- 8 1. Press **Hold** soft key during a conference call.
- 9 2. Do one of the following:
 - 10 • Press **Resume**.
 - 11 • Select the call appearance to resume the conference call.

12 **Dropping or Disconnecting the last participant from a** 13 **conference call**

14 **About this task**

15 You can use this procedure to disconnect the last participant who joined the conference. You
16 cannot disconnect other participants after you disconnect the last participant. You can use this
17 method to disconnect a participant again after you add another participant.

18 **Procedure**

- 19 1. From the phone screen, select your active conference call.
20 You will see the **More** soft key.
- 21 2. Press **More > Drop** when the conference is active.

22 **Result**

23 The participant who was added last gets disconnected from the conference.

24 **Related links**

25 [Adding a participant to no hold conference](#) on page 82

1 Viewing the details of a conference

3 About this task

4 Use this procedure to view the details of the participants on a conference call.

5 If you cannot, it might be due to the server on which your extension is configured. Contact your
6 system administrator.

7 Procedure

- 8 1. On the Phone screen, select your active call.
- 9 2. Press **Conf** soft key.
- 10 3. Do one of the following:
 - 11 • Dial the telephone number.
 - 12 • Call the person from the Contacts list.
 - 13 • Call the person from the Recents list.
- 14 4. When the person answers, press **Join** or **OK** to add the person to the existing call.
- 15 5. Press **Add** and repeat the steps to add another person to the conference.
- 16 6. Press the **Details** button to access the details of the participants.

Chapter 11: Advanced features

You can access advanced features available on your phone from the Features screen and some advance features from the Applications screen.

Most of the features are configured by the system administrator.

The LED next to the feature name indicates whether the feature is currently on or off.

LED state	Feature Status
Green	On
Red	Off

Accessing the Features screen

About this task

Use this procedure to gain access to the Features screen.

Procedure

1. Press **Main menu**, and scroll to **Features**.
2. Press **Select**.
3. Scroll to see the features that are configured for your extension.

Active call shortcut keys

With Active call shortcut keys, you can use Autodial and Contacts keys as shortcuts during an active call to perform the required action.

The following actions can be performed by pressing these keys:

- Transferring an active call to the selected user immediately or after talking to this user first
- Adding the selected user to an active call to set up a conference call

To configure any of these shortcut actions, contact your system administrator.

Making a call transfer with a shortcut key

About this task

If the caller needs the information that you cannot provide, you can transfer the ongoing call to another user using an Autodial key or a contact as shortcuts.

* Note:

The actual key used for a shortcut action depends on the current configuration.

Depending on the configuration set by the system administrator, the phone might make a blind transfer or an attended transfer immediately after the **Transfer** soft key is pressed. Contact your system administrator for more details.

Before you begin

Ensure the following:

- If the configured shortcut is a BLF key, the required user is idle.
- The administrator has set the shortcut action for the key as call transfer.

Procedure

1. While on an active call, depending on the configuration, do one of the following on the Phone screen:

- Press the Autodial or Contact line key.
- Scroll to the required Autodial line or contact, and press **Transfer**.

The phone displays the `Transfer now or talk with [BLF user extension]?` confirmation window.

2. Press one of the following:

- **Now:** To immediately transfer the call to the selected user.

The phone displays the Incoming Call screen with the extension the call was transferred to until the user answers the call.

- **Talk:** To place the call on hold, and to talk with the user first.

3. **(Optional)** If the user does not answer the BLF shortcut transferred call, press one of the following in the Incoming Call screen:

- **Pickup:** to answer the call on your phone.
- **Ignore:** to end the call.

Making a conference call with a shortcut key

About this task

If you need to include the other agent in your conversation with the caller, you can add an Autodial user or a contact to an active call to set up a conference call.

Before you begin

Ensure the following:

- If the configured shortcut is a BLF key, the required user is idle.
- The administrator has set the shortcut action for the key as conference call. Contact your system administrator for more details.

Procedure

1. While on an active call, depending on the configuration, do one of the following on the Phone screen:

- Press the Autodial or Contact line key.
- Scroll to the required Autodial line or contact, and press **Conf**.

The phone puts the existing call on hold.

2. When the user answers the call, press **Join**.

Activating the screen saver

Procedure

1. Press **Main menu**.
2. Press **Applications**.
3. Scroll down to **Activate screen saver**, and press **Select**.

Activating Send All Calls

About this task

When Send All Calls (SAC) feature is on, your incoming calls go directly to a predefined coverage number, typically your voice mail. Incoming calls ring once at your extension and then go directly to a number which is set by your system administrator.

You can also turn **Send All Calls** on or off by using the phone Features list.

Note:

- 24 Do not enable the SAC feature in case you selected the cover all option for the coverage path.
- 25 Enabling both features at the same time can cause duplicate entries in the call log.

Procedure

1. Navigate to the Features screen.
2. Scroll to choose **DND**.

 Note:

- 1 If you want the feature label to read as **Send all calls**, contact your administrator to
- 2 relabel the feature name.

3. Press **Select** or **OK** or the corresponding line button to activate the feature.

Automatic Callback

With the Automatic Callback feature, you receive a notification call to connect with the available extension number that was previously busy, unanswered, on another call, or out of coverage.

Setting up Automatic Callback

About this task

Use this procedure to get a notification call when the previously unanswered extension becomes available. You must use this feature only when a call is unanswered.

Before you begin

Ensure that the feature is activated by the administrator. Contact your administrator for details.

Procedure

1. Press **Main menu**, and scroll to **Features**.
2. Press **Select**.
3. Scroll to **Automatic Callback**, and press **Select**.

When you end the callback call, the phone deactivates the feature automatically.

Autodialing a pre-assigned number

About this task

The autodialing feature enables you to quickly call the pre-assigned numbers. While your phone is off-hook, on-hook, and from line key.

Before you begin

Your system administrator might set up few frequently called numbers, such as the IT Help Desk for autodialing. These numbers are displayed on the screen of your phone or button module.

Procedure

Do one of the following to autodial a number:

- If your phone is on-hook, choose the number which appears on your phone screen, and press the **Call** soft key or the **OK** button.
- If your phone is off-hook a autodialing screen appears, press the line key.
- You can choose a number from the JBM24 Button Module and press the line key.

Blocking your extension from displaying during calls

About this task

You can override the system (default) setting to display your extension on outgoing calls. Use the Calling Party Number Blocking feature to prevent your number from displaying.

Procedure

1. From the Phone screen, access the Features screen.
2. Select **CPN Block**.
3. Enter the extension number you do not want the called party to see.
4. Press **Enter** or **OK** to start calling party number blocking.

Bridged Call Appearance

Bridged Call Appearance is a unique extension number that is shared among multiple users to communicate through a single call appearance. You can make, receive, and join a call on behalf of the owner by using the bridged appearance. The bridged appearance might display the bridge owner's identity on the receiver's display screen.

Making a call on a bridged line

About this task

Use this procedure to make a call on another user's bridged line.

Before you begin

Ensure that the required bridged line is idle.

Procedure

1. Press the line key of the bridged number that you want to use.

2. Enter the number by using the dial pad.

The phone initiates the call when the inter digit timer times out.

Answering a bridged line call

About this task

When you receive a call from a bridged line, the Phone screen displays the bridge owner's identity. If you receive more than one bridged call, the Phone screen highlights the recent bridged call.

Procedure

1. Do one of the following:

- Lift the handset.
- Press **Speaker**.
- Press the **Answer** soft key.

2. **(Optional)** For multiple bridged call appearances, do the following:

- a. Press the line key of the bridged number that you want to answer.
- b. Continue with Step 1.

Joining a call on a bridged line

Procedure

On the phone, do one of the following:

- Press the line button with the active call.
- Select an active bridge line number, and press **Bridge**.

* Note:

- Do not use **Headset**, **Handset** or **Speaker** softkeys to join the call on a bridged line. Pressing **Headset**, **Handset** or **Speaker** opens the Dial screen. To cancel dialing and to press the required line button for joining a call, press the **End Call** key.

Busy Indicator

With the Busy Indicator (BI) feature, you can do the following:

- View the status of other users in the network
- Make quick calls to the monitored users

- Transfer calls by pressing the Busy Indicator line key

- Make conference calls with BI users

The icon next to the Busy Indicator line key displays the current status of the monitored user (idle or busy).

The user status is also reflected by the indication of LEDs integrated into the corresponding line keys.

You can relabel and move a Busy Indicator line key from the Phone keys customization menu. However, you cannot add or delete Busy Indicator keys configured on your phone. Contact your system administrator if you want to add more BI line keys or delete the existing ones.

Related links

[Customizing phone keys](#) on page 96

Busy Indicator icons and LED indication

Busy Indicator icons look the same as Presence “Available” and “On a call” icons but they might differ depending on the phone or the button module model.

Related links

[Customizing phone keys](#) on page 96

Busy Indicator call operations

Making a call to a monitored user

About this task

You can make a quick call to monitored users, for example, when you want to provide direct instructions to them.

Procedure

Do one of the following:

- On the Phone screen, scroll to the required Busy Indicator line, and press **Call**.
- Press the required Busy Indicator line key.

Making a conference call with a monitored user

About this task

Use this procedure to add a monitored user to an active call to set up a conference call.

Procedure

1. During an ongoing call, press **More > Conf**.

The phone puts the call on hold, and displays the `Select a participant` notification.

2. Press the **Phone** key.
3. Do one of the following:
 - Scroll to the required Busy Indicator line, and press **Call**.
 - Press the required Busy Indicator line key.
4. When the monitored user answers the call, press **Join**.

Call Transfer to a monitored user

Ongoing calls can be transferred to a user on the Busy Indicator line. This transfer is managed similarly to Call Transfer to a phone extension.

You can transfer a call immediately (blind transfer) or after making a consultative call to the monitored user (attended transfer).

Related links

[Call Transfer](#) on page 70

Making a blind transfer to a monitored user

About this task

Use this procedure to transfer immediately an active call to a monitored user.

Procedure

1. During an active call, press **Transfer**.
2. Do one of the following:
 - Press the Busy Indicator line key corresponding to the user you want to transfer the call to.
 - Press the **Phone** key, scroll to the required Busy Indicator line, and press **Select**.

The phone displays the Transfer now or talk with [BI extension number]? window.

3. Press **Now**.

Your call is transferred to the monitored line.

Making an attended transfer to a monitored user

About this task

Use this procedure to transfer an active call to a monitored user by talking to this user first.

Procedure

1. During an active call, press **Transfer**.

2. Do one of the following:

- Press the Busy Indicator line key corresponding to the user you want to transfer the call to.
- Press the **Phone** key, scroll to the required Busy Indicator line, and press **Select**.

The phone displays the Transfer now or talk with [BI extension number]? window.

3. Press **Talk**.

The current call is placed on hold, and a call to the monitored user is established.

4. To end your consultative call and to transfer the held call, press **Complete**.

Calendar

With the Calendar feature, you can access the Microsoft® Exchange Server calendar on your phone. You can also view and set a reminder for meetings or appointments.

When Exchange Calendar is active, appointments are displayed in the order of their start times and are removed once the meeting time expires. Calendar information is updated whenever you log in to your phone, change calendar settings, or access the Calendar.

Accessing calendar

About this task

Use this procedure to open calendar on your phone.

Before you begin

Ensure that your administrator has activated **Exchange credentials** on your phone.

Procedure

1. Press **Main menu**.
2. Scroll to **Applications**, and press **Select**.
3. Scroll down to **Calendar**, and press **Select**.

If you are accessing calendar for the first time, the phone displays Exchange credentials screen to access your Microsoft® Exchange Server.

Configuring the Microsoft® Exchange Server calendar

Before you begin

- Ensure that the feature is activated by the administrator. Contact your administrator for details.
- Get the following details from your administrator:
 - User name
 - Password
 - Domain name

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Applications**, and press **Select**.
4. Scroll to **Exchange credentials**, and press **Select**.
5. Type the following details:
 - **Exchange username**: Enter your email ID.
 - **Exchange password**: Enter your password.
 - **Exchange domain**: Enter the domain name, for example, `avaya.com`.
6. **(Optional)** To enable or disable **Name/Password Prompt**, do one of the following:
 - **Toggle**: To enable or disable the prompt.
 - The **Right Arrow** key: To enable the prompt.
 - The **Left Arrow** key: To disable the prompt.
7. Press **Save**.

Reviewing your Calendar event

About this task

Use this procedure to view your calendar appointments. You can set the **Enable Exchange Calendar** and **Enable Reminder** option to **Yes** to get a pop-up reminder of your upcoming calendar appointments.

Before you begin

Ensure Microsoft® Exchange is configured on your phone.

Procedure

1. Press **Main menu**.
2. Scroll to **Applications**, and press **Select**.
3. Scroll to **Calendar**, and press **Select**.
The phone displays the appointments in the start-time order.
4. To scroll from one appointment to another, press one of the following:
 - The **Up Arrow** key.
 - The **Down Arrow** key.
5. Select the calendar event, and press one of the following:
 - **Call**: To call the extension number available in the appointment.
 - **Details**: To view the details of the calendar event.
 - **Month**: To view the Calendar Event Month screen.
 - **Exit**: To exit from the event screen.
6. In the Calendar Event Month screen, press one of the following:
 - **Today**: To view calendar event of the current date.
 - **Day**: To view calendar event of the selected day.

Related links

- [Enabling and disabling Exchange calendar](#) on page 99
- [Enabling and Disabling Calendar reminder](#) on page 99

Call Forwarding

With the Call Forwarding feature, you can divert incoming calls to another number.

The phone supports the following Call Forward types:

- Call Forward: Diverts all incoming calls to another number.
- Call Forward Busy: Diverts incoming calls to another number if you are on a call.
- Call Forward No Answer: Diverts incoming calls to another number when you do not answer the call within the set time.

Enhanced Call Forward

The Enhanced Call Forward feature is used to set rules on call forwarding. You can set the rules by entering the internal and external phone numbers in the corresponding Call Forward types.

Example

For example, you enabled the Call Forwarding feature on your phone and the caller dials your extension number. In this case, your phone will redirect that incoming call to the assigned call forwarding number.

Forwarding a call to another extension

About this task

Use this procedure to forward incoming calls to a specified number.

In the IP Office environment, this feature is supported using short code dialing. Contact your system administrator for the list of short codes.

Before you begin

Ensure that the feature is activated by the administrator. Contact your administrator for details.

Procedure

1. Press **Main menu**.
 2. Scroll to **Features**, and press **Select**.
 3. To enable Call Forward feature, scroll to one of the following options:
 - **Call Fwd**
 - **Call Forward-Busy**
 - **Call Forward-No Answer**
 4. Press **Select**.
 5. In the **Destination** field, enter the number where you want to forward the incoming calls.
 6. Press **Save**.
- The phone generates a confirmation tone and returns to the Features screen.
7. To disable any of the Call Forward features, go to the respective screen and press **Select**.

Setting enhanced call forwarding

About this task

You can use this feature to forward the incoming calls on your phone to various destination numbers based on the call type and call state.

Before you begin

Ensure that the feature is activated by the administrator. Contact your administrator for details.

Procedure

1. Press **Main menu**.
2. Scroll to **Features**, and press **Select**.
3. Scroll to **Enhanced Call Forward**, and press **Select**.
4. Select the required rules from the following list, and enter the corresponding numbers.
 - Forward all calls:
 - Internal [Enter Number]
 - External [Enter Number]
 - Forward when busy:
 - Internal [Enter Number]
 - External [Enter Number]
 - Forward when no answer:
 - Internal [Enter Number]
 - External [Enter Number]

If you have configured a number for any of the rules, the phone displays that number instead of the text `Enter Number`.

5. Press **Save**.

Editing a rule for enhanced call forwarding

About this task

With the enhanced call forwarding feature, you can forward the incoming calls on your phone to various destination by setting the rules as per your requirements. To edit the already set rules, you can use the following procedure.

Before you begin

Ensure that the Enhanced Call Forward feature is activated by your administrator.

Procedure

1. Press **Main menu**.
2. Scroll to **Features**, and press **Select**.
3. Scroll to **Enhanced Call Forward**, and press **Select**.
4. Select the rule that you want to edit, and press **Edit**.
5. Enter the destination number.
6. Press **Save**.

1 Turning off rules for enhanced call forwarding

2 About this task

3 With the enhanced call forwarding feature, you can forward the incoming calls on your phone to
4 various destination by setting the rules as per your requirements. To turn off the already set rules,
5 you can use the following procedure.

6 Before you begin

7 Ensure that the Enhanced Call Forward feature is activated by your administrator.

8 Procedure

- 9 1. Press **Main menu**.
- 10 2. Scroll to **Features**, and press **Select**.
- 11 3. Scroll to **Enhanced Call Forward**, and press **Select**.
- 12 4. Do one of the following:
 - 13 • To turn off a rule, select the rule, and press **Turn off**.
 - 14 • To turn off all rules, press **All off**.
- 15 5. Press **Save**.

16 Call forwarding to your cell phone using EC500

17 About this task

18 Use this procedure to forward calls from your Avaya deskphone to your personal phone.

19 Before you begin

- 20 • Ensure that the feature is activated by the administrator. Contact your administrator for
21 details.
- 22 • Ensure that the system administrator sets your personal phone number as your destination
23 number.

24 Procedure

- 25 1. Press **Main menu**, and scroll to **Features**.
- 26 2. Press **Select**.
- 27 3. Scroll to **EC500**, and press **Select**.

1 Calling in your intercom group

2 About this task

3 Use this procedure to call a specific extension or an intercom group.

4 Before you begin

5 Ensure that the feature is activated by the administrator. Contact your administrator for details.

6 Procedure

7 1. Press **Main menu**, and scroll to **Features**.

8 2. Press **Select**.

9 3. Scroll to **Dial Icom**, and press **Select**.

10 The intercom group number shows next to the Dial Intercom feature.

11 4. Press the number that corresponds to the destination extension.

12 5. Press **Enter**.

13 Example

14 Auto icom 2 3: The first number denotes the intercom group number for the Dial Intercom feature.
15 The next number denotes the extension your administrator has predefined as your automatic
16 intercom destination extension.

17 Call Parking

18 With the Call Parking feature, you can put an active call on hold and resume the call from any
19 other phone in your organization. The administrator must activate this feature in your phone to
20 park a call in your extension. You can dial your extension number from any other phone to retrieve
21 the call.

23 Parking a call

24 About this task

25 Use this procedure to park an active call on your phone extension.

26 Before you begin

27 Ensure that you are on a call.

28 Procedure

29 1. Press **Main menu**.

30 2. Scroll to **Features**, and press **Select**.

3. Scroll to **Park Call**, and press **Select**.

Unparking a call

About this task

Use this procedure to unpark the call from another phone.

Before you begin

Ensure that you have parked a call on your extension.

Procedure

1. Press **Main menu**.
2. Scroll to **Features**, and press **Select**.
3. Scroll to **Unpark Call**, and press **Select**.
4. Enter your phone extension number.
5. Press **Select**.

Dynamic Park and Page

With the Dynamic Park and Page feature, you can park calls and announce the parked calls to other users. Park and page use a set of park slot numbers, that your system administrator configures. When you park a call in one of the park slots, you or any other user who receives the page can dial that park slot number to unpark the call.

Parking and paging an active call

About this task

You can park an active call in an administrator-configured slot. You can page this parked call to any user or administrator-configured page target group.

You cannot use this feature while on an active conference call.

Before you begin

Ensure that the feature is activated by the administrator. Contact your administrator for details.

Ensure that you are on an active call.

Procedure

1. Press **Main menu**, and scroll to **Features**.
2. Press **Select**.

3. Scroll to **Dynamic Park and Page**, and press **Select**.

The phone parks the call in one of the parking slots, and you receive an audio notification of the parked extension.

The phone is in the page mode.

4. Do one of the following to select the user or page target group that you want to page:

- Select the required page target group, and press **Page**.
- Dial the extension number of the user or page target group that you want to page, and press **Page**.
- Press **Contacts**. Select the required user, and press **Page**.
- Press **Recents**. Select the required user, and press **Page**.

The phone pages the parked call details to the selected user or the page target group.

Retrieving the parked call

About this task

If you have parked the call, you can retrieve a parked call before paging it. Other users can retrieve a parked call after receiving the page.

The phone displays the page details on the Application header, which is the second line from top of the phone screen.

You cannot use the following features on a paged call:

- Conference
- Hold
- Transfer
- Private Hold

Before you begin

Ensure that you have parked a call using the Dynamic Park and Page feature.

Procedure

Dial the park slot number that was assigned for the parked call.

The call is unparked.

Call Pickup

With the Call Pickup feature, you can answer an incoming call on behalf of a pickup group member. The administrator must add you to a Call Pickup group extension so that you can redirect

an incoming call of your group member to your phone. When Call Pickup feature is active on your phone displays the incoming call of your group member on a call appearance line.

Avaya J100 Series IP Phones support the following three ways of Call Pickup in Avaya Aura® Communication Manager.

- Call Pickup: Allows you to answer a call on behalf of a member of the same Call Pickup group.
- Call Pickup Extended: Allows you to answer a call of another pickup group by dialing the group extension number of that Call Pickup group.
- Call Pickup Directed: Allows you to answer a call of a member of another pickup group by dialing the extension number of the ringing phone.

Ensure that your administrator configures the call pickup feature for your extension.

When Call Pickup feature is active Avaya Aura® Communication Manager automatically searches for the incoming calls in the associated groups to make the call connection.

Answering a call for a Call Pickup group member

About this task

With the Call Pickup feature, you can answer an incoming call on behalf of a another call pickup group member. Use this procedure to answer a call for a group member.

Before you begin

Ensure that the feature is activated by the administrator. Contact your administrator for details.

Procedure

1. Press **Main menu**, and scroll to **Features**.
2. Press **Select**.
3. Scroll to **Call Pickup**, and press **Select**.
4. To answer a call, do one of the following:
 - Lift the handset.
 - Press **Answer**.
 - Press **OK**.
 - Press **Speaker**.

Answering a call in the same Call Pickup group

About this task

With the Call Pickup feature, you can answer an incoming call on behalf of a pickup group member. Use this procedure to answer a call in the same call pickup group.

Before you begin

Ensure that the feature is activated by the administrator. Contact your administrator for details.

Procedure

1. Press **Main menu**, and scroll to **Features**.
2. Press **Select**.
3. Scroll to **Call pickup extended**, and press **Select**.
4. To answer a call in the same pickup group, enter the extension number of the ringing phone.
5. Press **Enter**.

Answering a call using the extension number

About this task

With the Call Pickup feature, you can answer an incoming call on behalf of a pickup group member. Use this procedure to answer a call of another pickup group by using the extension number.

Before you begin

Ensure that the feature is activated by the administrator. Contact your administrator for details.

Procedure

1. Press **Main menu**, and scroll to **Features**.
2. Press **Select**.
3. Scroll to **Call pickup directed**, and press **Select**.
4. To answer a call of another pickup group, dial the extension number of the ringing phone.
5. Press **Enter**.

Call recording

With the Audix Record feature, you can record your current call.

Important:

- Some countries, states, and localities have laws that determine if and under what circumstances you can record telephone conversations. Before using the Audix Record feature, you must understand and comply with these laws.

Recording a call

Before you begin

Ensure that the feature is activated by the administrator. Contact your administrator for details.

Procedure

1. Press **Main menu**, and scroll to **Features**.
2. Press **Select**.
3. Scroll to **Audix Record**, and press **Select**.
4. Disconnect the call to stop recording.

Call Transfer

With the Call Transfer feature, you can transfer your call to another destination number.

The types of Call Transfer are:

- Consultative transfer: Transferring a call by connecting a call with the transfer recipient.
- Blind transfer: Transferring a call without connecting a call with the transfer recipient.

Making a consultative transfer

About this task

Transfer a call by connecting a call with the transfer recipient.

Procedure

1. While on an active call, press **Transfer** soft key.
The phone displays the Enter transfer destination screen.
The first call is placed on hold.
2. Do one of the following:
 - Dial the number to transfer the call.
 - Search for the number in Contacts or Recents.
3. To initiate a consultative transfer, press **Talk**.
The call transfer recipient's phone starts ringing.

4. Do one of the following:

- Press **Complete** after the recipient answers the call.

The call transfer is complete. This is also called attended transfer.

- Press **Complete** after the recipient's number starts ringing.

The call transfer is complete. This is also called unattended transfer.

Making a blind transfer

About this task

Use this procedure to transfer an active call without connecting a call with the transfer recipient.

Procedure

1. While on an active call, press **Transfer**.

The phone displays the Enter Transfer Destination screen.

2. Do one of the following:

- Dial the number to which you want to transfer the call.
- Search for the number in the Contacts or Recents list.

3. To initiate a blind transfer, press **Now**.

The call transfer is complete.

Crisis alert station

Table 1: Participants in a crisis alert

Participant	Description
Emergency caller	A person in your organization who calls the emergency number.
Crisis alert watcher	A person in your organization who gets an alert notification immediately after an outgoing emergency call.

Crisis alert station

In a crisis alert station, when an emergency caller calls an emergency number, all the crisis alert watchers receive a notification about this, so that they can attend to the caller immediately. The system administrator assigns the crisis alert watchers.

During a crisis alert, the crisis alert watchers receive the following types of notifications:

- Crisis alert view: A pop-up screen displays the emergency caller name and the call origination extension. The screen is visible until the watcher acknowledges it.
- Audio alert: An alert tone plays continuously until the watcher acknowledges it.
- Visual alert: The green feature LED flashes.

The system administrator configures the crisis alert feature. Depending upon the feature configuration, the crisis alert watchers receive the crisis alert notification in one of the following mode:

- Single user mode: When any one of the crisis alert watcher acknowledges the crisis, the alert stops on the IP Phones of the other crisis alert watchers.
- Every user mode: Each crisis alert watcher acknowledges the crisis for the alert to stop at their respective IP Phone.

Acknowledging the crisis alert

About this task

As a crisis alert watcher, you can acknowledge a crisis alert when you receive the following notifications on your phone:

- Alert tone
- LED flashes
- The screen displays the emergency caller information.

If the feature is configured in single-user mode, when you acknowledge the alert, the alerting at the other watcher's IP Phone stops.

You can use the same procedure to acknowledge the crisis alert even when the phone is locked.

Before you begin

Ensure that your system administrator designates you as a crisis alert watcher.

Procedure

1. The phone screen displays the emergency caller name and extension.
2. Press **OK**.
3. The phone screen displays the details of an emergency caller.

If there is a new crisis alert while you are viewing the details of the current alert, then the phone plays the alert tone again. To view the new crisis alert details, press **Back**.

Emergency caller information

The Phone screen displays the following details of an emergency caller:

Field	Description
Extension	The emergency caller extension.
The following fields will display details only if Avaya Aura® Communication Manager has this information.	
User name	The emergency caller name.
Date	The crisis occurrence date.
Time	The crisis occurrence time.
Zone	The crisis occurrence zone.
Crisis user room	The emergency call origination room.
Crisis user floor	The emergency call origination floor.
Crisis user building	The emergency call origination building.

Stopping the crisis alert

About this task

During a crisis alert, the phone plays the alert tone, the LED flashes, and the screen displays the emergency caller information. As a crisis alert watcher, in every user mode, you have to stop the alerts on your phone. In single-user mode, the alerts will stop on your phone if any one of the other crisis alert watchers stops the alerts before you do.

Before you begin

Ensure your that system administrator assigns you as one of the crisis alert watchers.

- Crisis alert view: press the **OK** soft key to stop the view.
- Audio alert: Press the **OK** soft key if you are in the crisis alert view, else press the Crisis Alert feature line key to stop the audio alert.
- Visual alert: Press the Crisis Alert feature line key to stop the LED flashing.

Acknowledging the crisis alert after an error in the first acknowledgment

About this task

Due to some technical issues, if there is an error in the acknowledgment process, the phone will display an error message while the alert tone continues to play. You can acknowledge this alert again.

Before you begin

Ensure that your system administrator designates you as a crisis alert watcher.

Procedure

1. Press the **Main menu**.
2. Scroll to **Features**, and press **Select**.
3. Scroll to **Crisis Alert**, and press **Select**.
4. The Phone screen displays the details of an emergency caller.

If there is a new crisis alert while you are viewing the details of the current alert, then the phone plays the alert tone again. To view the new crisis alert details, press **Back**.

Displaying your extension on outgoing calls

About this task

If you used the Calling Party Number (CPN) Block feature to block displaying your extension on the calls you make, you can change it back using CPN Unblock. CPN Unblock allows parties you call see your extension.

Procedure

1. From the Phone screen, access the Features screen.
2. Select **CPN Unblock**.
3. Enter your extension number.
4. Press **Enter** or **OK** to stop calling party number blocking.

Excluding others from bridging on to your call

About this task

Use the Exclusion feature to prevent others who are bridged to your extension from bridging onto a specific call. You can activate exclusion only during an active call.

Before you begin

Ensure that the feature is activated by the administrator. Contact your administrator for details.

Procedure

1. Press **Main menu**, and scroll to **Features**.
2. Press **Select**.
3. Scroll to **Exclusion**, and press one of the following:
 - **Select**
 - Corresponding line button

When you activate Exclusion during a call, all parties except you, the calling and the called party are dropped from the call.

Extending a call to your cell phone

About this task

Use this procedure to forward an ongoing call to your cell phone by using the EC500 feature. When you answer the extended call on your cell phone, the call remains active on your office phone. Later you can switch back to your office phone to continue the call.

Before you begin

- Ensure that the feature is activated by the administrator. Contact your administrator for details.
- Ensure that EC500 is configured on your mobile phone.
- Ensure that your administrator sets your personal phone number as your destination number.

Procedure

1. Press **Main menu**, and scroll to **Features**.
2. Press **Select**.
3. Scroll to **Extend Call**, and press **Select**.
4. Press **OK**.

You will receive a call on your cell phone to answer the extended call.

Retrieving a voice message

About this task

Use this procedure to listen to your voicemail messages. The beacon LED of the phone lights to indicate that you have a voice message.

Before you begin

- Ensure that the system administrator configures the voicemail for your extension.
- Obtain the user ID and password of your voicemail from your system administrator.

Procedure

1. To log in to your voicemail, press the **Message** button.
2. Follow the voice prompts to playback your voice messages.

Hunt Group Busy

Using the Hunt Group Busy feature, users can opt-in or opt-out of the calls specific to the hunt group. A hunt group is a group of users who handle the similar types of calls. A user can be a part of multiple hunt groups.

The Features screen displays the **Hunt Group Busy** buttons. Each **Hunt Group Busy** button corresponds to a specific hunt group. The **Hunt Group Busy** button label includes a unique four-digit index for each group.

Using Hunt Group Busy

About this task

Use the **Hunt Group Busy** buttons on the Features screen to manage the calls from a particular hunt group.

Procedure

1. To stop receiving calls from a particular hunt group, press the corresponding **Hunt Group Busy** button.
2. To turn off the Hunt Group Busy feature for a particular hunt group and start receiving calls, press the corresponding **Hunt Group Busy** button.

Interrupting a call with a whisper page

About this task

Use this procedure to make an announcement to a person on another extension who is active on a call. The person who is paged can only hear the announcement.

Before you begin

Ensure that the feature is activated by the administrator. Contact your administrator for details.

Procedure

1. Press **Main menu**, and scroll to **Features**.
2. Press **Select**.
3. Scroll to **Whisper page**, and press **Select**.
4. Enter the extension number that you want to call.
5. Press **Enter**.
6. Deliver the message when your call is received.

Example

You are on a call with users A, B, and C. You have an urgent message for user A. When you use the Whisper page feature to deliver a message to user A's extension, all three users hear the tone that signals the page, but only user A hears the message.

Limit Incoming Calls

With the Limit Incoming calls feature, you can limit the number of concurrent calls and change the call appearance. When you activate the feature, the multiple call appearance changes to a single call appearance, and the following is observed:

- When you are on a call, if you receive another call, the second caller gets a busy tone. If the Busy Station Call Log feature is enabled, this call is logged as a missed call in the call log.
- In Autodial mode, when you dial a number, if your phone receives a call, the phone logs this incoming call as a missed call in the call log.

Activating Limit Incoming Calls

About this task

You can activate the Limit Incoming Calls feature to limit the number of incoming calls and change multiple call appearance to a single call appearance.

Before you begin

Ensure that your administrator has configured the Limit Incoming Calls feature for your extension.

Procedure

1. Press the **Main menu**.
2. Scroll to **Features**, and press **Select**.
3. Scroll to **Limit incoming calls**, and press **Select**.

Result

The Limit Incoming Calls feature will be activated.

Deactivating Limit Incoming Calls

About this task

You can deactivate the Limit Incoming Calls feature to remove the limit on number of incoming calls and change a single call appearance to multiple call appearance.

Procedure

1. Press the **Main menu**.
2. Scroll to **Features**, and press **Select**.
3. Scroll to **Limit incoming calls**, and press **Select**.

Result

The Limit Incoming Calls feature will be deactivated.

Long-term acoustic exposure protection

Avaya J100 Series IP Phones have the long-term acoustic exposure protection to prevent the users from getting acoustic shocks. This feature reduces the loud volume of the conversations on the phone call to permissible acoustic limits. The user can set the permissible acoustic limit to dynamic or predefined static values. If a dynamic setting is selected, the feature activates itself and gradually reduces the loud volume of the phone conversations to prevent from reaching the damaging decibel levels.

Long-term acoustic exposure protection feature satisfies OSHA, ETSI and employee health safety requirements.

Important:

- Only L100 Series Headsets with RJ9 connector support long-term acoustic exposure protection when the headset profile is set to **Profile1**.

Configuring Long term acoustic protection

About this task

Long-term acoustic protection feature reduces the loud volume of the conversations on the phone call to permissible acoustic limits, you can configure the long-term acoustic exposure protection for your headset.

Before you begin

Ensure you set the headset profile to Profile1, and use L100 Series Headsets.

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Audio**, and press **Select**.
4. Scroll to **Long term acoustic protection**, and press **Select**.

5. Choose one of the following and press **Select**:

- **Default** : Sets the acoustic protection values to one of the following options that your administrator sets:

- Dynamic
- 8 hours
- 4 hours
- Off

Administrator configured value will be chosen as the default value.

- **Off**: Sets the acoustic protection off.
- **Dynamic**: Sets the acoustic feature to Dynamic, which activates itself and gradually reduces the loud volume of the phone conversations to prevent from reaching the damaging decibel levels.
- **4 hours**: Sets the acoustic protection for 4 hours.
- **8 hours**: Sets the acoustic protection to 8 hours.

6. Press **Save**.

Related links

[Setting a headset profile](#) on page 106

Multiple Device Access

With the Multiple Device Access (MDA) feature, you can register up to 10 SIP devices with the same extension to transfer active calls between devices.

This feature is available only in an Avaya Aura® environment. Multiple Device Access is configured on Avaya Aura® Session Manager.

MDA limitations

The limitations for Multiple Device Access are the following:

- There is no audio or visual alerting for the third incoming call if two call appearances are already in use.
- When you receive an MDA indication, press the **Phone** button to view the details and join the bridged call.

Related links

[Handling calls and conferences using Multiple Device Access](#) on page 29

[Adding a participant to no hold conference](#) on page 82

1 Using URI dialing to make a call

2 About this task

3 Use this procedure to dial an extension with the format `username@host` where the name of the
4 host includes one of the following:

- 5 • IPv4 address
- 6 • Fully qualified domain name

7 Before you begin

8 Ensure that the Manual dialing feature is enabled on your phone.

9 Procedure

- 10 1. Enter the URI extension by using relevant input method for uppercase and lowercase
11 letters, and numbers.
- 12 2. Press the **Call** soft key to make the call.

13 Related links

14 [Setting the dialing mode](#) on page 92

15 Making a priority call

16 About this task

17 Use the Priority Calling feature to provide a special type of internal call alerting for the users. The
18 called party hears a distinctive ringing when the calling party uses Priority Calling.

19 Procedure

- 20 1. Before dialing, press **Main menu**.
- 21 2. Scroll to **Features**, and press **Select**.
- 22 3. If necessary, scroll down to **Priority Call**, and press **OK**, or just press the corresponding
23 line button.
- 24 4. Enter the extension you want to call.
- 25 5. Press **Enter** or **OK** to immediately start dialing the priority call to the extension where the
26 call appearance will show the incoming call as a priority call.

27 Multicast Paging

28 With the Multicast Paging feature, you can receive a page that will be automatically played on the
29 phone. If configured by the system administrator, you can send a multicast page to a group of
30 phones in the network.

An incoming multicast page is played on the phone speaker. When the page is played, the Phone screen displays the `Page from <group name>` notification during the whole time of transmission.

All configured multicast groups that you can send a page to are available in the Features menu. You can add, move or delete the multicast page keys from the Phone screen by the common customization procedure.

Active calls with a lower priority than the multicast page are put on hold, all lower-priority incoming calls are ignored.

A multicast page is ignored if the agent is on an active call and has the Do Not Disturb status, or making an emergency call.

Related links

[Customizing phone keys](#) on page 96

Sending a multicast page

About this task

You can send a multicast page to a group of users by activating the Multicast Paging group on the Phone screen. If the required group is not added on this screen, you can access all multicast page groups configured for your phone in the Features menu.

Procedure

1. Do one of the following:
 - Lift the handset.
 - Press **Speaker**.
 - Press **Headset**.
2. **(Optional)** If you use the handset, press **End Call** to cancel dialing.
3. On the Phone screen, scroll to the required multicast page group, and press **Select**.
The phone displays the `Paging <group name>` box.
4. To end the multicast page, do one of the following:
 - Press **End Call**.
 - If you use the handset as an audio device, hang up.

No Hold Conference

With the No Hold Conference feature, you can add participants to your call while continuing your active conversation. The No Hold Conference feature lets you create a conference call without putting any call participant on hold.

For example, if you press the administered button and then dial an extension the participant that answers the call joins the no hold conference.

Using the button you can add more participants to the no hold conference.

The administrator can pre-configure only one number on System Manager. When you press the button, the call is placed to the pre-configured number when the participant answers the call joins the no hold conference.

If the participants do not answer the call within the configured time-out duration Avaya J100 Series IP Phones will display the appropriate message on the phone screen.

Adding a participant to no hold conference

About this task

You can add participants to your call while continuing your conversation without interruption. You can add up to six participants in the no hold conference call.

Before you begin

Ensure that the administrator has activated the no hold conference feature, and you are on an call.

Procedure

1. During an active call, on the phone screen, press **Main menu** > **Features**.
2. Press
3. You can add users to a no hold conference by using one of the following methods:
 - If an extension number is pre-configured by your administrator, you can press **Select**.
 - If the extension number is not pre-configured, you will get a Dial screen to enter the extension number, press **OK**.
4. To add more participants to the existing no hold conference, repeat Steps 2 and 3.

Related links

[Handling calls and conferences using Multiple Device Access](#) on page 29

[Multiple Device Access](#) on page 79

[Dropping or Disconnecting the last participant from a conference call](#) on page 49

Precedence call

You can override other calls by making a priority call with precedence. You can manually dial the extension number or select the extension from **Contacts** or **Recents**. The precedence level is valid for only one call session. The call precedence levels are:

- FO: Flash Override. Highest precedence.

- FL: Flash.
- IM: Immediate.
- PR: Priority.
- Routine: Lowest precedence. **Routine** is highlighted on the call session line if no call is made within five minutes.

You can start a precedence call from Bridged Appearance, but not from the Team button.

Making a precedence call by using the Main menu

Procedure

1. Press **Main menu**.
2. Scroll to **Applications**, and press **Select**.
3. Select **Call Priority**.
4. On the Precedence Selection screen, select the precedence level.
5. Dial the extension from one of the following:
 - **Contacts**
 - **Recents**
 - The dial pad

Making a precedence call by using dial plan configuration

About this task

Use this procedure to make a precedence call manually by dialing the extension number.

Before you begin

Ensure that the Dial plan is configured on the Local Session Controller or Enterprise Session Controller with the Feature Access Code (FAC).

Procedure

1. Lift the handset or press one of the following:
 - **Speaker**
 - **Headset**
 - Corresponding line button
2. Dial the FAC followed by the extension number.

1 Pre-configuration of keys

2 With the Pre-configuration of keys feature enabled, the Phone screen displays a pre-determined
3 set of phone keys for accessing features, applications, and line appearances. Phone extensions
4 for autodialing can be also added and accessed with this feature.

5 The phone configuration is forced by the system administrator, and you cannot change the
6 mapping or labels of pre-configured keys.

7 Contact your system administrator if you need to replace, move, or relabel the pre-configured
8 keys.

9 Presence

10 With the Presence feature, you can monitor the status of your contacts in real time. The
11 administrator must activate this feature to display presence information on your Phone screen.

12 You can change your status manually so that other users can see your availability for
13 communication.

15 Viewing the Presence status of your contacts

16 Before you begin

- 17 • Ensure that the feature is activated by the administrator. Contact your administrator for
18 details.
- 19 • Set **Track Presence** option to **Yes** when you add or edit a contact in the Contacts list.

20 Procedure

- 21 1. Press **Contacts**.
- 22 2. **(Optional)** To navigate through **Main menu**, do the following:
 - 23 a. Scroll to **Applications**, and press **Select**.
 - 24 b. Scroll to **Contacts**, and press **Select**.
- 25 3. Scroll to the required contact.

26 The phone displays the corresponding Presence icon of the contact.

27 Related links

28 [Adding a new contact](#) on page 36

Changing your Presence status

Before you begin

Ensure that the feature is activated by the administrator. Contact your administrator for details.

Procedure

1. Press **Main menu**.
2. Scroll to **Applications**, and press **Select**.
3. Scroll to **My Presence**, and press **Select**.
4. **(Optional)** Scroll to **Automatic**.
5. Scroll and press **Select** to choose one of the following:
 - **Available**
 - **Busy**
 - **Away**
 - **Do not Disturb**
 - **Out of Office**
 - **Offline**
6. Press **Save**.

Related links

[Presence icons](#) on page 25

SLA Mon™

SLA Mon™ technology is a patented Avaya technology embedded in Avaya products to facilitate advanced diagnostics. The phones support SLA Mon™ agent which works with Avaya Diagnostic Server (ADS).

SLA Mon™ server controls the SLA Mon™ agents to execute advanced diagnostic functions, such as:

- Endpoint diagnostics
 - To remotely control IP phones to assist end users with IP phone configuration and troubleshooting.
 - To remotely generate single and bulk test calls between IP phones.
 - To remotely execute limited packet captures on IP phones to troubleshoot and diagnose IP phone network traffic.

- Network monitoring
 - To monitor multiple network segments for performance in terms of packet loss, jitter, and delay.
 - To monitor hop-by-hop QoS markings for voice and video traffic.

Shared control

With the Shared Control feature, you can operate phones from the Avaya IX™ Workplace Client client and use high quality audio of the phone. Shared control is supported on all the Avaya J100 Series IP Phones models.

Phones must be registered with Avaya Aura® to establish a shared control connection. When you log in to your phone and Avaya IX™ Workplace Client in the shared control mode, you can control the phone through Avaya IX™ Workplace Client. A shared control session might not be established if multiple devices are registered to the same user, depending on the client implementation.

The Shared Control feature must be activated by the administrator and configured on Avaya IX™ Workplace Client.

Note:

- This feature is available only in Avaya Aura® environment.

You can perform the following tasks on the Avaya J100 Series IP Phones:

- make a call
- answer a call
- place and resume a call on hold
- mute and unmute a call
- call transfer
- conference

Notifications

You will get the following messages on your ePhone screen after the phone is configured or disconnected from Avaya IX™ Workplace Client:

- Shared Control is active
- Shared Control is inactive

For information on installing and configuring Avaya IX™ Workplace Client, see *Planning for and Administering Avaya IX™ Workplace Client for Android, iOS, Mac, and Windows* and *Using Avaya IX™ Workplace Client for Android, iOS, Mac, and Windows*.

Team Button

When the administrator configures the Team Button feature for your phone, you can do the following:

- Monitor another phone to know whether calls are redirected to another phone.
- Monitor another phone to know whether that phone has an active call.
- Answer calls that ring on the monitored phone.

Use the Team Button soft key to:

- Make a speed dial call to the monitored phone. You can do this when the monitored phone is not in use.
- Transfer an active call to the monitored phone.

The call redirection feature, Send All Calls, Call Forward, or ECF might be active on the monitored phone. The monitoring phone can override call redirection when speed dialing or transferring an active call to the monitored phone. The override feature ensures that the call made to the monitored phone rings on the monitored phone and is not routed to the redirected number.

To override call redirection, the administrator must configure on Avaya Aura® Session Manager:

- The monitored phone setting that enables the monitoring phone to override call redirection directly or through a choice provided to the user.
- The monitoring phone setting that enables the phone to override the call redirection feature that is active on a monitored phone.

For more information to set the overriding permission on Avaya Aura® Session Manager, see *Administering Avaya Aura® System Manager*.

Answering an active call on a monitored extension

Procedure

1. Press **Main menu**, and scroll to **Features**.
2. Press **Select**.
3. Scroll to choose the monitored extension for which you want to answer the incoming call.
4. Press **Select**.

Viewing the status of monitored stations

Procedure

1. Press **Main menu**, and scroll to **Features**.

2. Press **Select**.
 3. Scroll to view the status of the required monitored extension.
- The Team button screen remains active until you close the screen.

Speed dialing to a monitored extension

About this task

Use this task to make a call to a monitored phone. If the monitored phone has an active call redirection feature and you can override the feature, the monitored phone rings for 30 seconds. If no one answers the call during this time, the system redirects the call to the redirected number.

Before you begin

Ensure that the monitored phone to which you make the call is in an idle state.

Procedure

1. Press **Main menu**, and scroll to **Features**.
2. Press **Select**.
3. Scroll to choose the monitored phone that you want to call.
4. Press **Select** twice.

The phone makes a call to the monitored extension.

Transferring a call to a monitored phone

About this task

Use this procedure to transfer an active call to a monitored phone.

Before you begin

You must be on an active call.

Procedure

1. Press **Main menu**, and scroll to **Features**.
 2. Press **Select**.
 3. Scroll to choose the monitored phone to which you want to transfer the active call, and press **Select**.
- The system puts the active call on hold and rings the monitored phone.
4. To complete the transfer, perform one of the following actions:
 - Press the **Complete** soft key.

- On-hook the handset.
- Press the **Speaker** button.
- Press the **Now** soft key.
- Press the **Talk** soft key.

Monitoring other extensions at a glance

About this task

Use this procedure to monitor phones for others. You can see whether an extension is idle or busy at a glance.

Before you begin

Ensure that the feature is activated by the administrator. Contact your administrator for details.

Procedure

1. Press **Main menu**, and scroll to **Features**.
2. Press **Select**.
3. Scroll to the System Numbers.
4. If necessary, scroll to the line button for the extension you want to check.
5. If that extension is in use, the phone displays **Busy** next to the extension number.

Tracing a malicious call

About this task

Use this feature to trace a malicious call. Activating Malicious Call Trace (MCT Act) alerts a controller to begin call tracing and provide information for reporting this call. This feature is available only if your administrator has set up the phone system to trace and track malicious calls and there is an attendant or controlling user to oversee the trace.

Procedure

1. During an active call, access the Features menu.
2. To start a trace, scroll to **Malicious call trace**, and press one of the following:
 - **Select**
 - Corresponding line button

An alerting tone or flashing LED signifies the trace is active. Hanging up deactivates MCT Act.

 Important:

- 1 Some countries, states, and localities have laws that determine if and under what
- 2 circumstances you can use Malicious Call Trace (MCT). Before using the MCT feature,
- 3 you must understand and comply with these laws.

4 Using a Guest Login

5 About this task

6 Use this procedure to log in as a guest on another phone to access your applications and call
7 history for a limited time.

 Note:

- 8 You need to re-login if the phone reboots.

9 Before you begin

10 Ensure that the feature is activated by the administrator. Contact your administrator for details.

11 Procedure

- 12 1. Press **Main menu**.
- 13 2. Scroll to **Applications**, and press **Select**.
- 14 3. Scroll to **Guest login**, and press **Select**.
- 15 4. Enter your extension and password.
- 16 5. Press one of the following to set the duration in hours:
 - 17 • **Right** arrow key: To increase the value.
 - 18 • **Left** arrow key: To decrease the value.
- 19 6. Press **Enter**.

20 Related links

21 [Logging out of your phone](#) on page 19

22 WML browser

23 Wireless Markup Language (WML) is an XML-based markup language used by Avaya J100
24 Series IP Phones.

25 The WML browser feature allows you to view WML web pages.

26 With the WML browser feature, you can access the Home page, Click to Dial and Add to Contacts
27 applications.

1 All WML browser elements are designed by the system administrator. Contact your system
2 administrator if you want to change the pre-configured layout.

4 Accessing the WML browser

5 About this task

6 You can access pre-configured WML browser applications which are added to your phone in
7 addition to applications in the Settings menu.

8 Before you begin

9 Ensure the system administrator has configured the Browser application.

10 Procedure

- 11 1. Press **Main menu**.
- 12 2. Scroll to **Applications**, and press **Select**.
- 13 3. Scroll to **Browser**, and press **Select**.
- 14 4. Use the following controls to access the Browser application elements:
 - 15 a. **Up** and **Down** navigation arrows to scroll the Home page up or down
 - 16 b. **Left** and **Right** navigation arrows to navigate the history
 - 17 c. **OK** button to go to a page link or select an option
 - 18 d. **Home** to go to the Home page
 - 19 e. **Refresh** to reload the current card
 - 20 f. **Exit** to return to the Applications menu

Chapter 12: Customization

Phone

Setting the dialing mode

About this task

Use this procedure to set the dialing method used to initiate dialing.

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Phone**, and press **Select**.
4. Scroll to **Dialing mode**.
5. Press **Toggle** to select one of the following options:
 - **Manual**: Press the **Call** soft key to start a call.
 - **Auto**: Ensure that the dialed digits match the dial plan to start a call.
6. Press **Save**.

Related links

[Making a call by using the dial mode](#) on page 31

[Using URI dialing to make a call](#) on page 80

Displaying call timers

About this task

Use this procedure to display the duration of calls.

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.

3. Scroll to **Phone**, and press **Select**.
4. Use the **Down Arrow** key to go to the **Display call timers**.
5. Press **Toggle** to activate or deactivate the call timers.
6. Press **Save**.

Setting key repeat delay

Before you begin

Ensure that the key repeat delay settings are activated by your administrator.

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Phone**, and press **Select**.
4. Scroll to **Key repeat delay**.
5. Press **Toggle** to select one of the following:
 - **Default**
 - **Long**
 - **Longest**
 - **Off**
 - **Short**
6. Press **Save**.

Setting redial options

About this task

Use this procedure to see the last dialed numbers.

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Phone**, and press **Select**.
4. Scroll to the **Redial** option.
5. Press **Toggle** to one of the following:
 - **One number**: To see the last dialed number.

- **List:** To see a list of the last eight numbers.

6. Press **Save**.

Related links

[Redialing a number](#) on page 31

Assigning speed dial entries

About this task

Use this procedure to assign speed dial numbers to your contacts. You can assign up to nine speed dial entries.

This feature is only available in the Avaya Aura® environment.

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Phone**, and press **Select**.
4. Select **Assign speed dial entries**.
5. Use the **Up** and **Down Arrow** keys to select a speed dial number.
6. Press **Contacts** to select a contact.
7. Press **Select** to assign the contact to the selected speed dial number.

You can assign only one contact.

Related links

[Making a call by using speed dial](#) on page 32

Replacing and clearing a Speed Dial contact

About this task

Use this procedure to replace or remove a Speed Dial contact.

Before you begin

Assign a contact to a Speed Dial number.

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Phone**, and press **Select**.
4. Select **Assign speed dial entries**.
5. Use the **Down Arrow** key to go to the Speed Dial contact that you want to replace or clear.

6. Press one of the following:
 - **Replace**: To replace the contact with another contact.
 - **Clear**: To remove the contact from the Speed Dial.
7. Press **Replace** or **Clear** when the phone prompts for confirmation.

Setting Mute alert

About this task

Use this procedure to receive a notification alert when your phone is on mute and you try to answer a call.

Before you begin

Ensure that the feature is activated by the administrator. Contact your administrator for details.

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Phone**, and press **Select**.
4. Scroll to **Mute alerting** option.
5. Press **Toggle** to select one of the following:
 - **Audible**: The phone beeps to notify that you have muted your phone.
 - **Visual**: The phone displays the mute icon after some time on the phone status line.
 - **Both**: The phone beeps and displays a mute alert message.
 - **None**: The phone disables the mute alert.
6. Press **Save**.

Visual alerting

The beacon LED works in the following manner to indicate incoming calls and messages:

- If there is an incoming call, the beacon LED blinks.
- If there are new voice mail messages, the beacon LED is lit continuously.
- If the speaker is on during an active call and there are new voice mail messages, the beacon LED turns off every 15 seconds.

* Note:

- If the call is on hold, the beacon LED stops flashing.

1 Setting Visual alerting

2 About this task

3 Use this procedure to illuminate the beacon LED when there are incoming calls and messages.

4 Procedure

- 5 1. Press **Main menu**.
- 6 2. Scroll to **Settings**, and press **Select**.
- 7 3. Scroll to **Phone**, and press **Select**.
- 8 4. Scroll to **Alerting on calls**, and press **Select**.
- 9 5. Scroll to **Beacon LED**.
- 10 6. Press **Toggle** to enable or disable visual alerting.
- 11 7. Press **Save**.

13 Customizing phone keys

14 About this task

15 Use this procedure to add, relabel, move, or delete contacts, features, or applications from the
16 Phone screen.

17 Procedure

- 18 1. Press **Main menu**.
- 19 2. Scroll to **Settings**, and press **Select**.
- 20 3. Scroll to **Phone**, and press **Select**.
- 21 4. Scroll to **Phone keys customization**, and press **Select**.
- 22 5. Press **Customize key**.
- 23 6. Use **Navigation** keys to select the line key.
- 24 7. **(Optional)** On the phone screen, if the selected line is empty, press **Add**, and do the
25 following:

- 26 • To add a contact, press **Contact**.
- 27 • To add a feature, press **Feature**.
- 28 • To add an application, press **App**.

29 You can use the Navigation keys to scroll to the required functionality, and press **Select**.

- 30 8. To move the selected line key, do the following:
 - 31 a. Press **Move**.
 - 32 b. Use the Navigation keys to move the selected line.

- c. **(Optional)** If the new location is empty, press **Select**.
 - d. **(Optional)** If the new location is already assigned a key, press **Swap**.
9. To set a new label, do the following:
 - a. Press **Relabel**.
 - b. Type the name of the label.
 - c. If your native language uses extended Latin or non-Latin symbols, press **MoreSymbol** the soft key to open the Symbols menu and select the necessary symbols there. Press **Insert** > **More** > **Save**.
 10. To delete a key, press **Delete**, and then confirm the deletion.

Restoring customized keys to default

About this task

Use this procedure to restore the customized keys to administrator settings.

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Phone**, and press **Select**.
4. Scroll to **Phone keys customization**, and press **Select**.
5. Scroll to **Restore**, and press **Select**.
6. In the confirmation window, press **Restore**.

Applications

Enabling the Away timer

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Applications**, and press **Select**.
4. Scroll down to **Presence integration**, and press **Select**.
5. Scroll down to **Away timer**.

6. Press **Toggle** to turn on the timer.
7. Use the **Down Arrow** key to go to **Away timer value**.
8. Enter the time in seconds.
- You can enter any value from 0 to 999.
9. Press **Save**.

Enabling phone auto-lock

About this task

You can set your phone to auto-lock when not in use. The idle phone automatically locks itself after the set time period elapses.

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Applications**, and press **Select**.
4. Scroll down to **Lock**.
5. Enter the time in minutes.
- You can enter any value from –1 to 999.
- If you enter the value –1, the phone uses the administrator set value.
6. Press **Save**.

Turning call history on and off

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Applications**, and press **Select**.
4. Scroll to **Recents**, and press **Select**.
5. Scroll to **Log calls**, and press one of the following:
 - **Toggle**: To toggle call history on or off.
 - **Right Arrow** key: To turn on call history.
 - **Left Arrow** key: To turn off call history.
6. Press **Save**.

Enabling and disabling Microsoft® Exchange contact integration

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Applications**, and press **Select**.
4. Scroll to **Contacts**, and press **Select**.
5. Scroll to **Enable exchange contacts**, and press one of the following:
 - **Toggle**: To enable or disable Exchange contacts.
 - **Right Arrow** key: To enable Exchange contacts.
 - **Left Arrow** key: To disable Exchange contacts.
6. Press **Save**.

Calendar settings

Enabling and disabling Exchange calendar

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Applications**, and press **Select**.
4. Scroll to **Calendar**, and press **Select**.
5. Scroll to **Enable Exchange Calendar**, and press one of the following:
 - **Toggle**: To enable or disable Exchange calendar.
 - **Right Arrow** key: To enable Exchange calendar.
 - **Left Arrow** key: To disable Exchange calendar.
6. Press **Save**.

Related links

[Reviewing your Calendar event](#) on page 60

Enabling and Disabling Calendar reminder

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.

3. Scroll to **Applications**, and press **Select**.
4. Scroll to **Calendar**, and press **Select**.
5. Scroll to **Enable Reminder**, and press one of the following:
 - **Toggle**: To enable or disable calendar reminder.
 - **Right Arrow** key: To enable calendar reminder.
 - **Left Arrow** key: To disable calendar reminder.
6. Press **Save**.

Related links

[Reviewing your Calendar event](#) on page 60

Enabling and Disabling Calendar reminder tone

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Applications**, and press **Select**.
4. Scroll to **Calendar**, and press **Select**.
5. Scroll to **Reminder Tone**, and press one of the following:
 - **Toggle**: To enable or disable the reminder tone.
 - **Right Arrow** key: To enable the reminder tone.
 - **Left Arrow** key: To disable the reminder tone.
6. Press **Save**.

Setting a reminder and snooze time

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Applications**, and press **Select**.
4. Scroll to **Calendar**, and press **Select**.
5. Scroll to **Reminder Time**, and enter the number of minutes. The range is 0 to 99.
6. Scroll to **Snooze Time**, and enter the number of minutes. The range is 0 to 99.
7. Press **Save**.

Setting a day of the week for calendar reminder

Procedure

1. Press **Main menu**.

2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Applications**, and press **Select**.
4. Scroll to **Calendar**, and press **Select**.
5. Scroll to **First Day of Week**.
6. Press one of the following:
 - **Toggle**: To change the day.
 - **Right Arrow** key: To change the day in ascending order.
 - **Left Arrow** key: To change the day in descending order.
7. Press **Save**.

Setting Calendar list

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Applications**, and press **Select**.
4. Scroll to **Calendar**, and press **Select**.
5. Scroll down to **List Style**, and press one of the following:
 - **Expanded**
 - **Compact**
6. Press one of the following:
 - **Toggle**
 - **Right Arrow** key
 - **Left Arrow** key
7. Press **Save**.

Activating Do not disturb

About this task

Use this procedure to direct incoming calls to a predefined coverage number that is set by the system administrator.

In the IP Office environment, this feature is supported using short code dialing. Contact your system administrator for the list of short codes.

Before you begin

Your system administrator must activate the feature for your extension.

Procedure

1. Press **Main menu > Features**.
2. Use the **Down Arrow** key to go to the Do not disturb screen.
3. Select **Do not disturb**.

Redirecting calls when Do Not Disturb is active

About this task

When your Presence status is set to **Do Not Disturb**, use this procedure to redirect calls.

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Applications**, and press **Select**.
4. Scroll to **Presence Integration**, and press **Select**.
5. Scroll to **DND invokes SAC**.
6. Press **Toggle**, and set the value to **Yes**.
7. Press **Save**.

Audio

Turning automatic gain control on or off

About this task

Use this procedure to adjust the audio output level to for better quality audio.

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Audio**, and press **Select**.
4. Scroll to **Automatic gain control**, and press **Select**.
5. Select the handset, headset, or speaker for which you want to turn automatic gain control on or off.
6. Press **Toggle** to turn automatic gain control on or off.

1 7. Press **Save**.

3 Enabling and disabling Bluetooth

4 About this task

5 You can use Bluetooth enabled devices with your phone.

6 Before you begin

- 7 • Ensure the wireless module is installed in your phone.

8 Procedure

- 9 1. Press **Main menu**.
- 10 2. Scroll to **Settings**, and press **Select**.
- 11 3. Scroll down to **Bluetooth**, and press **Select**.
- 12 4. Scroll to **Bluetooth headset**, and press one of the following:
 - 13 • **Toggle**: To enable or disable Bluetooth.
 - 14 • **Right Arrow** key: To enable Bluetooth.
 - 15 • **Left Arrow** key: To disable Bluetooth.

★ Note:

- 16 For some Bluetooth headsets, volume can be adjusted during the first call after
- 17 rebooting the phone. Toggle the slider of the pop-up panel to the right to increase the
- 18 volume, and to the left to decrease it.

20 Pairing a Bluetooth enabled headset with your phone

21 About this task

22 You can pair a maximum of ten Bluetooth enabled headsets with the phone, but you can use only
23 one headset at a time. The phone displays the list of available devices and paired devices.

24 Before you begin

- 25 • Ensure the wireless module is installed in your phone.
- 26 • Ensure that the feature is activated by the administrator. Contact your administrator for
27 details.
- 28 • Ensure your Bluetooth headset is in pairing mode.

29 Procedure

- 30 1. Press **Main menu**.
- 31 2. Scroll to **Settings**, and press **Select**.

3. Scroll down to **Bluetooth**, and press **Select**.
4. Scroll to **Devices**, and press **Select**.
- The phone scans and displays the list of Bluetooth enabled devices.
5. To pair a device, scroll to the headset, and press **Pair**.
6. To disconnect a paired headset, under Paired devices, press **Disconct**.
7. To unpair a paired headset, under Paired devices, press **Forget**.

Turning button clicks on and off

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Audio**, and press **Select**.
4. Use the **Down Arrow** key to go to the Button clicks screen.
5. Press **Toggle** to turn the audio on or off.
6. Press **Save**.

Turning error tones on and off

About this task

Use this procedure to activate the error tone alarm when you perform an incorrect action while using the phone.

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Audio**, and press **Select**.
4. Use the **Down Arrow** key to go to the Error tones screen.
5. Press **Toggle** to turn error tones on or off.
6. Press **Save**.

Enabling wireless headset bidirectional signaling

Before you begin

Check if the headset supports electronic hook switch (EHS) signaling.

*** Note:**

- 1 **Headset Signaling** setting is used to configure only DECT headsets and cannot be applied to
- 2 Bluetooth headsets.

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Audio**, and press **Select**.
4. Scroll to **Headset signaling**.
5. Press **Toggle** to select one of the following options:
 - **Disabled**: Disables signaling from the phone to the headset.
 - **Switch hook and alert**: Activates the link to the headset if you press **Headset**. When the phone receives an incoming call, you hear the alert tone in the headset.
 - **Switch hook only**: Activates the link to the headset if you press **Headset**. When the phone receives an incoming call, you do not hear the alert tone in the headset.
6. Press **Save**.

Setting headset mic level

About this task

Use this procedure to adjust the best headset performance.

Before you begin

- Ensure that you are on a call and the caller's audio level is at 50%.
- Adjust the microphone position as recommended by your headset vendor.

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Audio**, and press **Select**.
4. Scroll to **Headset mic level**, and press **Select**.
5. Press one of the following:
 - **Right** arrow key: To increase the gain level.
 - **Left** arrow key: To decrease the gain level.
6. **(Optional)** To set the default gain level, press **Default**.

Configuring hearing aid compatibility

Procedure

1. Press **Main menu**.
 2. Scroll to **Settings**, and press **Select**.
 3. Scroll to **Audio**, and press **Select**.
 4. Scroll to **Handset profile**, and press **Select**.
 5. Press one of the following:
 - **Default**
 - **Normal**
 - **Amplified**: Magnifies the normal audio level. The option must be used with caution because long term extended use of the highest volume settings can cause ear damage.
-  **Note:**
- ¹³ The amplified audio level will return to normal when the call is ended.
- **Hearing Aid**: Optimizes the sound quality of hearing aids.
6. Press **Save**.

Setting a headset profile

About this task

Use the procedure to select the headset profile that best matches the acoustic properties of the headset.

 Note:

- ²¹ Headset profiles 6, 7, and 8 are designed to work only with wireless headsets.

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Audio**, and press **Select**.
4. Scroll to **Headset profile**, and press **Select**.
5. Scroll to the profile that matches your headset.
6. Press **Select**.
7. Press **Save**.

1 List of headset profiles

Headset Profile	Description
Profile 1	L100 Series Headsets
Profile 2	- Plantronics: SupraPlus® Wideband HW251N/HW261N (HIS) - Sennheiser: SH 330/SH 350, CC 510/CC 550 (CAVA-31)
Profile 3	- Plantronics: EncorePro® HW291N/HW301N (HIS) - Sennheiser: Circle™ SC 230/260 (CAVA-31)
Profile 4	- Jabra: BIZ™ 2400 (GN1216) - Sennheiser: Century™ SC 630/660 (CAVA-31) - VXI: CC Pro™ 4010V DC, CC Pro™ 4021V DC (OmniCord-V)
Profile 5	Jabra: GN2000 (GN1216)
Profile 6	Jabra: PRO™ 9470 (14201-33)
Profile 7	Plantronics: - CS500™ Series: CS510, CS520, CS530, CS540 (APV-63) - Savi® 700 Series: W710, W720, W730, W740, W745 (APV-63)
Profile 8	Sennheiser: - DW Pro1/DW Pro2 SD Pro1/SD Pro2 (CEHS-AV03/AV04) - DW Office, SD Office (CEHS-AV03/AV04)

2 --- 3 Setting a personalized ringtone

4 About this task

5 Use this procedure to set a ringtone for different uses.

6 Procedure

- 7 1. Press **Main menu**.
- 8 2. Scroll to **Settings**, and press **Select**.
- 9 3. Scroll to **Audio**, and press **Select**.
- 10 4. Scroll to **Personalize ringing**, and press **Select**.
- 11 5. Scroll to one of the following options:
 - 12 • **Primary**
 - 13 • **Team Key**
 - 14 • **Bridged CA**
 - 15 • **Call Pickup**
- 16 6. Press **Select**.

7. Scroll to the ringtone, and press **Select**.
8. **(Optional)** To play the ringtone, press **Play**.
9. Press **Save**.

Display

Changing the background image

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Display**, and press **Select**.
4. Scroll to **Background**, and press **Select**.
5. Scroll to **Primary display**, and press **Select**.
6. Scroll down to the new image.
7. **(Optional)** To preview the image, press **Preview** and then press **Back**.
8. Press **Select**.
9. Press **Save**.

Changing the screen saver

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Display**, and press **Select**.
4. Scroll to **Screen saver** and press **Select**.
5. Scroll to **Primary display**, and press **Select**.
6. Scroll down to the new image.
7. To preview the image, press **Preview** and then **Back**.
8. Press **Select**.
9. Press **Save**.

Setting the screen saver details

About this task

Use this procedure to change the time that elapses before the phone displays a screen saver and to enable clock display on the screen saver.

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Display**, and press **Select**.
4. Scroll to **Screen saver details**, and press **Select**.
5. To change the screen saver time, scroll down to **Timer (min)**, and enter time in minutes.
You can enter any value from 0 to 999.
6. To enable clock on the screen saver, scroll to **Clock**, and press **Toggle**.
7. Press **Save**.

Adjusting the brightness of a phone screen

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Display**, and press **Select**.
4. Scroll to **Brightness**.
5. Press **Select**.
The phone displays the following list:
 - **Phone**
 - Name of the button module attached to the phone.
6. On **Phone**, press one of the following:
 - **Right Arrow** key: To increase the brightness.
 - **Left Arrow** key: To decrease the brightness.

Setting the display language

Procedure

1. Press **Main menu**.
 2. Scroll to **Settings**, and press **Select**.
 3. Scroll to **Display**, and press **Select**.
 4. Scroll to **Language**, and press **Select**.
 5. Scroll to the language, and press **Select**.
 6. Press one of the following when the phone prompts for confirmation:
 - **Confirm**
 - **Cancel**
- The phone returns to the Display screen and the language changes to the selected language.

Setting the backlight timer

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Display**, and press **Select**.
4. Scroll to **Backlight timer**, and enter the number of minutes. The range is 0 to 999.
5. Press **Save**.

Setting the time format

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Display**, and press **Select**.
4. Use the **Down Arrow** key to go to the Time format screen.
5. Press **Toggle** to select one of the following options:
 - **Time format 24 Hour**
 - **Time format 12 Hour**

6. Press **Save**.

Setting the date format

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Display**, and press **Select**.
4. Use the **Down Arrow** key to go to the Date format screen.

The phone displays one of the following:

- **Default**
- **mm/dd**
- **dd/mm**
- **mm.dd**
- **dd.mm**
- **mm-dd**
- **dd-mm**
- **mmm dd**

5. Press **Toggle** to select one of the options.
6. Press **Save**.

Setting the time zone

About this task

Use this procedure to set the current time of the phone.

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Display**, and press **Select**.
4. Scroll to **Time zone**, and press **Select**.

The phone displays the following:

- **My time**
- **Time zone**

1 5. To set the required time, do one of the following:

- 2 • Use the **Left Arrow** and **Right Arrow** key.
- 3 • Press **-** or **+** soft key.

4 6. Press **Save**.

6 Setting the text size

7 Procedure

8 1. Press **Main menu**.

9 2. Scroll to **Settings**, and press **Select**.

10 3. Scroll to **Display**, and press **Select**.

11 4. Scroll down to **Text size**, and press **Select**.

12 5. Press one of the following:

- 13 • **Right** arrow key: To increase the font size.
- 14 • **Left** arrow key: To decrease the font size.

15 6. **(Optional)** Press **Default** to restore the default font size.

16 7. Press **Save**.

18 Setting the phone screen width

19 Procedure

20 1. Press **Main menu**.

21 2. Scroll to **Settings**, and press **Select**.

22 3. Scroll to **Display**, and press **Select**.

23 4. Scroll to **Phone screen width**, and press **Select**.

24 5. Press **Toggle** to select one of the following options:

- 25 • **Full**: Each call appearance or feature occupies the entire width of a line.
- 26 • **Half**: Each call appearance or feature occupies half the width of a line, effectively
- 27 splitting the screen in two halves.

28 6. Press **Save**.

Setting the network mode

About this task

You can set the network mode to **Ethernet** or **Wi-Fi**. You do not need to perform this procedure if your phone is configured to connect to Ethernet or a specific Wi-Fi network.

Before you begin

Ensure that the system administrator gave you access to perform this task.

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Network**, and press **Select**.
4. Scroll to **Network mode**.

The **Network mode** setting shows the following options:

- **Ethernet**: To connect to an Ethernet network.
 - **Wi-Fi**: To connect phone to a Wi-Fi network.
5. Press one of the following:
 - **Toggle**
 - **Right** arrow key
 - **Left** arrow key
 6. When **Network mode** displays **Wi-Fi**, the following lines are shown on the Phone screen:
 - **SSID**: The name of the Wi-Fi network that the phone is either currently connected to, or will attempt to connect to if you start the connection process.
 - **Wi-Fi network**: Scroll to this line and press **Select** to view the list of Wi-Fi networks.
 7. After selecting the network mode, press **Save**.
 8. When you switch **Network mode** from **Ethernet** to **Wi-Fi**, see “*Connecting to a Wi-Fi network*” section.
 9. When you switch **Network mode** from **Wi-Fi** to **Ethernet**, press **Save**.
 10. When the phone prompts for permission to restart, press **OK**.
Press **Cancel** to go back to previous step.

Setting the network configuration

About this task

To set the network configuration to Auto or Manual. You do not need to perform this procedure if your phone is configured to connect to Ethernet or a specific Wi-Fi network.

When network configuration is Auto, every time the phone restarts, it will connect to the pre-configured network that your administrator has set up.

When network configuration is Manual, every time the phone restarts, it will connect to the network that you manually configured by [Setting the network mode](#) on page 113 or [Connecting to a Wi-Fi network](#) on page 115, irrespective of the pre-configured network that your administrator has set up.

*** Note:**

- Any time you manually change the connected network, the phone will automatically set **Network config** to **Manual**.

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Network**, and press **Select**.
4. Scroll to **Network config**.

The Network configuration shows following two options:

- **Auto**: To automatically connect a network.
- **Manual**: To manually connect to a network.

5. Press one of the following:

- **Toggle**
- **Right** arrow key
- **Left** arrow key

6. Press one of the following:

- **Save**
- **OK**

*** Note:**

If you do not want your phone to restart and stay in the Manual mode when you switch **Network config** from **Auto** to **Manual**, press **Save**.

If you switch **Network config** from **Manual** to **Auto**, press **Save** and then do either of the following:

- If the currently-connected network is the same as the pre-configured network that your administrator has set up, the phone will not restart and stay in the Auto mode.
- If the currently-connected network is not the same as the pre-configured network that your administrator has set up, the phone will prompt you for permission to restart before connecting to the pre-configured network.

Connecting to a Wi-Fi network

About this task

Use this procedure if your phone is not configured to connect to a specific Wi-Fi network

Before you begin

- Ensure that the system administrator gave you access to perform this task.
- Select Wi-Fi as your network mode.
- When you set the network mode, note the SSID, as this is the name of the Wi-Fi network that the phone will attempt to connect to.
- Depending on the type of security in the Wi-Fi network, obtain the required credentials. Contact your system administrator for more details.

Procedure

1. Press **Main menu**.
2. Scroll to **Settings**, and press **Select**.
3. Scroll to **Network**, and press **Select**.
4. To access the list of available Wi-Fi networks, scroll to **Wi-Fi network**, and press **Select**.
5. Scroll to the required **Wi-Fi network**, and press **Connect** to start the connection process.
6. Press **OK** to restart the phone.
7. If the security is WEP or WPA/WPA2 PSK, in **Password**, enter the password for the Wi-Fi network.
8. If the security is 802.1x EAP, enter the following:
 - **Identity**: Either your personal user ID or the shared user ID provided by your system administrator.
 - **Anonymous Identity**: Leave blank or use the shared Anonymous Identity provided by your system administrator.
 - **Password**: Either your personal password or the shared password provided by your system administrator.

Result

If the credentials are authenticated successfully, the phone automatically restarts to complete the connection.

Chapter 13: Troubleshooting

Limited access during failover

One or more telephone system servers provide your phone with its connectivity, features, and functionality. If a disconnect or switch from one server to another occurs, your phone goes into Failover mode to keep it operating while alternate server resources are established. Depending on the server your phone is on, an icon may appear on the Top display line to notify you that failover is in effect.

Failover has different stages. For example, while your phone transitions to a new server it is in “limbo” and functionality may be limited. When the alternate server is active, your phone assumes the functionality available on that server, which may not be the same as your original server. When the original server is restored, your phone transitions back (failback) and functionality may again be limited during the transition. When your phone is back on the original server, normal functionality is restored. Failover and failback are automatic; you have no control over failure mode.

Keep in mind that during failover certain features may not be available and telephone functionality may be limited. Check the soft keys at the bottom of the display to determine the actions you can take during failover. You can also press the **Phone** button to display the for possible actions.

Important:

- Do not log your telephone off during failover or until normal service is restored on your original telephone server. Logging off during failover, during transition to or from an alternate server, or while your phone is active on an alternate server may cause your phone to become inoperable.

The following conditions apply when your telephone is in Failover mode:

- If you are on a call when failover occurs, the call will remain active. You cannot initiate new calls while your phone transitions to the alternate server.
- Certain soft keys may not display and their related functions may be unavailable until transition to the alternate server is complete.
- Call connection may take longer than usual.
- During the transition to a new server, any active conference calls, call transfers, and held calls may be dropped. Incoming calls might not reach you and can go to voice mail.
- Emergency calls might or might not work, depending on the stage of failover and the functionality available on the alternate server.

- The Message Waiting Indicator is cleared, but voice mail might still be available if the voice mail server to which calls are being sent is not in failover.
- Transitions back to the normal server will restore all original functionality.

Recording audio parameters

About this task

Use this procedure to record audio parameters information in your phone.

Note:

- 7 The saved audio parameters information is used for audio debugging.

Procedure

1. Press **Main menu**.
2. Scroll to **Network information**, and press **Select**.
3. Scroll to **Audio parameters**, and press **Select**.
4. Press the **Record** soft key.
5. To stop the recording, press the **Stop** soft key.

Viewing the Product ID

About this task

The product ID information is available on a label on the back panel of your phone. Alternatively, you can view the Product ID on the phone screen.

Procedure

1. Press **Main menu**.
2. Scroll to **Network information**, and press **Select**.
3. Scroll to **System**, and press **Select**.
4. Scroll to **Product ID**.

1 Viewing the Device type

2 About this task

3 View your device type when your system administrator asks you to provide your device type
4 information. The device type can be either Avaya SIP or Open SIP.

5 Procedure

- 6 1. Press **Main menu**.
- 7 2. Scroll to **Network information**, and press **Select**.
- 8 3. Scroll to **System**, and press **Select**.
- 9 4. Scroll to **Device type**.

10 Viewing the Server type

11 About this task

12 View your server type when your system administrator asks you to provide your server type
13 information. The server type can be of Avaya Aura® or an open SIP.

14 Procedure

- 15 1. Press **Main menu**.
- 16 2. Scroll to **Network information**, and press **Select**.
- 17 3. Scroll to **System**, and press **Select**.
- 18 4. Scroll to **Server type**.

Chapter 14: Resources

Documentation

See the following related documents at <http://support.avaya.com>.

Title	Use this document to:	Audience
Overview		
<i>Avaya Aura® Session Manager Overview and Specification</i>	See characteristics and capabilities, including feature descriptions, interoperability, performance specifications, security and licensing requirements of the Avaya Aura® Session Manager.	For people who want to gain a high-level understanding of the Avaya Aura® Session Manager features, functions, capacities, and limitations.
<i>Avaya IP Office™ Platform Feature Description</i>	See information about the feature descriptions.	For people who perform system administration tasks.
<i>Avaya IP Office™ Platform Solution Description</i>	See information about how the products and services interoperate with this solution.	For people who want to gain a high-level understanding of the IP Office features, functions, capacities, and limitations.
Implementing		
<i>Deploying Avaya Aura® Session Manager</i>	See the installation procedures and initial administration information for Avaya Aura® Session Manager.	For people who install, configure, and verify Avaya Aura® Session Manager on Avaya Aura® System Platform.
<i>Upgrading Avaya Aura® Session Manager</i>	See upgrading checklists and procedures.	For people who perform upgrades of Avaya Aura® Session Manager.

Table continues...

Title	Use this document to:	Audience
<i>Deploying Avaya Aura® System Manager on System Platform</i>	See the installation procedures and initial administration information for Avaya Aura® System Manager.	For people who install, configure, and verify Avaya Aura® System Manager on Avaya Aura® System Platform at a customer site.
<i>Avaya IP Office™ Platform SIP Telephone Installation Notes</i>	See the installation procedures and initial administration information for IP Office SIP telephone devices.	For people who install, configure and verify SIP telephone devices on IP Office.
Administering		
<i>Administering Avaya Aura® Session Manager</i>	See information about how to perform Avaya Aura® Session Manager administration tasks including how to use management tools, how to manage data and security, and how to perform periodic maintenance tasks.	For people who perform Avaya Aura® Session Manager system administration tasks.
<i>Administering Avaya Aura® System Manager</i>	See information about how to perform Avaya Aura® System Manager administration tasks including how to use management tools, how to manage data and security, and how to perform periodic maintenance tasks.	For people who perform Avaya Aura® System Manager administration tasks.
<i>Administering Avaya IP Office™ Platform with Manager</i>	See information about short code configurations for the feature list	For people who need to access IP Office features using short codes.
<i>Administering Avaya IP Office™ Platform with Web Manager</i>	See information about IP Office Web Manager administration tasks including how to use the management tool, how to manage data and security, and how to perform maintenance tasks.	For people who perform IP Office Web Manager administration tasks.
Maintaining		
<i>Maintaining Avaya Aura® Session Manager</i>	See information about the maintenance tasks for Avaya Aura® Session Manager.	For people who maintain Avaya Aura® Session Manager.
<i>Troubleshooting Avaya Aura® Session Manager</i>	See information for troubleshooting Avaya Aura® Session Manager, resolving alarms, replacing hardware, and alarm codes and event ID descriptions.	For people who troubleshoot Avaya Aura® Session Manager.
<i>Using Avaya IP Office™ Platform System Status Application</i>	See information about the maintenance tasks for System Status Application.	For people who maintain System Status Application.

Table continues...

Title	Use this document to:	Audience
<i>Using Avaya IP Office™ Platform System Monitor</i>	See information about the maintenance tasks for SysMonitor.	For people who maintain SysMonitor.

Finding documents on the Avaya Support website

Procedure

1. Go to <https://support.avaya.com>.
2. At the top of the screen, type your username and password and click **Login**.
3. Click **Support by Product > Documents**.
4. In **Enter your Product Here**, type the product name and then select the product from the list.
5. In **Choose Release**, select the appropriate release number.
The **Choose Release** field is not available if there is only one release for the product.
6. In the **Content Type** filter, click a document type, or click **Select All** to see a list of all available documents.
For example, for user guides, click **User Guides** in the **Content Type** filter. The list only displays the documents for the selected category.
7. Click **Enter**.

Avaya Documentation Center navigation

Customer documentation for some programs is now available on the Avaya Documentation Center website at <https://documentation.avaya.com>.

Important:

- 20 For documents that are not available at Avaya Documentation Center, click **More Sites > Support** on the top menu to open <https://support.avaya.com>.

Using the Avaya Documentation Center, you can:

- Search for content using one of the following:
 - Type a keyword in **Search**, and click **Filters** to search for content by product, release.
 - From **Products & Solutions**, select a solution and product, and select the appropriate document from the list.
- Sort documents on the search results page by last updated dated and relevance.
- Publish a PDF of the current section in a document, the section and its subsections, or the entire document.

- Add content to your collection by using **My Docs** (☆).

Navigate to the **Manage Content > My Docs** menu, and do any of the following:

- Create, rename, and delete a collection.
- Add topics from various documents to a collection.
- Save a PDF of selected content in a collection and download it to your computer.
- Share content in a collection with others through email.
- Receive collection that others have shared with you.

- Add yourself as a watcher by using the **Watch** icon (👁).

Navigate to the **Manage Content > Watchlist** menu, and do the following:

- Enable **Include in email notification** to receive email alerts.
- Unwatch selected content, all content in a document, or all content on the Watch list page.

As a watcher, you are notified when content is updated or deleted from a document, or the document is removed from the website.

- Share a section on social media platforms, such as Facebook, LinkedIn, and Twitter.
- Send feedback on a section and rate the content.

 Note:

- Some functionality is only available when you log on to the website. The available functionality depends on the role with which you are logged in.

Viewing Avaya Mentor videos

Avaya Mentor videos provide technical content on how to install, configure, and troubleshoot Avaya products.

About this task

Videos are available on the Avaya Support website, listed under the video document type, and on the Avaya-run channel on YouTube.

- To find videos on the Avaya Support website, go to <https://support.avaya.com/> and do one of the following:
 - In **Search**, type `Avaya Mentor Videos`, click **Clear All** and select **Video** in the **Content Type**.
 - In **Search**, type the product name. On the Search Results page, click **Clear All** and select **Video** in the **Content Type**.

The **Video** content type is displayed only when videos are available for that product.

In the right pane, the page displays a list of available videos.

- To find the Avaya Mentor videos on YouTube, go to www.youtube.com/AvayaMentor and do one of the following:
 - Enter a key word or key words in the **Search Channel** to search for a specific product or topic.
 - Scroll down Playlists, and click a topic name to see the list of videos available for the topic. For example, Contact Centers.

 Note:

- 7 Videos are not available for all products.

8 Support

9 Go to the Avaya Support website at <https://support.avaya.com> for the most up-to-date
10 documentation, product notices, and knowledge articles. You can also search for release notes,
11 downloads, and resolutions to issues. Use the online service request system to create a service
12 request. Chat with live agents to get answers to questions, or request an agent to connect you to a
13 support team if an issue requires additional expertise.

Index

A

access limited during failover	116
activating	
LNCC, limiting incoming calls	77
Active call shortcut keys	
adding a user	52
conference call	52
making a call transfer	52
overview	51
adding	
contacts	36
contacts from the Recents list	37
new call log entry to the Contacts list	37
number to contacts	37
administrative methods	
file server address	17
provisioning server	17
answering a call	
another call pickup group	68 , 69
when on another call	28
answering a call for a pickup group member	68
answering call on a monitored extension	87
applications	
access calendar	59
activating the screen saver	53
configuring calendar	60
guest login	90
application settings	
disabling calendar reminder	99
disabling calendar reminder tone	100
disabling contact exchange	99
disabling exchange calendar	99
enabling calendar reminder	99
enabling calendar reminder tone	100
enabling contact exchange	99
enabling exchange calendar	99
enabling SAC when DND is active	102
setting a week day for calendar reminder	100
setting calendar list	101
setting reminder time	100
setting snooze time	100
audio settings	
AGC	102
button clicks	104
configuring hearing aid compatibility	106
error tones	104
headset profile	106
setting a primary ringtone	107
setting headset mic level	105
Autodialing	
calling a person	54
Avaya support website	123

away timer	
timer value	97

B

blind transfer	71
Bluetooth	
pairing	103
unpairing	103
Bridged Call Appearance	
answering a bridged line call	56
joining a call on a bridged line	56
making a call on a bridged line	55
Bridging	74
Busy Indicator	
call transfer	
attended transfer	58
blind transfer	58
icons and LED indication	57
making a call	57
making a conference call	57
overview	56
transferring a call	58
button clicks	
turn off	104
turn on	104

C

calendar	
calendar reminder	99
calling a person	60
configuration	60
disabling calendar reminder	99
exchange calendar	99
list style	101
month calendar event	60
reminder time	100
reminder tone	100
reviewing event	60
setting a week day for reminder	100
snooze time	100
call	
recents	45
URI dialing	80
call forward,	
disable	62
enable	62
call forwarding	
call forward busy	61
call forward no answer	61
call history	
viewing	45

calling		connecting network (<i>continued</i>)	
corporate database list	33	automatically	113
dial pad	32, 33	manually	113
emergency calling	33, 34	contacts	
local Contacts list	32	adding	36
Main Menu	32	adding a contact from the Recents list	37
Calling a number		adding contacts to a group	41
using Autodial	54	adding members to a Contacts group	41
calling intercom group	65	assign a ringtone to a contact	42
calling using intercom	65	combine your contacts	39
calls		creating a new group	40
beacon LED	95	creating a Contacts group	40
consultative transfer	70	deleting	40
e.164 dialing	33	details	38
editing a contact	38	editing	37
hold	35	excluding contacts from your group	41
ignoring	29	LDAP Directory	43
incoming call	28	new contact	36
international	33	quick search	37
multiple device access	29	removing a contact from a group	41
muting a call	35	search	37
MWI	95	search from an enterprise directory	39
parking a call	65	search from the Contacts list	39
resume	35	searching	33
speed dialing	32	searching a contact	39
switching phone	29	speed dialing	32, 94
unmuting a call	35	content	
unparking a call	66	publishing PDF output	121
visual alerting	95, 96	searching	121
call transfer		sharing	121
blind	71	sort by last updated	121
to a monitored phone	88	watching for updates	121
Call Transfer		coverage	53
Busy Indicator user	58	crisis alert	
call transfer call transfer		acknowledge	72
attended	70	acknowledgement error	73
call transfer	70	acknowledging again	73
unattended	70	crisis alert watcher, emergency caller	71
collection		D	
delete	121	deactivating	
edit name	121	LNCC, limiting incoming calls	77
generating PDF	121	deleting	
sharing content	121	a call record from the recents list	46
conference, add participant using no hold conference	82	removing a contact	38
conference calls		details	
adding a person on hold	48	contacts	38
details	50	device type	
dropping a participant	49	Avaya SIP	118
putting a call on hold	49	Open SIP	118
setting up	48	dialing mode	
configuring		automatic dialing	92
long term acoustic protection	78	manual dialing	92
configuring provision server		Dial intercom call	65
file server address	17	disabling bluetooth	103
connecting		display brightness	109
Wi-Fi	115		
connecting network			

display settings		features	
changing the background image	108	accessing features	51
date format	111	advanced	51
enabling screen saver clock	109	automatic callback	54
language	110	blind transfer	70
setting backlight timer	110	call forward	62
setting screen saver time	109	call parking	65
setting text size	112	call pickup	68
time format	110	call pickup,	67
time zone	111	call pickup directed	67
documentation center	121	call pickup extended	67–69
finding content	121	call recording	69
navigation	121	call transfer	70
documentation portal	121	consultative transfer	70
finding content	121	enabling Send all Call	102
navigation	121	enhanced call forwarding	62–64
do not disturb		extending call to your cell phone	75
send all calls	101	interrupting a call with a whisper page	76
dynamic		multiple device access	79
call parking	66	parking a call	65
paging	66	priority call	80
parking	66	unparking a call	66
E		Features	
EC500		Automatic callback	54
extend a call	75	Bridged Call Appearance	55
forwarding call to your cell phone	64	Presence	84
editing		Setting up Automatic Callback	54
contact details	38	finding content on documentation center	121
contacts	37		
emergency calling		G	
dial pad	34	getting started	
Emerg	34	connecting to WiFi	20
lock screen	33	login	18
status screen	33	groups,	
emergency calls	19	another group call pickup	67
enable wireless headset	104	call pickup group	67
enabling bluetooth	103		
enhanced call forwarding		H	
deleting a rule	64	handset	
editing a rule	63	AGC	102
error tones		hearing aid compatibility	106
turn off	104	profile	106
turn on	104	headset	
exchange contacts	99	AGC	102
excluding others from bridging	74	mic level	105
exclusion	74	profile setting	106
extension		headset profile	107
blocking display	55	hold	
unblocking display	74	putting a conference call on hold	49
F		Hunt Group Busy	
failover	116	using	76
feature			
Hunt Group Busy	76		

I		
icons		
MLPP icons	26	
phone icons	23	
presence icons	25	
identifying		
device type	18	
ignoring		
incoming calls	29	
incoming call		
audio alert	28	
decline	30	
setting a ringtone	107	
visual alert	28	
incoming call of a group member	68	
incoming calls		
do not disturb	101	
enabling call forward	62	
send all calls	101	
sending to coverage	53	
information		
emergency caller	72	
Intercom group	65	
J		
Join a bridged call	56	
L		
LDAP Directory		
contacts	43	
overview	42	
Line keys	22	
LNCC		
overview	77	
lock		
unlock	19	
log		
calls	45	
encryption	45	
logging out of your phone	19	
M		
main menu		
language	110	
Main menu	23	
making a call		
auto	31	
dial mode	31	
dial plan	83	
manual	31	
precedence call	82 , 83	
prefix digits	83	
making a call (<i>continued</i>)		
priority	80	
recents	45	
using the dial mode	31	
malicious call tracing	89	
managing calendar	59	
messages		
visual alerting	96	
monitoring other extensions	89	
Multicast Paging		
overview	80	
sending a multicast page	81	
multiple device access		
handling calls	29	
handling conference	29	
limitations	79	
My Docs	121	
N		
navigation		
navigating cluster	21	
selection	21	
Navigation cluster		
left arrow, right arrow, up arrow, down arrow	21	
network settings		
configuration	113	
mode	113	
no hold conference	81	
no hold conference, add participant	82	
O		
optional components	16	
outgoing calls		
blocking extension display	55	
international	33	
unblocking extension display	74	
overview	13	
call forwarding	61	
Hunt Group Busy	76	
P		
phone		
boot-up	18	
phone lock		
auto-lock	98	
manual lock	19	
unlock	19	
phone settings		
call history	98	
call timers	92	
customizing phone keys	96	
dialing mode	92	
key repeat delay		

key repeat delay (<i>continued</i>)		security	
key repeat delay (<i>continued</i>)		WEP, WPA/WPA2 PSK, 802.1x EAP	115
setting key auto repeat process	93	SENDALL	53
log recent calls	98	Server	
setting mute alert	95	Avaya Aura	118
setting redial options	93	Open SIP	118
visual alerting	96	setting network mode	
physical layout	14	Ethernet	113
precedence call	83	Wi-Fi	113
dial plan		settings	
making a call	83	call history	98
prefix digits	83	call timers	92
making a call	82	configuring calendar in your phone	60
Pre-configuration of keys		customizing keys	
overview	84	restoring keys to default	97
Presence		date format	111
change your presence status	85	display settings	
change your presence status manually	85	brightness	109
DND invokes SAC	102	changing the screen saver	108
enabling contacts presence status	84	language	110
Presence integration	102	log recent calls	98
viewing contacts presence	84	screen width	112
presence status		time format	110
away timer	97	time zone	111
problems with the phone	116	visual alerting	96
Product ID		shared control mode	86
phone	117	sharing content	121
protection		signaling	104
long term acoustic exposure	78	SLA Mon™	85
provisioning server	17	sort documents by last updated	121
R		Speaker	
recents		AGC	102
clearing all	47	speed dialing	
clearing all entries	47	contacts	94
deleting a call record	46	removing contact	94
making a call	45	replacing contact	94
viewing call details	45	stop	
recording a call	70	alert view	73
recording audio parameters information	117	audio alert	73
redial a number	31	visual alert	73
related documentation	119	support	123
retrieve		T	
parked call	67	team button	
retrieving a voice message	75	speed dialing	88
S		viewing station status	87
screen saver	108	Team Button	87
screen saver details		transferring a call to a monitored phone	88
screen saver clock	109	text input	
screen saver time	109	enter, edit	22
screen width	112	time zone	
searching		display settings	111
corporate database	33	settings	111
searching for content	121	tracing calls	89

U

unlockPIN	
password	19
using	
Hunt Group Busy	76

V

videos	122
Viewing	
product ID	117

W

watch list	121
Wi-Fi	
icons	27
WML browser	
accessing application	91
overview	90