

FCG / IC

This device complies with part 15 of the FCC and Industry Canada (Nominally RSS standards). Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

**FCC NOTE:** The manufacturer is not responsible for any radio or TV interference caused by unauthorized modifications to this equipment. Such modifications could void the user's authority to operate the equipment.

**NOTE:** This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If the equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

**Important note:** To comply with the FCC/RF exposure compliance requirements, no change to the antenna or the device is permitted. Any change to the antenna or the device could result in the device exceeding the RF exposure requirements and void the user's authority to operate the device.

El presente equipo cumple con los requisitos de la Parte 15 de las normas FCC y de la CNI para los aparatos emisores de radio de Clase B. Estas limitaciones están sujetas a las dos condiciones siguientes:

(1) Este equipo no debe ocasionar interferencia perjudicial; (2) el presente equipo debe aceptar toda interferencia recibida, incluyendo la interferencia que provoque un funcionamiento no deseado.

**NOTA DE LA FCC:** El fabricante no es responsable de las interferencias con las frecuencias radioeléctricas o televisivas producidas por causas de modificaciones no autorizadas de su equipo. Dichas modificaciones podrían anular la autoridad del usuario para operar el equipo.

**NOTA:** Este equipo ha sido probado y cumple con los límites para aparatos digitales de Clase B, de conformidad con el apartado 15 de las normas de la FCC. Estas limitaciones están diseñadas para proveer protección razonable contra interferencias perjudiciales en una instalación residencial. Este equipo genera, usa y puede irradiar energía de radiofrecuencia y, si no se instala y usa según las instrucciones, puede provocar interferencia perjudicial a las radio comunicaciones. No obstante, no hay garantía de que no ocurra interferencia en una instalación en particular. Si este equipo provoca interferencia perjudicial a la recepción de radio o televisión, lo que puede determinarse encendiendo y apagando el equipo, se recomienda al usuario intentar corregir la interferencia por medio de la implementación de una o más de las siguientes medidas:

- Reorientar o reducir la antena receptora.
- Incrementar la separación entre el equipo y el receptor.
- Conectar el equipo a un tomacorriente de un circuito diferente del circuito al que está conectado el receptor.
- Consultar al distribuidor o a un técnico con experiencia en radio/televisión para solicitar asistencia.

**Nota importante:** Para cumplir con los requisitos de cumplimiento de radiofrecuencia de la FCC, no se permiten cambios a la antena o el dispositivo. Cualquier cambio a la antena o dispositivo podría hacer que el dispositivo supiera los requisitos de radiofrecuencia y anule la autoridad del usuario para operar el dispositivo.

Al brand names shown are trademarks of their respective owners.

DISTRIBUIDOR POR:  
JASCO PRODUCTS COMPANY LLC,  
10 E. MEMORIAL RD.,  
OKLAHOMA CITY, OK 73114.  
© JASCO 2014 14318 ZW4005 / 14317

MANUAL • MANUEL • MANUAL

### In-wall Wireless Smart Switch

Montage mural sans fil intelligent enfichable

Interruptor inalámbrico de pared inteligente

Scan to view installation guide

Balayez ce code pour consulter le guide d'installation

Escanear para ver la guía de instalación

14318 ZW4005

© Z-WAVE®

Z-Wave® Certified Wireless Lighting Control

Certifié Z-Wave Commande d'éclairage sans fil

Control inalámbrico para iluminación certificado por Z-Wave®

## DO NOT RETURN THIS PRODUCT TO THE STORE

## NE RETOURNEZ PAS CE PRODUIT AU MAGASIN

## NO DEVUELVA ESTE PRODUCTO A LA TIENDA.

If you have any problems or questions, contact our tech support team at 1-800-654-8483, option 1 Monday-Friday 7:30-5pm CST.

For the most up-to-date product support, accessories, electronic (PDF) format manuals and more, visit [www.jascoproducts.com/support](http://www.jascoproducts.com/support)

No user serviceable parts in this unit.

Si vous avez des problèmes ou des questions, communiquez avec notre équipe de soutien technique au 1-800-654-8483, option 1 du lundi au vendredi, de 7 h 30 à 17 h (PAC).

Pour un soutien technique d'après-vente, les nouveaux accessoires, les plus récents manuels en format électronique (PDF) et plus encore, visitez le site [www.jascoproducts.com/support](http://www.jascoproducts.com/support)

Aucun des pièces de ce dispositif ne peut être réparé par l'utilisateur.

Si tiene problemas o dudas, comuníquese con nuestro equipo técnico al número: 1-800-654-8483, opción 1 de lunes a viernes, de 7:30 a 17 h, hora estándar del centro (CST).

Para recibir el soporte técnico más actualizado sobre productos, accesorios, manuales en formato digital (PDF), entre otros, visite [www.jascoproducts.com/support](http://www.jascoproducts.com/support)

Esta unidad no contiene piezas que el usuario pueda reparar.

### WARRANTY

JASCO Products warrants this product to be free from manufacturing defects for a period of two years from the original date of consumer purchase. This warranty is limited to the repair or replacement of this product only and does not extend to consequential or incidental damage to other products which may be used with this product. This warranty is in lieu of all other warranties, expressed or implied. Some states do not allow limitations on how long an implied warranty lasts to permit the exclusion or limitation of incidental or consequential damage, so the above limitations may not apply to you. This warranty gives you specific rights, and you may also have other rights which vary from state to state. Please contact Customer Service at 800-654-8483 (option 1) between 7:30AM - 5:00PM CST or visit our website [www.jascoproducts.com](http://www.jascoproducts.com) if the unit should prove defective within the warranty period.

### GARANTIE

JASCO Products garantit que ce produit est exempt de défaut de fabrication pour une période de deux ans à compter de la date de l'achat original par l'acheteur. Cette garantie se limite exclusivement à la réparation ou au remplacement de ce produit et n'est pas applicable aux dommages indirects ou accessoires survenant en raison de l'utilisation de ce produit. Cette garantie remplace à la fois toute garantie implicite ou implicite. Certains États ne permettent pas de restrictions quant à la durée d'une garantie implicite ou permettent l'exclusion ou la limitation des dommages indirects et accessoires. Il peut, par conséquent, que cette garantie ne s'applique pas dans votre cas.

Cette garantie vous confère des droits juridiques précis; vous pouvez avoir d'autres droits qui peuvent varier d'un État à l'autre. Veuillez communiquer avec le service à la clientèle au 1-800-654-8483 (option 1) entre 7 h 30 et 17 h, heure normale du Centre ou par l'intermédiaire du service Web ([www.jascoproducts.com](http://www.jascoproducts.com)) si l'appareil s'avère défectueux au cours de la période de garantie.

### GARANTIA

JASCO Products garantiza que este producto está libre de defectos de fabricación durante un periodo de dos años a partir de la fecha original de compra por parte del consumidor. Esta garantía se limita exclusivamente a la reparación o sustitución de este producto únicamente y no se extiende a daños derivados o accidentales causados a otros productos que se usen con este unidad. Esta garantía reemplaza a todas las demás garantías expresas o implícitas. Algunos estados no autorizan limitaciones en cuanto a la duración de una garantía implícita ni permiten la exclusión o limitación por daños accidentales o derivados por lo tanto, puede que las anteriores limitaciones no apliquen en su caso. Esta garantía le da un derecho específico, y otros que usted puede tener y que varían según el estado en el que usted reside. Si la unidad resulta defectuosa dentro del periodo de garantía, comuníquese por favor con Atención al Cliente en el 800-654-8483 (opción 1) entre 7:30 y 17 h, Hora del Centro, a través de nuestro sitio de Internet.

JASCO Products Company, Building B  
10 E Memorial Rd, Oklahoma City, OK 73114

### SPECIFICATIONS

ZW4005

Power: 120 VAC, 60 Hz

Signal Frequency: 908.4/916 MHz

Maximum Load: 960 W, Incandescent, 1/2 HP Motor or 1800 W (15 A) Resistive

Range: Up to 100 feet in sight between the Wireless Controller and the device

Operating Temperature Range: 32-104° F (0-40° C)

For indoor use only.

Specifications subject to change without notice due to continuing product improvement

### SPECIFICATIONS

ZW4005

Tension: 120 V CA, 60 Hz

Signal (Frecuencia): 908.4/916 MHz

Cargas máximas: 960 vatios (incandescente, motor de 1/2 HP o resistencia de 1800 W (15 A)).

Rango: Hasta 100 pies en línea de visión directa entre el control inalámbrico y el módulo receptor.

Temperatura de funcionamiento: de 32 a 104 °F (de 0 a 40 °C).

Para uso en espacios interiores solamente.

Especificaciones sujetas a cambio sin aviso debido a continuas mejoras del producto

## 1.

### Tools You Will Need

- Turn ON/OFF manually or remotely via the Z-Wave controller
- Can be installed in multiple Groups and Scenes
- May be used in single pole installation or with up to two Jasco Add-on switches in 3-way or 4-way wiring configurations
- Compatible with all incandescent and CFL/LED bulbs
- Interchangeable Paddle switch — White & light almond paddle in package
- Uses a standard, decorative-size wall plate for single gang installations (wall plate not included)
- Blue LED indicates switch location in a dark room
- Z-Wave Certified for simple pairing and integrated home automation
- Screen Terminal Installation — requires wiring connections for Line (Hot), Load, Neutral, and Ground. Traveler wire required for 3-way or 4-way installation
- This Z-Wave device has advanced features that allow you to customize your experience. These features can only be adjusted by a Z-Wave enabled controller that support the Z-Wave Configuration command class. For a complete list of Adjustable Configurations, visit [www.jascoproducts.com/zwaveconfig](http://www.jascoproducts.com/zwaveconfig)

**IMPORTANT!**

The fixture controlled by the Z-Wave In-wall Smart Switch must not exceed 960 watts (incandescent), 150W (15A) Resistive, or 1/2 HP Motor. The switch is designed only for use with permanently installed fixtures.

Getting To Know Your New Z-Wave Device

- Turn ON/OFF manually or remotely via the Z-Wave controller
- Can be installed in multiple Groups and Scenes
- May be used in single pole installation or with up to two Jasco Add-on switches in 3-way or 4-way wiring configurations
- Compatible with all incandescent and CFL/LED bulbs
- Interchangeable Paddle switch — White & light almond paddle in package
- Uses a standard, decorative-size wall plate for single gang installations (wall plate not included)
- Blue LED indicates switch location in a dark room
- Z-Wave Certified for simple pairing and integrated home automation
- Screen Terminal Installation — requires wiring connections for Line (Hot), Load, Neutral, and Ground. Traveler wire required for 3-way or 4-way installation
- This Z-Wave device has advanced features that allow you to customize your experience. These features can only be adjusted by a Z-Wave enabled controller that support the Z-Wave Configuration command class. For a complete list of Adjustable Configurations, visit [www.jascoproducts.com/zwaveconfig](http://www.jascoproducts.com/zwaveconfig)

**IMPORTANT!**

The fixture controlled by the Z-Wave In-wall Smart Switch must not exceed 960 watts (incandescent), 150W (15A) Resistive, or 1/2 HP Motor. The switch is designed only for use with permanently installed fixtures.

## 3.

### WARNING — SHOCK HAZARD

Turn OFF the power to the branch circuit for the switch and lighting fixture at the service panel. All wiring connections must be made with the POWER OFF to avoid personal injury and/or damage to the switch.

This device is intended for installation in accordance with the National Electrical Code and local regulations in the United States, or the Canadian Electrical Code and local regulations in Canada. If you are unsure or uncomfortable about performing this installation consult a qualified electrician.

## 4.

### WARNING — SHOCK HAZARD

Turn OFF the power to the branch circuit for the switch and lighting fixture at the service panel. All wiring connections must be made with the POWER OFF to avoid personal injury and/or damage to the switch.

This device is intended for installation in accordance with the National Electrical Code and local regulations in the United States, or the Canadian Electrical Code and local regulations in Canada. If you are unsure or uncomfortable about performing this installation consult a qualified electrician.

## 5.

### WARNING — SHOCK HAZARD

Turn OFF the power to the branch circuit for the switch and lighting fixture at the service panel. All wiring connections must be made with the POWER OFF to avoid personal injury and/or damage to the switch.

This device is intended for installation in accordance with the National Electrical Code and local regulations in the United States, or the Canadian Electrical Code and local regulations in Canada. If you are unsure or uncomfortable about performing this installation consult a qualified electrician.

## 2.

### WARNING — SHOCK HAZARD

Turn OFF the power to the branch circuit for the switch and lighting fixture at the service panel. All wiring connections must be made with the POWER OFF to avoid personal injury and/or damage to the switch.

This device is intended for installation in accordance with the National Electrical Code and local regulations in the United States, or the Canadian Electrical Code and local regulations in Canada. If you are unsure or uncomfortable about performing this installation consult a qualified electrician.

## 4.

### WARNING — SHOCK HAZARD

Turn OFF the power to the branch circuit for the switch and lighting fixture at the service panel. All wiring connections must be made with the POWER OFF to avoid personal injury and/or damage to the switch.

This device is intended for installation in accordance with the National Electrical Code and local regulations in the United States, or the Canadian Electrical Code and local regulations in Canada. If you are unsure or uncomfortable about performing this installation consult a qualified electrician.

## 4.

### WARNING — SHOCK HAZARD

Turn OFF the power to the branch circuit for the switch and lighting fixture at the service panel. All wiring connections must be made with the POWER OFF to avoid personal injury and/or damage to the switch.

This device is intended for installation in accordance with the National Electrical Code and local regulations in the United States, or the Canadian Electrical Code and local regulations in Canada. If you are unsure or uncomfortable about performing this installation consult a qualified electrician.

## 5.

### WARNING — SHOCK HAZARD

Turn OFF the power to the branch circuit for the switch and lighting fixture at the service panel. All wiring connections must be made with the POWER OFF to avoid personal injury and/or damage to the switch.

This device is intended for installation in accordance with the National Electrical Code and local regulations in the United States, or the Canadian Electrical Code and local regulations in Canada. If you are unsure or uncomfortable about performing this installation consult a qualified electrician.

## 2.

### WARNING — SHOCK HAZARD

Turn OFF the power to the branch circuit for the switch and lighting fixture at the service panel. All wiring connections must be made with the POWER OFF to avoid personal injury and/or damage to the switch.

This device is intended for installation in accordance with the National Electrical Code and local regulations in the United States, or the Canadian Electrical Code and local regulations in Canada. If you are unsure or uncomfortable about performing this installation consult a qualified electrician.

## 4.

### WARNING — SHOCK HAZARD

Turn OFF the power to the branch circuit for the switch and lighting fixture at the service panel. All wiring connections must be made with the POWER OFF to avoid personal injury and/or damage to the switch.

This device is intended for installation in accordance with the National Electrical Code and local regulations in the United States, or the Canadian Electrical Code and local regulations in Canada. If you are unsure or uncomfortable about performing this installation consult a qualified electrician.

## 4.

### WARNING — SHOCK HAZARD

Turn OFF the power to the branch circuit for the switch and lighting fixture at the service panel. All wiring connections must be made with the POWER OFF to avoid personal injury and/or damage to the switch.

This device is intended for installation in accordance with the National Electrical Code and local regulations in the United States, or the Canadian Electrical Code and local regulations in Canada. If you are unsure or uncomfortable about performing this installation consult a qualified electrician.

## 5.

### WARNING — SHOCK HAZARD

Turn OFF the power to the branch circuit for the switch and lighting fixture at the service panel. All wiring connections must be made with the POWER OFF to avoid personal injury and/or damage to the switch.

This device is intended for installation in accordance with the National Electrical Code and local regulations in the United States, or the Canadian Electrical Code and local regulations in Canada. If you are unsure or uncomfortable about performing this installation consult a qualified electrician.

FCG / IC

This device complies with part 15 of the FCC and Industry Canada (Nominally RSS standards). Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

**FCC NOTE:** The manufacturer is not responsible for any radio or TV interference caused by unauthorized modifications to this equipment. Such modifications could void the user's authority to operate the equipment.

**NOTE:** This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If the equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

**Important note:** To comply with the FCC/RF exposure compliance requirements, no change to the antenna or the device is permitted. Any change to the antenna or the device could result in the device exceeding the RF exposure requirements and void the user's authority to operate the device.

El presente equipo cumple con los requisitos de la Parte 15 de las normas FCC y de la CNI para los aparatos emisores de radio de Clase B. Estas limitaciones están sujetas a las dos condiciones siguientes:

(1) Este equipo no debe ocasionar interferencia perjudicial; (2) el presente equipo debe aceptar toda interferencia recibida, incluyendo la interferencia que provoque un funcionamiento no deseado.

**NOTA DE LA FCC:** El fabricante no es responsable de las interferencias con las frecuencias radioeléctricas o televisivas producidas por causas de modificaciones no autorizadas de su equipo. Dichas modificaciones podrían anular la autoridad del usuario para operar el equipo.

**NOTA:** Este equipo ha sido probado y cumple con los límites para aparatos digitales de Clase B, de conformidad con el apartado 15 de las normas de la FCC. Estas limitaciones están diseñadas para proveer protección razonable contra interferencias perjudiciales en una instalación residencial. Este equipo genera, usa y puede irradiar energía de radiofrecuencia y, si no se instala y usa según las instrucciones, puede provocar interferencia perjudicial a las radio comunicaciones. No obstante, no hay garantía de que no ocurra interferencia en una instalación en particular. Si este equipo provoca interferencia perjudicial a la recepción de radio o televisión, lo que puede determinarse encendiendo y apagando el equipo, se recomienda al usuario intentar corregir la interferencia por medio de la implementación de una o más de las siguientes medidas:

- Reorientar o reducir la antena receptora.
- Incrementar la separación entre el equipo y el receptor.
- Conectar el equipo a un tomacorriente de un circuito diferente del circuito al que está conectado el receptor.
- Consultar al distribuidor o a un técnico con experiencia en radio/televisión para solicitar asistencia.

**Nota importante:** Para cumplir con los requisitos de cumplimiento de radiofrecuencia de la FCC, no se permiten cambios a la antena o el dispositivo. Cualquier cambio a la antena o dispositivo podría hacer que el dispositivo supiera los requisitos de radiofrecuencia y anule la autoridad del usuario para operar el dispositivo.

Al brand names shown are trademarks of their respective owners.

DISTRIBUIDOR POR:  
JASCO PRODUCTS COMPANY LLC,  
10 E. MEMORIAL RD.,  
OKLAHOMA CITY, OK 73114.  
© JASCO 2014 14318 ZW4005 / 14317

### In-wall Wireless Smart Switch

Montage mural sans fil intelligent enfichable

Interruptor inalámbrico de pared inteligente

Scan to view installation guide

Balayez ce code pour consulter le guide d'installation

Escanear para ver la guía de instalación

14318 ZW4005

© Z-WAVE®

Z-Wave® Certified Wireless Lighting Control

Certifié Z-Wave Commande d'éclairage sans fil

Control inalámbrico para iluminación certificado por Z-Wave®

## DO NOT RETURN THIS PRODUCT TO THE STORE

## NE RETOURNEZ PAS CE PRODUIT AU MAGASIN

## NO DEVUELVA ESTE PRODUCTO A LA TIENDA.

If you have any problems or questions, contact our tech support team at 1-800-654-8483, option 1 Monday-Friday 7:30-5pm CST.

For the most up-to-date product support, accessories, electronic (PDF) format manuals and more, visit [www.jascoproducts.com/support](http://www.jascoproducts.com/support)

No user serviceable parts in this unit.

Si vous avez des problèmes ou des questions, communiquez avec notre équipe de soutien technique au 1-800-654-8483, option 1 du lundi au vendredi, de 7 h 30 à 17 h (PAC).

Pour un soutien technique d'après-vente, les nouveaux accessoires, les plus récents manuels en format électronique (PDF) et plus encore, visitez le site [www.jascoproducts.com/support](http://www.jascoproducts.com/support)

Aucun des pièces de ce dispositif ne peut être réparé par l'utilisateur.

Si tiene problemas o dudas, comuníquese con nuestro equipo técnico al número: 1-800-654-8483, opción 1 de lunes a viernes, de 7:30 a 17 h, hora estándar del centro (CST).

Para recibir el soporte técnico más actualizado sobre productos, accesorios, manuales en formato digital (PDF), entre otros, visite [www.jascoproducts.com/support](http://www.jascoproducts.com/support)

Esta unidad no contiene piezas que el usuario pueda reparar.

### WARRANTY

JASCO Products warrants this product to be free from manufacturing defects for a period of two years from the original date of consumer purchase. This warranty is limited to the repair or replacement of this product only and does not extend to consequential or incidental damage to other products which may be used with this product. This warranty is in lieu of all other warranties, expressed or implied. Some states do not allow limitations on how long an implied warranty lasts to permit the exclusion or limitation of incidental or consequential damage, so the above limitations may not apply to you. This warranty gives you specific rights, and you may also have other rights which vary from state to state. Please contact Customer Service at 800-654-8483 (option 1) between 7:30AM - 5:00PM CST or visit our website [www.jascoproducts.com](http://www.jascoproducts.com) if the unit should prove defective within the warranty period.

### GARANTIE

JASCO Products garantit que ce produit est exempt de défaut de fabrication pour une période de deux ans à compter de la date de l'achat original par l'acheteur. Cette garantie se limite exclusivement à la réparation ou au remplacement de ce produit et n'est pas applicable aux dommages indirects ou accessoires survenant en raison de l'utilisation de ce produit. Cette garantie remplace à la fois toute garantie implicite ou implicite. Certains États ne permettent pas de restrictions quant à la durée d'une garantie implicite ou permettent l'exclusion ou la limitation des dommages indirects et accessoires. Il peut, par conséquent, que cette garantie ne s'applique pas dans votre cas.

Cette garantie vous confère des droits juridiques précis; vous pouvez avoir d'autres droits qui peuvent varier d'un État à l'autre. Veuillez communiquer avec le service à la clientèle au 1-800-654-8483 (option 1) entre 7 h 30 et 17 h, heure normale du Centre ou par l'intermédiaire du service Web ([www.jascoproducts.com](http://www.jascoproducts.com)) si l'appareil s'avère défectueux au cours de la période de garantie.

### GARANTIA

JASCO Products garantiza que este producto está libre de defectos de fabricación durante un periodo de dos años a partir de la fecha original de compra por parte del consumidor. Esta garantía se limita exclusivamente a la reparación o sustitución de este producto únicamente y no se extiende a daños derivados o accidentales causados a otros productos que se usen con este unidad. Esta garantía reemplaza a todas las demás garantías expresas o implícitas. Algunos estados no autorizan limitaciones en cuanto a la duración de una garantía implícita ni permiten la exclusión o limitación por daños accidentales o derivados por lo tanto, puede que las anteriores limitaciones no apliquen en su caso. Esta garantía le da un derecho específico, y otros que usted puede tener y que varían según el estado en el que usted reside. Si la unidad resulta defectuosa dentro del periodo de garantía, comuníquese por favor con Atención al Cliente en el 800-654-8483 (opción 1) entre 7:30 y 17 h, Hora del Centro, a través de nuestro sitio de Internet.

JASCO Products Company, Building B  
10 E Memorial Rd, Oklahoma City, OK 73114

### SPECIFICATIONS

ZW4005

Power: 120 VAC, 60 Hz

Signal Frequency: 908.4/916 MHz

Maximum Load: 960 W, Incandescent, 1/2 HP Motor or 1800 W (15 A) Resistive

Range: Up to 100 feet in sight between the Wireless Controller and the device

Operating Temperature Range: 32-104° F (0-40° C)

For indoor use only.

Specifications subject to change without notice due to continuing product improvement

### SPECIFICATIONS

ZW4005

Tension: 120 V CA, 60 Hz

Signal (Frecuencia): 908.4/916 MHz

Cargas máximas: 960 vatios (incandescente, motor de 1/2 HP o resistencia de 1800 W (15 A)).

Rango: Hasta 100 pies en línea de visión directa entre el control inalámbrico y el módulo receptor.

Temperatura de funcionamiento: de 32 a 104 °F (de 0 a 40 °C).

Para uso en espacios interiores solamente.

Especificaciones sujetas a cambio sin aviso debido a continuas mejoras del producto

## 1.

### Tools You Will Need

- Turn ON/OFF manually or remotely via the Z-Wave controller
- Can be installed in multiple Groups and Scenes
- May be used in single pole installation or with up to two Jasco Add-on switches in 3-way or 4-way wiring configurations
- Compatible with all incandescent and CFL/LED bulbs
- Interchangeable Paddle switch — White & light almond paddle in package
- Uses a standard, decorative-size wall plate for single gang installations (wall plate not included)
- Blue LED indicates switch location in a dark room
- Z-Wave Certified for simple pairing and integrated home automation
- Screen Terminal Installation — requires wiring connections for Line (Hot), Load, Neutral, and Ground. Traveler wire required for 3-way or 4-way installation
- This Z-Wave device has advanced features that allow you to customize your experience. These features can only be adjusted by a Z-Wave enabled controller that support the Z-Wave Configuration command class. For a complete list of Adjustable Configurations, visit [www.jascoproducts.com/zwaveconfig](http://www.jascoproducts.com/zwaveconfig)

**IMPORTANT!**

The fixture controlled by the Z-Wave In-wall Smart Switch must not exceed 960 watts (incandescent), 150W (15A) Resistive, or 1/2 HP Motor. The switch is designed only for use with permanently installed fixtures.

Getting To Know Your New Z-Wave Device

- Turn ON/OFF manually or remotely via the Z-Wave controller
- Can be installed in multiple Groups and Scenes
- May be used in single pole installation or with up to two Jasco Add-on switches in 3-way or 4-way wiring configurations
- Compatible with all incandescent and CFL/LED bulbs
- Interchangeable Paddle switch — White & light almond paddle in package
- Uses a standard, decorative-size wall plate for single gang installations (wall plate not included)
- Blue LED indicates switch location in a dark room
- Z-Wave Certified for simple pairing and integrated home automation
- Screen Terminal Installation — requires wiring connections for Line (Hot), Load, Neutral, and Ground. Traveler wire required for 3-way or 4-way installation
- This Z-Wave device has advanced features that allow you to customize your experience. These features can only be adjusted by a Z-Wave enabled controller that support the Z-Wave Configuration command class. For a complete list of Adjustable Configurations, visit [www.jascoproducts.com/zwaveconfig](http://www.jascoproducts.com/zwaveconfig)

**IMPORTANT!**

The fixture controlled by the Z-Wave In-wall Smart Switch must not exceed 960 watts (incandescent), 150W (15A) Resistive, or 1/2 HP Motor. The switch is designed only for use with permanently installed fixtures.

## 3.

### WARNING — SHOCK HAZARD

Turn OFF the power to the branch circuit for the switch and lighting fixture at the service panel. All wiring connections must be made with the POWER OFF to avoid personal injury and/or damage to the switch.

This device is intended for installation in accordance with the National Electrical Code and local regulations in the United States, or the Canadian Electrical Code and local regulations in Canada. If you are unsure or uncomfortable about performing this installation consult a qualified electrician.

## 4.

### WARNING — SHOCK HAZARD

Turn OFF the power to the branch circuit for the switch and lighting fixture at the service panel. All wiring connections must be made with the POWER OFF to avoid personal injury and/or damage to the switch.

This device is intended for installation in accordance with the National Electrical Code and local regulations in the United States, or the Canadian Electrical Code and local regulations in Canada. If you are unsure or uncomfortable about performing this installation consult a qualified electrician.

## 5.

### WARNING — SHOCK HAZARD

Turn OFF the power to the branch circuit for the switch and lighting fixture at the service panel. All wiring connections must be made with the POWER OFF to avoid personal injury and/or damage to the switch.

This device is intended for installation in accordance with the National Electrical Code and local regulations in the United States, or the Canadian Electrical Code and local regulations in Canada. If you are unsure or uncomfortable about performing this installation consult a qualified electrician.

## 2.

### WARNING — SHOCK HAZARD

Turn OFF the power to the branch circuit for the switch and lighting fixture at the service panel. All wiring connections must be made with the POWER OFF to avoid personal injury and/or damage to the switch.

This device is intended for installation in accordance with the National Electrical Code and local regulations in the United States, or the Canadian Electrical Code and local regulations in Canada. If you are unsure or uncomfortable about performing this installation consult a qualified electrician.

## 4.

### WARNING — SHOCK HAZARD

Turn OFF the power to the branch circuit for the switch and lighting fixture at the service panel. All wiring connections must be made with the POWER OFF to avoid personal injury and/or damage to the switch.

This device is intended for installation in accordance with the National Electrical Code and local regulations in the United States, or the Canadian Electrical Code and local regulations in Canada. If you are unsure or uncomfortable about performing this installation consult a qualified electrician.

## 4.

### WARNING — SHOCK HAZARD

Turn OFF the power to the branch circuit for the switch and lighting fixture at the service panel. All wiring connections must be made with the POWER OFF to avoid personal injury and/or damage to the switch.

This device is intended for installation in accordance with the National Electrical Code and local regulations in the United States, or the Canadian Electrical Code and local regulations in Canada. If you are unsure or uncomfortable about performing this installation consult a qualified electrician.

## 5.

### WARNING — SHOCK HAZARD

Turn OFF the power to the branch circuit for the switch and lighting fixture at the service panel. All wiring connections must be made with the POWER OFF to avoid personal injury and/or damage to the switch.

This device is intended for installation in accordance with the National Electrical Code and local regulations in the United States, or the Canadian Electrical Code and local regulations in Canada. If you are unsure or uncomfortable about performing this installation consult a qualified electrician.

## 2.

### WARNING — SHOCK HAZARD

Turn OFF the power to the branch circuit for the switch and lighting fixture at the service panel. All wiring connections must be made with the POWER OFF to avoid personal injury and/or damage to the switch.

This device is intended for installation in accordance with the National Electrical Code and local regulations in the United States, or the Canadian Electrical Code and local regulations in Canada. If you are unsure or uncomfortable about performing this installation consult a qualified electrician.

## 4.

### WARNING — SHOCK HAZARD

Turn OFF the power to the branch circuit for the switch and lighting fixture at the service panel. All wiring connections must be made with the POWER OFF to avoid personal injury and/or damage to the switch.

This device is intended for installation in accordance with the National Electrical Code and local regulations in the United States, or the Canadian Electrical Code and local regulations in Canada. If you are unsure or uncomfortable about performing this installation consult a qualified electrician.

## 4.

### WARNING — SHOCK HAZARD

Turn OFF the power to the branch circuit for the switch and lighting fixture at the service panel. All wiring connections must be made with the POWER OFF to avoid personal injury and/or damage to the switch.

This device is intended for installation in accordance with the National Electrical Code and local regulations in the United States, or the Canadian Electrical Code and local regulations in Canada. If you are unsure or uncomfortable about performing this installation consult a qualified electrician.

## 5.

### WARNING — SHOCK HAZARD

Turn OFF the power to the branch circuit for the switch and lighting fixture at the service panel. All wiring connections must be made with the POWER OFF to avoid personal injury and/or damage to the switch.

This device is intended for installation in accordance with the National Electrical Code and local regulations in the United States, or the Canadian Electrical Code and local regulations in Canada. If you are unsure or uncomfortable about performing this installation consult a qualified electrician.