

VOKKERO GUARDIAN US

User Guide
Version 1.0.0



XXXX

VOKKERO

Adeunis
283 rue Louis Néel - Parc Technologique Pré Roux
38920 CROLLES - France
www.vokkero.com



PREAMBLE

- This guide describes the functionality of the system VOKKERO GUARDIAN US, options and accessories. It explains how to configure it to allow a conference-type communication between multiple users.
- No part of this document may be reproduced or transmitted (in electronic or paper, or photocopying) without the agreement Adeunis. This document may be changed without notice. All trademarks mentioned in this guide are the subject of intellectual property rights. Adeunis.

Adeunis NA

25 Main Street, 3rd Floor
Tuckahoe, NY 10707
Call us at (914) 337-2167

Adeunis

283, rue Louis Néel
38920 Crolles
France

Web

www.VOKKEROusa.com

PREAMBLE	2
	34
ENGLISH	35
INFORMATIONS	36
DISCLAIMER	36
TECHNICAL SUPPORT	36
INTRODUCTION	39
ENVIRONMENTAL RECOMMENDATIONS	40
WARNINGS	40
RECOMMENDATIONS REGARDING USE	41
DISPOSAL OF WASTE BY USERS IN PRIVATE HOUSEHOLDS WITHIN THE USAN UNION	41
INTRODUCTION	42
1. SYSTEM INSTALLATION PROCEDURE	42
2. SYSTEM DESCRIPTION	43
2.1. VOKKERO® Guardian Terminal	43
2.1.1. Description of product interface	43
2.1.2. General characteristics	43
2.2. VOKKERO® Guardian Charger/Configurator	44
2.2.1. Description of product interface	44
2.2.2. General Technical Specifications	44
3. STARTING UP THE TERMINAL	45
3.1. Screen Icons (by Default)	45
3.2. Setting up Audio Conference	45
3.3. Connecting a headset	46
3.3.1. Plugging in a headset	46
3.3.2. Removing the headset	46
3.4. Terminal operation	47
3.4.1. Volume	47
3.4.2. Channel (mode activated by default)	47
3.4.3. Group (accessible by configuration)	47
3.4.4. "Micro" button (Latch mode by default)	48
3.4.5. Call button	48
3.4.6. Locking the terminal	48
3.4.7. Side Tone	49
3.4.8. Bluetooth (Option)	49
3.4.9. Battery	50
3.4.10. Belt clip	50
4. DESCRIPTION OF THE CONFIGURATOR	51
4.1. Home Screen	51
4.2. Quick configuration	51
4.3. Settings	52
4.3.1. Configuring the terminal	53
4.3.2. System configuration	57
4.3.3. Configuring the configurator	62
4.4. Resetting the configurator functions	63
DOCUMENT HISTORY	63

EN

ENGLISH

INFORMATIONS

Document Information	
Title	VOKKERO GUARDIAN US
Subtitle	US
Document type	User Guide
Version	Version 1.0.0

This document applies to the following products:

Nom	Référence
VOKKERO GUARDIAN US	Up to : ARF8320 A/B/C/D/E/F/G/H/I/J

EN

DISCLAIMER

This document and the use of any information contained therein, is subject to the acceptance of the VOKKERO terms and conditions. They can be downloaded from www.vokkerousa.com

VOKKERO makes no warranties based on the accuracy or completeness of the contents of this document and reserves the right to make changes to specifications and product descriptions at any time without notice.

VOKKERO reserves all rights to this document and the information contained herein. Reproduction, use or disclosure to third parties without express permission is strictly prohibited. Copyright © 2016, VOKKERO.

VOKKERO is a registered trademark in the EU and other countries.

TECHNICAL SUPPORT

Website

Our website contains a lot of useful information: information on modules and wireless modems, user guides, and configuration software and technical documents which can be accessed 24 hours a day.

If you have technical problems or cannot find the required information in the provided documents, contact our Technical Support on our website: www.vokkerousa.com. This ensures that your request will be processed as soon as possible.

Helpful Information when Contacting Technical Support

When contacting Technical Support, please have the following information ready:

- Product type (for example Guardian)
- Firmware version (for example V1.0)
- A clear description of your question or the problem
- A short description of the application

COMPLIANCE TO FCC US/CAN

• This device complies with part 15 of the FCC rules and Industry Canada licence-exempt RSS standard(s). Operation is subject to the following two conditions: (1). this device may not cause Harmful interference, and (2). this device must accept any interference received, including interference that may cause undesired operation of the device.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instruction, may cause harmful interference to radiocommunication. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off

and on, the user is encouraged to try to correct the interference by one or more of the following measures :

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

• CHANGES OR MODIFICATIONS NOT EXPRESSLY APPROVED BY ADEUNIS COULD VOID THE USER'S AUTHORITY TO OPERATE THE EQUIPMENT.

Under Industry Canada regulations, this radio transmitter may only operate using an antenna of a type and maximum (or lower) gain approved for the transmitter by Industry Canada. To reduce potential radio interference to other users, the antenna type and its gain should be chosen so that the equivalent isotropically radiated power (e.i.r.p.) is not superior than necessary for successful communication.

Ce dispositif est conforme aux règles de la FCC part 15 and à la norme CNR-210 d'Industrie Canada applicable aux appareils radio exempts de licence. Son fonctionnement est sujet aux deux conditions suivantes: (1) le dispositif ne doit pas produire de brouillage préjudiciable, et (2) ce dispositif doit accepter tout brouillage reçu, y compris un brouillage susceptible de provoquer un fonctionnement indésirable.

Cet équipement a été testé et déclaré conforme aux limites d'un appareil numérique de classe B, conformément à la partie 15 des règles de la FCC. Ces limites sont conçues pour fournir une protection raisonnable contre les interférences nuisibles dans une installation résidentielle. Cet équipement génère, utilise et peut émettre de l'énergie radiofréquence et, s'il n'est pas installé et utilisé conformément aux instructions, peut causer des interférences nuisibles aux radiocommunications. Il est cependant toujours possible que des interférences se produisent dans le cadre d'une installation particulière.

Si cet appareil produit des interférences nuisibles à la réception des programmes de radio et de télévision –détectables lors de la mise hors tension ou en tension de l'appareil–l'utilisateur est encouragé à mettre en œuvre une ou plusieurs des mesures suivantes pour remédier à ces interférences :

- Réorienter ou déplacer l'antenne de réception.
- Augmenter la distance entre l'équipement et le récepteur.
- Branchez le matériel à une sortie sur un circuit différent de celui auquel le récepteur est branché.
- Prendre conseil auprès du commerçant ou d'un technicien de radio/TV expérimenté.

Tout changement ou modification non expressément approuvé par la partie responsable des mesures de conformité peut amener l'utilisateur à se voir interdire l'usage de l'appareil.

Cet appareil est limité à l'exploitation des fréquences autorisées Partie 15, et ne peut pas être configuré par des utilisateurs finaux ou des installateurs professionnels à fonctionner en dehors des bandes autorisées.

Conformément à la réglementation d'Industrie Canada, le présent émetteur radio peut fonctionner avec une antenne d'un type et d'un gain maximal (ou inférieur) approuvé pour l'émetteur par Industrie Canada. Dans le but de réduire les risques de brouillage radioélectrique à l'intention des autres utilisateurs, il faut choisir le type d'antenne et son gain de sorte que la puissance isotrope rayonnée équivalente (p.i.r.e.) ne dépasse pas l'intensité nécessaire à l'établissement d'une communication satisfaisante.

FOR PORTABLE DEVICE USAGE (<20cm from body/SAR needed)

Radiation Exposure Statement:

The product comply with the FCC and ISED portable RF exposure limit set forth for an uncontrolled environment and are safe for intended operation as described in this manual. The further RF exposure reduction can be achieved if the product can be kept as far as possible from the user body or set the device to lower output power if such function is available. This portable equipment with its antenna complies with FCC's and ISED RF radiation exposure limits set forth for an uncontrolled environment. To maintain compliance follow the instructions below:

1. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.
2. Avoid direct contact with the antenna, or keep it to a minimum while using this equipment.

The SAR limit adopted by USA and Canada is 1.6 W/kg averaged over 1 gram of tissue. The highest SAR value reported to FCC and ISED for this device complies with this limit.

Déclaration d'exposition aux radiations:

Le produit est conforme aux limites d'exposition pour les appareils portables RF FCC pour les Etats-Unis, l'ISED pour le Canada et établies pour un environnement non contrôlé. Le produit est sûr pour un fonctionnement tel que décrit dans ce manuel. La réduction aux expositions RF peut être augmentée si l'appareil peut être conservé aussi loin que possible du corps de l'utilisateur ou que le dispositif est réglé sur la puissance de sortie la plus faible si une telle fonction est disponible.

Cet équipement portable avec son antenne est conforme aux limites d'exposition aux radiations RF de la FCC définies pour un environnement non contrôlé.

Pour maintenir la conformité, suivez les instructions ci-dessous :

1. Cet émetteur ne doit pas être situé ou fonctionner conjointement avec une autre antenne ou un autre émetteur.
2. Évitez ou réduisez au minimum tout contact direct avec l'antenne pendant l'utilisation de cet équipement.

La limite de DAS adoptée par les États-Unis et le Canada est de 1,6 W / kg en moyenne sur 1 gramme de tissu. La valeur SAR la plus élevée signalée à la FCC et à ISED pour cet appareil est conforme à cette limite.

Identification :

- FCC ID : U3Z-ARF8320
- CANADAIC : 7016A-ARF8320
- Product with Bluetooth: Contains FCC ID SSSBC127-X and IC ID : 11012A-BC127

Product reference: USA/CANADA: ARF8320 A/B/C/D/E/F/G/H/I/J

Authorised representative in Canada

ZEAT SPORTS

310-5253 Blvd Décarie - H3W 3C3 MONTREAL - CANADA

Phone : +1-877-750.2012

USAGE RESTRICTIONS : THE USE OF VOKKERO GUARDIAN IN US/CAN

FHSS tables / Channel setting

IMPORTANT: Before using the device, please observe the legal provisions in force in your country.

In this 915 MHz FHSS version, Vokkero GUARDIAN is transmitting in frequency hopping mode. You can set the terminal with 7 different tables of channels.

Table ID Frequencies

C1	32 channels within the 902.188MHz to 927.688MHz band
H1 A1	25 channels within the 916.698MHz to 927.573MHz band 27 channels within the 902.188MHz to 916.063MHz band
H2 A2	25 channels within the 903.688MHz to 927.313MHz band 26 channels within the 902.750MHz to 926.375MHz band
H3 A3	25 channels within the 902.188MHz to 917.938MHz band 26 channels within the 903.313MHz to 917.563MHz band

INTRODUCTION

All rights to this manual are the exclusive property of VOKKERO. All rights reserved. Copying this manual (without written permission from the owner) via printing, copying, recording or by any other means, translating this manual (in full or partially) into any other language, including all programming languages, using any electrical, mechanical, magnetic or optical devices, manually or any by other methods, is prohibited.

VOKKERO reserves the right to change the technical specifications or functions of its products, or to cease manufacturing any of its products, or to cease technical support for one of its products without notice in writing and urges its customers to make sure that the information they have is valid.

VOKKERO configuration software and programs are available free of charge in a non-modifiable version. VOKKERO can make no guarantees, including guarantees concerning suitability and applicability for a certain type of application. Under no circumstances can the manufacturer, or the distributor of an VOKKERO program, be held liable for any damage caused by the use of the afore-said program. Program names, as well as all copyright relating to programs, are the exclusive property of VOKKERO. Any transfer, granting of licences to a third party, leasing, hire, transport, copying, editing, translation, modification into another programming language or reverse engineering are prohibited without VOKKERO's prior written authorisation and consent.

Adeunis NA

25 Main Street, 3rd Floor
Tuckahoe, NY 10707
Call us at (914) 337-2167

Adeunis

283, rue Louis Néel
38920 Crolles
France

ENVIRONMENTAL RECOMMENDATIONS

All superfluous packaging materials have been eliminated. We have done everything possible to make it easy to separate the packaging into three types of materials: cardboard (box), expanded polystyrene (filler material) and polyethylene (packets, foam protective sheets). Your device is composed of materials that can be recycled and reused if it is dismantled by a specialist company. Please observe local regulations concerning the manner in which waste packaging material, used batteries and your obsolete equipment are disposed of.

WARNINGS

Valid for :
VOKKERO GUARDIAN US : ARF8320 A/B/C/D/E/F/G/H/I/J



Read the instructions in the manual.



The safety of this product is only guaranteed when it is used in accordance with its purpose.
Maintenance should only be carried out by qualified persons.

Please note: Do not install the equipment close to a heat source or in damp conditions.

Please note: When the equipment is open, do not carry out any operations other than the ones set out in this document.



Please note: Do not open the product as there is a risk of electrical shock.



Please note: For your own safety, you must ensure that the equipment is switched off before carrying out any work on it.



Please note: For your own safety, the power supply circuit must be SELV (Safety Extra Low Voltage) and must be from limited power sources.

The product must be equipped with a switching mechanism so that the power can be cut. This must be close to the equipment. Any electrical connection of the product must be equipped with a protection device against voltage spikes and short-circuits.

RECOMMENDATIONS REGARDING USE

- Before using the system, check that the power supply voltage shown in the user manual corresponds to your supply. If it doesn't, please consult your supplier.
- Place the device against a flat, firm and stable surface.
- The device must be installed in a location that is sufficiently ventilated so that there is no risk of internal heating and it must not be covered with objects such as newspapers, cloths, curtains, etc.
- The device must never be exposed to heat sources such as heating equipment.
- Do not place the device close to objects with naked flames such as lit candles, blowtorches, etc.
- The device must not be exposed to harsh chemical agents or solvents likely to damage the plastic or corrode the metal parts.
- The device must be attached to belt with the belt-clip.

DISPOSAL OF WASTE BY USERS IN PRIVATE HOUSEHOLDS WITHIN THE USAN UNION



This symbol on the product or on its packaging indicates that this product must not be disposed of with your other household waste. Instead, it is your responsibility to dispose of your waste by taking it to a collection point designated for the recycling of electrical and electronic appliances. Separate collection and recycling of your waste at the time of disposal will contribute to conserving natural resources and guarantee recycling that respects the environment and human health. For further information concerning your nearest recycling centre, please contact your nearest local authority/town hall offices, your household waste collection company or the shop where you bought the product



Warning: If the charger is used with any other batteries or products whatsoever, there is a risk of an explosion. After use, the batteries must be disposed of at an appropriate recycling centre. They must not be thrown away to degrade in the environment. When batteries are replaced, the device must be correctly implemented.



Warning for Switzerland : the annex 4.10 of SR 814.013 Standard must be applied for batteries.



This symbol on the device or its packaging means the use of a DC voltage.

INTRODUCTION

The operations described below allow you to rapidly and easily implement your VOKKERO Guardian communication system.

All the operations described are valid for all the VOKKERO[®] Guardian terminals listed below:

ARF8320 A/B/C/D/E/F/G/H/I/J

Note:

Your product reference is given on the label on the back of the terminal housing.

The VOKKERO Guardian system is ready-to-use; it comprises the following three main elements:

- Terminals
- Configurator/Charger
- (Optional) Charger extension (1 to 4 maximum)

All the operating settings of the VOKKERO Guardian system are managed by the configurator which gives access to the Settings menu via a touchscreen. The configurator must be connected to the power unit (otherwise it will not work) and up to 4 extensions can be associated with the configurator.

1. SYSTEM INSTALLATION PROCEDURE


- Connect the power unit to the end charger (if several are connected in a row).
- Connect the power unit to the mains.
- Connect the VOKKERO Guardian terminals as shown below.

Note 1: the order and position of the terminals on the charger(s) are irrelevant.

Note 2: if the purpose of the operation is solely to charge terminals, then the configurator is not required.



The first configurator slot (i.e., closest to the LCD) is of importance to the system-configuration process; for more details, refer to §3.4.



2. SYSTEM DESCRIPTION

2.1. VOKKERO® Guardian Terminal

2.1.1. Description of product interface



2.1.2. General characteristics

General Specifications	Value
Supply voltage	3.7V nominal
Maximum consumption	800mA (emission)
Terminal power supply	Lithium battery
Battery life	11 hours (normal usage) 7 hours (permanent communication) If Bluetooth option activated, then 10% drop in battery life
Operating temperature	-20°C / +55°C
Dimensions	110 x 70 x 27mm
Weight	190g (including battery)
Standards	FCC CFR 47 part 15, RSS-210, IEC 62209-2

2.2. VOKKERO® Guardian Charger/Configurator

2.2.1. Description of product interface



2.2.2. General Technical Specifications

Specifications	Value
AC/DC Power Converter (standard)	100 to 240V 12VDC/5A - 50/60Hz (maximum of 10 terminals charging)
AC/DC power converter (extended system)	100 to 240V, 12 VDC/6.67A - 50/60Hz (more than 10 terminals charging)
Operating temperature	-5°C / +40°C
Dimensions Configurator/Charger	337 x 95 x 58mm
Dimension extension	216 x 95 58mm
Weight configurator/charger	470g
Weight extension	310g
Standards	EN 60950, EN 301-489, EN55032


3. STARTING UP THE TERMINAL

Before starting your terminal, make sure that it has been properly charged using a compatible charger.

- Press the On/Off button to turn on the terminal.



The LCD screen should turn on and display the VOKKERO® logo. The LED above the On/off button should also light up permanently.




Next, the Welcome Screen displays, followed by the product name. By default, the product name "Guardian" displays. This text can however be customized in the configurator for each terminal (refer to §4.3.1).

- To turn off the terminal, press and hold the "on/off" button.

Note 1: all settings, including volume, remain unchanged when the terminal is turned off (i.e., will be identical when the terminal is turned again).

3.1. Screen Icons (by Default)



3.2. Setting up Audio Conference

You can set up a VOKKERO audio conference. The first step consists in attributing the Master role (M1) to a single terminal. This role is used to synchronize the other terminals.

The Master role (M1) is automatically attributed to the terminal located in the first slot of the configurator during a quick configuration (see §4.2).


If you want to add other terminals to an existing audio conference chain without having to reposition all the terminals on the configurator, the first configurator slot must remain available.



3.3. Connecting a headset

Several types of headsets from the VOKKERO range can be connected to VOKKERO Guardian. The headset is automatically detected by the terminal when the headset is plugged in.

3.3.1. Plugging in a headset



3.3.2. Removing the headset

To remove the headset

- Firstly, pull on the ring of the headset to release the connector switch.
- Then remove the headset connector



Attention

Do not attempt to remove the headset by pulling the cable.



Attention

Do not turn the connector



Use the "Micro" icon on the terminal screen to make sure that the headset is properly connected. After disconnection of a headset, it is necessary to wait a few moments for the micro icon to be crossed out before reconnecting a headset.



No accessory connected



Accessory connected

3.4. Terminal operation

3.4.1. Volume

Adjust the terminal volume with the Volume trigger button.


- Push the trigger upwards to increase the volume
- Push the trigger downwards to decrease the volume

The volume can be adjusted in a range from 0 to 10

When you increase or decrease the volume, you will hear a beep.

When you reach the maximum or minimum volume setting, you will hear 2 consecutive beeps.

The volume setting is also indicated on the terminal LCD.



3.4.2. Channel (mode activated by default)

Adjust the terminal's communication channel with the Channel trigger button.



- Push the trigger upwards to increase the channel number
- Push the trigger downwards to decrease the channel number

The channels available on the terminal depend on the terminal version; for more information, refer to the channels table (document annex).

When you change channel, you will hear a beep.

When you reach the top or bottom channel, you will hear 2 consecutive beeps.

The selected channel is also indicated on the terminal LCD.



3.4.3. Group (accessible by configuration)

To change groups, you must also use the Channel trigger button:

- Push the trigger up to increase the group number
- Push the trigger down to lower the group number

VOKKERO® Guardian - Standard terminals (References ARF8150AA / ARF8152AA), have 4 groups from 1 to 4 (Gr1 to Gr4).

VOKKERO® Guardian - Plus terminals (References ARF8154AA / ARF8156AA), have 3 groups from 1 to 3 (Gr1 to Gr3).

Group 0 links all available groups.

Thus, the terminals in groups 1 to 4 can only hear and speak with the members of their group.

Group 0 terminals (Gr0) can hear and speak with all groups.

When you change groups, a beep in the accessory's loudspeaker signals that the terminal has taken the change of group into account.

A double beep signals that you have reached the upper or lower limit.

Check the number of the selected group on the terminal's LCD.




3.4.4. "Micro" button (Latch mode by default)

Adjust the Microphone setting using the Micro button.

The microphone can be configured in various modes using the configurator; for full information on available modes, refer to §4.3.1.

Check the microphone status on the terminal LCD:

- if there is a Struck-through micro icon, then the microphone is Off and you can be heard on the network.
- if there is no Struck-through micro icon, then the microphone is On and you cannot be heard on the network.



3.4.5. Call button

Use the Call button to send an alert to all the terminals on the network; concretely, the terminal gives off a beep for 1 second and vibrates for 4 seconds and the LED above the On/Off button blinks.

The terminal screen displays the "Call" icon, as well as the name of the terminal. All the other terminals connected to the network behave in the same way, namely, beep for 1 second, vibration for 4 seconds, LED blinking, and the calling terminal displays.

Note: if the "GROUP" function is active, then the notification is only sent to that group to which the calling terminal belongs.



3.4.6. Locking the terminal

You can lock the terminal by pressing and holding the Channel button. The locked functions are as follows:

- Channel
- Push To Talk
- Bluetooth (option)

By contrast, even if the terminal is locked, the following functions are made available:

- Volume
- Call
- On/Off

The 'Locked' status of the terminal will display on the LCD.



3.4.7. Side Tone




By default, the side tone is disabled. To activate the side tone, press and hold the centre of the volume knob.

The product then displays the side tone menu. To choose among the following options toggle the trigger:

- Side tone disabled (OFF)
- Side tone volume 1, 2 or 3

The system automatically exits the menu after a few seconds.

We do not recommend using the side tone (especially at high-level) if you use a Push-to-Talk other than the one you can set up and run on the terminal (if, for example, you use a Push-to-Talk from an accessory headset).



3.4.8. Bluetooth (Option)

The Bluetooth function is used to send and make phone calls whilst remaining on the work device. This function can also be used to connect a Bluetooth wireless headset.

You can only pair one Bluetooth device per terminal; reconnection takes place automatically on restarting the terminal.

Pairing with a mobile phone:

- Open the Bluetooth device manager on your mobile phone (if necessary, consult the user guide of your mobile phone for more information on connecting a Bluetooth-enabled device).
- As soon as your mobile phone is ready to detect new devices, press and hold the Bluetooth key of the VOKKERO Guardian terminal; the indication "Guardian Pairing" should display on the LCD screen.
- You should see a new Bluetooth device with the name of your terminal (Guardian, by default) on your mobile phone.
- Select this device to terminate pairing.



Pairing with a Bluetooth headset:

- Start the pairing mode of your headset (if necessary, consult the user guide).
- As soon as your headset is ready to detect a new device, press and hold the Bluetooth key of the VOKKERO Guardian terminal.
- Complete the pairing by following the procedure of your Bluetooth headset.

As soon as the pairing has been completed, the Bluetooth icon displays on the screen of your terminal; you can now send and receive phone calls via your terminal.

Making a phone call

To make a call from your mobile phone, you use the telephone interface (consult the User guide of your mobile phone for more information). It is not unusual to have to select "Bluetooth headset" on your mobile phone in order to switch the audio communication to the Bluetooth device.

During a phone call, the terminal's LCD screen displays a blinking icon for the duration of the call.



Receiving a phone call

Si vous recevez un appel téléphonique, le terminal vibre et un double bip est émis dans l'accessoire micro-casque.

- To answer the call, press the Bluetooth button.
- To end the call, press the Bluetooth button.




During the phone call, the terminal's LCD screen displays a blinking icon for the duration of the call.

Switching between Smart Phone/Audio Conference

You can be using the terminal as a mobile phone and switch back to an ongoing audio conference by pressing the Blue-tooth button twice.

Press the button again to return to your phone call.



EN

Ending a phone call

To end a phone call, press once on the Bluetooth button.

3.4.9. Battery

The terminal's battery can be removed and recharged on the charger.



Removing the battery

Remove the battery from the terminal by pressing the locking mechanism at the top of the terminal and then slide the battery downwards.



Inserting the battery

Slide in the battery at the back of the product; keep pushing until you hear the locking clip.

3.4.10. Belt clip

Removing the belt clip

The terminal comes with a belt clip. However, you can remove this; simply take out the battery, pull on the locking mechanism in the center of the belt clip, and then slide it downwards.

Attaching the belt clip

Slide the belt clip into the slot; keep pushing until you hear the locking clip.



NOTE : the terminal must always be positioned at the belt.


4. DESCRIPTION OF THE CONFIGURATOR

The configurator does not have an On-Off switch. To turn it on, the configurator must be connected to the power unit provided with the VOKKERO Guardian. The configurator has a USB port for updates. The configurator screen is a high-resistance touchscreen. The configurator can also be used to download products.

Immediately upon starting up the system, the configurator displays the VOKKERO logo, with the firmware version of the configurator, followed by the Home Screen.

4.1. Home Screen

The screen indicates the number of terminals that the configurator can hold (each number corresponds to one terminal). The configurator uses a color code to indicate the terminal's charging status or the battery's charging status, using the following code:



The Guardian Home Screen displays a large blue speech bubble logo with the word "Guardian" above it. Below the logo are ten numbered circles (1-10) arranged in a semi-circle. At the bottom left is a person icon, and at the bottom right is a gear icon.

-  Empty space
-  Terminal in charge
-  Terminal loaded
-  Terminal battery fault
-  Battery in charge
-  Battery loaded
-  Battery in error



If red icon, then the terminals placed on the configurator have not been correctly configured to work together;



A "WI" icon displays when you connect the WI interface on the configurator.
This system is optional.

You can rapidly configure the entire system by selecting the  icon. Alternatively, you can fine-tune the system configuration by using the settings icon. 

You can also proceed directly to the configuration of the terminal by selecting the desired terminal number.

4.2. Quick configuration

The terminals are delivered pre-configured and ready-to-use. With Quick Configuration, you can rapidly reconfigure all system devices; with this option, any devices on the configurator/charger will be automatically reconfigured in one single action, and will once again be ready-to-use.

The screen displays the channel that you have configured.


You can choose another channel from the list of channels available for your terminal; do this using the Channel setting.

This channel is the terminal start-up channel; the other channels are available using the Channel button on the terminal.

Start the configuration by selecting "GO" on the screen, and then validating the confirmation screen; the configuration starts.


If the configuration completes successfully, the indication "DONE" displays. Alternatively, the indication "ERROR" displays if a problem is encountered.

To return to the Home Screen, use the left arrow.




EN

4.3. Settings



This menu enables a more detailed configuration of the system in order to configure the terminals, the system or the configurator. In "Devices", you can change the name of your terminal as well as the operation of the "Call" button, the «Alarm» mode, set the



Voice sensitivity mode or reset your terminals to the factory configuration.

In "Systems", you can change the system language, change the radio operation of the products, activate the multi-master mode, update the terminal and the configurator's software, and change the encryption mode.

In Configurator, you can calibrate the touchscreen and lock the access to the configurator.

The details for each element are given below.

4.3.1. Configuring the terminal



This screen indicates the terminals present on the configurator. The charge status as well as the name of each terminal displays. The terminals display in their order of presence on the configurator, going from the closest (position 1) to the furthest away.

To modify a product, select the product row; this displays all the settings available for the selected product.



The available settings are as follows:

- Terminal name (1): product name displayed on the LCD
- Microphone action (2): defines the behavior of the audio button in the middle of the terminal
- Alarm mode (3): defines the operating mode of the alarm
- Voice sensitivity (4) : Provides access to the whisper mode
- Advanced Settings (5): Provides access to the following options: Assignment buttons, Alarm button, Expert mode
- Version (6)
- Factory Setting (7): allows to reset the products to factory settings

1 - Terminal name

To change the name of the terminal, you can use the available keyboard. Three screens/keyboards are available to de-fine the product name. To switch between screens/keyboards, use the button on the bottom right-hand side.


"abc" to switch to the lowercase words screen

"123" to switch to the numbers and symbols screen

"ABC" to switch to the uppercase words screen

Use  to delete the most recently entered character.

To validate, select  on the bottom right-hand side.



2 - Microphone action

The central button can have a number of operating modes:

- **Latch**: press to switch the microphone from Microphone On to Microphone Off; the microphone status displays on the terminal LCD
 - **Push to talk**: the microphone is On for as long as the button is pushed and held
 - **Latch / Push-To-Talk**: combination of Latch and Push-to-Talk functions
- A short press switches from Microphone On to Microphone Off.
 If the microphone is Off, press and hold this button to switch to Microphone On.
- **Push to mute**: The microphone is Off for as long as the button is pushed and held


Make your selection and validate.



3 - Alarm Mode

Whenever the product receives a call from another terminal or from a paired Bluetooth device, it can notify the user depending on the configured mode.
 The modes available are:

- Silent: visual notification on the screen
- Vibration: the terminal vibrates + visual notification on LCD
- Audio + Vibration: combined action: sound beep + vibration + visual notification on LCD




4 - Voice sensitivity

Normal mode is the default mode. This allows clear communication in noisy environments.

Whisper mode allows the terminal to recognize whispers and low tones.


Important note: Whisper mode only works in a quiet environment (it should not be activated in a noisy environment).



5- Advanced settings

Provides access to the following options:

- Assign buttons: to change the functions of the buttons on the terminal
- Alarm button: to change the press mode of the alarm button
- Expert mode: Users cannot access this mode as it has settings that can disrupt the smooth-running of your VOKKERO® Guardian system.




5.1 Assignment buttons

Reset the functions of the terminal buttons or disable certain functions.

The microphone On / Off + Call + Bluetooth buttons can be switched or deactivated. Click the option shown by the pictogram on the button of your choice and reassign the chosen function to it.

The Channel and Volume Selector triggers can only be turned on or off.

To reset the original functions, reload the terminal's default settings via the «Factory Setup» menu.




5.2 Alarm button

Allows you to change the way you press the «Call» button to activate the alarm, regardless of the selected alarm mode (silencer, vibrator or sound + vibrator).

The possible ways of activating the alarm are:

- **Short:** 1 short press on the Call button triggers the alarm
- **Long:** 1 long press on the Call button triggers the alarm
- **Long + Acknowledgment:** 1 long press on the Call button triggers a loop alarm. To stop the alarm, press again continuously on the same button from one of the network terminals.



6 - Version



Shows you the factory version of the terminal used.



7 - Factory settings

This menu returns, to the factory setting, a product or all products connected to the configurator. After selecting and validating your choice, the configurator lets you know if the return to factory settings completed successfully.

To finalize the operation, select the arrow on the bottom left-hand side to return to the configuration screen of the terminals.





4.3.2. System configuration

In this screen you can see all the settings related to the system configuration. The settings in this menu apply to all the terminals present on the configurator.

The available settings are:

- Channel Tables: Allows you to select the product's operating channel table
- Group Mode: Enables or disables group mode
- Encryption: allows you to choose the encryption operating-mode
- Multi-master: allows you to maintain communication with the terminals out of reach of the Master M1
- Language: allows you to select the display language of the configurator
- Software: allows you to update the software version of the terminals and configurator

The settings are displayed over several pages. To browse the pages, select the left and right arrows at the bottom of the screen.



1 - Channel tables

Use this setting to select a predefined table of channels so as to be able to use the terminal in a given geographic area. By default, the terminals are configured without any channel restrictions; this means that all the channels can be used while making sure to correctly respect the use case of each country in which the product is used. Use this setting to select a predefined table of channels so as to be able to use the system in different area/context.

6 channel tables are available: H1, A1, H2, A2, H3, A3.

By default, standard channel tables are H1 and A1. You can activate access to others with the System menu.

2 - Group mode

Use this setting to activate and deactivate the Group mode.



If activated, the terminal works in Group mode; use the Channel button (front of terminal) to switch between groups.

When first used, all the products are configured in the same group (group 0). After first use, a group must be selected individually on each terminal; this choice will be retained.

Details of groups:

Group 0 (Gr0): you can hear and talk with all groups.

Group 1 to 4 (Gr1 to Gr4)



3 - Encryption

The encryption key is used to make communications within a given system secure. Only the devices using the same encryption key are authorized to communicate on the network.

Several options are available:

- **No encryption:** the communications are not secure; all the Guardian devices can join the network, even if they have no encryption key.
- **Single key:** the system uses one single encryption key; this key can be occasionally changed by the user by selecting "New Key"
- **New Key with each configuration:** the configurator generates a new key with each new successfully performed con-figuration.

EN

4 - Multi-master

In standard configuration mode, communication is established only between terminals within range of role #1. In addition, only terminals within range of each other can communicate with each other.

The multi-master option allows terminals whose role is between 1 and 8 to extend the network. As in standard configuration, the terminals must remain within range of each other.

Important note: each time a new terminal is added you must reconfigure all the terminals. When configuring only the «New key at each conf» option is available (System>Encryption).

5 - Language

You can change the system's display language by means of the "Language" setting. Choose the language you want and validate with  on the bottom right-hand side.

6 - Updating software

Used to update the software versions of the terminals and / or the configurator.

6.1 - Updating terminals

To update terminals you have to use a USB key.
Contact your vendor to obtain the most recent software version.

The USB key used must be < or = 4Go.

On the USB key:

- Copy the update software to the root
- The files mustn't be in a folder
- No others files or folder have to be on the USB key


To know the version currently installed in the terminal:

Menu > System > Software > Device update:

The version currently installed in the terminal appear on the display. (Screen No. 1).

To configure a new software version on the terminals:

- Once the USB key ready, insert it into the dedicated USB port, situated on the left located on the left side of the configurator. (Screen No. 2)
 - Once the USB key connected, the available software version is displayed. (Screen No. 3)
- (If the USB key is empty or involves wrongs files, you will read on the display: «Update file missing from the USB key»)
- Click «GO» to validate. (Screen No. 3)
 - Then, click  to launch the installation. (Screen No. 4)



- The update of the terminals is launched (Screen No. 5).
- The update is finished (Screen No. 6).

Note: All terminals on the Configurator will be updated regardless of their location on the Configurator.

6.2 - Updating the configurator

To update the configurator you have to use a USB key.
Contact your vendor to obtain the most recent software version.


The USB key used must be < or = 4Go.

On the USB key:

- Copy the update software to the root
- The files mustn't be in a folder
- No others files or folder have to be on the USB key

To know the version currently installed in the configurator:

EN



Menu > Configurator > Software update:

The version currently installed in the configurator appear on the display.
(Screen No. 1).

To configure a new software version on the configurator:

- Once the USB key ready, insert it into the dedicated USB port, situated on the left located on the left side of the configurator. (Screen No. 2)
- Once the USB key connected, the available software version is displayed. (Screen No. 3)
- (If the USB key is empty or involves wrongs files, you will read on the display: «Update file missing from the USB key»)
- Click «GO» to validate. (Screen No. 3)
- Then, click ✓ to launch the installation. (Screen No. 4)

• The update of the configurator is launched (Screen No. 5).


• The update is finished (Screen No. 6).

4.3.3. **Configuring the configurator**

Use this setting to adjust the screen.
In this area, you can adjust the screen lighting, calibrate the touchscreen, and lock the configurator.

1 - Adjusting the screen lighting





Slide the cursor from left and right to decrease and increase, respectively, screen lighting.



2 - Calibrating the touchscreen

The configurator touchscreen is already calibrated in the factory; you can however calibrate your own touchscreen if you note a significant change in screen detection.

To do this, carry out the following 5 steps:
Select each angle with the yellow pointer, then select the circle at the middle of the screen.
The calibration is complete.




3 - Locking

Allows you to block access to the configurator using a PIN code.
In Lock mode, only the «Quick Config” option is available. You can only access the other settings after validating the PIN code.

Note: The PIN code consists of 1 to 6 digits

Once the lock has been activated, the PIN code can be modified or deactivated (see screen below showing the options available in the «Lock» menu, once the lock has been activated).



4.4. Resetting the configurator functions

In order to put the configurator back in factory mode (and thus cancel all the configuration changes made previously), do the following:

- 1. Unplug the configurator
- 2. Reconnect the configurator
- 3. When the configurator is switched on, on the first home screen, consisting of the «VOKKERO®» logo: press the 2nd «O” of VOKKERO®.
- 4. Then you can restore the default settings of the configurato
- 5. Confirm
- 6. The configurator parameters have been reset.

DOCUMENT HISTORY

Version	Contents
V1.0.0	Creation

