

It is recommended that the unit be charged overnight before the first extended use. The power supply charging jack is located on left side of the Footswitch.

The Unit has 4 push button footswitches and 2 LED indicators, **TX low Battery LED** and **Battery Charge LED**. Both LED indicators are located on the top left hand side of the Foot Switch unit.

The TX Low Battery indicator has dual functions.

- A. When any footswitch is depressed the TX light will flash to indicate a valid transmission has been sent.
- B. When the Battery is low and needs to be recharged, it will flash slowly.

The battery charge LED lights when the charger is plugged in during recharging.

Remove the Foot Switch and install the antenna on the rear of the unit

as shown by screwing clockwise only until snug. Be careful not to over tighten the antenna as damage to your Foot Switch may result.

Receiver: WR4

Operating Frequency:	315MHz
Memory Capacity:	15 transmitter button codes per channel, 60 per receiver.
Operating Voltage:	12VDC Adapter
Operating Current:	35 mA @ 12VDC (standby), 25mA/channel @ 12VDC (activated)
Relay Contact Rating:	Form C type; 10A @ 24VDC or 120VAC per channel
Connectors:	RCA connector with N.O., N.C., and COM per channel
Dimensions:	5.3 x 3.9 x 1.1 inch (135 x 100 x 27.5 mm)

Transmitter: FRT4PRO

Operation Frequency	315MHz
Transmitter switch button	4 Transmitter switch buttons
Operating Voltage	9 VDC Rechargeable battery
Code Combination	Fix code, 68 billion
Operating current	10mA (active)
Dimensions	12.5 x 4.75 x 2 inch (318 x 121 x 50 mm)

Notice : The changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

IMPORTANT NOTE: To comply with the FCC RF exposure compliance requirements, no change to the antenna or the device is permitted. Any change to the antenna or the device could result in the device exceeding the RF exposure requirements and void user's authority to operate the device.

Installation Manual SKY WYRE



FRT4PRO / WR4 Four-Channel RF Transmitter and Receiver

- Operates on 12 VDC Adapter For WR4 Receiver
9 VDC Rechargeable battery for FRT4PRO Transmitter.
- Up to 500 ft. range

Introduction

The FRT4PRO / WR4 is a four-channel transmitter and receiver which meets the growing demand for a multi-channel receiver with multiple and independently controlled output modes. The receiver can be used to control a variety of home automation devices, such as garage door openers, lights, motorized gates, lifts, or other devices, by remote control

Installation Notes

1. Mount out of sight in a location where it is not surrounded by metal, and where it is not exposed to the weather or to moisture. Metal will block the RF signal, resulting in a reduced range.
2. For best range, pull the antenna as straight as possible. If the receiver receives interference from local RF activity (e.g., an airport or military base), the antenna can be rotated to other direction.

Code Learning a New Transmitter Button

Each receiver channel can learn the codes of up to 15 different transmitter buttons on a first-in, first-out basis. Below is the procedure for code learning a new transmitter button. The same procedure applies to all the receiver's four channels.

1. Press the mode switch of the desired channel to be programmed for 3 seconds or more. The channel's red LED will start to flash quickly to indicate that it is in the learning mode.
2. While the red LED is quickly flashing, press the button of the transmitter to be learned once. The red LED will flash once to indicate a successful learning of that button's code.

NOTE: a) The mode switches can be found at the rear of the receiver's case. The switch marked #1 represents the mode switch for channel 1, switch #2 is the mode switch for channel 2, and so on.

b) The channel's red LED will flash a maximum of 15 seconds. If no transmitter button is pressed during this time, the receiver will exit the code-learning mode, and the red LED will turn off.

c) If the code being learned has already been learned, the red LED for the channel which learned the code will turn steady ON, and the code will not be learned a second time.

d) Each channel can learn the codes of a maximum of 15 transmitter buttons. If you attempt to learn a sixteenth button, the earliest code learned will be deleted.

Channel Memory Clear

To clear all codes in the channel's memory, enter the channel learning mode first, then press the channel mode switch for 3 or more seconds again. The LED flashes twice to indicate that all codes associated with that channel are now deleted.

Channel Memory Display

To see how many codes have been learned in a channel, press that channel's mode switch once. The number of codes stored in the channel's memory is equal to the number of LED flashes.

Programming Each Channel Relay Output Mode

Each receiver's channel can be programmed for one of four different modes, and each individual channel may operate at a different output mode, depending on the user's application. Applications are as follows:

- **Timed Output** — Press the transmitter button once. The timed output relay will activate 1 second.
- **Toggle Output** — Works much like a toggle switch to turn a device ON & OFF alternately. Press the transmitter button once, and the relay turns on. Press a compatible transmitter button again, and the relay turns off (factory pre-set).
- **Latch Output** — Press the transmitter button once, and the relay turns on and stays on. The relay will remain on until the appropriate channel mode switch is pressed once to reset, regardless of whether a compatible transmitter button is pressed again or not.
- **Validity Output** — The channel will turn the relay ON for as long as the transmitter button is pressed.

Note: Care must be taken when using validity output. Due to possible interference or drops in transmitter battery power while the transmitter button is continuously pressed (even for short periods of time), the receiver may lose the transmitter's signal and turn the relay off.

To program each channel output mode, press the programming mode switch once (switch #5). Each channel's red LED will flash a number of times equal to the output mode that it is in. Below are the channel output LED flash indicators:

- | | |
|---------------------------------|------------------------------------|
| 1.) One flash — Timed Output | 3.) Three flashes — Latch Output |
| 2.) Two flashes — Toggle Output | 4.) Four flashes — Validity Output |

Press the mode switch of the desired channel to be programmed a number of times until the required output is achieved. The programming procedure for all four channels is the same.

To exit programming, press programming mode switch again.

Programming each channel Relay N.O. or N.C. output by the relay output programming switch (pre-set N.O. output).

Channel Mode Switch Operation (one per channel)


- **Learn mode** — Press and hold the switch for three seconds or more.
- **Clear memory** — Press and hold the switch for three seconds or more, then when the LED starts flashing, press again for three seconds to delete all previously learned codes.
- **Reset latched output** — If this channel was programmed for latch output, once the relay is turned on with a transmitter button, press the mode switch of that channel once to turn the relay OFF.
- **Memory Display** — Press and release the mode switch to show the number of codes stored. The LED will flash a number of times corresponding to the number of codes stored.

LED Indication (one per channel)


- **Steady ON** — Senses signal from a transmitter button or indicates a transmitter button's code already exists in the receiver's memory during code learning.
- **Fast flash** — In the code-learning mode or channel memory display mode, or during the programming channel output mode.
- **One flash** — A transmitter button's code was learned, or the relay is in time output mode.
- **Two flashes** — All previously learned transmitter button codes were deleted, or the relay is in toggle output mode.
- **Three flashes** — Latched output.
- **Four flashes** — Validity output.
- **0~15 flashes** — In the normal operation mode, pressing the channel mode switch (1~4) once will display the number of codes learned.
- **Power ON Red Led.**
- **Relay output indicator Led.**
Red Led for channel 1, Blue Led for channel 2,
Green Led for channel 3, Yellow Led for channel 4.

Typical Applications:


Positive Output:




Negative Output:




24VAC output driving a motor:



To driving 24VDC motor:



12VDC power input, 12VDC positive output: Typical N.C. application (access control).



12VDC power input, 12VDC positive output:

