



Kydera[®]



Thank you for your interest in our products. This manual will help you to master the operation and use of the CDR-300UV. This manual should be read and studied to ensure that the user understands the operation of the CDR-300UV. Please read the Safety Information Manual before use.

This manual applies to the model,
CDR-300UV series digital mobile radio.

DISCLAIMER

We strive for the accuracy and completeness of this manual, but no warranty is given on its content. All the specifications and designs are subject to change without prior notice due to continuous technology development. No part of this manual may be copied, modified, translated or distributed in any form without our prior written authorization.

The third-party products referred to in this manual are property of those third parties. We do not guarantee their accuracy, validity, timeliness, legality or completeness.

USER INSTRUCTIONS

- Explosive environments (gas, dust and smoke, etc)

Please turn off the radio while refueling or parking in the gas station. If your radio is installed in the car's rear luggage compartment, please don't put the spare fuels in the trunk.

- Radio signal transmission damage

Please do not operate your radio when you are located near the antenna in order to avoid the radio frequencies that may cause damage or related physical damage

- Gunpowder, Detonators / Exploders

For 150 meter (500 feet) of the detonators can lead to explosion. Please turn off your radio within the blasting or bidirectional area. If you want to full the gunpowder, please make sure it is installed in the black sealed metal box with the internal padding. Do not transmit the signals when the exploders are placed in or out the box.

NOTE:

Please observe the following precautions to prevent the occurrence of fire, physical injury or damage to the radio.

- Please do not try to set the radio while driving otherwise it will lead to dangerous consequences.
- Please do not transmit the radio at high power output for a long time otherwise it may overheat.
- Please do not disassemble or refit the radio for no any reason except which is written in the manual or instruction.
- Please do not put the radio directly to sunlight for a long time and do not put it near the heating apparatus
- Please do not put the radio on the extreme, moisture and water splashing places or unstable surfaces.
- If you find unusual smell or smoke from the radio, you should immediately turn off the radio and contact with the local repair store or distributor.
- Please check and follow the local traffic regulations before using the radio.
- Please do not use other optional accessories instead of our company'S accessories.
- Please use DC 13.8V (15%) power supply ! Do not use 24V battery power to operate the radio. Please check the battery polarity and voltage on the car before installing the radio on the car.
- Please use the DC power cable or purchase a DC power supply.
- Please do not insert metal objects into cooling fans.

- Please do not cut off or remove the fuse holder on the DC line. Error/wrong connection and/or surge current may cause fire.
- In order to protect your safety, please use the solid mounting bracket and screw sets to install the radio to prevent the slips when the car is in collision condition.
- When transmitting the radio, the unprotected of the radio frequency energy to various electronic devices may cause damages to them, such as electronic fuel injector, skid brakes and navigation control systems. If your car is equipped with these devices, please consult with the car dealers and make sure if these devices need to be protected while the radio is transmitting.

HOW TO USE THIS USER MANUAL

This manual introduces the basic operation of DMR / Analog handheld transceiver.

Your dealer or system administrator may have already preset the features of this radio based on your operational requirements. Please consult with your dealer or system administrator about the details.

The icons below are used for distinguishing between analog and digital features.



This icon indicates the function is only available in Analog mode.



This icon indicates the function is only available in Digital mode.

Notes:

When programming the radio, be sure to read out the original factory data first before changing desired relevant frequency, settings and other parameter values, otherwise it may result in incorrect set parameter values due to unmatched model or frequency band and other reasons.

CONTENTS

Packing list.....	5
Preparation for operating the radio	6
Radio installation.....	6
Connecting cable power.....	6
Radio operation.....	6
Base station operation.....	7
Replace fuse.....	8
Antenna connection.....	8
Accessories connection.....	8
Speaker Microphone or headset + MIC.....	8
Microphone.....	9
Keypad operations.....	9
Radio Controls.....	10
Parts description & function applications.....	10
TFT Status Icons.....	13
LED indicators.....	15
Programmable Function keys.....	15
Keypads & ENC (Channel Selector) Operation..	16
Main functions description.....	17
Operations for Speaker microphone keypad.....	19

CONTENTS

Transmit / Receive Icons.....	19
Basic operations.....	19
Power On/Off the radio.....	19
Operating Frequency Band Selection.....	19
Volume Adjustment.....	19
Squelch.....	19
Busy Channel Lockout.....	19
NarrowBand.....	20
CTCSS / DCS.....	20
Channel Selection.....	20
Switch between VFO and Channel Mode.....	20
VFO Frequency Set.....	20
Zone / Channel Selection.....	20
Monitor.....	21
Permanent monitoring.....	21
Repeater / Talk Around.....	21
Emergency Alarm.....	21
Scan On/Off.....	22
Roaming On / Off.....	22
Main menu contains item index.....	22

CONTENTS

Menu accessing and operations.....	23
PTT Call.....	23
High / low power.....	24
Select the transmitting band.....	24
Receive and Answer to a radio call.....	24
Initiate a call.....	25
Initiate and receive calls in analog mode.....	25
Advanced functions for DMR.....	25
Menu functions operations.....	26
Contacts.....	26
Message.....	29
Call Log.....	32
Scan.....	33
Zones & Channel.....	38
Local Set.....	38
Parameters.....	40
Tone Set.....	43
Appendix.....	45
Record.....	48
Device Info	48

CONTENTS

User_defined Mode.....	49
Function Applications.....	51
Maintenance and Clean.....	51
General guide for fault handling.....	52
Standard accessories.....	54

Packing list

The following items are contained in the gift box. If any item is missing or damaged, please contact your dealer.

Item Name	Quantity (pc)	Item Name	Quantity (pc)
Radio unit	1	Speaker microphone	1
Mounting bracket	1	Mounting screw sets	1
DC cable (with 20A fuse)	1	User manual	1
GPS antenna	1		

 Note:

After purchase, please check the items and quantity in the box to ensure everything is correct.

Preparation for operating the radio


Radio installation

For sake of your own and passengers safeties, please find a safe and convenient position in order to prevent the damage caused by moving car. - You can consider installing the radio in front of the front passenger seat below the panel section or the car trunk. This will prevent your knees and legs crashing the radio in emergency brake. You should install it with good ventilation and avoiding the direct sunlight.

1. Install the mounting bracket to the car with using the self tapping screws and flat washers (2 pcs screws each kind).


- Screws can be put upside down (under the dashboard mounting) or upwards the mounting bracket.

- When installing the mounting bracket, please make sure the screw side edge with slots on the bracket are backwards.




2. Fixed the radio and then insert the equipped with six angles combination screw and flat washers (each equipped with 2 sides and each side of 1 screw set) and tighten them.

- Please make sure all the screws are tightened to prevent the stent and radio losing caused by car vibration.



- With the rotatable fixed point on the left and right sides of the vehicle rear bracket, the rotating bracket can tilt the main body at an appropriate angle.



Connecting Cable Power

■ Radio Operation


Make sure to use 12V car batteries. If the radio's power is not enough during transmitting the screen will grow dark and the output power may be significantly decreased. Please do not connect the radio to the 24V power battery.

Note: If the battery is not fully charged or when the engine is switched off but the battery is still not fully charged, the battery may discharge and there will not be enough power to start the car. In this case, please avoid using the radio in following situation:

1. Use the radio with the DC power cord to directly connect to the car battery and radio within shortest area.

- If you use a noise filter, the metal parts of the car shall be fitted with an insulator to prevent it from touching the car.

- We do not recommend you to use the cigarette lighter socket because some of the cigarette lighter socket will cause big substantial voltage.
 - If you have to connect the power cord through a car chassis or a hole on the car (such as a firewall in front of the passenger compartment), please use the rubber ring to prevent the power cord and remove the fuse holder to pass the power cord through the firewall.
 - The entire power cord must be wrapped in order to keep the heat insulated and insulation from the engine (high pressure) system.
2. After the power cord is already installed, wrap around the fuse holder to make it moisture-proof, including the whole power cord.
 3. Please cut off all wire connections on the negative battery terminal before connecting the radio to prevent the short circuit.
 4. To confirm the connection is correct then connect the power cord to the power supply; red connection to the positive (+) , black connection to the negative(-)
 - To use the whole power line, please do not cut off excessive parts of power line even if it is longer than desired length. Remember, do not remove the fuse holder from the power cord.
 5. Reconnect all wiring connections that were previously disconnected on the negative terminal.
 6. Connect the DC power supply to radio.
 - Connect the plug into the socket until you hear a click sound.




■ Base Station Operation

To use it as a base station, you need a separate 13.8V DC power supply. This power supply is recommended for current capacity above 12A.

Note: Do not connect the DC power to the AC power socket before completing all connections.

1. Make sure that both radios and DC power are off.
2. Connect the DC power supply to the regulated DC power supply and make sure that the polarity is correct. (Red: positive, black: negative).
- Use the DC power cord to connect the radio to the regulated power supply. Don't connect the radio directly to the AC power socket.
- Do not use the smaller size of the power cord to make a replacement.
3. Connect the DC power cord to the radio.
- Connect and press the socket together until you hear a click sound.



Replace fuse

If the fuse is blown, please find out the cause and then solve the problem. After the problem is fixed then replace the fuse. But if after re-installation the fuse is still blown, please disconnect the power cord and contact the local authorized dealer or authorized service center for assistance.

Fuse position	Fuse rated current
Radio (in DC connector)	10A
Equipped with DC power cord	10A

Note: Please use only the specified type and the rated value of the fuse; otherwise it might damage the radio.


Antenna connection

Before operation, you must first install and adjust well the antenna. Success installation depends mainly on the antenna type and a correct installation. The radio will have best

performance if the appropriate antenna is properly installed. A low loss coaxial feeder line with 50Ω impedance is used to match the input impedance of the radio. If the transmission impedance of the feeder line is less than 50Ω the antenna connection will reduce the effectiveness of the antenna system, and will cause interference to the nearby radio and television receivers, radio receivers and other electronic devices, and even damage the radio.

Note:


- If transmitting without an antenna or other matched load line, it could damage the radio. The antenna must connect to the radio before transmitting
- All base stations should be equipped with lightning arrester to reduce the risk of fire, electric shock or radio damage.



Accessories connection

■ Speaker Microphone or headset + MIC


1. Please insert a select a speaker with 8Ω impedance or a suitable headset. External speaker socket can be connected with 2.5MM mono plug and 3.5MM MIC plug.



The left side of the walkie-talkie has two jacks for SP and MIC. Please refer to the instructions to determine how to use an external speaker or headset + MIC accessory.

■ Microphone

Please insert the provided speaker microphone (with built-in speaker) to the RJ45 jack on left side of the radio to make voice communication. Press the connector until you hear a click sound from the locating plate in place.




■ Keypad operations

Please follow the key operation described below to simplify the instructions and avoid unnecessary duplication.

Instruction	Operation
Press [XXX] button	Short press the button and release it quickly.
Press and hold [XXX] button	Long press and hold down the button for 3 seconds or more
Press [MENU] tuning knob (button 1)+ [XXX] button 2	Short press the [Menu] tuning knob button (button 1), and release it; then press button 2 and release it to enter into function menu.
Rotate [MENU] tuning knob	Select set options
Press and hold power switch	Press and hold the power switch for more than 3s to turn on/off the radio.

Radio Controls



Parts description & function applications

NO.	Part Name	Function description and applications
①	[] Power Switch	Press and hold it for more than 3s to turn on/off the radio.
②	P1	Programmable function key 1
③	P2	Programmable function key 2
④	P3	Programmable function key 3
⑤	[VOL / SQL] key Note: SQL is for analog mode only	1) Short press to set the volume of the band with "  " icon; 2) In analog mode, long press to set the squelch level of the band with "  " icon.
⑥	[TONE/T.SEL] key	1) In analog mode, short press and rotate it to select the signaling type of the band with "  " icon; 2) After selecting the signaling type, long press it to change the signaling code / frequency. The TX/RX signaling code/frequency can be set.


NO.	Part Name	Function description and applications
⑦	[B/E] key	1) In Standby, short press to switch between band A/B. The band with "➡" icon is the main band for transmitting or menu set. 2) For operating the band with "➡" icon, in menu mode, short press to return to the previous level, and long press to exit menu mode. 3) In Standby, long press to enter the User-defined mode of the main band with "➡" icon.
⑧	LED indicator	Used to indicate the RX/TX status, etc.
⑨	Speaker	Used to receive audio from others
⑩	TFT display	Display various working states, and combine with visual icons for easy use and operation;
⑪	RJ45 (MIC) and PC connection port	1) Connect the original speaker microphone to this port 2) Connect the programming cable here to get connection with the PC for data programming.
⑫	[Menu] key [OK] key [Select] Key	1). In standby, short press to access the menu of the main band with "➡" icon; 2). In the current menu mode, short press to be [Menu] key or [OK] key for parameter selection and confirmation.
⑬	ENC selection knob	In standby, rotate the knob to operate and set frequency, channel, menu selection and parameters etc. of main band with "➡" icon.
⑭	SP/MIC jacket	For external accessories connection, such as earpiece
⑮	Mounting bracket	For fixing the radio at some place.
⑯	Antenna port	Install the external antenna to this port. In TX testing, please install a dummy load to replace the antenna. The antenna or dummy load should be with 50* impedance.
⑰	Heat Sink	Cool the internal power tube to avoid too high temperature to damage the related components

NO.	Part Name	Function description and applications
⑱	GPS antenna port	Install the GPS antenna to this port for GPS receiving.
⑲	Rack mounting screws	Release the left and right screws to adjust a proper fuselage angle and then re-fasten.
㉔	External power plug	Carefully check the polarity (Red: +, Black: -) and power ratings (DC13.8V / 15%) of the power supply before connecting to the radio.
㉕	Speaker microphone	Used to receive audio from others (Audio output options can be set from the menu option)
㉖	[PTT] key	Press and then speak in to the microphone to transmit; Release it to receive.
㉗	Numeric Keypad	Used to input frequency / channel number, alias, ID and SMS
㉘	MIC	Speak to the microphone when pressing the PTT key to transmit; (3-5CM from the mouth)
㉙	LED indicator of the speaker microphone	In transmitting, LED lights red; if operating on speaker microphone keypad, LED light will be always on.
㉚	MIC P1	Programmable function key 1 of speaker microphone
㉛	MIC P2	Programmable function key 2 of speaker microphone
㉜	MIC P3	Programmable function key 3 of speaker microphone
㉝	MIC P4	Programmable function key 4 of speaker microphone

 Note:

For convenient use, there are programmable [P] keys for definition.

TFT Statu Icons



Icom	Icon description	Applications and function description
	High Power	6 red bars indicate high power
	Low Power	3 red bars indicate low power
	Standby	White bars indicates the radio being in standby mode
	RSSI	In RX mode, the more green bars, the stronger signal
	Keylock	Appears when the keypad is locked
	Monitor	Appears when monitor is on
	VOX	Appears when VOX is on
	GPS	Appears when GPS is on
	Scan	Appears when SCAN is on
	Emergency Mode	Appears when the radio is in emergency mode.
	Encryption	Appears when Encryption is on
QT	CTCSS	In analog mode, appears when CTCSS is on

Icon	Icon description	Applications and function description
DQI	CDCSS	In analog mode, appears when Reverse DCS is on
DQT	CDCSS	In analog mode, appears when Normal DCS is on
	Prompt Tone on	Appears when profile is in standard mode
	Prompt Tone Off	Appears when profile is in silent mode
I-I	Talk Around	Appears when the radio is in Talk Around Mode
	Roaming	Appears when Roaming is on
	Roaming Lock	For locking current channel in Roaming
	Offset Frequency Negative direction	Appears when RX frequency is higher than TX frequency
	Offset Frequency Positive direction	Appears when TX frequency is higher than RX frequency
DN	Digital Mode	Indicates the current band working in digital mode
FM	Analog Mode	Indicates the current band working in analog mode
DN	Digital/Analog Mode	The current band is in digital/analog auto RX mode. Digital Mode is for main TX
DN	Analog/Digital Mode	The current band is in analog/digital auto RX mode. Analog Mode is for main TX
	Operating Main Band	The band with this icon indicates that the current band can make a call or is operable and settable
	Time Slot 1	Indicates the working slot of current frequency or channel
	Time Slot 2	Indicates the working slot of current frequency or channel
	Zone	Indicates the working zone of current frequency or channel
VFO	Frequency Mode	Indicates working in frequency mode, can input frequency directly via numeric keypad
	SMS	Appears when received a new message.

LED Indicators

LED indicator	Radio Status
● Green	In receiving
● Red	In transmitting
● Fast Flashing Green	In scanning

Programmable Function keys

If desired, the following terminal features can be preset for programmable keys:

Type	Features	Description
	Radio Revive	Revive a target radio that has been remotely disabled
	Radio Detection	Determine if targeted radio is active
	Radio Kill	Disable targeted radio remotely
	Remote Monitor	Covert activation of targeted radios transmitter without local indicators.
	Encryption On/Off	Turn on/off encryption
	Emergency On/Off	Initiate an emergency alarm mode or call based on programmed preset.
	Record On/Off	Turn on/Off audio Record
	Contacts	Direct access to the contact list
	A/B Repeat Sw	Turn On/Off A/B band Repeat mode
	A/B Monitor Sw	Turn On/Off the speaker audio in the A/B band Repeat Mode
	Zone Switch	Changes from selected Zone to new Zone

Type	Features	Description
	Permanent Monitor	Always monitor the selected channel until disabled.
	Scan On/Off	Turn scanning on/off
	VOX On/Off	Switch between VOX On and Off.
	Backlight On/Off	Turn backlight On/Off
	Keypad Lock	Switch between keypad lock and unlock.
	High /Low Power	Switch transmit power between high and low power
	Man Down On/Off	Switch between Man Down alarm On and Off (Optional)
	Scan Mode	Select the desired scan mode (switch between SE, TO, CO mode)
	Repeat / Talk Around Selection	Switch between the Repeat and Talk Around Mode
	SMS	Direct access to SMS list
	Monitor	Turn On/Off the radio RX squelch circuit. Receive weak analog signals
	DTMF On/Off	Turn On/Off DTMF
	Squelch Level Adjustment	Select a suitable SQ level for opening the noise suppression circuit of the receiving audio circuit (applicable to products without display)

Note:

© Short Press: press and release quickly (programmable range is from 50ms-750ms).

© Long Press: press and hold for programmed time length (programmable range is from 500ms-5000ms).

Keys & ENC (Channel Selector) operation

The following keys can be used to quickly achieve the desired function.

Keypad	Status	Operation	Description
[ENC]	Standby	Short Press	Access to the Menu
		Long Press	[Keylock] or [Unlock]
	In Menu Mode	Long Press	[Confirm] or [Menu]
	Standby	Rotate	Select channel, frequency and other parameters
	In Menu Mode		Select Menu and other setting parameters
	User-defined Mode		Select programming items or other parameters;
	Edit (SMS)		Move the editing position of the blink cursor to the left or right
[⏻]	Standby	Long Press (3S)	Power On /Off
[P1]	Standby	Short Press	Preset function based on customization
		Long Press (3S)	Preset function based on customization
[P2]	Standby	Short Press	Preset function based on customization
		Long Press (3S)	Preset function based on customization
[P3]	Standby	Short Press	Preset function based on customization
		Long Press (3S)	Preset function based on customization

Keypad	Status	Operation	Description
[VOL /SQL]	Standby	Short Press	For adjusting the output volume
		Long Press (3S)	In analog mode, adjust the squelch level
[TONE /T.SEL]	Standby	Short Press	In analog mode, choose signaling type
		Long Press (3S)	To select signaling code / frequency after selecting the signaling type, and short press to choose signaling code / frequency for RX / TX
[B/E]	Standby	Short Press	Select the operated Band A/B to make a call or menu operation
		Long Press (3S)	Operations for Channel/ VFO user-defined mode and storage and other parameters
	Menu Mode	Short Press	Back to the previous level
MIC [P1]	Standby	Short Press	Preset function based on customization
		Long Press (3S)	Preset function based on customization
MIC [P2]	Standby	Short Press	Preset function based on customization
		Long Press (3S)	Preset function based on customization
MIC [P3]	Standby	Short Press	Preset function based on customization
		Long Press (3S)	Preset function based on customization
MIC [P4]	Standby	Short Press	Preset function based on customization
		Long Press (3S)	Preset function based on customization

Main functions description

Classification	Function	Description
Public Functions	Zone	A zone is a group of channels. Support end users to build and expand zones by themselves.
	VFO Mode	In VFO mode, the user can directly input the required frequency through the numeric keyboard
	Channel	Support end users to build and expand channels by themselves, up to 4000 channels, 16 zones.
	Power	The power level is for the transmission power level of the current channel, which can be set to high or low power.
	Emergent alarm	Emergency alarm has the highest priority.
	Scan	When the terminal scans a signal on a channel, it will stay on the channel to listen, so as to understand the current activity status of the relevant team members.
	VOX	If VOX is on, when the voice is detected to reach the transmission condition by the microphone, it will be transmitted automatically. The user can Initiate a call without pressing the [PTT] key.
	Busy channel lockout	Busy channel lockout prohibits transmission and prevents interference to other users when the radio is receiving traffic.

Classification	Function	Description
Public Functions	TOT	When a transmission times out, the terminal will automatically terminate the transmission and issue a warning sound. The user can Initiate a call without pressing the[PTT]key.
	Keyboard lock	Keyboard lock is used to lock keys to prevent inadvertent key operation. The radio may be set to automatic or manual lock mode.
Digital Functions	Private call	Private call is a one-to-one call.
	Group call	Group call is a one-to-many call.
	All call	All call is a call to all contacts on the current digital channel.
	Talk around	When the repeater fails to work or the radio exceeds the coverage of the repeater, it can communicate off-line (RX & TX at the same frequency) to communicate
	Roaming Setting	Roam Mode, RSSI Set, Connect Check Timer, Connect Re Check Timer, Connect Timer
	Roaming	When the radio moves from one site to another, it will automatically find the next available site through roaming.
	Recording	Can record any receive or transmit audio, or receive + transmit audio of the radio
	DTMF RX / TX reminder	Used as the TX PTT prompt tone and RX prompt tone before receiving the voice.

Classification	Function	Description
Digital functions	TDMA direct mode	TDMA direct mode is used to divide a direct channel (simplex) into two time slots to allow efficient channel usage. Multiple parties may share the channel without interference depending on slot setting.
Analog functions	Analog channel call	An analog call is a call on an analog channel.
	Band	Working band for the radio (12.5KHz)
	Squelch Level	It is the signal strength required to adjust the received signal. Normally the higher squelch level, the higher received signal strength is required. Settable squelch level is from 0 ~ 9. Level 0 is normally open, and there is background sound from the speaker once the radio is on. Level 9 is the highest and the required received signal strength is the strongest.
	Busy Channel Lockout	If it is ON, when received the carrier signal, it is prohibited to transmitting when pressing the PTT button.
	Monitor	Monitor allows the user to open the receiver squelch manually to listen to on-channel signals.
	CTCSS	CTCSS code for RX radio must be same as TX radio, so that the audio can be received successfully
	DCS	DCS code for RX radio must be same as TX radio, so that the audio can be received successfully

Operations for Speaker microphone keypad

The numeric keypad of the speaker microphone can be used to access the radio functions. It can be used to input frequency/channel number, user alias or ID or SMS. Many characters require pressing a key for several times

Keystrokes

Keypad	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	Note
	,	o	?	!	:	;	\	"	"	"	'	(	)	«	»																"PY" input mode
	.	'	? !	-	()	@ /	:	—	;	+	&	%	*	=	<	>	\$	[	]	{	}	~	^	'	#	!					"AB" / "ab" input mode
	A B C																														
	D E F																														
	G H I																														
	J K L																														
	M N O																														
	P Q R S																														
	T U V																														
	W X Y Z																														
	Note: in the digital editing mode, a short press of this key enters the value of "0", while long press enters the symbol "+" in the digital, English and Chinese editing mode.																														
	Note: in the digital, English and Chinese editing mode, a short press of this key enters the "" symbol, and a long press enters a "space".																														
	Note: in the editing mode of Numbers, English and Chinese, a short press of this key inputs the symbol "#", while a long press switches between the editing input mode of English, Numbers, Chinese (pinyin) (" AB "in upper case," ab" in lower case," 12 "in figure," PY "in Chinese pinyin)																														

Transmit / Receiving Icons

The following icon appears on the radio screen to indicate the radio status.

Mode	Type	ICON	Terminal product status
	Private call		Sending a private call
			Receiving an private call
	Group Call		Sending a group call
			Receiving an group call
	All Call		Sending an All Call
			Receiving an All Call
	—		Sending an analog transmission
			Receiving an analog transmission

Note:

In the contact list, user aliases, names, ID numbers, codes, etc can be used.

Basic operation

Power On/Off the radio

ON: Make sure the power supply is connected correctly, long press the [P]key power on the radio till "Beep sound" is heard (if turned onn). After power on, the brand logo and "is powering" character show on the display screen. And the LCD enters the standby interface.

OFF: long press the [P]key power off the radio, then the brand logo and "is powering" character show on the display screen.

Operating Frequency Band Selection

In standby mode, press the [B/E] key to switch to the Band A or B for operation and set. The current operable and settable band displays the "➡" icon on the upper left.

Volume Adjustment

For adjusting the volume, short press [VOL/ SQL] key, after the volume level is displayed at the upper right, rotate [ENC] key clockwise (increase) or counterclockwise (decrease) to adjust the volume. The green volume scroll bar below will change according to the volume level.

Squelch

When "➡" icon displays at the upper left of the Band A or B, set the squelch level of the Band A or B separately by accessing the menu or long press [VOL/SEL] key. In general, the higher squelch level, the received signal strength is stronger. Settable squelch level range is from "0, 1 ~ 9". Level 0 is normally open, and there is background sound from the speaker once the radio is on. Level 9 is the highest and the required received signal strength is the strongest.

Busy Channel Lockout

When "➡" icon displays at the upper left of Band A or B, set the Busy Channel Lock On/Off of the Band A or B separately by accessing the menu. If it is ON, when received the carrier signal, it is prohibited to transmitting when pressing the PTT button.

Band

When "➡" icon displays at the upper left of Band A or B, set the operating bandwidth of Band A or B separately by accessing the menu.

CTCSS / DCS

When "➡" icon displays at the upper left of Band A or B, set the CTCSS and DCS signaling of Band A or B by accessing the menu or self-programming.

1. In standby, press **[Menu]** key to access the menu to choose **"Parameters"**.
2. In standby, long press **[B/E]** key to User-defined item, and choose **"RX/TX signaling"**.
3. In standby, press **[TONE/T.SET]** button, and then choose **"Signaling"**.

Processes:

- ① **Choose the signaling type:** single click **[TONE/T.SET]** key to choose from **QT → DQT → DQI**, the signaling icon will display at the upper right of current frequency band.
- ② **Choose the signaling code / frequency:** long press **[TONE/T.SET]** key to display current signaling code/frequency at the upper right of current frequency band, rotate **[ENC]** key to choose desired signaling code/frequency and press **[Menu]** key to confirm. Or press **[TONE/T.SET]** key to set RX (R:XXXX) or TX (T:XXXX) signaling code/frequency.

Channel Selection

The desired working channel can be selected by following two ways.

1. When "➡" icon displays at the upper left of Band A or B, rotate the **[ENC]** knob to select the desired channel.
2. When "➡" icon displays at the upper left of Band A or B, input the desired channel number by speaker microphone keypad.

Switch between VFO and Channel Mode

In standby mode, When "➡" icon displays at the upper left of Band A or B, access the menu to choose the desired display mode, the selectable modes are VFO/CHN(Channel) /CHN+FREQ/Single band/dual band etc.

VFO Frequency Set

In standby mode, when "➡" icon displays at the upper left of Band A or B, and the current band is in VFO mode, the desired frequency can be entered through the speaker microphone keypad. For example: 446.050000MHZ; directly input **[4] [4] [6] [0] [5] [0] [0] [0] [0]** through the numeric keyboard.

Note:

- ◇ The current frequency can be increased / decreased by pressing the **[ENC]** knob.
 - ◇ For detail user-defined operation, parameters set and storage, please refer to "VFO / Channel" on page 20.
-

Zone / Channel Selection

When "➡" icon displays at the upper left of the current Band

A or B, the following two methods can be used to select the desired zone, channels switching and zone name modification or editing.

1. By presetting the programming key to **[Channel Switching]** feature.
2. Select **[Zone]** item by accessing the menu

 Note:

- ◇ For detail operation and steps, please refer to "Zone/Channel" on page 38.
-

Monitor

In standby mode or before pressing the [PTT] key to transmit, press and hold the preset [Monitor] key to monitor channel activity, or receive weak signals, or confirm whether the current channel is free.

Permanent monitoring

In standby mode, press the preset [Permanent Monitor] key to continuous monitor the current channel activity.

Repeater / Talk Around

When the repeater fails to work, or the radio exceeds the coverage of the repeater but within the call range of other radio users, press the preset [Repeater / Talk Around] key or set sub-menu "Timeslot / Repeater" thru Parameter in Menu to talk around actively and press [PTT] key to continue the communication. This is the so-called Talk Around.

 Note:

- ◇ This function is supported in digital mode only;
 - ◇ For detail operation and steps, please refer to "Timeslot / repeater" on page 41.
-

Emergency Alarm

The emergency alarm function is mainly used in an emergency situation. In any mode, press the preset [Emergency Alarm] key to initiate an Emergency Call.

- ⊙ There are 3 Emergency Alarm modes supported:

- Emergency Alarm
- Emergency Alarm & Call
- Emergency Alarm & Voice

An alarm is a type of non-voice signaling that can trigger a prompt to another radio. This function refers to the alarm behavior of the radio after it is activated.

- ⊙ The alarm has the following types:

- Disable - The radio can't send the alarm signal.
- Standard - The radio can send the alarm signal with voice & visual prompts.
- Mute - The radio sends alarm signaling without audio or visual prompts, and will not alert to any received audio.
- Mute with voice - The radio sends alarm signaling without audio or visual prompts, but can send signal to the eligible channels.

 Note:

- ◇ This feature is available in digital mode only.
-

Scan On/Off

When "  " icon displays at the upper left of the current Band A or B, turn on / off scan by the following two ways.

1. Turn on / off scan by programming **[Scan On / Off]** key.
2. Select the **[Scan]** item by accessing the menu to turn on/off it.

Roam On / Off

If necessary, turn on / off roaming by the following two ways.

1. Turn on / off roaming by programming **[Roam on / off]** key.
2. Select the submenu **[Scan]** item by accessing the menu to enable / disable roaming.

Note:

- ◇ Make sure the "Scan List" is pre-selected before turning on "Scan" or "Roaming" feature , otherwise, none of the scan types will be enabled.
- ◇ The radio will work in Band A as default when "Roaming" is enabled.
- ◇ When "Roaming" is enabled, the radio will start to scan all repeater channels in the "scan list" (TX/RX with inter-frequency), and the non-repeater channels in the "scan list" (RX/TX with same frequency) will not be scanned. If there is no repeater channel in the scan list, the radio will exit the roaming after scanning the current "scan list";
- ◇ When "Scan" is enabled, the radio will open all the receivable channels in the "scan list".
- ◇ For detailed setting and operation of the "Scan", please refer to page 33.

Main menu contains item index

Set various functions and parameters by accessing the main menu and submenu of the radio. The menu function options supported by this unit are shown in the table below.

The user-defined [FP] programming keys are function shortcut keys, for specific function application, please pre-program by CPS, or consult the system administrator or local dealer.

No.	Icon	Main Menu Item	Available setting items
1		Contacts	Contact List, New contact, Manual Dial
2		Message	Create Msg, Comm Msg, Inbox, Outbox, Draft box.
3		Call log	Dialed Numbs, Received Calls, Missed Calls.
4		Scan	Scan (On/Off), Scan List, Scan Mode, Roam Scan
5		Zone&Channel	Zone List, Modify Name
6		Local Set	Language, Keypad lock, Back Light, LEDs, Display Mode, VOX, Channel Sw, Factory Reset, A/B Repeater
7		Parameters	TOT, Power, Repeat, Sleep Mode, SQ Level, Band, BCLO, Signaling, Enc Level
8		Tone Set	Profiles, Key Tone, Msg Tone, P Call Tone, G Call Tone, Alert Tone, Power On Tone.

No.	Icon	Main Menu Item	Available setting items
9		Appendix	GPS(Optional), FM radio, Time, DTMF (Optional), Speaker/Earpiece (Optional)
10		Record	Record Set, Record List, Clear Record, Space Info.
11		Device Info	Radio ID, RX Group List, CH contact, Version.
12		User_defined Mode	Self-program the channel of current band(CTRL stays) or various parameters of VFO mode. Including: Mode selection, frequency, power, etc

Menu accessing and operations

Access the main menu and submenu options to set or browse various parameters (like message checking, editing and sending, etc) through the following operations and step. If there is access right preset by administrator or dealer, please contact them firstly.

Below icons may appear during menu accessing:

- ⊙  /  indicate On / Off selection;
- ⊙  /  indicate selected and executed items;
- ⊙  indicates to enter the next submenu option;

Processes:

1. In Standby Mode, press **[Menu]** key to access the menu.

2. Rotate [ENC] knob to select the desired "Main Menu" item, and press the **[Menu]** key to enter.

3. Rotate [ENC] knob to select the desired "Level 2 Menu" item, and then press the **[Menu]** key to enter.

OR

Rotate [ENC] knob to select and set the current parameter value and press the **[Menu]** key to confirm and return to the previous level.

OR

Press the **[Menu]** key to select "On or Off".

4. Press **[B/E]** key to return to the previous level.

5. If needed, continue to browse other menus by repeating steps 2 ~ 4 or return to the "Main Menu" interface for other operation.

Note:

- ◇ No matter the "  " is displayed at Band A or B, the selecting and set for some menu parameters (public functions) work for both bands.
- ◇ For details please refer to "Main Functions Description" on page 17.

PTT Call

To ensure an optimal transmission, hold the radio in a vertical position at one to two inches (2.5 to 5.0 centimeters) away from the mouth.

High / low power

In standby mode, if needed, when "  " icon displays at the upper left of the current band to be set, switch radio power by following two ways to extend the service time of the battery.

1. Press the preset [High / Low Power] key to switch between high and low power. The "red" indicator at the bottom of the screen of the current band will change according to the set power level.

2. Access "Power" through the menu to set the output power level of the radio. After setting, the "red" indicator at the bottom of the screen of the current band will change according to the set power level.

Note:

- ◇ High power gets further communicate distance.
- ◇ Low power gets closer communication distance.
- ◇ Please refer to the operation of menu "Power" on page 41.

Select the transmitting band

In standby mode, press [B/E] key to switch between Band A and B for desired transmission, and the current transmitting band will have "  " icon displaying at left of the screen.

Receive and Answer to a radio call

Private calls, Group calls, and All calls can be made to the preset contacts on the current digital channel (All call rights needs to be allowed by the dealer), and the methods for

initiating and receiving all types of calls are the same. Each digital channel can be preset by the dealer with a "transmission contact" for Private call, group call or call contact.

Call type	Operation method	
	Making call	Receiving call
Private call	In standby mode, press [PTT] key to initiate the call. When a call is initiated, the screen displays:  ;	When a private call received, the screen displays:  ;
Group call	When initiated a group call, the screen displays:  ;	When a group call received, the screen displays:  ;
All call	When Initiated an all call, the screen displays:  ;	When an all call received, the screen displays:  ;

Notes:

◇ If the "Tx Begin Tone" and "TX End Tone" for private and group calls are activated, when press [PTT] key of the speaker microphone to make a call, a short prompt tone will be heard indicating that the call is in progress. You can speak clearly into the MIC. And when release the [PTT] key, a short beep sound will be heard indicating that it is ready for receiving.

◇ If "Rx Begin Tone" and "Rx End Tone" for private and group calls are activated, when the other part press the [PTT] key to transmit, you will hear a short prompt tone indicating that the current channel is in receiving. And when the transmitter releases the [PTT] key, you will hear a short beep, indicating that the channel is idle and waiting for your answer.

◇ Please refer to the operation and steps of "Tone Set" on page 43.

Initiate a call

If necessary, a call can be initiated by any of the following ways.

1. Rotate **[ENC]** knob to select any preset channel, and then press the **[PTT]** key of the speaker microphone to call.
2. Access the **"Contact"** list through the menu, or press the pre-set "Contact" key to access the list. Select the desired contact by rotating **[ENC]** knob, and then press **[PTT]** key of the speaker microphone to make a call.
3. Access "Contacts" through the menu to select "Manual Dial" to input the user ID with the numeric keypad of speaker microphone to the popping up dialog box on the screen. It is used for private calls only.

Note:

- ◇ Encryption must be enabled on the current channel of your radio before sending encrypted transmission. Only when the target radio has the same key value and key ID with your radio, can the transmitted voice be decrypted.
- ◇ Please refer to the operation of "Encryption" on page 41.
- ◇ Please refer to the initiating call steps of "Contact" on page 27.

Initiate and receive calls in analog mode

When on the currently preset analog channel, press and hold

the **[PTT]** key to initiate a call to all users, the TFT display screen shows . When receive a call indicated by other users on the current analog channel or monitor is activated, the TFT display screen shows .

Note:

- ◇ If the transmitter or receiver is with "CTCSS / DCS" code, the other party radio can decode the audio successfully with same "CTCSS / DCS" code only.
- ◇ Please refer to details of "Signaling" on page 42.

Advanced functions for DMR

Use the dedicated CPS software to enable/disable and preset DMR advanced functions (application) on / off and parameters set.

Remote monitor

Pre-set to prohibit the radio from being remotely monitored by others; or allow other users to remote monitor and set time for continuing to keep the MIC and transmitter on (Time range is from 10s ~ 120s).

Remote Kill

Pre-set to prohibit the radio from receiving "Remote Kill" command sent by other users; or allow the other users to receive and process the "Remote Kill" command to disable the

radio. This function can be used to disable the radio when it is stolen or lost.

Radio Revive

Pre-set to restrict the radio from receiving "Radio Revive" command sent by other users; or allow the radio to receive and process the "Radio Revive" command to activate it remotely. This function can be used to enable the radio when it is lost and found.

Radio Detection

Pre-set to prohibit or allow the radio from being remotely detected whether the radio is in communication range or active state without any prompt.

Call Alert

Pre-set to prohibit or allow the radio from receiving alert tone to ask for calling back when you are free.

GPS (optional)

Turn on/off GPS and position report feature to report the position information to the preset designated channel at the preset intervals.

Record

Pre-set to prohibit or allow the recording for any of receive, transmit, receive + transmit voice.

DTMF

Pre-set to prohibit sending DTMF tones; or allow to send a

DTMF prompt tone when press the [PTT] key to transmit. It can remind the receiver that there is a call need to listen in time.

Encryption

Preset to encrypt the voice transmission of the digital channels. But the encryption is a software-based scrambling solution for preventing eavesdropping. The receiver radio must have same encryption method, level, alias and value as the transmitter radio to decrypt the encrypted voices from each other.

Notes:

- ◇ DMR Advanced functions (application) apply to digital mode only.
 - ◇ For DMR advanced functions (application), please refer to "Menu" operation on page 26.
 - ◇ Transmission of remote monitor, Remote kill, Radio Revive, Radio Detection, Call Alert, etc. Please refer to "Application" operation of the "Contacts" on page 27.
-

Menu function operation

The various functions, applications and parameter configuration of the radio can be check and set by menus, if they are allowed by the dealer or system administrator.

Contacts

The contacts provide the "address book" for the radio. Each entry corresponds to an alias or ID used to initiate a call, as

well as operations and applications for DMR advanced functions (Application).

Contact list

Processes:

1. Press the preset **[Contact]** key to access the menu.

OR

1. Access the menu, press [Menu] key and rotate **[ENC]** knob to select Contacts, and press **[Menu]** key to enter.

2. Rotate **[ENC]** knob to select the **Contact list**, press [Menu] key to enter and select the desired contact.

○ Press **[PTT]** key to initiate a call;

○ Press **[Select]** key to make following options:

Group Call ID:

SendMsg → press [Select] key → Edit SMS → rotate [ENC] knob to choose operation of **SendMsg** (Send Message),

InsertComMsg (Insert Common Message), **Save, Exit Editor** → press [Select] key to confirm → return back to the previous level;

Private Call ID:

① **Application(Advanced)** → press [Select] key → rotate [ENC] knob to choose of **Radio Detection, Call Alert, Remote Mon(Monitor), Radio Kill, Radio Revive** → press [Select] key to send → "success" or "Fail" character pops up on the screen → Return to the previous level;

② **Edit (contact)** → Press [Select] key → rotate [ENC] knob to choose operation of **Number, Name and Save** → press [Select] key to input number and name or Save → press [OK] key to confirm → return to previous level;

③ **Delete** → press [Select] key → "Are you sure?" pops up on the screen → press [OK] key to confirm deletion, or press [Back] key to cancel deletion → return back to previous level;

④ **SendMsg** → press [Select] key to Edit SMS → rotate [ENC] knob to choose operation of **SendMsg** (Send Message), **InsertComMsg** (Insert Common Message), **Save, Exit Editor** → press [Select] key to confirm the operation → return to the previous level.

New Contact

Processes:

1. Press the preset [Contact] key to access the contact.

OR

1. Access the menu, press [Menu] key and rotate [ENC] knob to select **Contacts**, and press [Select] key to enter.

2. Rotate [ENC] knob to choose the **New Contact**, press [Select] key to enter.

3. Rotate [ENC] knob to choose the desired option and press [Select] key to enter.

① **Number** → press [Select] key → edit interface → input the numbers with the numeric keypad of speaker microphone → press [OK] key to confirm → return back to the previous level;

② **Name** → press [Select] key → edit interface → input the numbers with the numeric keypad of speaker microphone → press [OK] key to confirm → return back to the previous level;

③ **Save** → press [Select] key to confirm → Return back to the previous level

Manual Dial

Processes:

1. Press the preset **[Contact]** key to access the contact.

OR

1. Access the menu, press [Select] key and rotate [ENC] knob to select **Contacts**, and press [Select] key to enter.

2. Rotate [ENC] knob to select the **Manual Dial**, press [Select] key to enter the interface for inputting the ID.

3. Input the ID with numeric keypad of speaker microphone.

○ Press [PTT] key to initiate a call;

○ Press [OK] key and rotate [ENC] knob to make following options:

① **Application** → press [Select] key → rotate [ENC] knob to choose operation of **Radio Detection, Call Alert, Remote Mon(Monitor), Radio Kill, Radio Revive** → press [Select] to send → "success" or "fail" character pops up on the screen → Return to the previous level;

② **SendMsg** → press [Select] key to Edit SMS → rotate [ENC] knob to choose operation of **SendMsg** (Send Message), **InsertComMsg** (Insert Common Message), **Save, Exit Editor** → press [Menu] key to confirm the operation → return to the previous level.

Ham Private Contacts

Processes:

1. Access the menu and rotate ENC knob to select Contacts, and press [Select] key to enter.

2. Rotate ENC knob to select the **Ham Private Contacts**, press [Select] key to enter the Ham Private Call Contacts List. Up to 200,000 private contacts can be added.

3. Choose the desired private contact by rotating ENC knob, the selected contact ID number will display at the top left of the screen and the serial No of the contact displays at the upper right.

OR

○ Long press and hold the [MENU] key for 3 seconds, a dialogue window pops up on the interface.

○ Input the first few digits of the private contact ID to search with the numeric keypad, after that press the [MENU] key to confirm, and then the screen jumps to the search results. Rotate ENC knob to choose the desired ID.

4. Press the [PTT] key to initiate a private call;

OR

○ Press the [MENU] key → rotate ENC knob to make the following options:

① **Application** → press [Select] key to choose operation of **Radio Detection, Call Alert, Remote Mon(Monitor), Radio Kill, Radio Revive** by ENC knob → press [Select] key to confirm the operation → "success" or "fail" character pops up on the screen → Return to the previous level;

② **SendMsg** → press [Select] key to Edit SMS → press [Ok] key to choose operation of **SendMsg** (Send Message), **InsertComMsg** (Insert Common Message), **Save, Exit Editor** by ENC knob → press [Select] key to confirm the operation → return to the previous level.

③ **Details** → press [Select] key → the display shows ID, nick name, name, city, province, country etc information → press [Select] key to confirm → Return to the previous level.

 Notes:

◇ "128Bytes" mode must be selected firstly before writing Ham Private Contacts list, so that details like name, city, province, country, etc information can be checked. But this mode requires a long writing time. Make sure the radio keeps normal power supply during the writing process.

◇ If "16Bytes" mode is selected before writing Ham Private Contacts list, only contact ID and Nick name can be checked. This mode has a shorter writing time which takes about 10 minutes. Make sure the radio keeps normal power supply during the writing process.

Ham Group Contacts

Processes:

1. Access the menu and rotate ENC knob to select **Contacts**, and press [Select] key to enter.
2. Rotate ENC knob to select the **Ham Group Contacts**, press [Select] key to enter the Ham Group Call Contacts List. Up to 20,000 group contacts can be added.
3. Choose the desired group contact by rotating ENC knob, then the selected contact ID number will display at the top left of the screen and the serial No of the contact displays at the upper right.

OR

- Long press and hold the [MENU] key for 3 seconds, a dialogue window pops up on the interface.
 - Input the first few digits of the group contact ID to search with the numeric keypad, after that press the [MENU] key to confirm, and then the screen jumps to the search results. Rotate ENC knob to choose the desired ID.
4. Press the [PTT] key to initiate a group call;
 5. Press [Back] key to return to the previous level.

Ham RX Group List

If allowed in software, Ham RX Group List can be set On or Off in menu to allow/disable the radio to receive any group call from the receiving group call list when it has same working channel/frequency.

Processes:

1. Access the menu and rotate ENC knob to select **Contacts**, and press [Select] key to enter.
2. Rotate ENC knob to select the **Ham RX Group List**, press [Select] key to enter the Ham RX Group Call Contacts List. Up to 20,000 group contacts can be added.
3. Rotate ENC knob to Ham RX Group List ON/OFF selection.
4. Press [MENU] key to turn it On or OFF.
5. Press [Back] key to return to the previous level.

Message

The radio can receive and send text messages from / to the other radios. The below ways can be used to send messages.

CreateMsg

Processes:

1. Press the preset [Message] key to access the menu.

OR

1. Access the menu, press [Menu] key and rotate [ENC] knob to select **Message**, and press [Select] key to enter.
2. Rotate [ENC] knob to **CreateMsg** and press [Select] key to enter message editing interface.
3. After editing, press [OK] key to make following options:
 - ① **SearchLinkman** → rotate [ENC] knob to choose the contact → press the [PTT] key of the speaker microphone to initiate a call or press [Select] key to send the message → the message sending status pops up on the screen;
 - ② **WriteNumber** → input the contact number with the numeric keypad of the speaker microphone → press [OK] key to send the message → the message sending status pops up on the screen;

- ③ **InsertComMsg** (Insert Common Message) → press [Select] key → rotate [ENC] knob to choose the desired message → press [OK] key → edit or press [Menu] key to choose contact to send.
- ④ **Save** → press [Select] key to save the message → return to the previous level;
- ⑤ **ExitEditor** → press [Select] key to return to the previous level;

CommMsg

Processes:

1. Access the menu, press [Menu] key and rotate [ENC] knob to select **Message**, and press [Select] key to enter.
2. Rotate [ENC] knob to select **CommMsg** and press [Select] key to enter the common message list or "Empty! Do you want Add?" character pops up on the screen.
 - ① In common message list → rotate [ENC] knob to select the desired message → press [OK] key to make following options:
 - ◇ **Display** → Press [Select] key to display the full message → Press [Back] key to return to the previous level;
 - ◇ **AddCommMsg** → press [Select] key → input the message with the numeric keypad of speaker microphone → press [OK] key → **Save** or **ExitEditor** → press [Select] key → return to the previous level;
 - ◇ **Edit** → press [Select] key → edit the message with the numeric keypad of speaker microphone → press [OK] key → **Save** or **ExitEditor** → press [Select] key to save the message or exit the edition → return to the previous level;
 - ◇ **Delete** → press [Select] key → "Are you sure?" pops up on the screen → press [OK] key to confirm deletion or press

- [Back] key to cancel deletion → return back to previous level;
- ◇ **Send** → Press [Select] key → edit SMS and press [Select] key to search a contact or write a receiver ID → press [OK] key to send a message → return to the previous level;
- ② **Add message** → press [Select] key to add new common message / press [Back] key to cancel → rotate [ENC] knob to choose operation of **Save** or **ExitEditor** → press [Select] key to confirm → return to the previous level.

Inbox

Processes:

1. Access the menu, press [Menu] key and rotate [ENC] knob to select **Message**, and press [Select] key to enter.
2. Rotate [ENC] knob to **Inbox**, and press [Select] key to make the following options:
 - ① **Inbox List** → press [Select] key → rotate [ENC] knob to choose the received message → press [Select] key to display full message → press [Select] key to perform the following options and processes:
 - ◇ **Reply** → press [Select] key → edit SMS → rotate [ENC] knob to choose operation of **SendMsg**, **InsertComMsg**, **ExitEditor** → press [Select] key to confirm the operation;
 - ◇ **Forward** → Press [Select] key → search or Write the contacts by Search or WriteNumber → Press [Select] key → rotate [ENC] knob to choose contact or input ID number → Press [OK] key to send SMS;
 - ◇ **Edit** → press [Select] key to write the message → Press [OK] key → rotate [ENC] knob to choose operations of **SearchLinkman**, **WriteNumber**, **InsertComMsg**, **Save** or

ExitEditor → press [Select] key to send message or save or exit edition and return to the previous level;

◇ **Delete** → "Are you sure?" pops up on the screen → press [OK] key to confirm deletion or press [Back] key to cancel deletion → return back to previous level;

② **Delete All** → "Are you sure?" pops up on the screen → press [OK] key to confirm deletion or press [Back] key to cancel deletion → return back to previous level;

Outbox

Processes:

1. Access the menu, press [Menu] key and rotate [ENC] knob to select **Message**, and press [Select] key to enter.

2. Rotate [ENC] knob to **Outbox**, and press [Select] key to make the following options:

①. **Outbox List** → press [Select] key → rotate [ENC] knob to choose the message → press [Select] key to display full message → press [OK] key to perform the following options and processes:

◇ **Search** → rotate [ENC] knob to search the contact * press the [PTT] key to initiate a call or press [Select] key to send the message → the message sending status pops up on the screen;

◇ **WriteNumber** → input the contact number with the numeric keypad of the speaker microphone → press [OK] key to send the message → the message sending status pops up on the screen;

◇ **InsertComMsg** (Insert Common Message) → press [Select] key → rotate [ENC] knob to choose the message → press [Select] key → edit or press [OK] key to choose the contact to send.

◇ **Save** → press [Select] key to save the message → return to the previous level;

◇ **Delete** → "Are you sure?" pops up on the screen → press [OK] key to confirm deletion or press [Back] key to cancel deletion → return back to previous level;

◇ **Exit Editor** → press [Select] key to return to the previous level;

②. **Delete All** → "Are you sure?" pops up on the screen → press [OK] key to confirm deletion or press [Back] key to cancel deletion → return back to previous level;

Draft Box

1. Access the menu, press [Menu] key and rotate [ENC] knob to select **Message**, and press [Select] key to enter.

2. Rotate [ENC] knob to **Draftbox**, and press [Select] key to make the following options:

① **Draft List** → press [Select] key → rotate [ENC] knob to choose the message → press [Select] key to display full message → press [OK] key to perform the following options and processes:

◇ **Search** → rotate [ENC] knob to search the contact → press the [PTT] key to initiate a call or press [Select] key to send the message → the message sending status pops up on the screen;

◇ **WriteNumber** → Press [Select] key to input the contact ID with numeric keypad of speaker microphone → Press [OK] key to send the message → the message sending status pops up on the screen;

◇ **InsertComMsg** (Insert Common Message) → press [Select]

key → rotate [ENC] knob to choose the desired message → press [Select] key → rotate [ENC] knob to choose the contact to send.
 ◇ **Save** → press [Select] key to save the message → return to the previous level;
 ◇ **Delete** → "Are you sure?" pops up on the screen → press [OK] key to confirm deletion or press [Back] key to cancel deletion → return back to previous level;
 ◇ **ExitEditor** → press [Select] key to return to the previous level;
 ②. **Delete All** → "Are you sure?" pops up on the screen → press [OK] key to confirm deletion or press [Back] key to cancel deletion → return back to previous level;

Notes:

◇ If Common Message list is empty, you should pre-program the common messages by CPS software or enter into "CommMsg" menu to add messages firstly;
 ◇ Hold and long press the "#" key for 3 seconds to change the Input modes in writing and editing messages and other processes. The input modes are AB / uppercase, ab / lowercase, 12 / digits, and PY / Chinese.
 ◇ In the process of searching contacts or inputting ID numbers to send SMS, when press the [PTT] key, the radio initiates a call.

Call Log

Information for recent dialed calls, received calls and missed calls can be checked by users thru Call Log menu. Call logs

help to manage the recent call activities.

Dialed Calls

Processes:

1. Access the menu, press [Menu] key and rotate [ENC] knob to select **CallLog**, and press [Select] key to enter.
 2. Rotate [ENC] knob to **DailedNumbs**, and press [Select] key to make the following options:

①. **DialedNumbs List** → press [Select] key → rotate [ENC] knob to choose the number → press [Select] key to make the following options and processes:

◇ **View** → Press [Select] key to check the dialed number → Press [Back] key to return to the previous level;

◇ **TimeOfCall** → press [Select] key to display the call time and duration information → press [Back] key to return to previous level;

◇ **SendMsg** → Press [Select] key to edit the message → Press [OK] key → rotate [ENC] knob to choose operation of **SendMsg, InsertComMsg, ExitEditor** → Press [Select] key to confirm the operation → Return to the previous level;

◇ **Delete** → "Are you sure?" characters pops up on the screen → press [OK] key to confirm deletion or press [Back] key to cancel deletion → return back to previous level;

②. **Delete All** → "Are you sure?" characters pops up on the screen → press [OK] key to confirm deletion or press [Back] key to cancel deletion → return back to previous level;