

---

---

# Antenna Test Result of Tooling

**ACCTON**

---

---

# Contents

- Antenna Description
- Experimental Setup & Coordinate System
- Gain
- 2D Radiation Pattern Results

# Antenna Description


| Company name                  | Address                                                                 |
|-------------------------------|-------------------------------------------------------------------------|
| ACCTON Technology Corporation | No.1, Creation Road3, Hsinchu Science Park, Hsinchu 30077,Taiwan, R.O.C |

| Location | Antenna model | Antenna application    | Material | Antenna Type | Peak Gain |
|----------|---------------|------------------------|----------|--------------|-----------|
| 1        | 120G00000289A | Bluetooth & Zigbee ANT | FR-4     | Omni         | 6.16 dBi  |

# Experimental Setup & Coordinate System

Chamber name: SATIMO (MVG) SG-24 Multi-Probe Standard OTA Test Lab

| Describe                            | Manufacturer | Model Number | Serial Number | Cal.Date  | Cal. Due Date |
|-------------------------------------|--------------|--------------|---------------|-----------|---------------|
| Full Anechoic Wireless Test chamber | MVG          | SG - 24      | X             | Oct.-2025 | Oct.-2026     |
| Network Analyzer                    | Agilent      | E5071B       | MY42402996    | Jun.-2024 | Jun.-2026     |



# Efficiency & Gain

| Bluetooth & Zigbee ANT ANT [1] |                                |                                |                                 |
|--------------------------------|--------------------------------|--------------------------------|---------------------------------|
| Frequency                      | 2400 MHz                       | 2447 MHz                       | 24835 MHz                       |
| Peak Gain                      | 6.16 dBi                       | 5.87 dBi                       | 5.48 dBi                        |
| Peak gain at polarization      | ( $\Phi$ )48°( $\theta$ ) -33° | ( $\Phi$ )141°( $\theta$ ) -9° | ( $\Phi$ )108°( $\theta$ ) -12° |


※ $\Phi$ (Phi) ;  $\Theta$ (Theta)

※Peak Gain (G) and directivity (D) are linked by the formula  $G = k \times D$ , where the antenna effective factor k ( $0 \leq k \leq 1$ ) corresponds to the overall losses of the antenna. Accordingly antenna gain can be calculated by the following formula, where represents antenna losses comprising of all ohm and dielectric losses between the input connector and the outer surface of the radome and the loss due to the impedance mismatch.

# 2D Radiation Pattern

## 1X Bluetooth & Zigbee ANT [1]

| ZX-Plane | ZY-Plane | XY-Plane |
|----------|----------|----------|
|----------|----------|----------|



Test date: 2025