

Mouse Product Engineering Specification

I. Outline Specifications

MOUSE			
1	Model No.	PJT-BMS2002	
2	Length	79 mm	
3	Width	46.5 mm	
4	Height	33 mm	
5	Weight (receiver included)	36 g	

II. Electrical Parameters

No.	Parameter	Specification
1	Mouse type:	2.4G wireless mouse
2	Interface:	Type-C receiver
3	Solution (chipset):	Hantianxia
4	Sensor:	MX8650
5	Acceleration:	10 g
6	Tracking speed:	30 ips
7	Resolution:	1200 DPI
8	Lighting mode:	None
9	Bottom slide switch:	None
10	Button function:	3 buttons: left / middle / right
10	Bottom indicator light:	Red
11	2.4G report rate:	120 Hz
12	Bluetooth BLE report rate:	None
22	Pairing:	2.4G mode: factory pre-paired (no re-pairing required)
25	First-level sleep time:	90 s (after mouse inactivity); wake by moving the mouse
26	Deep sleep time:	10 min; wake by pressing any button
29	Wireless current:	1) Active mode 25 mA 2) Light sleep 0.6 mA 3) Deep sleep mode 0.02 mA
32	Supported OS:	Windows 7 / 8 / 10 / Vista / XP
33	Full-load output power:	0.1 W
34	Operating temperature / humidity:	0 °C ~ +40 °C / 0-90% RH

FCC Caution.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.