

DEKCOcare

Hi Customer
Thank you for choosing DEKCO security products. We have always put our customers first and foremost.
There are 3 things you should know before using this product:
1. Micro SD card
If you don't have a Micro-SD card available at home now and don't want to spend extra time choosing one, please contact us directly. *Tip: the Micro-SD card gotta be formatted after inserting it up.
2. Select 2.4G wifi
The product only supports 2.4G wifi, please select 2.4G wifi when setting up the app.
3. Select installation location.
Please use your mobile phone to test the coverage of the home wifi signal at the planned installation position before installation, so that the product can receive a better signal.
Get all the tutorial videos of using product including but no limit to set up the app, installation and format micro sd card, visit: dekcolife.com/DEKCOcare
Join "DEKCO Care" today as three ways below to get all of your problems solved by one-on-one live chat and phone service tech support.

www.dekcolife.com

support@dekcolife.com

@DEKCOLIFE

US: 1-877-277-5797

TABLE OF CONTENTS

01 What's Included01

02 Product overview02

03 CloudEdge App installation and Setup03

04 Mounting the camera04

05 Register an account04

06 Set up WIFI for the camera05-09

07 Safety Statement10

What's Included

Camera

Screw Pack

Power Adapter

Sticker

Warning Sticker

User Manual

USB cable

01

Product overview

Status Light

IR Light

Microphone

TF card slot

Reset

Speaker

Micro USB

CAUTION: Please insert the Micro SD Card according to the direction shown in the diagram. Micro SD Card might JAM if inserted incorrectly and device could be damaged.

SD Card Port: Support micro SD card for local storage (Max 128GB).

Reset button: Used to restore the camera to factory settings (Press and hold on 5-8s).

Card capacity requirements: 5-128GB.

Read and write speed requirements: class10 level.

File format: FAT32.

02

CloudEdge App installation and Setup

Search "CloudEdge" on apple store or google play to download the app.

CloudEdge

from Google Play

from Apple Store

Download on the App Store

GET IT ON Google Play

03

Mounting the camera

1. Put the camera on a flat surface.
2. Use the included mounting bracket to fix the camera to a clean surface.

What is required:

Power supply (not provided)

2x Phillips #2 screw

Register an account

The CloudEdge app that is necessary to operate the camera.
Signing up for storage in the cloud is totally optional and is really not necessary when using an onboard Micro SD card.
1. Open the APP to sign up an account. Go to the login interface, and click "Sign Up".
2. Sign up with your email address, and click "Next".
3. Set up an "Nickname" and "Password" for your APP, click "Done" to complete.

04

DEKCO

Set up WIFI for the camera

1. Bring both your mobile phone and your DEKCO camera close to your router (max distance of 5 meters/16 feet).
Note: The DEKCO camera can only connect to a 2.4 GHz WIFI signal. It does not support using a 5 GHz signal. Therefore, please ensure you connect to a 2.4 GHz signal on your network as shown in the below illustration.

05

2. Log in to "CloudEdge", then tap the "+" icon in the center. Tap "Camera" to add device.

2-1

2-2

2-3

3. Reset the device and wait for a flashing RED indicator light, then tap "Next".

06

4. Selecting the Wi-Fi the device needs to connect with (your home Wi-Fi), input the password and click "Next".

4-1

4-2

07

5. Use the DEKCO camera to scan the QR code on your mobile phone as noted below. When the scan is complete you will hear a prompt tone then push "Next".

5-1

5-2

08

6. When connecting, as stated earlier, you should make sure that the router, mobile phone and the DEKCO camera are as close together as possible (max 5 meters/16 feet). When a successful connection occurs a "click" will be heard and a checkmark will be noted as shown below. The DEKCO camera will show with a numerical name that can be changed to your likings such as Driveway Camera, Street View Camera or whatever.

6-1

6-2

6-3

09

Safety Statement

FCC Statement

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.
Warning: Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.
Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.
This equipment generates noise and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures: (1) Reorient or relocate the receiving antenna. (2) Increase the separation between the equipment and receiver. (3) Connect the equipment into an outlet on a circuit different from that to which the receiver is connected. (4) Consult the dealer or an experienced radio/TV technician for help.

FCC Radio Frequency Exposure Statement

The device has been evaluated to meet general RF exposure requirements. The device can be used in free/mobile exposure condition. The min separation distance is 20cm. Notice: Shielded cables
All connections to other computing devices must be made using shielded cables to maintain compliance with FCC regulations.

10

DEKCO

SMART WIFI HD CAMERA

Quick Start Guide

www.dekcolife.com

support@dekcolife.com

@DEKCOLIFE

US: 1-877-277-5797