























E.4 Restrict Band

Condition	Mode	Frequency (MHz)	Spur Freq (MHz)	Power (dBm)	Gain (dBi)	E (dBuV/m)	Detector	Limit (dBuV/m)	Verdict
NVNT	a	5260	4500	-51.22	2.1	46.11	Peak	68.2	Pass
NVNT	a	5260	4500	-58.08	2.1	39.25	Average	54	Pass
NVNT	a	5260	5142.72	-46.88	2.1	50.45	Peak	68.2	Pass
NVNT	a	5260	5136.48	-55.88	2.1	41.45	Average	54	Pass
NVNT	a	5260	5150	-48.86	2.1	48.47	Peak	68.2	Pass
NVNT	a	5260	5150	-55.92	2.1	41.41	Average	54	Pass
NVNT	a	5320	5350	-47.94	2.1	49.39	Peak	68.2	Pass
NVNT	a	5320	5350	-54.18	2.1	43.15	Average	54	Pass
NVNT	a	5320	5350.4	-44.86	2.1	52.47	Peak	68.2	Pass
NVNT	a	5320	5351.2	-53.98	2.1	43.35	Average	54	Pass
NVNT	a	5320	5460	-47.95	2.1	49.38	Peak	68.2	Pass
NVNT	a	5320	5460	-56.52	2.1	40.81	Average	54	Pass
NVNT	n20mimo	5260	4500	-48.57	5.11	51.77	Peak	68.2	Pass
NVNT	n20mimo	5260	4500	-57.93	5.11	42.41	Average	54	Pass
NVNT	n20mimo	5260	5031.18	-46.15	5.11	54.19	Peak	68.2	Pass
NVNT	n20mimo	5260	5148.18	-55.85	5.11	44.49	Average	54	Pass
NVNT	n20mimo	5260	5150	-49.56	5.11	50.78	Peak	68.2	Pass
NVNT	n20mimo	5260	5150	-55.87	5.11	44.47	Average	54	Pass
NVNT	n20mimo	5320	5350	-41.95	5.11	58.39	Peak	68.2	Pass
NVNT	n20mimo	5320	5350	-53.84	5.11	46.50	Average	54	Pass
NVNT	n20mimo	5320	5350.2	-53.74	5.11	46.60	Average	54	Pass
NVNT	n20mimo	5320	5460	-50.51	5.11	49.83	Peak	68.2	Pass
NVNT	n20mimo	5320	5460	-56.47	5.11	43.87	Average	54	Pass
NVNT	n40mimo	5270	4500	-50.85	5.11	49.49	Peak	68.2	Pass
NVNT	n40mimo	5270	4500	-57.87	5.11	42.47	Average	54	Pass
NVNT	n40mimo	5270	5087.25	-46.63	5.11	53.71	Peak	68.2	Pass
NVNT	n40mimo	5270	5147.19	-55.56	5.11	44.78	Average	54	Pass
NVNT	n40mimo	5270	5150	-49.32	5.11	51.02	Peak	68.2	Pass
NVNT	n40mimo	5270	5150	-55.88	5.11	44.46	Average	54	Pass
NVNT	n40mimo	5310	5350	-46.28	5.11	54.06	Peak	68.2	Pass
NVNT	n40mimo	5310	5350	-50.65	5.11	49.69	Average	54	Pass
NVNT	n40mimo	5310	5353	-33.39	5.11	66.95	Peak	68.2	Pass
NVNT	n40mimo	5310	5460	-49.59	5.11	50.75	Peak	68.2	Pass
NVNT	n40mimo	5310	5460	-56.29	5.11	44.05	Average	54	Pass
NVNT	ac20mimo	5260	4500	-50.65	5.11	49.69	Peak	68.2	Pass
NVNT	ac20mimo	5260	4500	-57.94	5.11	42.40	Average	54	Pass
NVNT	ac20mimo	5260	4975.02	-46.71	5.11	53.63	Peak	68.2	Pass
NVNT	ac20mimo	5260	5148.18	-55.76	5.11	44.58	Average	54	Pass
NVNT	ac20mimo	5260	5150	-48.72	5.11	51.62	Peak	68.2	Pass





NVNT	ac20mimo	5260	5150	-55.88	5.11	44.46	Average	54	Pass
NVNT	ac20mimo	5320	5350	-47.05	5.11	53.29	Peak	68.2	Pass
NVNT	ac20mimo	5320	5350	-53.95	5.11	46.39	Average	54	Pass
NVNT	ac20mimo	5320	5351.8	-40.97	5.11	59.37	Peak	68.2	Pass
NVNT	ac20mimo	5320	5460	-49.49	5.11	50.85	Peak	68.2	Pass
NVNT	ac20mimo	5320	5460	-56.49	5.11	43.85	Average	54	Pass
NVNT	ac40mimo	5270	4500	-50.46	5.11	49.88	Peak	68.2	Pass
NVNT	ac40mimo	5270	4500	-57.7	5.11	42.64	Average	54	Pass
NVNT	ac40mimo	5270	5149.62	-44.95	5.11	55.39	Peak	68.2	Pass
NVNT	ac40mimo	5270	5113.98	-55.42	5.11	44.92	Average	54	Pass
NVNT	ac40mimo	5270	5150	-44.95	5.11	55.39	Peak	68.2	Pass
NVNT	ac40mimo	5270	5150	-55.6	5.11	44.74	Average	54	Pass
NVNT	ac40mimo	5310	5350	-34.39	5.11	65.95	Peak	68.2	Pass
NVNT	ac40mimo	5310	5350	-52.7	5.11	47.64	Average	54	Pass
NVNT	ac40mimo	5310	5350.6	-51.88	5.11	48.46	Average	54	Pass
NVNT	ac40mimo	5310	5460	-50.19	5.11	50.15	Peak	68.2	Pass
NVNT	ac40mimo	5310	5460	-56.31	5.11	44.03	Average	54	Pass
NVNT	ac80mimo	5290	4500	-52.46	5.11	47.88	Peak	68.2	Pass
NVNT	ac80mimo	5290	4500	-57.21	5.11	43.13	Average	54	Pass
NVNT	ac80mimo	5290	5119.44	-46.38	5.11	53.96	Peak	68.2	Pass
NVNT	ac80mimo	5290	5070.72	-54.79	5.11	45.55	Average	54	Pass
NVNT	ac80mimo	5290	5150	-48.55	5.11	51.79	Peak	68.2	Pass
NVNT	ac80mimo	5290	5150	-55.12	5.11	45.22	Average	54	Pass
NVNT	ac80mimo	5290	5350	-42.02	5.11	58.32	Peak	68.2	Pass
NVNT	ac80mimo	5290	5350	-49.12	5.11	51.22	Average	54	Pass
NVNT	ac80mimo	5290	5379.75	-39.6	5.11	60.74	Peak	68.2	Pass
NVNT	ac80mimo	5290	5350.75	-48.72	5.11	51.62	Average	54	Pass
NVNT	ac80mimo	5290	5460	-50.03	5.11	50.31	Peak	68.2	Pass
NVNT	ac80mimo	5290	5460	-56.23	5.11	44.11	Average	54	Pass


Note: 802.11a mode, only show the worst set of antenna data.






Test Graphs

Restrict Band NVNT a 5260MHz Peak



Restrict Band NVNT a 5260MHz Average







Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity









Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity









Shenzhen LCS Compliance Testing Laboratory Ltd.



Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity











Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity









Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity





Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



E.5 Frequency Stability


Condition	Mode	Frequency (MHz)	Antenna	Measured Frequency (MHz)	Frequency Error (Hz)	Deviation (ppm)	Limit (ppm)	Verdict
NVNT	ac20	5260	Ant0	5259.98	-20000	-3.8	25	Pass
NVNT	ac20	5300	Ant0	5300	0	0	25	Pass
NVNT	ac20	5320	Ant0	5320.02	20000	3.76	25	Pass
NVNT	ac40	5270	Ant0	5270	0	0	25	Pass
NVNT	ac40	5310	Ant0	5309.96	-40000	-7.53	25	Pass
NVNT	ac80	5290	Ant0	5290.08	80000	15.12	25	Pass






Test Graphs

Freq. Stability NVNT ac20 5260MHz Ant0



Freq. Stability NVNT ac20 5300MHz Ant0







Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity





Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Condition	Mode	Frequency (MHz)	Antenna	Measured Frequency (MHz)	Frequency Error (Hz)	Deviation (ppm)	Limit (ppm)	Verdict
NVNT	ac20	5260	Ant1	5260	0	0	25	Pass
NVNT	ac20	5300	Ant1	5300	0	0	25	Pass
NVNT	ac20	5320	Ant1	5320	0	0	25	Pass
NVNT	ac40	5270	Ant1	5270.04	40000	7.59	25	Pass
NVNT	ac40	5310	Ant1	5310	0	0	25	Pass
NVNT	ac80	5290	Ant1	5290	0	0	25	Pass

