RF Exposure evaluation

According to 447498 D04 Interim General RF Exposure Guidance v01

$$P_{th}\,(\text{mW}) = \begin{cases} ERP_{20\,\text{cm}}(d/20\,\text{cm})^{x} & d \le 20\,\text{cm} \\ ERP_{20\,\text{cm}} & 20\,\text{cm} < d \le 40\,\text{cm} \end{cases} \qquad \text{(B.2)}$$

where

$$x = -\log_{10}\left(\frac{60}{ERP_{20\,\text{cm}}\sqrt{f}}\right)$$

$$P_{th}\,(\text{mW}) = ERP_{20\,\text{cm}}\,(\text{mW}) = \begin{cases} 2040f & 0.3\,\text{GHz} \le f < 1.5\,\text{GHz} \\ 3060 & 1.5\,\text{GHz} \le f \le 6\,\text{GHz} \end{cases} \qquad \text{(B.1)}$$

Table B.2—Example Power Thresholds (mW)

Frequency (MHz) \ Distance (mm)	5	10	15	20	25	30	35	40	45	50
300	39	65	88	110	129	148	166	184	201	217
450	22	44	67	89	112	135	158	180	203	226
835	9	25	44	66	90	116	145	175	207	240
1900	3	12	26	44	66	92	122	157	195	236
2450	3	10	22	38	59	83	111	143	179	219
3600	2	8	18	32	49	71	96	125	158	195
5800	1	6	14	25	40	58	80	106	136	169

eirp = pt x gt = $(EXd)^2/30$

where:

pt = transmitter output power in watts,

gt = numeric gain of the transmitting antenna (unitless),

E = electric field strength in V/m, --- $10^{((dBuV/m)/20)}/10^6$

d = measurement distance in meters (m)---3m

Sopt = $(EXd)^2/30$ x gt

Ant gain =-3.0dBi so Ant numeric gain= 0.501

Field strength =82.17dBμV/m @3m@433.92MHz

So Pt={ $[10^{(82.17/20)}/10^6$ x3$]^2/(30x0.501)\}x1000$ mW = 0.1mW <23.1657mW

Then SAR evaluation is not required