



US4901-D1052A-说明书-V1.0
成品尺寸：65*90mm，展开尺寸：325x90mm
材质：70g双胶纸
工艺：啤、折，双面单黑印刷，风琴折

65.00 mm

90.00 mm

ZIKE

产品使用说明书

10000mAh固态电池磁吸移动电源

使用设备前请阅读这些说明，以确保安全和正确使用

安全须知

1. 请勿撞击、扔掷、针刺本产品，并避免跌落、挤压、弯曲产品。

2. 请避免在高温、低温、潮湿、多尘及长期暴露于阳光下使用。

3. 充电时请勿将本产品放在易燃物质上（床和毛毯）。

4. 请勿将本产品投入火中、水中或置于有腐蚀性物品的环境，严禁使用其他化学溶液清洗本产品。

5. 请勿将产品放置于具有强大电磁场的器具中，以及远离磁性设备。

6. 请勿拆解本产品，以免引起设备故障。

7. 请勿将本产品浸水，如浸水后严禁使用。

8. 人体在潮湿状态下请勿接触移动电源。

9. 长时间不使用时，请断开连接电源。

10. 请按所在地区的环保法规处理废弃移动电源。

11. 请勿自行拆卸更换内置电池，避免出现爆炸危险。

12. 请勿将本产品存放在过热或过冷的环境。

13. 请使用获得安全认证的电源适配器为本产品充电，以免产生安全风险。

14. 如发现产品有膨胀或其它不良现象和故障时，请立即停止使用本产品，并联系客服或经销商。

15. 使用过程中，产品温度会略高于常温，属正常现象，建议与产品的接触时间<10S。

16. 注意：如果电池更换不当会有爆炸危险，更换电池仅维修人员可更换，非专业人员不可更换电池。

产品指示

①

②

③

④

⑤

① Qi2磁吸无线充电面板

② 开/关机键

③ USB-C1充电口

④ USB-C2充电口

⑤ 显示屏

⑥ C to C 充电线

① Qi2磁吸无线充电面板

支持吸附在iPhone 12及后续机型，带有Qi2无线充电功能，最大15W功率

② 开关机键

单击按键“开机”，打开移动电源和无线充，双击按键“关机”

③ USB-C1充电口

输入：5V $\Rightarrow$ 3A, 9V $\Rightarrow$ 3A (Max 27W)

输出：5V $\Rightarrow$ 3A, 9V $\Rightarrow$ 3A, 12V $\Rightarrow$ 2.5A, 15V $\Rightarrow$ 2A, 20V $\Rightarrow$ 1.5A (Max 30W)

④ USB-C2充电口

输入：5V $\Rightarrow$ 3A, 9V $\Rightarrow$ 3A (Max 27W)

输出：5V $\Rightarrow$ 3A, 9V $\Rightarrow$ 3A, 12V $\Rightarrow$ 2.5A, 15V $\Rightarrow$ 2A, 20V $\Rightarrow$ 1.5A (Max 30W)

⑤ 显示屏

实时显示剩余电量百分比

单击开关机键，未检测到设备时，LED灯亮3秒后熄灭

当接口有设备插入时自动激活点亮，显示当前电量

⑥ C to C 充电线

搭配挂绳孔，可作为移动电源提绳，可以取下用作充电线

防跌落设计:

包装清单

移动电源 X 1，C to C充电线 X 1，说明书 X 1

规格参数

10000mAh固态电池磁吸移动电源

型号：Z1052

电芯规格：5000mAh*2pcs 电芯容量：5000mAh/74V/37Wh

额定容量：6000mAh (5V $\Rightarrow$ 3A)

Qi2输出功率：5W/7.5W/15W

C1/C2输入功率：5V $\Rightarrow$ 3A, 9V $\Rightarrow$ 3A (Max 27W)

C1/C2输出功率：5V $\Rightarrow$ 3A, 9V $\Rightarrow$ 3A, 12V $\Rightarrow$ 2.5A, 15V $\Rightarrow$ 2A, 20V $\Rightarrow$ 1.5A (Max 30W)

C1+C2输出功率：7.5W+7.5W C1+Qi2输出功率：12W+5W

C2+Qi2输出功率：12W+5W C1+C2+Qi2输出功率：7.5W+7.5W+5W

产品尺寸：105*72*19.6 mm 重量：220 g

合规性

FCC声明:

本设备符合 FCC 规则的第 15 部分。操作需满足以下两个条件:

(1) 本设备不会造成有害干扰。

(2) 本设备必须接受任何接收到的干扰，包括可能导致意外操作的干扰。

警告：未经合规责任方明确批准的更改或修改可能会使用户操作设备的权限失效。

注意：根据 FCC 规则第 15 部分，本设备已经经过测试，并符合B类数字设备的限制。这些限制旨在提供合理的保护，防止安装中的有害干扰。本设备会产生用途并可辐射射频能量，如未

按照说明安装和使用，可能会对无线电通信造成有害干扰，但是不能保证在特定安装中不会发生干扰。如果此设备确实对无线电或电视接收造成有害干扰，可以通过关闭和打开设备来确定。鼓励用户尝试通过以下一项或多项措施来纠正干扰:

重新调整或摆放接收天线。

增加设备和接收器之间的距离。

将设备连接到与接收器连接的不同电路上的插座。

请咨询经销商或有经验的无线电/电视技术人员寻求帮助。

FCC 辐射暴露声明:

本设备符合针对不受控制的环境规定的FCC辐射暴露限制。安装和操作本设备时，辐射器与您的身体之间应保持至少 20 厘米的距离。

CE

本设备符合以下法规的要求: EN 62368-1, EN IEC 62311, ETSI EN 301489 和 ETSI EN 303417

WEEE

对于 EU（欧盟）成员用户：根据 WEEE（废弃电气和电子设备）指令，请勿将本产品作为家庭垃圾或商业垃圾处理。废弃的电气和电子设备应按照英国制定的惯例进行适当收集和回收。有关本产品回收的信息，请联系当地的政府部门、家庭垃圾处理服务机构或您购买该产品的商店。

ZIKE

ZIKETECH LLC

200 CONTINENTAL DRIVE STE 401 RM434 NEWARK ,DE 19713

ZIKE TECHNOLOGY (HK) CO., LIMITED/齊睿科技（香港）有限公司

UNIT 2508A, 25/F BANK OF AMERICA TOWER 12 HARCOURT ROAD CENTRAL HONG KONG

香港中环皇后大道12号美国银行中心大厦25楼2508A室

GUANGDONG ZIKE TECHNOLOGY CO.,LTD/广东省齐睿科技有限公司

ROOM 902, BLOCK C, LIANJIANG INDUSTRIAL PARK II, HUARONG ROAD, SHANGHENGUANG COMMUNITY, DALANG STREET, LONGHUA DISTRICT, SHENZHEN, CHINA

深圳市龙华区大浪街道土横朗社区华荣路联建产业园二期C座902

1 YEAR WARRANTY

ZIKE

USER MANUAL

10000mAh

Solid-State Battery Power Bank

Please read these instructions before using the device to ensure safety and proper use

SAFETY NOTICE

1. Do not hit, throw, puncture, drop, crush, or bend this product.

2. Avoid using the product in high/low temperatures, humid, dusty environments, or under direct sunlight for extended periods.

3. Do not charge the product on flammable materials (e.g., beds, blankets).

4. Do not expose the product to fire, water, or corrosive substances. Never clean with chemical solvents.

5. Keep the product away from strong electromagnetic fields and magnetic devices.

6. Do not disassemble the product to avoid malfunction.

7. Do not immerse the product in water; if it becomes wet, stop using it immediately.

8. Avoid contact with the power bank when your body is wet.

9. Disconnect from power if not in use for a long time.

10. Dispose of the product according to local environmental regulations.

11. Do not attempt to replace the built-in battery yourself to avoid explosion risk.

12. Do not store the product in excessively hot or cold environments.

13. Use only certified power adapters to charge the product to avoid safety hazards.

14. If the product shows swelling, damage, or malfunction, stop using it immediately and contact customer service or the dealer.

15. The product may feel slightly warm during use; this is normal. Limit direct contact to less than 10 seconds.

16. Warning: Improper battery replacement can cause explosion. Only qualified service personnel should replace the battery.

PRODUCT INSTRUCTIONS

①

②

③

④

⑤

① Qi2 Magnetic Wireless Charging Panel

② Power On/Off Button

③ USB-C1 Charging Port

④ USB-C2 Charging Port

⑤ Display Screen

⑥ C-to-C Charging Cable

① Qi2 Magnetic Wireless Charging Panel

Supports attachment to iPhone 12 and later models with Qi2 wireless charging, up to 15W.

② Power On/Off Button

Single press: Power on the power bank and wireless charging.

Double press: Power off.

③ USB-C1 Charging Port

Input: 5V $\Rightarrow$ 3A, 9V $\Rightarrow$ 3A (Max 27W)

Output: 5V $\Rightarrow$ 3A, 9V $\Rightarrow$ 3A, 12V $\Rightarrow$ 2.5A, 15V $\Rightarrow$ 2A, 20V $\Rightarrow$ 1.5A (Max 30W)

④ USB-C2 Charging Port

Input: 5V $\Rightarrow$ 3A, 9V $\Rightarrow$ 3A (Max 27W)

Output: 5V $\Rightarrow$ 3A, 9V $\Rightarrow$ 3A, 12V $\Rightarrow$ 2.5A, 15V $\Rightarrow$ 2A, 20V $\Rightarrow$ 1.5A (Max 30W)

⑤ LED Display Screen

Shows remaining battery percentage in real time.

When the power button is pressed and no device is detected, the LED lights up for 3 seconds then turns off.

Automatically lights up when a device is connected, showing current battery level.

⑥ C-to-C Cable

Includes a lanyard hole for carrying; can be detached and used as a charging cable.

Anti-drop design:

PRODUCT SPECIFICATION

10000mAh Solid-State Battery Power Bank

Model: Z1052

Battery Specification: 5000mAh*2pcs Battery Capacity: 5000mAh/74V/37Wh

Rated Capacity: 6000mAh (5V $\Rightarrow$ 3A)

Qi2 Output Power: 5V / 7.5W / 15W

C1 / C2 Input Power: 5V $\Rightarrow$ 3A, 9V $\Rightarrow$ 3A (Max 27W)

C1 / C2 Output Power: 5V $\Rightarrow$ 3A, 9V $\Rightarrow$ 3A, 12V $\Rightarrow$ 2.5A, 15V $\Rightarrow$ 2A, 20V $\Rightarrow$ 1.5A (Max 30W)

Combined Output: C1 + C2: 7.5W + 7.5W C1 + Qi2: 12W + 5W C2 + Qi2: 12W + 5W

C1 + C2 + Qi2: 7.5W + 7.5W + 5W

Product Dimensions: 105 × 72 × 19.6 mm Weight: 220 g

PACKAGING LIST

Power bank X 1，C to C Charging cable X 1，User manual X 1

COMPLIANCE

FCC statement:

This device complies with Part 15 of the FCC Rules. Operation needs to meet the following two conditions:

(1) This device will not cause harmful interference.

(2) This device must accept any interference received, including interference that may cause undesired operation.

WARNING: Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in the installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in

accordance with the instructions, may cause harmful interference to radio communications, but there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on. Users are encouraged to try to correct the interference by one or more of the following measures:

Re-adjust or relocate the receiving antenna.

Increase the separation between the equipment and receiver.

Connect the equipment into an outlet on a circuit different from that to which the receiver is connected. Consult the dealer or an experienced radio/TV technician for help.

FCC Radiation Exposure Statement:

The device has been evaluated to meet general RF exposure requirement.

The device can be used in portable exposure condition without restriction.

CE

This device complies with the requirements of the following regulations: EN 62368-1, EN IEC 62311, ETSI EN 301489 and ETSI EN 303417.

WEEE

For users from EU (European Union) members: In compliance with the WEEE (Waste Electrical and Electronic Equipment) directive, do not dispose of this product as household or commercial waste. Waste electrical and electronic equipment should be collected and recycled appropriately in accordance with the practices established in your country. For information about recycling of this product, please contact your local government agency, household waste disposal service or the store where you purchased this product.

ZIKE

ZIKETECH LLC

200 CONTINENTAL DRIVE STE 401 RM434 NEWARK ,DE 19713

ZIKE TECHNOLOGY (HK) CO., LIMITED/齊睿科技（香港）有限公司

UNIT 2508A, 25/F BANK OF AMERICA TOWER 12 HARCOURT ROAD CENTRAL HONG KONG

香港中环皇后大道12号美国银行中心大厦25楼2508A室

GUANGDONG ZIKE TECHNOLOGY CO.,LTD/广东省齐睿科技有限公司

ROOM 902, BLOCK C, LIANJIANG INDUSTRIAL PARK II, HUARONG ROAD, SHANGHENGUANG COMMUNITY, DALANG STREET, LONGHUA DISTRICT, SHENZHEN, CHINA

深圳市龙华区大浪街道土横朗社区华荣路联建产业园二期C座902

1 YEAR WARRANTY

Project	US4901	Model	D1052A	Edition	V1.0
Design	Irene	Approval		Date	2025-10-16