


Wireless Portable Amplifier User Manual		产品概述		Operation Guide		2. Bluetooth Speaker Function		3. Click on "PA267" to pair it 4. Then you can playback songs Attention: A. The default setting for the amplifier is "USB flash drive" mode. In this mode, you can insert a USB flash drive into the amplifier to playback. B. In your USB flash drive, please place the data in the root directory. Do not put data in folders, as this may result in playback failure. 3. Charging 1. Turn off the microphone and amplifier 2. Place the microphone on the amplifier's back, and the indicator light on the microphone flashing red indicates that it is charging; and will goes off when fully charged. 3. Use a USB-C charging cable to charge the amplifier. Note: The only way to charge the microphone is to place it on the back of the amplifier, which acts as a charging case. 4		System Function																																																																																																																																																
		 PA267-V1 防尘网: Dustproof Net / 指示灯: Indicator Light 电源按键: Power Button / 磁片: Magnetic Sheet 领夹: Magnetic Clip 模式按键: Mode Switch / 下一曲: Next / 上一曲: Previous / 播放/暂停键: Play/Pause / 电源按钮: Rotate Button / 蓝牙指示灯: Bluetooth Indicator Light / 麦克风指示灯: Mic Indicator Light / 电量显示: Battery display / 3.5mm耳麦接口: 3.5MM port 1		1. Amplifier 1. Press the bottom of the microphone and remove it from the amplifier. 2. Peel off the sticker on the back of the microphone for first use. 3. And then press the power button on the right of microphone to turn it on.(green and red lights flashing). 4. Rotate the rotate button to turn on the amplifier (the green light on the microphone indicates connection) 5. You can attach the microphone to your clothes through magnetic sheet or clip before use 6. In addition, you can also plug the head mounted microphone's connector into the 3.5mm port of the amplifier to use it 2				<table><tr><th colspan="4">Transmitter</th></tr><tr><th>Function</th><th>Operation</th><th>Indiation Light</th><th>Remark</th></tr><tr><td>Power On</td><td>Press power button for 1s</td><td>The red and green light flashes</td><td>Automatically turns on when removed</td></tr><tr><td>Power Off</td><td>Long press power button for 2s</td><td>The light is off</td><td></td></tr><tr><td>Paired</td><td></td><td>Green light always on</td><td>automatic pairing</td></tr><tr><td>Mute</td><td>When recording, press the power button</td><td>Green light flashes</td><td></td></tr><tr><td>Exit Mute</td><td>When mute, press thepower button</td><td>Green light always on</td><td></td></tr><tr><td>Low Battery</td><td></td><td>Red light flashes slowly</td><td></td></tr><tr><td>Charging</td><td>Place the microphone in theamplifier charging slot</td><td>Red light stays on when charging, Light off when fully charged</td><td></td></tr><tr><td colspan="4">The mics will automatic shutdown in 3 minutes without connection</td></tr></table>		Transmitter				Function	Operation	Indiation Light	Remark	Power On	Press power button for 1s	The red and green light flashes	Automatically turns on when removed	Power Off	Long press power button for 2s	The light is off		Paired		Green light always on	automatic pairing	Mute	When recording, press the power button	Green light flashes		Exit Mute	When mute, press thepower button	Green light always on		Low Battery		Red light flashes slowly		Charging	Place the microphone in theamplifier charging slot	Red light stays on when charging, Light off when fully charged		The mics will automatic shutdown in 3 minutes without connection																																																																																																												
Transmitter																																																																																																																																																										
Function	Operation	Indiation Light	Remark																																																																																																																																																							
Power On	Press power button for 1s	The red and green light flashes	Automatically turns on when removed																																																																																																																																																							
Power Off	Long press power button for 2s	The light is off																																																																																																																																																								
Paired		Green light always on	automatic pairing																																																																																																																																																							
Mute	When recording, press the power button	Green light flashes																																																																																																																																																								
Exit Mute	When mute, press thepower button	Green light always on																																																																																																																																																								
Low Battery		Red light flashes slowly																																																																																																																																																								
Charging	Place the microphone in theamplifier charging slot	Red light stays on when charging, Light off when fully charged																																																																																																																																																								
The mics will automatic shutdown in 3 minutes without connection																																																																																																																																																										
		5		6																																																																																																																																																						
Amplifier						Specifications		Troubleshooting		Attention																																																																																																																																																
<table><tr><th>Function</th><th>Operation</th><th>Indicator Light</th><th>Prompt Sound</th><th>Remark</th></tr><tr><td>Power On</td><td>Rotate the rotate button clockwise</td><td>The 2 mics indicator light and the battery display is on</td><td>Power on</td><td></td></tr><tr><td>Power off</td><td>Rotate this button counterclockwise</td><td>All lights off</td><td></td><td></td></tr><tr><td>one TX connected</td><td>/</td><td>MIC1 light stays on, MIC2 light off</td><td></td><td></td></tr><tr><td>two TX connected</td><td>/</td><td>MIC1 and MIC2 light stays on</td><td></td><td></td></tr><tr><td>Unconnected</td><td>/</td><td>MIC1 and MIC2 light flashes</td><td></td><td></td></tr><tr><td>External headset</td><td>Plug the headset's connector into the amplifier's 3.5mm jack.</td><td>/</td><td></td><td></td></tr><tr><td>Volume+</td><td>Rotate the rotate button clockwise</td><td>/</td><td>/</td><td></td></tr><tr><td>Volume-</td><td>Rotate this button counterclockwise</td><td>/</td><td>/</td><td></td></tr><tr><td>Bluetooth mode</td><td>Click the mode button</td><td>Bluetooth indicator light flashes</td><td>Bluetooth mode</td><td>Default U Disk mode upon startup</td></tr><tr><td>Bluetooth connection</td><td>Search for Bluetooth "PA267" and connect it</td><td>Bluetooth indicator stays on</td><td>Bluetooth connected</td><td></td></tr><tr><td>U Disk mode</td><td>Click the mode button in Bluetooth</td><td>Bluetooth indicator off</td><td>USB mode</td><td>Default U Disk mode upon startup</td></tr><tr><td>U Disk playback</td><td>Insert the U Disk into the USB-A port</td><td>/</td><td>/</td><td>Automatically playback music from the U Disk, supporting MP3/WAV/FLAC/PAP formats</td></tr><tr><td>Previous song</td><td>Click the previous button</td><td>/</td><td>/</td><td>Valid in USB or Bluetooth mode</td></tr><tr><td>Next song</td><td>Click the next button</td><td>/</td><td>/</td><td>Valid in USB or Bluetooth mode</td></tr><tr><td>Pause/Play</td><td>Click the play/pause button</td><td>/</td><td>/</td><td>Valid in USB or Bluetooth mode</td></tr><tr><td>Singles loop</td><td rowspan="3">Double click the play/pause button to cycle switch modes</td><td>/</td><td>Single loop</td><td>Valid for playing on U Disk with memory</td></tr><tr><td>Loop mode</td><td>/</td><td>Loop mode</td><td>Valid for playing on U Disk with memory</td></tr><tr><td>Randomly play</td><td>/</td><td>Randomly play</td><td>Valid for playing on U Disk with memory</td></tr><tr><td>Charing when device is ON</td><td rowspan="2">Insert the adapter & charging cable into the TYPE-C charging port</td><td>The last digit of the battery display jumps, and it stays on when fully charged to 100</td><td>/</td><td>After unplugging the charging cable for 6 seconds, the digital display will turn off</td></tr><tr><td>Charing when device is OFF</td><td></td><td>/</td><td></td></tr><tr><td>7</td><td colspan="2">8</td><td colspan="2">9</td></tr></table>		Function	Operation	Indicator Light	Prompt Sound	Remark	Power On	Rotate the rotate button clockwise	The 2 mics indicator light and the battery display is on	Power on		Power off	Rotate this button counterclockwise	All lights off			one TX connected	/	MIC1 light stays on, MIC2 light off			two TX connected	/	MIC1 and MIC2 light stays on			Unconnected	/	MIC1 and MIC2 light flashes			External headset	Plug the headset's connector into the amplifier's 3.5mm jack.	/			Volume+	Rotate the rotate button clockwise	/	/		Volume-	Rotate this button counterclockwise	/	/		Bluetooth mode	Click the mode button	Bluetooth indicator light flashes	Bluetooth mode	Default U Disk mode upon startup	Bluetooth connection	Search for Bluetooth "PA267" and connect it	Bluetooth indicator stays on	Bluetooth connected		U Disk mode	Click the mode button in Bluetooth	Bluetooth indicator off	USB mode	Default U Disk mode upon startup	U Disk playback	Insert the U Disk into the USB-A port	/	/	Automatically playback music from the U Disk, supporting MP3/WAV/FLAC/PAP formats	Previous song	Click the previous button	/	/	Valid in USB or Bluetooth mode	Next song	Click the next button	/	/	Valid in USB or Bluetooth mode	Pause/Play	Click the play/pause button	/	/	Valid in USB or Bluetooth mode	Singles loop	Double click the play/pause button to cycle switch modes	/	Single loop	Valid for playing on U Disk with memory	Loop mode	/	Loop mode	Valid for playing on U Disk with memory	Randomly play	/	Randomly play	Valid for playing on U Disk with memory	Charing when device is ON	Insert the adapter & charging cable into the TYPE-C charging port	The last digit of the battery display jumps, and it stays on when fully charged to 100	/	After unplugging the charging cable for 6 seconds, the digital display will turn off	Charing when device is OFF		/		7	8		9				<table><tr><th colspan="2">Microphone</th></tr><tr><td>Product</td><td>Magnetic wireless lavalier microphone</td></tr><tr><td>Vocal System</td><td>Dual channel</td></tr><tr><td>Operation Mode</td><td>Button</td></tr><tr><td>Sound Sensitivity</td><td>-38db</td></tr><tr><td>SNR</td><td>>65db</td></tr><tr><td>Operating Frequency</td><td>2.4G-2.4835GHZ</td></tr><tr><td>Frequency Response</td><td>20Hz-20KHz</td></tr><tr><td>Transmission</td><td>Forward accessibility: 80 meters, Backward accessibility: 35 meters</td></tr><tr><td>Battery</td><td>100mAh</td></tr><tr><td>Charging Time</td><td>1.5 hours</td></tr><tr><td>Working Time</td><td>About 5-6 hours</td></tr><tr><td>Bluetooth Version</td><td>5.3</td></tr><tr><td>Charging Input</td><td>DC-5V/MAX 80±10mA</td></tr><tr><th colspan="2">Amplifier</th></tr><tr><td>Battery</td><td>2600mAh</td></tr><tr><td>Charging Time</td><td>2.5-3H</td></tr><tr><td>Working Time</td><td>About 15 hours</td></tr><tr><td>10</td><td></td></tr></table>		Microphone		Product	Magnetic wireless lavalier microphone	Vocal System	Dual channel	Operation Mode	Button	Sound Sensitivity	-38db	SNR	>65db	Operating Frequency	2.4G-2.4835GHZ	Frequency Response	20Hz-20KHz	Transmission	Forward accessibility: 80 meters, Backward accessibility: 35 meters	Battery	100mAh	Charging Time	1.5 hours	Working Time	About 5-6 hours	Bluetooth Version	5.3	Charging Input	DC-5V/MAX 80±10mA	Amplifier		Battery	2600mAh	Charging Time	2.5-3H	Working Time	About 15 hours	10		11		12	
Function	Operation	Indicator Light	Prompt Sound	Remark																																																																																																																																																						
Power On	Rotate the rotate button clockwise	The 2 mics indicator light and the battery display is on	Power on																																																																																																																																																							
Power off	Rotate this button counterclockwise	All lights off																																																																																																																																																								
one TX connected	/	MIC1 light stays on, MIC2 light off																																																																																																																																																								
two TX connected	/	MIC1 and MIC2 light stays on																																																																																																																																																								
Unconnected	/	MIC1 and MIC2 light flashes																																																																																																																																																								
External headset	Plug the headset's connector into the amplifier's 3.5mm jack.	/																																																																																																																																																								
Volume+	Rotate the rotate button clockwise	/	/																																																																																																																																																							
Volume-	Rotate this button counterclockwise	/	/																																																																																																																																																							
Bluetooth mode	Click the mode button	Bluetooth indicator light flashes	Bluetooth mode	Default U Disk mode upon startup																																																																																																																																																						
Bluetooth connection	Search for Bluetooth "PA267" and connect it	Bluetooth indicator stays on	Bluetooth connected																																																																																																																																																							
U Disk mode	Click the mode button in Bluetooth	Bluetooth indicator off	USB mode	Default U Disk mode upon startup																																																																																																																																																						
U Disk playback	Insert the U Disk into the USB-A port	/	/	Automatically playback music from the U Disk, supporting MP3/WAV/FLAC/PAP formats																																																																																																																																																						
Previous song	Click the previous button	/	/	Valid in USB or Bluetooth mode																																																																																																																																																						
Next song	Click the next button	/	/	Valid in USB or Bluetooth mode																																																																																																																																																						
Pause/Play	Click the play/pause button	/	/	Valid in USB or Bluetooth mode																																																																																																																																																						
Singles loop	Double click the play/pause button to cycle switch modes	/	Single loop	Valid for playing on U Disk with memory																																																																																																																																																						
Loop mode		/	Loop mode	Valid for playing on U Disk with memory																																																																																																																																																						
Randomly play		/	Randomly play	Valid for playing on U Disk with memory																																																																																																																																																						
Charing when device is ON	Insert the adapter & charging cable into the TYPE-C charging port	The last digit of the battery display jumps, and it stays on when fully charged to 100	/	After unplugging the charging cable for 6 seconds, the digital display will turn off																																																																																																																																																						
Charing when device is OFF			/																																																																																																																																																							
7	8		9																																																																																																																																																							
Microphone																																																																																																																																																										
Product	Magnetic wireless lavalier microphone																																																																																																																																																									
Vocal System	Dual channel																																																																																																																																																									
Operation Mode	Button																																																																																																																																																									
Sound Sensitivity	-38db																																																																																																																																																									
SNR	>65db																																																																																																																																																									
Operating Frequency	2.4G-2.4835GHZ																																																																																																																																																									
Frequency Response	20Hz-20KHz																																																																																																																																																									
Transmission	Forward accessibility: 80 meters, Backward accessibility: 35 meters																																																																																																																																																									
Battery	100mAh																																																																																																																																																									
Charging Time	1.5 hours																																																																																																																																																									
Working Time	About 5-6 hours																																																																																																																																																									
Bluetooth Version	5.3																																																																																																																																																									
Charging Input	DC-5V/MAX 80±10mA																																																																																																																																																									
Amplifier																																																																																																																																																										
Battery	2600mAh																																																																																																																																																									
Charging Time	2.5-3H																																																																																																																																																									
Working Time	About 15 hours																																																																																																																																																									
10																																																																																																																																																										
				FCC Compliance Notice																																																																																																																																																						
				This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device must not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Important Notice Any unauthorized modifications may void your authority to operate the equipment. This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. It may be operated in portable exposure conditions without restriction. Interference Guidance (Class B Digital Device) This equipment may cause interference to radio communications. If it does (which can be determined by turning the equipment off and on), try the following measures: ◆ Reorient or relocate the receiving antenna. ◆ Increase the distance between the equipment and the receiver. ◆ Connect the equipment to an outlet on a different circuit. ◆ Consult the dealer or a radio/TV technician for assistance.																																																																																																																																																						
				13																																																																																																																																																						