

Test Report

Report No. : CQASZ20260300485E-01
Applicant: Shenzhen guard dragon Electronics Co., LTD
Address of Applicant: Room 302, No. 437, Hengkeng Hedong Village, Guancheng Community,
Guanlan Street, Longhua District, Shenzhen China
Equipment Under Test (EUT):
Product: Car player
Model No.: F9101W, JP01, TY01, TY02, FD01-B, FD01-S, F9090W, F9210W, OB01-B,
OB01-G, OB01-S, F9095W, F9093W, FD02-B, FD02-S, F9074W, LN01-F
Test Model No.: F9101W
Brand Name: BQCC
FCC ID: 2A4S3-9101W
Standards: 47 CFR Part 15, Subpart C
KDB558074 D01 15.247 Meas Guidance v05r02
ANSI C63.10:2020
Date of Receipt: 2026-03-12
Date of Test: 2026-03-12 to 2026-04-22
Date of Issue: 2026-06-25
Test Result : PASS*

*In the configuration tested, the EUT complied with the standards specified above.

Tested By: Lewis Zhou
(Lewis Zhou)

Reviewed By: Timo Lei
(Timo Lei)

Approved By: Jack Ai
(Jack Ai)



1 Version

Revision History Of Report

Report No.	Version	Description	Issue Date
CQASZ20260300485E-01	Rev.01	Initial report	2026-06-25

2 Test Summary

Test Item	Test Requirement	Test method	Result
Antenna Requirement	47 CFR Part 15.203	/	PASS
AC Power Line Conducted Emission	47 CFR Part 15, Subpart C Section 15.207	ANSI C63.10-2020+Cor. 1-2023+C63.10a-2024 + Errata to C63.10a-2024	N/A
Conducted Peak Output Power	47 CFR Part 15.247	ANSI C63.10-2020+Cor. 1-2023+C63.10a-2024 + Errata to C63.10a-2024	PASS
20dB Occupied Bandwidth	47 CFR Part 15.247	ANSI C63.10-2020+Cor. 1-2023+C63.10a-2024 + Errata to C63.10a-2024	PASS
Carrier Frequencies Separation	47 CFR Part 15.247	ANSI C63.10-2020+Cor. 1-2023+C63.10a-2024 + Errata to C63.10a-2024	PASS
Hopping Channel Number	47 CFR Part 15.247	ANSI C63.10-2020+Cor. 1-2023+C63.10a-2024 + Errata to C63.10a-2024	PASS
Dwell Time	47 CFR Part 15.247	ANSI C63.10-2020+Cor. 1-2023+C63.10a-2024 + Errata to C63.10a-2024	PASS
Pseudorandom Frequency Hopping Sequence	47 CFR Part 15.247	ANSI C63.10-2020+Cor. 1-2023+C63.10a-2024 + Errata to C63.10a-2024	PASS
Band-edge for RF Conducted Emissions	47 CFR Part 15.247	ANSI C63.10-2020+Cor. 1-2023+C63.10a-2024 + Errata to C63.10a-2024	PASS
RF Conducted Spurious Emissions	47 CFR Part 15.247	ANSI C63.10-2020+Cor. 1-2023+C63.10a-2024 + Errata to C63.10a-2024	PASS
Radiated Spurious emissions	47 CFR Part 15.209	ANSI C63.10-2020+Cor. 1-2023+C63.10a-2024 + Errata to C63.10a-2024	PASS
Restricted bands around fundamental frequency (Radiated Emission)	47 CFR Part 15.205/15.209	ANSI C63.10-2020+Cor. 1-2023+C63.10a-2024 + Errata to C63.10a-2024	PASS

Remark:

The tested sample(s) and the sample information are provided by the client.

Tx: In this whole report Tx (or tx) means Transmitter.

Rx: In this whole report Rx (or rx) means Receiver.

RF: In this whole report RF means Radiated Frequency.

CH: In this whole report CH means channel.

Volt: In this whole report Volt means Voltage.

Temp: In this whole report Temp means Temperature.

Humid: In this whole report Humid means humidity.

Press: In this whole report Press means Pressure.

N/A: In this whole report not application

3 Contents

	Page
1 VERSION	2
2 TEST SUMMARY	3
3 CONTENTS	5
4 GENERAL INFORMATION	6
4.1 CLIENT INFORMATION	6
4.2 GENERAL DESCRIPTION OF EUT	6
4.3 ADDITIONAL INSTRUCTIONS	8
4.4 TEST ENVIRONMENT	9
4.5 DESCRIPTION OF SUPPORT UNITS	9
4.6 TEST CONFIGURATION	9
4.7 STATEMENT OF THE MEASUREMENT UNCERTAINTY	10
4.8 TEST LOCATION	11
4.9 TEST FACILITY	11
4.10 ABNORMALITIES FROM STANDARD CONDITIONS	11
4.11 OTHER INFORMATION REQUESTED BY THE CUSTOMER	11
4.12 EQUIPMENT LIST	12
5 TEST RESULTS AND MEASUREMENT DATA	13
5.1 ANTENNA REQUIREMENT	13
5.2 CONDUCTED PEAK OUTPUT POWER	14
5.3 20dB OCCUPIED BANDWIDTH	23
5.4 CARRIER FREQUENCIES SEPARATION	28
5.5 HOPPING CHANNEL NUMBER	32
5.6 DWELL TIME	35
5.7 BAND-EDGE FOR RF CONDUCTED EMISSIONS	44
5.8 SPURIOUS RF CONDUCTED EMISSIONS	51
5.9 OTHER REQUIREMENTS FREQUENCY HOPPING SPREAD SPECTRUM SYSTEM	62
5.10 RADIATED SPURIOUS EMISSION & RESTRICTED BANDS	64
5.10.1 Radiated Emission below 1GHz	67
5.10.2 Transmitter Emission above 1GHz	94
6 PHOTOGRAPHS - EUT TEST SETUP	97
6.1 RADIATED EMISSION	97
6.2 RF CONDUCTED MEASUREMENT	99
7 PHOTOGRAPHS - EUT CONSTRUCTIONAL DETAILS	100

4 General Information

4.1 Client Information

Applicant:	Shenzhen guard dragon Electronics Co., LTD
Address of Applicant:	Room 302, No. 437, Hengkeng Hedong Village, Guancheng Community, Guanlan Street, Longhua District, Shenzhen China
Manufacturer:	Shenzhen guard dragon Electronics Co., LTD
Address of Manufacturer:	Room 302, No. 437, Hengkeng Hedong Village, Guancheng Community, Guanlan Street, Longhua District, Shenzhen China
Factory:	Shenzhen guard dragon Electronics Co., LTD
Address of Factory:	Room 302, No. 437, Hengkeng Hedong Village, Guancheng Community, Guanlan Street, Longhua District, Shenzhen China

4.2 General Description of EUT

Product Name:	Car player
Model No.:	F9101W, JP01, TY01, TY02, FD01-B, FD01-S, F9090W, F9210W, OB01-B, OB01-G, OB01-S, F9095W, F9093W, FD02-B, FD02-S, F9074W, LN01-F
Test Model No.:	F9101W
Trade Mark:	BQCC
Software Version:	V1.0
Hardware Version:	V1.0
Operation Frequency:	2402MHz~2480MHz
Bluetooth Version:	V5.0
Modulation Technique:	Frequency Hopping Spread Spectrum(FHSS)
Modulation Type:	GFSK, $\pi/4$ DQPSK, 8DPSK
Transfer Rate:	1Mbps/2Mbps/3Mbps
Number of Channel:	79
Hopping Channel Type:	Adaptive Frequency Hopping systems
Product Type:	☒ Mobile ☐ Portable ☐ Fix Location
Test Software of EUT:	BT Tool
Antenna Type:	PCB antenna
Antenna Gain:	0dBi
Power Supply:	Power supply DC12-24V
Simultaneous Transmission	☒ Simultaneous TX is supported and evaluated in this report. ☐ Simultaneous TX is not supported.

Operation Frequency each of channel							
Channel	Frequency	Channel	Frequency	Channel	Frequency	Channel	Frequency
0	2402MHz	20	2422MHz	40	2442MHz	60	2462MHz
1	2403MHz	21	2423MHz	41	2443MHz	61	2463MHz
2	2404MHz	22	2424MHz	42	2444MHz	62	2464MHz
3	2405MHz	23	2425MHz	43	2445MHz	63	2465MHz
4	2406MHz	24	2426MHz	44	2446MHz	64	2466MHz
5	2407MHz	25	2427MHz	45	2447MHz	65	2467MHz
6	2408MHz	26	2428MHz	46	2448MHz	66	2468MHz
7	2409MHz	27	2429MHz	47	2449MHz	67	2469MHz
8	2410MHz	28	2430MHz	48	2450MHz	68	2470MHz
9	2411MHz	29	2431MHz	49	2451MHz	69	2471MHz
10	2412MHz	30	2432MHz	50	2452MHz	70	2472MHz
11	2413MHz	31	2433MHz	51	2453MHz	71	2473MHz
12	2414MHz	32	2434MHz	52	2454MHz	72	2474MHz
13	2415MHz	33	2435MHz	53	2455MHz	73	2475MHz
14	2416MHz	34	2436MHz	54	2456MHz	74	2476MHz
15	2417MHz	35	2437MHz	55	2457MHz	75	2477MHz
16	2418MHz	36	2438MHz	56	2458MHz	76	2478MHz
17	2419MHz	37	2439MHz	57	2459MHz	77	2479MHz
18	2420MHz	38	2440MHz	58	2460MHz	78	2480MHz
19	2421MHz	39	2441MHz	59	2461MHz		

Note:


In section 15.31(m), regards to the operating frequency range over 10 MHz, the Lowest frequency, the middle frequency, and the highest frequency of channel were selected to perform the test, and the selected channel see below:

Channel	Frequency
The Lowest channel	2402MHz
The Middle channel	2441MHz
The Highest channel	2480MHz

4.3 Additional Instructions

EUT Test Software Settings:		
Mode:	☒ Special software is used. ☐ Through engineering command into the engineering mode. engineering command: *##3646633##*	
EUT Power level:	(Power level is built-in set parameters and cannot be changed and selected)	
Use test software to set the lowest frequency, the middle frequency and the highest frequency keep transmitting of the EUT.		
Mode	Channel	Frequency(MHz)
DH1/DH3/DH5	CH0	2402
	CH39	2441
	CH78	2480
2DH1/2DH3/2DH5	CH0	2402
	CH39	2441
	CH78	2480
3DH1/3DH3/3DH5	CH0	2402
	CH39	2441
	CH78	2480

Run Software:



4.4 Test Environment


Operating Environment:	
Temperature:	25 °C
Humidity:	54% RH
Atmospheric Pressure:	1009mbar
Test Mode:	Use test software to set the lowest frequency, the middle frequency and the highest frequency keep transmitting of the EUT.

4.5 Description of Support Units

The EUT has been tested with associated equipment below.

Description	Manufacturer	Model No.	Remark	Supplied
/	/	/	/	/

4.6 Test configuration



4.7 Statement of the measurement uncertainty

The data and results referenced in this document are true and accurate.

The reader is cautioned that there may be errors within the calibration limits of the equipment and facilities.

The measurement uncertainty was calculated for all measurements listed in this test report acc. to CISPR 16 - 4 „Specification for radio disturbance and immunity measuring apparatus and methods – Part 4: Uncertainty in EMC Measurements“ and is documented in the **SHENZHEN HUAXIA TESTING TECHNOLOGY CO., LTD** quality system acc. to DIN EN ISO/IEC 17025.

Furthermore, component and process variability of devices similar to that tested may result in additional deviation. The manufacturer has the sole responsibility of continued compliance of the device.

Hereafter the best measurement capability for CQA laboratory is reported:

No.	Item	Uncertainty
1	Radiated Emission (Below 1GHz)	5.12dB
2	Radiated Emission (Above 1GHz)	4.60dB
3	Conducted Disturbance (0.15~30MHz)	3.34dB
4	Radio Frequency	3×10^{-8}
5	Duty cycle	0.6 %
6	Occupied Bandwidth	1.1%
7	RF conducted power	0.86dB
8	RF power density	0.74
9	Conducted Spurious emissions	0.86dB
10	Temperature test	0.8℃
11	Humidity test	2.0%
12	Supply voltages	0.5 %
13	Frequency Error	5.5 Hz

4.8 Test Location

All tests were performed at:

SHENZHEN HUAXIA TESTING TECHNOLOGY CO., LTD

SHENZHEN HUAXIA TESTING TECHNOLOGY CO., LTD 102A, 102B, Building 2, Shanghenglang New Industrial Zone, Shanghenglang Community, Dalang Street, Longhua District, Shenzhen, Guangdong, People's Republic of China, 518000

4.9 Test Facility

The test facility is recognized, certified, or accredited by the following organizations:

IC Registration No.: 22984-1

The 3m Semi-anechoic chamber of SHENZHEN HUAXIA TESTING TECHNOLOGY CO., LTD has been registered by Certification and Engineering Bureau of Industry Canada for radio equipment testing

The test facility is recognized, certified, or accredited by the following organizations:

• CNAS (No. CNAS L5785)

CNAS has accredited SHENZHEN HUAXIA TESTING TECHNOLOGY CO., LTD Shenzhen Branch
EMC

Lab to ISO/IEC 17025:2005 General Requirements for the Competence of Testing and Calibration Laboratories (CNAS-CL01 Accreditation Criteria for the Competence of Testing and Calibration Laboratories) for the competence in the field of testing.

• A2LA (Certificate No. 4742.01)

SHENZHEN HUAXIA TESTING TECHNOLOGY CO., LTD, Shenzhen EMC Laboratory is accredited by the

American Association for Laboratory Accreditation(A2LA). Certificate No. 4742.01.

• FCC Registration No.: 522263

SHENZHEN HUAXIA TESTING TECHNOLOGY CO., LTD, Shenzhen EMC Laboratory has been registered and fully described in a report filed with the (FCC) Federal Communications Commission. The acceptance letter from the FCC is maintained in our files. Registration No.:522263

4.10 Abnormalities from Standard Conditions

None.

4.11 Other Information Requested by the Customer

None.

4.12 Equipment List

Test Equipment	Manufacturer	Model No.	Instrument No.	Calibration Date	Calibration Due Date
EMI Test Receiver	R&S	ESR7	CQA-005	2025/9/1	2026/8/31
Spectrum analyzer	R&S	FSU26	CQA-038	2025/9/1	2026/8/31
Spectrum analyzer	R&S	FSU40	CQA-075	2025/9/1	2026/8/31
Preamplifier	MITEQ	AFS4-00010300-18-10P-4	CQA-035	2025/9/1	2026/8/31
Preamplifier	MITEQ	AMF-6D-02001800-29-20P	CQA-036	2025/9/1	2026/8/31
Preamplifier	EMCI	EMC184055SE	CQA-089	2025/9/1	2026/8/31
Loop antenna	Schwarzbeck	FMZB1516	CQA-060	2023/9/8	2026/9/7
Bilog Antenna	R&S	HL562	CQA-011	2023/11/01	2026/10/31
Horn Antenna	R&S	HF906	CQA-012	2023/11/01	2026/10/31
Horn Antenna	Schwarzbeck	BBHA 9170	CQA-088	2023/9/7	2026/9/6
Coaxial Cable (Above 1GHz)	CQA	N/A	C007	2025/9/1	2026/8/31
Coaxial Cable (Below 1GHz)	CQA	N/A	C013	2025/9/1	2026/8/31
Antenna Connector	CQA	RFC-01	CQA-080	2025/9/1	2026/8/31
RF cable(9KHz~40GHz)	CQA	RF-01	CQA-079	2025/9/1	2026/8/31
Power meter	R&S	NRVD	CQA-029	2025/9/1	2026/8/31
Power divider	MIDWEST	PWD-2533-02-SMA-79	CQA-067	2025/9/1	2026/8/31
EMI Test Receiver	R&S	ESR7	CQA-005	2025/9/1	2026/8/31
LISN	R&S	ENV216	CQA-003	2025/9/1	2026/8/31
Coaxial cable	CQA	N/A	CQA-C009	2025/9/1	2026/8/31
DC power	KEYSIGHT	E3631A	CQA-028	2025/9/1	2026/8/31

Test software:

	Manufacturer	Software brand	Software version
Radiated Emissions test software	Tonscend	JS1120-3	Version:8
Conducted Emissions test software	Audix	e3	Version:9
RF Conducted test software	Audix	e3	V3.5.39

Note:



The temporary antenna connector is soldered on the PCB board in order to perform conducted tests and this temporary antenna connector is listed in the equipment list.

5 Test results and Measurement Data

5.1 Antenna Requirement

Standard requirement:	47 CFR Part 15C Section 15.203 /247(c)
15.203 requirement: An intentional radiator shall be designed to ensure that no antenna other than that furnished by the responsible party shall be used with the device. The use of a permanently attached antenna or of an antenna that uses a unique coupling to the intentional radiator, the manufacturer may design the unit so that a broken antenna can be replaced by the user, but the use of a standard antenna jack or electrical connector is prohibited. 15.247(b) (4) requirement: The conducted output power limit specified in paragraph (b) of this section is based on the use of antennas with directional gains that do not exceed 6 dBi. Except as shown in paragraph (c) of this section, if transmitting antennas of directional gain greater than 6 dBi are used, the conducted output power from the intentional radiator shall be reduced below the stated values in paragraphs (b)(1), (b)(2), and (b)(3) of this section, as appropriate, by the amount in dB that the directional gain of the antenna exceeds 6 dBi.	
EUT Antenna:	
The antenna is PCB antenna. The connection/connection type between the antenna to the EUT's antenna port is: permanently attachment. This is either permanently attachment or a unique coupling that satisfies the requirement.	

5.2 Conducted Peak Output Power


Test Requirement:	47 CFR Part 15C Section 15.247 (b)(1)
Test Method:	ANSI C63.10-2020+Cor. 1-2023+C63.10a-2024 + Errata to C63.10a-2024
Test Setup:	Setup for Power meter measurement method  Setup for Spectrum analyser measurement method  <i>Remark: Offset=Cable loss+ attenuation factor.</i>
Limit:	21dBm
Exploratory Test Mode:	Non-hopping transmitting with all kind of modulation and all kind of data type
Final Test Mode:	Only the worst case is recorded in the report.
Test Results:	Pass

Operated Mode for Worst Duty Cycle:				
Test Mode	On time [Ton] (ms)	Period [Ttotal] ms)	Duty Cycle(%)	Average correction factor(dB)
GFSK	2.91	3.75	77.60	1.10
$\pi/4$ DQPSK	2.92	3.75	77.87	1.09
8DPSK	2.92	3.75	77.87	1.09

Remark:


- 1) Duty cycle= On Time/ Period;
- 2) Duty Cycle factor = $10 * \log(1/ \text{Duty cycle})$;

Test Graph_GFSK Duty Cycle:




Date: 17.MAR.2026 10:36:01

Test Graph_π/4DQPSK Duty Cycle:



Date: 17.MAR.2026 10:41:28

Test Graph_8DPSK Duty Cycle:





Date: 17.MAR.2026 10:46:00

Measurement Data


GFSK mode			
Test channel	Peak Output Power (dBm)	Limit (dBm)	Result
Lowest	4.16	21.00	Pass
Middle	5.12	21.00	Pass
Highest	4.54	21.00	Pass
$\pi/4$ DQPSK mode			
Test channel	Peak Output Power (dBm)	Limit (dBm)	Result
Lowest	4.13	21.00	Pass
Middle	4.81	21.00	Pass
Highest	4.34	21.00	Pass
8DPSK mode			
Test channel	Peak Output Power (dBm)	Limit (dBm)	Result
Lowest	3.83	21.00	Pass
Middle	4.52	21.00	Pass
Highest	4.48	21.00	Pass

Test plot as follows:







2DH5_Ant1_2402




2DH5_Ant1_2441




2DH5_Ant1_2480




3DH5_Ant1_2402




3DH5_Ant1_2441



3DH5_Ant1_2480




5.3 20dB Occupied Bandwidth


Test Requirement:	47 CFR Part 15C Section 15.247 (a)(1)
Test Method:	ANSI C63.10-2020+Cor. 1-2023+C63.10a-2024 + Errata to C63.10a-2024
Test Setup:	 Remark: Offset=Cable loss+ attenuation factor.
Limit:	NA
Exploratory Test Mode:	Non-hopping transmitting with all kind of modulation and all kind of data type
Final Test Mode:	Only the worst case is recorded in the report.
Test Results:	Pass

Measurement Data

Test channel	20dB Occupy Bandwidth (MHz)		
	GFSK	$\pi/4$ DQPSK	8DPSK
Lowest	0.94	1.18	1.20
Middle	0.95	1.18	1.20
Highest	0.95	1.18	1.20


Test plot as follows:






Date: 17. MAR 2026 11:00:37

2DH5_Ant1_2402




Date: 17. MAR 2026 11:06:10

2DH5_Ant1_2441




Date: 17. MAR 2026 11:08:40


2DH5_Ant1_2480



3DH5_Ant1_2402



3DH5_Ant1_2441




3DH5_Ant1_2480



Date: 17 MAR 2026 11:20:35

5.4 Carrier Frequencies Separation


Test Requirement:	47 CFR Part 15C Section 15.247 (a)(1)
Test Method:	ANSI C63.10-2020+Cor. 1-2023+C63.10a-2024 + Errata to C63.10a-2024
Test Setup:	 Remark: Offset=Cable loss+ attenuation factor.
Limit:	2/3 of the 20dB bandwidth
	Remark: the transmission power is less than 0.125W.
Exploratory Test Mode:	Hopping transmitting with all kind of modulation and all kind of data type
Final Test Mode:	Only the worst case is recorded in the report.
Test Results:	Pass


Measurement Data

TestMode	Freq(MHz)	Result[MHz]	Limit[MHz]	Verdict
DH5	Hop	1	≥ 0.633	PASS
2DH5	Hop	1.023	≥ 0.787	PASS
3DH5	Hop	0.997	≥ 0.800	PASS


Mode	20dB bandwidth (MHz) (worse case)	Limit (MHz) (Carrier Frequencies Separation)
GFSK	0.95	≥ 0.633
$\pi/4$ DQPSK	1.18	≥ 0.787
8DPSK	1.20	≥ 0.800

Test plot as follows:






5.5 Hopping Channel Number


Test Requirement:	47 CFR Part 15C Section 15.247 (a)(1)
Test Method:	ANSI C63.10-2020+Cor. 1-2023+C63.10a-2024 + Errata to C63.10a-2024
Test Setup:	 <i>Remark: Offset=Cable loss+ attenuation factor.</i>
Limit:	At least 15 channels
Exploratory Test Mode:	hopping transmitting with all kind of modulation and all kind of data type
Final Test Mode:	Only the worst case is recorded in the report.
Test Results:	Pass

Measurement Data


Mode	Hopping channel numbers	Limit
GFSK	79	≥15
$\pi/4$ DQPSK	79	≥15
8DPSK	79	≥15

Test plot as follows:





5.6 Dwell Time

Test Requirement:	47 CFR Part 15C Section 15.247 (a)(1)
Test Method:	ANSI C63.10-2020+Cor. 1-2023+C63.10a-2024 + Errata to C63.10a-2024
Test Setup:	 <i>Remark: Offset=Cable loss+ attenuation factor.</i>
Test Mode:	Hopping transmitting with all kind of modulation and all kind of data type.
Limit:	0.4 Second
Test Results:	Pass


Measurement Data


TestMode	Freq(MHz)	BurstWidth [ms]	TotalHops [Num]	Result[s]	Limit[s]	Verdict
DH1	Hop	0.405	320	0.13	≤0.4	PASS
DH3	Hop	1.653	190	0.314	≤0.4	PASS
DH5	Hop	2.893	120	0.347	≤0.4	PASS
2DH1	Hop	0.415	320	0.133	≤0.4	PASS
2DH3	Hop	1.658	170	0.282	≤0.4	PASS
2DH5	Hop	2.899	120	0.348	≤0.4	PASS
3DH1	Hop	0.414	330	0.137	≤0.4	PASS
3DH3	Hop	1.655	180	0.298	≤0.4	PASS
3DH5	Hop	2.900	100	0.29	≤0.4	PASS

Remark:


The test period: $T = 0.4 \text{ Second/Channel} \times 79 \text{ Channel} = 31.6 \text{ s}$

Test plot as follows:






Date: 17. MAR 2026 11:41:20




Date: 17. MAR 2026 11:41:26



DH5_Ant1_Hop




Date: 17. MAR 2026 11:26:44




2DH1_Ant1_Hop



2DH3_Ant1_Hop




Date: 17. MAR 2026 12:01:17




Date: 17. MAR 2026 12:01:23



2DH5_Ant1_Hop




Date: 17. MAR 2026 11:55:22




3DH1_Ant1_Hop



3DH3_Ant1_Hop




Date: 17. MAR 2026 14:27:29




Date: 17. MAR 2026 14:27:35

3DH5_Ant1_Hop




Date: 17. MAR 2026 14:17:05



Date: 17 MAR 2026 14:17:10


5.7 Band-edge for RF Conducted Emissions


Test Requirement:	47 CFR Part 15C Section 15.247 (d)
Test Method:	ANSI C63.10-2020+Cor. 1-2023+C63.10a-2024 + Errata to C63.10a-2024
Test Setup:	 <i>Remark: Offset=cable loss+ attenuation factor.</i>
Limit:	In any 100 kHz bandwidth outside the frequency band in which the spread spectrum intentional radiator is operating, the radio frequency power that is produced by the intentional radiator shall be at least 20 dB below that in the 100 kHz bandwidth within the band that contains the highest level of the desired power, based on either an RF conducted or a radiated measurement.
Exploratory Test Mode:	Hopping and Non-hopping transmitting with all kind of modulation and all kind of data type
Final Test Mode:	Only the worst case is recorded in the report.
Test Results:	Pass

Measurement Data

TestMode	ChName	Freq(MHz)	RefLevel [dBm]	Result [dBm]	Limit [dBm]	Verdict
DH5	Low	2402	3.64	-49.93	≤ -16.36	PASS
	High	2480	3.95	-52.29	≤ -16.05	PASS
	Low	Hop_2402	3.08	-52.83	≤ -16.92	PASS
	High	Hop_2480	4.03	-51.85	≤ -15.97	PASS
2DH5	Low	2402	3.65	-49.29	≤ -16.35	PASS
	High	2480	3.96	-51.99	≤ -16.04	PASS
	Low	Hop_2402	3.39	-50.68	≤ -16.61	PASS
	High	Hop_2480	4.72	-50.96	≤ -15.28	PASS
3DH5	Low	2402	3.66	-51.13	≤ -16.34	PASS
	High	2480	3.95	-51.85	≤ -16.05	PASS
	Low	Hop_2402	-1.53	-52.95	≤ -21.53	PASS
	High	Hop_2480	4.47	-51.75	≤ -15.53	PASS


Test plot as follows:






Date: 17. MAR 2026 11:23:39

DH5_Ant1_High_Hop_2480




Date: 17. MAR 2026 11:43:16

2DH5_Ant1_Low_2402




Date: 17. MAR 2026 11:06:27

2DH5_Ant1_High_2480




Date: 17. MAR 2026 11:09:59

2DH5_Ant1_Low_Hop_2402




Date: 17. MAR 2026 11:52:14

2DH5_Ant1_High_Hop_2480




Date: 17. MAR 2026 12:06:32

3DH5_Ant1_Low_2402




Date: 17. MAR 2026 11:13:54

3DH5_Ant1_High_2480




Date: 17. MAR 2026 11:20:53

3DH5_Ant1_Low_Hop_2402




Date: 17. MAR 2026 14:10:19

3DH5_Ant1_High_Hop_2480




Date: 17. MAR 2026 14:28:42


5.8 Spurious RF Conducted Emissions

Test Requirement:	47 CFR Part 15C Section 15.247 (d)
Test Method:	ANSI C63.10-2020+Cor. 1-2023+C63.10a-2024 + Errata to C63.10a-2024
Test Setup:	 Remark: Offset=cable loss+ attenuation factor.
Limit:	In any 100 kHz bandwidth outside the frequency band in which the spread spectrum intentional radiator is operating, the radio frequency power that is produced by the intentional radiator shall be at least 20 dB below that in the 100 kHz bandwidth within the band that contains the highest level of the desired power, based on either an RF conducted or a radiated measurement.
Exploratory Test Mode:	Non-hopping transmitting with all kind of modulation and all kind of data type
Final Test Mode:	Through Pre-scan, find the DH5 of data type is the worst case of GFSK modulation type, 2-DH5 of data type is the worst case of $\pi/4$ DQPSK modulation type, 3-DH5 of data type is the worst case of 8DPSK modulation type.
Test Results:	Pass


DH5_Ant1_2402_0~Reference




DH5_Ant1_2402_30~1000




DH5_Ant1_2402_1000~26500




DH5_Ant1_2441_0~Reference




DH5_Ant1_2441_30~1000




DH5_Ant1_2441_1000~26500




DH5_Ant1_2480_0~Reference




DH5_Ant1_2480_30~1000




DH5_Ant1_2480_1000~26500




2DH5_Ant1_2402_0~Reference




2DH5_Ant1_2402_30~1000




2DH5_Ant1_2402_1000~26500




2DH5_Ant1_2441_0~Reference




2DH5_Ant1_2441_30~1000




2DH5_Ant1_2441_1000~26500




2DH5_Ant1_2480_0~Reference




2DH5_Ant1_2480_30~1000




2DH5_Ant1_2480_1000~26500




3DH5_Ant1_2402_0~Reference




3DH5_Ant1_2402_30~1000




3DH5_Ant1_2402_1000~26500




3DH5_Ant1_2441_0~Reference




3DH5_Ant1_2441_30~1000




3DH5_Ant1_2441_1000~26500




3DH5_Ant1_2480_0~Reference



3DH5_Ant1_2480_30~1000



3DH5_Ant1_2480_1000~26500



Remark:

Pre test 9kHz to 25GHz, find the highest point when testing, so only the worst data were shown in the test report. Per FCC Part 15.33 (a) and 15.31 (o) ,The amplitude of spurious emissions from intentional radiators which are attenuated more than 20 dB below the permissible value need not be reported unless specifically required elsewhere in this part.

5.9 Other requirements Frequency Hopping Spread Spectrum System

Test Requirement:	47 CFR Part 15C Section 15.247 (a)(1), (h) requirement:
	The system shall hop to channel frequencies that are selected at the system hopping rate from a Pseudorandom ordered list of hopping frequencies. Each frequency must be used equally on the average by each transmitter. The system receivers shall have input bandwidths that match the hopping channel bandwidths of their corresponding transmitters and shall shift frequencies in synchronization with the transmitted signals. Frequency hopping spread spectrum systems are not required to employ all available hopping channels during each transmission. However, the system, consisting of both the transmitter and the receiver, must be designed to comply with all of the regulations in this section should the transmitter be presented with a continuous data (or information) stream. In addition, a system employing short transmission bursts must comply with the definition of a frequency hopping system and must distribute its transmissions over the minimum number of hopping channels specified in this section. The incorporation of intelligence within a frequency hopping spread spectrum system that permits the system to recognize other users within the spectrum band so that it individually and independently chooses and adapts its hopsets to avoid hopping on occupied channels is permitted. The coordination of frequency hopping systems in any other manner for the express purpose of avoiding the simultaneous occupancy of individual hopping frequencies by multiple transmitters is not permitted.
Compliance for section 15.247(a)(1)	
	According to Bluetooth Core Specification, the pseudorandom sequence may be generated in a nine-stage shift register whose 5th and 9th stage outputs are added in a modulo-two addition stage. And the result is fed back to the input of the first stage. The sequence begins with the first ONE of 9 consecutive ONES; i.e. the shift register is initialized with nine ones. • Number of shift register stages: 9 • Length of pseudo-random sequence: $2^9 - 1 = 511$ bits • Longest sequence of zeros: 8 (non-inverted signal) <i>Linear Feedback Shift Register for Generation of the PRBS sequence</i> An example of Pseudorandom Frequency Hopping Sequence as follow: Each frequency used equally on the average by each transmitter. According to Bluetooth Core Specification, Bluetooth receivers are designed to have input and IF bandwidths that match the hopping channel bandwidths of any Bluetooth transmitters and shift frequencies in synchronization with the transmitted signals.
Compliance for section 15.247(g)	
	According to Bluetooth Core Specification, the Bluetooth system transmits the packet with the pseudorandom hopping frequency with a continuous data and the short burst transmission from the Bluetooth system is also transmitted under the frequency hopping system with the pseudorandom hopping frequency system.

Compliance for section 15.247(h)

According to Bluetooth Core specification, the Bluetooth system incorporates with an adaptive system to detect other user within the spectrum band so that it individually and independently to avoid hopping on the occupied channels.

According to the Bluetooth Core specification, the Bluetooth system is designed not have the ability to coordinated with other FHSS System in an effort to avoid the simultaneous occupancy of individual hopping frequencies by multiple transmitter.

5.10 Radiated Spurious Emission & Restricted bands

Test Requirement:	47 CFR Part 15C Section 15.209 and 15.205				
Test Method:	ANSI C63.10-2020+Cor. 1-2023+C63.10a-2024 + Errata to C63.10a-2024				
Test Site:	Measurement Distance: 3m (Semi-Anechoic Chamber)				
Receiver Setup:	Frequency	Detector	RBW	VBW	Remark
	0.009MHz-0.090MHz	Peak	10kHz	30kHz	Peak
	0.009MHz-0.090MHz	Average	10kHz	30kHz	Average
	0.090MHz-0.110MHz	Quasi-peak	10kHz	30kHz	Quasi-peak
	0.110MHz-0.490MHz	Peak	10kHz	30kHz	Peak
	0.110MHz-0.490MHz	Average	10kHz	30kHz	Average
	0.490MHz -30MHz	Quasi-peak	10kHz	30kHz	Quasi-peak
	30MHz-1GHz	Peak	120 kHz	300kHz	Peak
	Above 1GHz	Peak	1MHz	3MHz	Peak
		Peak	1MHz	10Hz	Average
Limit:	Frequency	Field strength (microvolt/meter)	Limit (dBuV/m)	Remark	Measurement distance (m)
	0.009MHz-0.490MHz	2400/F(kHz)	-	-	300
	0.490MHz-1.705MHz	24000/F(kHz)	-	-	30
	1.705MHz-30MHz	30	-	-	30
	30MHz-88MHz	100	40.0	Quasi-peak	3
	88MHz-216MHz	150	43.5	Quasi-peak	3
	216MHz-960MHz	200	46.0	Quasi-peak	3
	960MHz-1GHz	500	54.0	Quasi-peak	3
	Above 1GHz	500	54.0	Average	3
	Note: 15.35(b), Unless otherwise specified, the limit on peak radio frequency emissions is 20dB above the maximum permitted average emission limit applicable to the equipment under test. This peak limit applies to the total peak emission level radiated by the device.				

Test Setup:




Figure 1. Below 30MHz




Figure 2. 30MHz to 1GHz




Figure 3. Above 1 GHz

Test Procedure:


- a. 1) Below 1G: The EUT was placed on the top of a rotating table 0.8 meters above the ground at a 3 meter semi-anechoic camber. The table was rotated 360 degrees to determine the position of the highest radiation.
2) Above 1G: The EUT was placed on the top of a rotating table 1.5 meters above the ground at a 3 meter semi-anechoic camber. The table was rotated 360 degrees to determine the position of the highest radiation.
Note: For the radiated emission test above 1GHz:
Place the measurement antenna away from each area of the EUT determined to be a source of emissions at the specified measurement distance, while keeping the measurement antenna aimed at the source of emissions at each frequency of significant emissions, with polarization oriented for maximum response. The measurement antenna may have to be higher or lower than the EUT, depending on the radiation pattern of the emission and staying aimed at the emission source for receiving the maximum signal. The final measurement antenna elevation shall be that which maximizes the emissions. The measurement antenna elevation for maximum emissions shall be restricted to a range of heights of from 1 m to 4 m above the ground or reference ground plane.
- b. The EUT was set 3 meters away from the interference-receiving antenna, which was mounted on the top of a variable-height antenna tower.
- c. The antenna height is varied from one meter to four meters above the ground to determine the maximum value of the field strength. Both horizontal and vertical polarizations of the antenna are set to make the measurement.

	d. For each suspected emission, the EUT was arranged to its worst case and then the antenna was tuned to heights from 1 meter to 4 meters (for the test frequency of below 30MHz, the antenna was tuned to heights 1 meter) and the rotatable table was turned from 0 degrees to 360 degrees to find the maximum reading. e. The test-receiver system was set to Peak Detect Function and Specified Bandwidth with Maximum Hold Mode. f. If the emission level of the EUT in peak mode was 10dB lower than the limit specified, then testing could be stopped and the peak values of the EUT would be reported. Otherwise the emissions that did not have 10dB margin would be re-tested one by one using peak, quasi-peak or average method as specified and then reported in a data sheet. g. Test the EUT in the lowest channel (2402MHz), the middle channel (2441MHz), the Highest channel (2480MHz) h. The radiation measurements are performed in X, Y, Z axis positioning for Transmitting mode, and found the X axis positioning which it is the worst case. i. Repeat above procedures until all frequencies measured was complete.
Exploratory Test Mode:	Non-hopping transmitting mode with all kind of modulation and all kind of data type Transmitting mode
Final Test Mode:	Through Pre-scan, find the DH5 of data type and GFSK modulation is the worst case. For below 1GHz part, through pre-scan, the worst case is the highest channel. Only the worst case is recorded in the report.
Test Results:	Pass

5.10.1 Radiated Emission below 1GHz

30MHz~1GHz		
Test mode:	Transmitting	Vertical

F9101W



	Freq	Read Level	Factor	Level	Limit Line	Over Limit	Remark	Pol/Phase
	MHz	dBuV	dB/m	dBuV/m	dBuV/m	dB		
1	235.82	23.59	14.79	38.38	46.00	-7.62	Peak	VERTICAL
2	269.43	22.95	16.17	39.12	46.00	-6.88	Peak	VERTICAL
3	284.98	24.22	16.52	40.74	46.00	-5.26	Peak	VERTICAL
4	323.32	19.39	17.46	36.85	46.00	-9.15	Peak	VERTICAL
5	537.59	13.37	21.44	34.81	46.00	-11.19	Peak	VERTICAL
6 pp	866.09	12.62	28.73	41.35	46.00	-4.65	Peak	VERTICAL

Remark:


The field strength is calculated by adding the Antenna Factor, Cable Factor & Preamplifier. The basic equation with a sample calculation is as follows:

Factor= Antenna Factor + Cable Factor – Preamplifier Factor,

Level = Read Level + Factor,

Over Limit=Level-Limit Line.


Test mode:	Transmitting	Horizontal
------------	--------------	------------



	Freq	Read Level	Factor	Level	Limit Line	Over Limit	Remark	Pol/Phase
	MHz	dBuV	dB/m	dBuV/m	dBuV/m	dB		
1	71.83	16.20	9.27	25.47	40.00	-14.53	Peak	HORIZONTAL
2	154.82	30.09	8.96	39.05	43.50	-4.45	Peak	HORIZONTAL
3 pk	207.12	26.71	12.52	39.23	43.50	-4.27	Peak	HORIZONTAL
4	246.81	27.90	15.63	43.53	46.00	-2.47	QP	HORIZONTAL
5 pp	308.91	28.20	17.10	45.30	46.00	-0.70	QP	HORIZONTAL
6	893.86	10.11	29.20	39.31	46.00	-6.69	Peak	HORIZONTAL

30MHz~1GHz		
Test mode:	Transmitting	Vertical

JP01



	Freq	Read Level	Factor	Level	Limit Line	Over Limit	Remark	Pol/Phase
	MHz	dBuV	dB/m	dBuV/m	dBuV/m	dB		
1	54.07	15.66	12.77	28.43	40.00	-11.57	Peak	VERTICAL
2	228.49	23.90	13.97	37.87	46.00	-8.13	Peak	VERTICAL
3	242.53	23.10	15.42	38.52	46.00	-7.48	Peak	VERTICAL
4	280.02	23.92	16.41	40.33	46.00	-5.67	Peak	VERTICAL
5	506.48	13.20	21.02	34.22	46.00	-11.78	Peak	VERTICAL
6 pp	866.09	13.51	28.73	42.24	46.00	-3.76	Peak	VERTICAL

Remark:


The field strength is calculated by adding the Antenna Factor, Cable Factor & Preamplifier. The basic equation with a sample calculation is as follows:

Factor= Antenna Factor + Cable Factor – Preamplifier Factor,

Level = Read Level + Factor,

Over Limit=Level-Limit Line.


Test mode:	Transmitting	Horizontal
------------	--------------	------------



	Read			Limit	Over		
Freq	Level	Factor	Level	Line	Limit	Remark	Pol/Phase
MHz	dBuV	dB/m	dBuV/m	dBuV/m	dB		
1	154.82	29.39	8.96	38.35	43.50	-5.15	Peak
2	pk 204.24	26.85	12.44	39.29	43.50	-4.21	Peak
3	pp 313.28	28.30	17.21	45.51	46.00	-0.49	QP
4	497.68	12.07	20.86	32.93	46.00	-13.07	Peak
5	699.30	11.17	23.74	34.91	46.00	-11.09	Peak
6	866.09	11.10	28.73	39.83	46.00	-6.17	Peak

30MHz~1GHz		
Test mode:	Transmitting	Vertical

TY01



	Read		Limit	Over			
Freq	Level	Factor	Level	Line	Limit	Remark	Pol/Phase
MHz	dBuV	dB/m	dBuV/m	dBuV/m	dB		
1	31.84	19.63	8.40	28.03	40.00	-11.97 Peak	VERTICAL
2	125.01	13.12	9.50	22.62	43.50	-20.88 Peak	VERTICAL
3 pp	284.98	26.22	16.52	42.74	46.00	-3.26 Peak	VERTICAL
4	537.59	14.37	21.44	35.81	46.00	-10.19 Peak	VERTICAL
5	866.09	13.62	28.73	42.35	46.00	-3.65 Peak	VERTICAL
6	993.01	12.62	28.26	40.88	54.00	-13.12 Peak	VERTICAL

Remark:


The field strength is calculated by adding the Antenna Factor, Cable Factor & Preamplifier. The basic equation with a sample calculation is as follows:

Factor= Antenna Factor + Cable Factor – Preamplifier Factor,

Level = Read Level + Factor,

Over Limit=Level-Limit Line.


Test mode:	Transmitting	Horizontal
------------	--------------	------------



	Read			Limit	Over		
Freq	Level	Factor	Level	Line	Limit	Remark	Pol/Phase
MHz	dBuV	dB/m	dBuV/m	dBuV/m	dB		
1	152.13	27.98	8.85	36.83	43.50	-6.67 Peak	HORIZONTAL
2 pk	203.52	26.06	12.42	38.48	43.50	-5.02 Peak	HORIZONTAL
3	246.81	28.46	15.63	44.09	46.00	-1.91 QP	HORIZONTAL
4 pp	305.68	27.17	17.01	44.18	46.00	-1.82 QP	HORIZONTAL
5	893.86	10.11	29.20	39.31	46.00	-6.69 Peak	HORIZONTAL
6	996.50	11.19	28.28	39.47	54.00	-14.53 Peak	HORIZONTAL

30MHz~1GHz		
Test mode:	Transmitting	Vertical

TY02



	Freq	Read Level	Factor	Level	Limit Line	Over Limit	Remark	Pol/Phase
	MHz	dBuV	dB/m	dBuV/m	dBuV/m	dB		
1	30.00	19.67	8.11	27.78	40.00	-12.22	Peak	VERTICAL
2	54.07	15.66	12.77	28.43	40.00	-11.57	Peak	VERTICAL
3	202.81	23.32	12.40	35.72	43.50	-7.78	Peak	VERTICAL
4	228.49	24.90	13.97	38.87	46.00	-7.13	Peak	VERTICAL
5	280.02	24.92	16.41	41.33	46.00	-4.67	Peak	VERTICAL
6 pp	866.09	13.51	28.73	42.24	46.00	-3.76	Peak	VERTICAL

Remark:


The field strength is calculated by adding the Antenna Factor, Cable Factor & Preamplifier. The basic equation with a sample calculation is as follows:

Factor= Antenna Factor + Cable Factor – Preamplifier Factor,

Level = Read Level + Factor,

Over Limit=Level-Limit Line.


Test mode:	Transmitting	Horizontal
------------	--------------	------------



	Freq	Read	Factor	Level	Limit	Over	Remark	Pol/Phase
	MHz	dBuV	dB/m	dBuV/m	dBuV/m	dB		
1	71.83	15.39	9.27	24.66	40.00	-15.34	Peak	HORIZONTAL
2	154.82	29.39	8.96	38.35	43.50	-5.15	Peak	HORIZONTAL
3	210.79	25.94	12.62	38.56	43.50	-4.94	Peak	HORIZONTAL
4 pk	248.55	26.17	15.68	41.85	46.00	-4.15	Peak	HORIZONTAL
5 pp	313.28	26.76	17.21	43.97	46.00	-2.03	QP	HORIZONTAL
6	893.86	9.77	29.20	38.97	46.00	-7.03	Peak	HORIZONTAL

30MHz~1GHz		
Test mode:	Transmitting	Vertical

FD01-B



	Freq	Read		Limit	Over		
	MHz	Level	Factor	Level	Limit	Limit	Remark
	MHz	dBuV	dB/m	dBuV/m	dBuV/m	dB	Pol/Phase
1	252.95	24.40	15.79	40.19	46.00	-5.81	Peak
2	284.98	26.22	16.52	42.74	46.00	-3.26	Peak
3	326.74	20.30	17.55	37.85	46.00	-8.15	Peak
4	440.20	14.54	19.21	33.75	46.00	-12.25	Peak
5	537.59	14.37	21.44	35.81	46.00	-10.19	Peak
6	866.09	12.62	28.73	41.35	46.00	-4.65	Peak

Remark:


The field strength is calculated by adding the Antenna Factor, Cable Factor & Preamplifier. The basic equation with a sample calculation is as follows:

Factor= Antenna Factor + Cable Factor – Preamplifier Factor,

Level = Read Level + Factor,

Over Limit=Level-Limit Line.


Test mode:	Transmitting	Horizontal
------------	--------------	------------



	Read			Limit	Over		
Freq	Level	Factor	Level	Line	Limit	Remark	Pol/Phase
MHz	dBuV	dB/m	dBuV/m	dBuV/m	dB		
1	71.83	16.20	9.27	25.47	40.00	-14.53 Peak	HORIZONTAL
2	154.82	29.09	8.96	38.05	43.50	-5.45 Peak	HORIZONTAL
3 pk	207.12	26.71	12.52	39.23	43.50	-4.27 Peak	HORIZONTAL
4	251.18	28.48	15.74	44.22	46.00	-1.78 QP	HORIZONTAL
5 pp	308.91	27.20	17.10	44.30	46.00	-1.70 QP	HORIZONTAL
6	893.86	10.11	29.20	39.31	46.00	-6.69 Peak	HORIZONTAL

30MHz~1GHz		
Test mode:	Transmitting	Vertical

F9090W



	Freq	Read		Limit	Over		
	MHz	Level	Factor	Level	Limit	Limit	Remark
	MHz	dBuV	dB/m	dBuV/m	dBuV/m	dB	Pol/Phase
1	30.11	20.58	8.12	28.70	40.00	-11.30	Peak
2	54.07	14.66	12.77	27.43	40.00	-12.57	Peak
3	228.49	22.90	13.97	36.87	46.00	-9.13	Peak
4	280.02	22.92	16.41	39.33	46.00	-6.67	Peak
5	506.48	13.20	21.02	34.22	46.00	-11.78	Peak
6 pp	866.09	12.51	28.73	41.24	46.00	-4.76	Peak

Remark:


The field strength is calculated by adding the Antenna Factor, Cable Factor & Preamplifier. The basic equation with a sample calculation is as follows:

Factor= Antenna Factor + Cable Factor – Preamplifier Factor,

Level = Read Level + Factor,

Over Limit=Level-Limit Line.


Test mode:	Transmitting	Horizontal
------------	--------------	------------



	Read			Limit	Over		
Freq	Level	Factor	Level	Line	Limit	Remark	Pol/Phase
MHz	dBuV	dB/m	dBuV/m	dBuV/m	dB		
1	153.74	29.91	8.91	38.82	43.50	-4.68 Peak	HORIZONTAL
2 pk	204.24	26.85	12.44	39.29	43.50	-4.21 Peak	HORIZONTAL
3	248.55	28.17	15.68	43.85	46.00	-2.15 QP	HORIZONTAL
4 pp	313.28	26.76	17.21	43.97	46.00	-2.03 QP	HORIZONTAL
5	332.52	21.87	17.70	39.57	46.00	-6.43 Peak	HORIZONTAL
6	866.09	11.10	28.73	39.83	46.00	-6.17 Peak	HORIZONTAL

30MHz~1GHz		
Test mode:	Transmitting	Vertical

F9210W



	Freq	Read Level	Factor	Level	Limit Line	Over Limit	Remark	Pol/Phase
	MHz	dBuV	dB/m	dBuV/m	dBuV/m	dB		
1	156.46	20.41	9.03	29.44	43.50	-14.06	Peak	VERTICAL
2	235.82	23.59	14.79	38.38	46.00	-7.62	Peak	VERTICAL
3	284.98	24.22	16.52	40.74	46.00	-5.26	Peak	VERTICAL
4	323.32	19.39	17.46	36.85	46.00	-9.15	Peak	VERTICAL
5	440.20	13.54	19.21	32.75	46.00	-13.25	Peak	VERTICAL
6 pp	866.09	12.62	28.73	41.35	46.00	-4.65	Peak	VERTICAL

Remark:


The field strength is calculated by adding the Antenna Factor, Cable Factor & Preamplifier. The basic equation with a sample calculation is as follows:

Factor= Antenna Factor + Cable Factor – Preamplifier Factor,

Level = Read Level + Factor,

Over Limit=Level-Limit Line.


Test mode:	Transmitting	Horizontal
------------	--------------	------------



	Read			Limit	Over		
	Freq	Level	Factor	Level	Line	Limit	Remark
	MHz	dBuV	dB/m	dBuV/m	dBuV/m	dB	Pol/Phase
1	71.83	16.20	9.27	25.47	40.00	-14.53	Peak
2 pk	154.82	29.09	8.96	38.05	43.50	-5.45	Peak
3	212.27	25.02	12.66	37.68	43.50	-5.82	Peak
4 pp	265.68	28.50	16.08	44.58	46.00	-1.42	QP
5	308.91	27.20	17.10	44.30	46.00	-1.70	QP
6	893.86	10.11	29.20	39.31	46.00	-6.69	Peak

30MHz~1GHz		
Test mode:	Transmitting	Vertical

OB01-B



	Read Freq	Read Level	Factor	Level	Limit Line	Over Limit	Remark	Pol/Phase
	MHz	dBuV	dB/m	dBuV/m	dBuV/m	dB		
1	228.49	25.90	13.97	39.87	46.00	-6.13	Peak	VERTICAL
2	251.18	25.57	15.74	41.31	46.00	-4.69	Peak	VERTICAL
3 pp	280.02	25.92	16.41	42.33	46.00	-3.67	Peak	VERTICAL
4	332.52	22.58	17.70	40.28	46.00	-5.72	Peak	VERTICAL
5	716.68	12.29	23.93	36.22	46.00	-9.78	Peak	VERTICAL
6	866.09	13.51	28.73	42.24	46.00	-3.76	Peak	VERTICAL

Remark:


The field strength is calculated by adding the Antenna Factor, Cable Factor & Preamplifier. The basic equation with a sample calculation is as follows:

Factor= Antenna Factor + Cable Factor – Preamplifier Factor,

Level = Read Level + Factor,

Over Limit=Level-Limit Line.


Test mode:	Transmitting	Horizontal
------------	--------------	------------



		Read		Limit	Over		
	Freq	Level	Factor	Level	Line	Limit	Remark
	MHz	dBuV	dB/m	dBuV/m	dBuV/m	dB	Pol/Phase
1	pk	154.82	29.39	8.96	38.35	43.50	-5.15 Peak
2		199.29	25.08	12.25	37.33	43.50	-6.17 Peak
3		256.52	24.95	15.87	40.82	46.00	-5.18 Peak
4	pp	313.28	27.60	17.21	44.81	46.00	-1.19 QP
5		699.30	11.17	23.74	34.91	46.00	-11.09 Peak
6		866.09	11.10	28.73	39.83	46.00	-6.17 Peak

30MHz~1GHz		
Test mode:	Transmitting	Vertical

F9095W



	Read			Limit	Over		
Freq	Level	Factor	Level	Line	Limit	Remark	Pol/Phase
MHz	dBuV	dB/m	dBuV/m	dBuV/m	dB		
1	55.41	12.76	25.52	40.00	-14.48	Peak	VERTICAL
2	157.56	23.11	32.17	43.50	-11.33	Peak	VERTICAL
3	278.07	24.76	41.12	46.00	-4.88	Peak	VERTICAL
4	326.74	21.30	38.85	46.00	-7.15	Peak	VERTICAL
5	537.59	12.37	33.81	46.00	-12.19	Peak	VERTICAL
6 pp	866.09	12.62	41.35	46.00	-4.65	Peak	VERTICAL

Remark:


The field strength is calculated by adding the Antenna Factor, Cable Factor & Preamplifier. The basic equation with a sample calculation is as follows:

Factor= Antenna Factor + Cable Factor – Preamplifier Factor,

Level = Read Level + Factor,

Over Limit=Level-Limit Line.


Test mode:	Transmitting	Horizontal
------------	--------------	------------



	Freq	Read Level	Factor	Level	Limit	Over Limit	Remark	Pol/Phase
	MHz	dBuV	dB/m	dBuV/m	dBuV/m	dB		
1	154.82	28.09	8.96	37.05	43.50	-6.45	Peak	HORIZONTAL
2	179.39	27.19	10.31	37.50	43.50	-6.00	Peak	HORIZONTAL
3 pk	211.53	25.83	12.64	38.47	43.50	-5.03	Peak	HORIZONTAL
4 pp	246.81	28.46	15.63	44.09	46.00	-1.91	QP	HORIZONTAL
5	301.42	26.89	16.90	43.79	46.00	-2.21	QP	HORIZONTAL
6	893.86	10.11	29.20	39.31	46.00	-6.69	Peak	HORIZONTAL

30MHz~1GHz		
Test mode:	Transmitting	Vertical

F9093W



	Freq	Read		Limit	Over		
	MHz	Level	Factor	Line	Limit	Remark	Pol/Phase
	MHz	dBuV	dB/m	dBuV/m	dBuV/m	dB	
1	30.11	20.58	8.12	28.70	40.00	-11.30 Peak	VERTICAL
2	54.07	16.66	12.77	29.43	40.00	-10.57 Peak	VERTICAL
3	154.82	20.92	8.96	29.88	43.50	-13.62 Peak	VERTICAL
4	228.49	24.90	13.97	38.87	46.00	-7.13 Peak	VERTICAL
5	282.99	24.22	16.48	40.70	46.00	-5.30 Peak	VERTICAL
6 pp	866.09	13.51	28.73	42.24	46.00	-3.76 Peak	VERTICAL

Remark:


The field strength is calculated by adding the Antenna Factor, Cable Factor & Preamplifier. The basic equation with a sample calculation is as follows:

Factor= Antenna Factor + Cable Factor – Preamplifier Factor,

Level = Read Level + Factor,

Over Limit=Level-Limit Line.


Test mode:	Transmitting	Horizontal
------------	--------------	------------



	Read			Limit	Over		
Freq	Level	Factor	Level	Line	Limit	Remark	Pol/Phase
MHz	dBuV	dB/m	dBuV/m	dBuV/m	dB		
1	157.56	29.04	9.06	38.10	43.50	-5.40 Peak	HORIZONTAL
2	204.24	27.85	12.44	40.29	43.50	-3.21 Peak	HORIZONTAL
3 pk	248.55	27.17	15.68	42.85	46.00	-3.15 Peak	HORIZONTAL
4 pp	313.28	26.60	17.21	43.81	46.00	-2.19 QP	HORIZONTAL
5	866.09	11.10	28.73	39.83	46.00	-6.17 Peak	HORIZONTAL
6	932.27	11.93	27.92	39.85	46.00	-6.15 Peak	HORIZONTAL

30MHz~1GHz		
Test mode:	Transmitting	Vertical

FD02-B



	Freq	Read		Limit	Over		
	MHz	Level	Factor	Level	Line	Limit	Remark
	MHz	dBuV	dB/m	dBuV/m	dBuV/m	dB	Pol/Phase
1	30.00	19.62	8.11	27.73	40.00	-12.27	Peak
2	53.69	11.94	12.76	24.70	40.00	-15.30	Peak
3	156.46	19.41	9.03	28.44	43.50	-15.06	Peak
4	235.82	24.59	14.79	39.38	46.00	-6.62	Peak
5 pp	284.98	25.22	16.52	41.74	46.00	-4.26	Peak
6	304.61	20.62	16.99	37.61	46.00	-8.39	Peak

Remark:


The field strength is calculated by adding the Antenna Factor, Cable Factor & Preamplifier. The basic equation with a sample calculation is as follows:

Factor= Antenna Factor + Cable Factor – Preamplifier Factor,

Level = Read Level + Factor,

Over Limit=Level-Limit Line.


Test mode:	Transmitting	Horizontal
------------	--------------	------------



		Read		Limit	Over		
	Freq	Level	Factor	Level	Line	Limit	Remark
	MHz	dBuV	dB/m	dBuV/m	dBuV/m	dB	Pol/Phase
1	pk	152.13	29.98	8.85	38.83	43.50	-4.67 Peak
2		186.44	26.02	10.98	37.00	43.50	-6.50 Peak
3		211.53	25.83	12.64	38.47	43.50	-5.03 Peak
4		246.81	27.76	15.63	43.39	46.00	-2.61 QP
5	pp	292.06	28.01	16.69	44.70	46.00	-1.30 QP
6		893.86	10.11	29.20	39.31	46.00	-6.69 Peak

30MHz~1GHz		
Test mode:	Transmitting	Vertical

F9074W



	Freq	Read		Limit	Over		
	MHz	Level	Factor	Level	Line	Limit	Remark
		dBuV	dB/m	dBuV/m	dBuV/m	dB	
1	228.49	22.90	13.97	36.87	46.00	-9.13	Peak
2	242.53	22.10	15.42	37.52	46.00	-8.48	Peak
3	280.02	22.92	16.41	39.33	46.00	-6.67	Peak
4	443.29	14.71	19.28	33.99	46.00	-12.01	Peak
5	506.48	14.20	21.02	35.22	46.00	-10.78	Peak
6 pp	866.09	13.51	28.73	42.24	46.00	-3.76	Peak

Remark:


The field strength is calculated by adding the Antenna Factor, Cable Factor & Preamplifier. The basic equation with a sample calculation is as follows:

Factor= Antenna Factor + Cable Factor – Preamplifier Factor,

Level = Read Level + Factor,

Over Limit=Level-Limit Line.


Test mode:	Transmitting	Horizontal
------------	--------------	------------



	Freq	Read Level	Factor	Level	Limit Line	Over Limit	Remark	Pol/Phase
	MHz	dBuV	dB/m	dBuV/m	dBuV/m	dB		
1	154.82	28.39	8.96	37.35	43.50	-6.15	Peak	HORIZONTAL
2	204.24	25.85	12.44	38.29	43.50	-5.21	Peak	HORIZONTAL
3	243.38	25.94	15.48	41.42	46.00	-4.58	Peak	HORIZONTAL
4	259.23	27.48	15.93	43.41	46.00	-2.59	Peak	HORIZONTAL
5 pp	313.28	28.76	17.21	45.97	46.00	-0.03	Peak	HORIZONTAL
6	866.09	10.10	28.73	38.83	46.00	-7.17	Peak	HORIZONTAL

30MHz~1GHz		
Test mode:	Transmitting	Vertical

LN01-F



	Freq	Read Level	Factor	Level	Limit Line	Over Limit	Remark	Pol/Phase
	MHz	dBuV	dB/m	dBuV/m	dBuV/m	dB		
1	235.82	24.59	14.79	39.38	46.00	-6.62	Peak	VERTICAL
2	284.98	24.22	16.52	40.74	46.00	-5.26	Peak	VERTICAL
3	323.32	21.39	17.46	38.85	46.00	-7.15	Peak	VERTICAL
4	440.20	14.54	19.21	33.75	46.00	-12.25	Peak	VERTICAL
5	719.20	14.37	23.96	38.33	46.00	-7.67	Peak	VERTICAL
6 pp	866.09	12.62	28.73	41.35	46.00	-4.65	Peak	VERTICAL

Remark:


The field strength is calculated by adding the Antenna Factor, Cable Factor & Preamplifier. The basic equation with a sample calculation is as follows:

Factor= Antenna Factor + Cable Factor – Preamplifier Factor,

Level = Read Level + Factor,

Over Limit=Level-Limit Line.

Test mode:	Transmitting	Horizontal
------------	--------------	------------



	Freq	Read Level	Factor	Level	Limit Line	Over Limit	Remark	Pol/Phase
	MHz	dBuV	dB/m	dBuV/m	dBuV/m	dB		
1 pk	157.01	28.09	9.05	37.14	43.50	-6.36	Peak	HORIZONTAL
2	199.29	24.78	12.25	37.03	43.50	-6.47	Peak	HORIZONTAL
3	275.16	28.10	16.30	44.40	46.00	-1.60	QP	HORIZONTAL
4 pp	313.28	28.10	17.21	45.31	46.00	-0.69	QP	HORIZONTAL
5	533.83	11.05	21.39	32.44	46.00	-13.56	Peak	HORIZONTAL
6	893.86	10.11	29.20	39.31	46.00	-6.69	Peak	HORIZONTAL

ReMark:

The field strength is calculated by adding the Antenna Factor, Cable Factor & Preamplifier. The basic equation with a sample calculation is as follows:

Factor= Antenna Factor + Cable Factor – Preamplifier Factor,

Level = Read Level + Factor,

Over Limit=Level-Limit Line.

5.10.2 Transmitter Emission above 1GHz

Worse case mode:		GFSK(DH5)		Test channel:		Lowest			
Frequency	Meter Reading	Factor	Emission Level	Limits	Over	Detect or Type	Ant. Pol.	Antenna Height	Table Angle
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)		H/V	(m)	(Degree)
2390	54.38	-9.2	45.18	74	-28.82	Peak	H	1.5	310
2400	55.59	-9.39	46.20	74	-27.80	Peak	H	1.5	58
4804	52.62	-4.33	48.29	74	-25.71	Peak	H	1.5	144
7206	49.27	1.01	50.28	74	-23.72	Peak	H	1.5	31
2390	55.63	-9.2	46.43	74	-27.57	Peak	V	1.5	117
2400	54.75	-9.39	45.36	74	-28.64	Peak	V	1.5	283
4804	55.00	-4.33	50.67	74	-23.33	Peak	V	1.5	178
7206	50.93	1.01	51.94	74	-22.06	Peak	V	1.5	321

Worse case mode:		GFSK(DH5)		Test channel:		Middle			
Frequency	Meter Reading	Factor	Emission Level	Limits	Over	Detect or Type	Ant. Pol.	Antenna Height	Table Angle
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)		H/V	(m)	(Degree)
4882	51.68	-4.11	47.57	74	-26.43	peak	H	1.5	21
7323	48.33	1.51	49.84	74	-24.16	peak	H	1.5	209
4882	52.92	-4.11	48.81	74	-25.19	peak	V	1.5	77
7323	50.46	1.51	51.97	74	-22.03	peak	V	1.5	219

Worse case mode:		GFSK(DH5)		Test channel:		Highest			
Frequency	Meter Reading	Factor	Emission Level	Limits	Over	Detect or Type	Ant. Pol.	Antenna Height	Table Angle
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)		H/V	(m)	(Degree)
2483.5	54.86	-9.29	45.57	74	-28.43	Peak	H	1.5	168
4960	50.93	-4.04	46.89	74	-27.11	Peak	H	1.5	3
7440	50.05	1.57	51.62	74	-22.38	Peak	H	1.5	6
2483.5	55.61	-9.29	46.32	74	-27.68	Peak	V	1.5	310
4960	48.31	-4.04	44.27	74	-29.73	Peak	V	1.5	80
7440	49.14	1.57	50.71	74	-23.29	Peak	V	1.5	89

Worse case mode:		$\pi/4$ DQPSK (2DH5)		Test channel:		Lowest			
Frequency	Meter Reading	Factor	Emission Level	Limits	Over	Detect or Type	Ant. Pol.	Antenna Height	Table Angle
(MHz)	(dB μ V)	(dB)	(dB μ V/m)	(dB μ V/m)	(dB)		H/V	(m)	(Degree)
2390	55.88	-9.2	46.68	74	-27.32	Peak	H	1.5	109
2400	55.79	-9.39	46.40	74	-27.60	Peak	H	1.5	37
4804	53.01	-4.33	48.68	74	-25.32	Peak	H	1.5	32
7206	49.66	1.01	50.67	74	-23.33	Peak	H	1.5	319
2390	55.97	-9.2	46.77	74	-27.23	Peak	V	1.5	246
2400	56.58	-9.39	47.19	74	-26.81	Peak	V	1.5	56
4804	52.80	-4.33	48.47	74	-25.53	Peak	V	1.5	78
7206	48.43	1.01	49.44	74	-24.56	Peak	V	1.5	114

Worse case mode:		$\pi/4$ DQPSK (2DH5)		Test channel:		Middle			
Frequency	Meter Reading	Factor	Emission Level	Limits	Over	Detect or Type	Ant. Pol.	Antenna Height	Table Angle
(MHz)	(dB μ V)	(dB)	(dB μ V/m)	(dB μ V/m)	(dB)		H/V	(m)	(Degree)
4882	52.69	-4.11	48.58	74	-25.42	peak	H	1.5	340
7323	49.92	1.51	51.43	74	-22.57	peak	H	1.5	192
4882	51.55	-4.11	47.44	74	-26.56	peak	V	1.5	105
7323	48.41	1.51	49.92	74	-24.08	peak	V	1.5	36

Worse case mode:		$\pi/4$ DQPSK (2DH5)		Test channel:		Highest			
Frequency	Meter Reading	Factor	Emission Level	Limits	Over	Detect or Type	Ant. Pol.	Antenna Height	Table Angle
(MHz)	(dB μ V)	(dB)	(dB μ V/m)	(dB μ V/m)	(dB)		H/V	(m)	(Degree)
2483.5	56.56	-9.29	47.27	74	-26.73	Peak	H	1.5	170
4960	53.04	-4.04	49.00	74	-25.00	Peak	H	1.5	25
7440	49.07	1.57	50.64	74	-23.36	Peak	H	1.5	47
2483.5	53.30	-9.29	44.01	74	-29.99	Peak	V	1.5	278
4960	48.79	-4.04	44.75	74	-29.25	Peak	V	1.5	348
7440	50.92	1.57	52.49	74	-21.51	Peak	V	1.5	198

Worse case mode:		8DPSK (3DH5)		Test channel:		Lowest			
Frequency	Meter Reading	Factor	Emission Level	Limits	Over	Detect or Type	Ant. Pol.	Antenna Height	Table Angle
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)		H/V	(m)	(Degree)
2390	55.02	-9.2	45.82	74	-28.18	Peak	H	1.5	197
2400	56.44	-9.39	47.05	74	-26.95	Peak	H	1.5	76
4804	53.92	-4.33	49.59	74	-24.41	Peak	H	1.5	106
7206	50.87	1.01	51.88	74	-22.12	Peak	H	1.5	91
2390	56.03	-9.2	46.83	74	-27.17	Peak	V	1.5	243
2400	55.79	-9.39	46.40	74	-27.60	Peak	V	1.5	293
4804	54.51	-4.33	50.18	74	-23.82	Peak	V	1.5	245
7206	49.13	1.01	50.14	74	-23.86	Peak	V	1.5	80

Worse case mode:		8DPSK (3DH5)		Test channel:		Middle			
Frequency	Meter Reading	Factor	Emission Level	Limits	Over	Detect or Type	Ant. Pol.	Antenna Height	Table Angle
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)		H/V	(m)	(Degree)
4882	50.60	-4.11	46.49	74	-27.51	peak	H	1.5	208
7323	50.18	1.51	51.69	74	-22.31	peak	H	1.5	71
4882	52.72	-4.11	48.61	74	-25.39	peak	V	1.5	330
7323	49.46	1.51	50.97	74	-23.03	peak	V	1.5	247

Worse case mode:		8DPSK (3DH5)		Test channel:		Highest			
Frequency	Meter Reading	Factor	Emission Level	Limits	Over	Detect or Type	Ant. Pol.	Antenna Height	Table Angle
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)		H/V	(m)	(Degree)
2483.5	54.73	-9.29	45.44	74	-28.56	Peak	H	1.5	77
4960	51.19	-4.04	47.15	74	-26.85	Peak	H	1.5	330
7440	49.02	1.57	50.59	74	-23.41	Peak	H	1.5	164
2483.5	54.46	-9.29	45.17	74	-28.83	Peak	V	1.5	8
4960	50.82	-4.04	46.78	74	-27.22	Peak	V	1.5	302
7440	49.12	1.57	50.69	74	-23.31	Peak	V	1.5	303


Remark:

- The field strength is calculated by adding the Antenna Factor, Cable Factor & Preamplifier. The basic equation with a sample calculation is as follows:
Final Test Level = Receiver Reading + Antenna Factor + Cable Factor – Preamplifier Factor
- Scan from 9kHz to 25GHz, the disturbance above 10GHz and below 30MHz was very low. As shown in this section, for frequencies above 1GHz, the field strength limits are based on average limits. However, the peak field strength of any emission shall not exceed the maximum permitted average limits specified above by more than 20 dB under any condition of modulation. So, only the peak measurements were shown in the report.


6 Photographs - EUT Test Setup

6.1 Radiated Emission

9KHz~30MHz:



30MHz~1GHz:



Above 1GHz:



6.2 RF Conducted measurement

7 Photographs - EUT Constructional Details

Refer to PHOTOGRAPHS OF EUT for External photos and Internal photos.

*** END OF REPORT ***