



FCC RF Test Report

APPLICANT : Qingdao Chuangjian Weilai Technology Co., Ltd
EQUIPMENT : VR All-In-One Headset
BRAND NAME : PICO
MODEL NAME : A9210
FCC ID : 2A5NV-A9210
STANDARD : FCC Part 15 Subpart C §15.247
CLASSIFICATION : (DTS) Digital Transmission System
TEST DATE(S) : May 06, 2024 ~ May 22, 2024

We, Sporton International Inc. (Kunshan), would like to declare that the tested sample has been evaluated in accordance with the test procedures and has been in compliance with the applicable technical standards.

The test results in this report apply exclusively to the tested model / sample. Without written approval of Sporton International Inc. (Kunshan), the test report shall not be reproduced except in full.

Jason Jia

Approved by: Jason Jia



Sporton International Inc. (Kunshan)

**No. 1098, Pengxi North Road, Kunshan Economic Development Zone Jiangsu Province 215300
People's Republic of China**



TABLE OF CONTENTS

REVISION HISTORY.....	3
SUMMARY OF TEST RESULT	4
1 GENERAL DESCRIPTION.....	5
1.1 Applicant.....	5
1.2 Manufacturer.....	5
1.3 Product Feature of Equipment Under Test.....	5
1.4 Product Specification of Equipment Under Test.....	5
1.5 Modification of EUT	6
1.6 Testing Location	7
1.7 Test Software.....	7
1.8 Applicable Standards.....	7
2 TEST CONFIGURATION OF EQUIPMENT UNDER TEST.....	8
2.1 Carrier Frequency Channel	8
2.2 Test Mode.....	9
2.3 Connection Diagram of Test System.....	10
2.4 Support Unit used in test configuration and system	11
2.5 EUT Operation Test Setup	11
2.6 Measurement Results Explanation Example.....	11
3 TEST RESULT	12
3.1 6dB and 99% Bandwidth Measurement	12
3.2 Output Power Measurement.....	13
3.3 Power Spectral Density Measurement	14
3.4 Conducted Band Edges and Spurious Emission Measurement	15
3.5 Radiated Band Edges and Spurious Emission Measurement	16
3.6 AC Conducted Emission Measurement.....	20
3.7 Antenna Requirements.....	22
4 LIST OF MEASURING EQUIPMENT.....	23
5 MEASUREMENT UNCERTAINTY.....	24
APPENDIX A. CONDUCTED TEST RESULTS	
APPENDIX B. AC CONDUCTED EMISSION TEST RESULT	
APPENDIX C. RADIATED SPURIOUS EMISSION	
APPENDIX D. DUTY CYCLE PLOTS	
APPENDIX E. SETUP PHOTOGRAPHS	



REVISION HISTORY

REPORT NO.	VERSION	DESCRIPTION	ISSUED DATE
FR432502D	Rev. 01	Initial issue of report	Jun. 11, 2024

SUMMARY OF TEST RESULT

Report Section	FCC Rule	Description	Limit	Result	Remark
3.1	15.247(a)(2)	6dB Bandwidth	$\geq 0.5\text{MHz}$	Pass	-
3.1	-	99% Bandwidth	-	Report only	-
3.2	15.247(b)(3)	Peak Output Power	$\leq 30\text{dBm}$	Pass	-
3.3	15.247(e)	Power Spectral Density	$\leq 8\text{dBm}/3\text{kHz}$	Pass	-
3.4	15.247(d)	Conducted Band Edges and Spurious Emission	$\leq 20\text{dBc}$	Pass	-
3.5	15.247(d)	Radiated Band Edges and Spurious Emission	15.209(a) & 15.247(d)	Pass	Under limit 3.07 dB at 2483.500 MHz
3.6	15.207	AC Conducted Emission	15.207(a)	Pass	Under limit 18.25 dB at 0.186 MHz
3.7	15.203 & 15.247(b)	Antenna Requirement	15.203 & 15.247(b)	Pass	-

Conformity Assessment Condition:

- The test results (PASS/FAIL) with all measurement uncertainty excluded are presented against the regulation limits or in accordance with the requirements stipulated by the applicant/manufacture who shall bear all the risks of non-compliance that may potentially occur if measurement uncertainty is taken into account.
- The measurement uncertainty please refer to each test result in the section "Measurement Uncertainty"

Disclaimer:

The product specifications of the EUT presented in the test report that may affect the test assessments are declared by the manufacturer who shall take full responsibility for the authenticity.

1 General Description

1.1 Applicant

Qingdao Chuangjian Weilai Technology Co., Ltd

3rd Floor, Building 4, No. 393 Songling Road, Laoshan District, Qingdao City, Shandong Province
PEOPLE'S REPUBLIC OF CHINA

1.2 Manufacturer

Qingdao Chuangjian Weilai Technology Co., Ltd

3rd Floor, Building 4, No. 393 Songling Road, Laoshan District, Qingdao City, Shandong Province
PEOPLE'S REPUBLIC OF CHINA

1.3 Product Feature of Equipment Under Test

Product Feature	
Equipment	VR All-In-One Headset
Brand Name	 PICO
Model Name	A9210
FCC ID	2A5NV-A9210
SN	Conducted: HMD2PB4030100417M Conduction: HMD2PB4031201018M Radiation: HMD2PB4031201018M
HW Version	Sparrow_HMD_MB_VER1P0
SW Version	c000_rf01_bv1.0.1_sv6.0.0_202403140018_sparrow_b371
EUT Stage	Production Unit

Remark: The above EUT's information was declared by manufacturer. Please refer to the specifications or user's manual for more detailed description.

1.4 Product Specification of Equipment Under Test

Standards-related Product Specification	
Tx/Rx Frequency Range	2402 MHz ~ 2480 MHz
Number of Channels	40
Maximum Output Power to Antenna	<ANT1>: 6.24 dBm (0.0042 W) <ANT2>: 6.16 dBm (0.0041 W)
99% Occupied Bandwidth	<ANT1>: 2.038MHz <ANT2>: 2.038MHz
Antenna Type / Gain	<ANT1>: FPC Antenna with gain 3.77 dBi <ANT2>: FPC Antenna with gain 2.77 dBi
Type of Modulation	nRF: GFSK

Note: The device supports nRF SISO mode only.



1.5 Modification of EUT

No modifications are made to the EUT during all test items.

1.6 Testing Location

Sporton International Inc. (Kunshan) is accredited to ISO/IEC 17025:2017 by American Association for Laboratory Accreditation with Certificate Number 5145.02.

Test Firm	Sporton International Inc. (Kunshan)		
Test Site Location	No. 1098, Pengxi North Road, Kunshan Economic Development Zone Jiangsu Province 215300 People's Republic of China TEL : +86-512-57900158		
Test Site No.	Sporton Site No.	FCC Designation No.	FCC Test Firm Registration No.
	CO01-KS 03CH06-KS TH01-KS	CN1257	314309

1.7 Test Software

Item	Site	Manufacturer	Name	Version
1.	TH01-KS	Tonscend	JS1120-3 test system China_210602	3.3.10
2.	03CH06-KS	AUDIX	E3	210616
3.	CO01-KS	AUDIX	E3	6.2009-8-24

1.8 Applicable Standards

According to the specifications of the manufacturer, the EUT must comply with the requirements of the following standards:

- ♦ 47 CFR Part 15 Subpart C §15.247
- ♦ FCC KDB 558074 D01 15.247 Meas Guidance v05r02
- ♦ ANSI C63.10-2013

Remark:

1. All test items were verified and recorded according to the standards and without any deviation during the test.
2. This EUT has also been tested and complied with the requirements of FCC Part 15, Subpart B, recorded in a separate test report.



2 Test Configuration of Equipment Under Test

2.1 Carrier Frequency Channel

Frequency Band	Channel	Freq. (MHz)	Channel	Freq. (MHz)
2400-2483.5 MHz	0	2402	21	2444
	1	2404	22	2446
	2	2406	23	2448
	3	2408	24	2450
	4	2410	25	2452
	5	2412	26	2454
	6	2414	27	2456
	7	2416	28	2458
	8	2418	29	2460
	9	2420	30	2462
	10	2422	31	2464
	11	2424	32	2466
	12	2426	33	2468
	13	2428	34	2470
	14	2430	35	2472
	15	2432	36	2474
	16	2434	37	2476
	17	2436	38	2478
	18	2438	39	2480
	19	2440	-	-
	20	2442	-	-



2.2 Test Mode


- a. The EUT has been associated with peripherals and configuration operated in a manner tended to maximize its emission characteristics in a typical application. Frequency range investigated: r conduction emission (150 kHz to 30 MHz), Radiation emission (9 kHz to the 10th harmonic of the highest fundamental frequency or to 40 GHz, whichever is lower). For radiated measurement, pre-scanned in three orthogonal panels, X, Y, Z. The worst cases (X plane) were recorded in this report.
- b. AC power line Conducted Emission was tested under maximum output power.

The following summary table is showing all test modes to demonstrate in compliance with the standard.


Summary table of Test Cases	
Test Item	Data Rate / Modulation
	nRF / GFSK
Conducted TCs	Mode 1: nRF TX CH00_2402 MHz Mode 2: nRF TX CH19_2440 MHz Mode 3: nRF TX CH39_2480 MHz
Radiated TCs	Mode 1: nRF TX CH00_2402 MHz Mode 2: nRF TX CH19_2440 MHz Mode 3: nRF TX CH39_2480 MHz
AC Conducted Emission	Mode 1: nRF Tx + Bluetooth Link + WLAN Link (2.4G) + USB Cable (Charging from Adapter)
Remark: For Radiated Test Cases, The tests were performed with Adapter and USB Cable.	

2.3 Connection Diagram of Test System

AC Conducted Emission:



Radiated Emission:



2.4 Support Unit used in test configuration and system

Item	Equipment	Trade Name	Model Name	FCC ID	Data Cable	Power Cord
1.	WLAN AP	D-Link	DIR-628	KA2DIR628A2	N/A	Unshielded, 1.8 m
2.	Bluetooth Earphone	Lenovo	thinkplus-BH3	N/A	N/A	N/A
3.	Notebook	Lenovo	G480	QDS-BRCM1050I	N/A	shielded cable DC O/P 1.8m , Unshielded AC I/P cable 1.8m
4.	Adapter	N/A	N/A	N/A	N/A	N/A
5.	Controllers	PICO	N/A	N/A	N/A	N/A

2.5 EUT Operation Test Setup

For nRF function, the engineering test program was provided and enabled to make EUT continuous transmit.

For AC power line conducted emissions, the EUT was set to connect with the WLAN AP under large package sizes transmission.

2.6 Measurement Results Explanation Example

For all conducted test items:

The offset level is set in the spectrum analyzer to compensate the RF cable loss and attenuator factor between EUT conducted output port and spectrum analyzer. With the offset compensation, the spectrum analyzer reading level is exactly the EUT RF output level.

Example :

The spectrum analyzer offset is derived from RF cable loss and attenuator factor.

Offset = RF cable loss + attenuator factor.

Following shows an offset computation example with cable loss 2.19 dB and 10dB attenuator.

$$\begin{aligned}
 \text{Offset(dB)} &= \text{RF cable loss(dB)} + \text{attenuator factor(dB)}. \\
 &= 2.19 + 10 = 12.19 \text{ (dB)}
 \end{aligned}$$

3 Test Result

3.1 6dB and 99% Bandwidth Measurement

3.1.1 Limit of 6dB and 99% Bandwidth

The minimum 6 dB bandwidth shall be at least 500 kHz.


3.1.2 Measuring Instruments

The section 4.0 of List of Measuring Equipment of this test report is used for test.

3.1.3 Test Procedures

1. The testing follows ANSI C63.10-2013 clause 11.8
2. The RF output of EUT was connected to the spectrum analyzer by RF cable and attenuator. The path loss was compensated to the results for each measurement.
3. Set to the maximum power setting and enable the EUT transmit continuously.
4. Make the measurement with the spectrum analyzer's resolution bandwidth (RBW) = 100 kHz. Set the Video bandwidth (VBW) = 300 kHz. In order to make an accurate measurement. The 6 dB bandwidth must be greater than 500 kHz.
5. For 99% Bandwidth Measurement, the spectrum analyzer's resolution bandwidth (RBW) is set 1% to 5% of the 99% OBW and the VBW is set to 3 times of the RBW.
6. Measure and record the results in the test report.

3.1.4 Test Setup



3.1.5 Test Result of 6dB Bandwidth and 99% Occupied Bandwidth

Please refer to Appendix A.

3.2 Output Power Measurement

3.2.1 Limit of Output Power

For systems using digital modulation in the 2400-2483.5MHz, the limit for peak output power is 30dBm. If transmitting antenna of directional gain greater than 6dBi is used, the peak output power from the intentional radiator shall be reduced below the above stated value by the amount in dB that the directional gain of the antenna exceeds 6 dBi. In case of point-to-point operation, the limit has to be reduced by 1dB for every 3dB that the directional gain of the antenna exceeds 6dBi.


3.2.2 Measuring Instruments

The section 4.0 of List of Measuring Equipment of this test report is used for test.

3.2.3 Test Procedures

1. The testing follows the Measurement Procedure of ANSI C63.10-2013 clause 11.9.1.3 PKPM1 Peak power meter or ANSI C63.10-2013 clause 11.9.2.3.1 Method AVGPM method.
2. The RF output of EUT was connected to the power meter by RF cable and attenuator. The path loss was compensated to the results for each measurement.
3. Set to the maximum power setting and enable the EUT transmit continuously.
4. Measure the conducted output power and record the results in the test report.

3.2.4 Test Setup



3.2.5 Test Result of Peak Output Power

Please refer to Appendix A.

3.2.6 Test Result of Average Output Power (Reporting Only)

Please refer to Appendix A.

3.3 Power Spectral Density Measurement

3.3.1 Limit of Power Spectral Density

The peak power spectral density shall not be greater than 8dBm in any 3kHz band at any time interval of continuous transmission.


3.3.2 Measuring Instruments

The section 4.0 of List of Measuring Equipment of this test report is used for test.

3.3.3 Test Procedures

1. The testing follows Measurement Procedure of ANSI C63.10-2013 clause 11.10.2 Method PKPSD.
2. The RF output of EUT was connected to the spectrum analyzer by RF cable and attenuator. The path loss was compensated to the results for each measurement.
3. Set to the maximum power setting and enable the EUT transmit continuously.
4. Make the measurement with the spectrum analyzer's resolution bandwidth (RBW) = 3 kHz. Video bandwidth VBW = 10 kHz In order to make an accurate measurement, set the span to 1.5 times DTS Channel Bandwidth. (6dB BW)
5. Detector = peak, Sweep time = auto couple, Trace mode = max hold, Allow trace to fully stabilize. Use the peak marker function to determine the maximum power level.
6. Measure and record the results in the test report.
7. The Measured power density (dBm)/ 100kHz is a reference level and used as 20dBc down limit line for Conducted Band Edges and Conducted Spurious Emission.

3.3.4 Test Setup



3.3.5 Test Result of Power Spectral Density

Please refer to Appendix A.

3.3.6 Test Result of Power Spectral Density Plots (100kHz and 3kHz)

Please refer to Appendix A.

3.4 Conducted Band Edges and Spurious Emission Measurement

3.4.1 Limit of Conducted Band Edges and Spurious Emission

All harmonics/spurious must be at least 20 dB down from the highest emission level within the authorized band.


3.4.2 Measuring Instruments

The section 4.0 of List of Measuring Equipment of this test report is used for test.

3.4.3 Test Procedure

1. The testing follows ANSI C63.10-2013 clause 11.13
2. The RF output of EUT was connected to the spectrum analyzer by RF cable and attenuator. The path loss was compensated to the results for each measurement.
3. Set to the maximum power setting and enable the EUT transmit continuously.
4. Set RBW = 100 kHz, VBW=300 kHz, Peak Detector. Unwanted Emissions measured in any 100 kHz bandwidth outside of the authorized frequency band shall be attenuated by at least 20 dB relative to the maximum in-band peak PSD level in 100 kHz when maximum peak conducted output power procedure is used. If the transmitter complies with the conducted power limits based on the use of RMS averaging over a time interval, the attenuation required under this paragraph shall be 30 dB instead of 20 dB.
5. Measure and record the results in the test report.
6. The RF fundamental frequency should be excluded against the limit line in the operating frequency band.

3.4.4 Test Setup



3.4.5 Test Result of Conducted Band Edges and Conducted Spurious Emission Plots

Please refer to Appendix A.

3.5 Radiated Band Edges and Spurious Emission Measurement

3.5.1 Limit of Radiated Band Edges and Spurious Emission

In any 100 kHz bandwidth outside the intentional radiator frequency band, all harmonics/spurious must be at least 20 dB below the highest emission level within the authorized band. If the output power of this device was measured by spectrum analyzer, the attenuation under this paragraph shall be 30 dB instead of 20 dB. In addition, radiated emissions which fall in the restricted bands must also comply with the limits as below.

Frequency (MHz)	Field Strength (microvolts/meter)	Measurement Distance (meters)
0.009 – 0.490	2400/F(kHz)	300
0.490 – 1.705	24000/F(kHz)	30
1.705 – 30.0	30	30
30 – 88	100	3
88 – 216	150	3
216 - 960	200	3
Above 960	500	3

3.5.2 Measuring Instruments


The section 4.0 of List of Measuring Equipment of this test report is used for test.

3.5.3 Test Procedures


1. The testing follows ANSI C63.10-2013 clause 11.11 & 11.12
2. The EUT was arranged to its worst case and then tune the antenna tower (from 1 m to 4 m) and turntable (from 0 degree to 360 degrees) to find the maximum reading. A pre-amp and a high pass filter are used for the test in order to get better signal level.
3. The EUT was placed on a turntable with 0.8 meter for frequency below 1GHz and 1.5 meter for frequency above 1GHz respectively above ground.
4. The EUT was set 3 meters from the interference receiving antenna, which was mounted on the top of a variable height antenna tower.
5. Corrected Reading: Antenna Factor + Cable Loss + Read Level - Preamp Factor = Level
6. For testing below 1GHz, if the emission level of the EUT in peak mode was 3 dB lower than the limit specified, then peak values of EUT will be reported, otherwise, the emissions will be repeated one by one using the CISPR quasi-peak method and reported.
7. For testing above 1GHz, the emission level of the EUT in peak mode was 20dB lower than peak limit (that means the emission level in average mode also complies with the limit in average mode), then peak values of EUT will be reported, otherwise, the emissions will be measured in average mode again and reported.
8. Use the following spectrum analyzer settings:
 - (1) Span shall wide enough to fully capture the emission being measured;
 - (2) Set RBW=100 kHz for $f < 1$ GHz; $VBW \geq RBW$; Sweep = auto; Detector function = peak; Trace = max hold;
 - (3) Set RBW = 1 MHz, VBW= 3MHz for $f \geq 1$ GHz for peak measurement.
For average measurement:
 - $VBW = 10$ Hz, when duty cycle is no less than 98 percent.
 - $VBW \geq 1/T$, when duty cycle is less than 98 percent where T is the minimum transmission duration over which the transmitter is on and is transmitting at its maximum power control level for the tested mode of operation.

3.5.4 Test Setup


For radiated emissions below 30MHz



For radiated emissions from 30MHz to 1GHz



For radiated emissions above 1GHz



**3.5.5 Test Results of Radiated Spurious Emissions (9 kHz ~ 30 MHz)**

The low frequency, which started from 9 kHz to 30MHz, was pre-scanned and the result which was 20dB lower than the limit line was not reported.

There is a comparison data of both open-field test site and semi-Anechoic chamber, and the result came out very similar.

3.5.6 Test Result of Radiated Spurious at Band Edges

Please refer to Appendix C.

3.5.7 Duty Cycle

Please refer to Appendix D.

3.5.8 Test Result of Radiated Spurious Emission (30MHz ~ 10th Harmonic or 40GHz, whichever is lower)

Please refer to Appendix C.

3.6 AC Conducted Emission Measurement

3.6.1 Limit of AC Conducted Emission

For equipment that is designed to be connected to the public utility (AC) power line, the radio frequency voltage that is conducted back onto the AC power line on any frequency or frequencies within the band 150 kHz to 30 MHz shall not exceed the limits in the following table.

Frequency of emission (MHz)	Conducted limit (dB μ V)	
	Quasi-peak	Average
0.15-0.5	66 to 56*	56 to 46*
0.5-5	56	46
5-30	60	50

*Decreases with the logarithm of the frequency.


3.6.2 Measuring Instruments

The section 4.0 of List of Measuring Equipment of this test report is used for test.

3.6.3 Test Procedures

1. The EUT was placed 0.4 meter from the conducting wall of the shielding room was kept at least 80 centimeters from any other grounded conducting surface.
2. Connect EUT to the power mains through a line impedance stabilization network (LISN).
3. All the support units are connecting to the other LISN.
4. The LISN provides 50 ohm coupling impedance for the measuring instrument.
5. The FCC states that a 50 ohm, 50 microhenry LISN should be used.
6. Both sides of AC line were checked for maximum conducted interference.
7. The frequency range from 150 kHz to 30 MHz was searched.
8. Set the test-receiver system to Peak Detect Function and specified bandwidth (IF Bandwidth = 9kHz) with Maximum Hold Mode. Then measurement is also conducted by Average Detector and Quasi-Peak Detector Function respectively.

3.6.4 Test Setup



3.6.5 Test Result of AC Conducted Emission

Please refer to Appendix B.



3.7 Antenna Requirements

3.7.1 Standard Applicable

If directional gain of transmitting antennas is greater than 6dBi, the power shall be reduced by the same level in dB comparing to gain minus 6dBi. The use of a permanently attached antenna or of an antenna that uses a unique coupling to the intentional radiator shall be considered sufficient to comply with the rule.

3.7.2 Antenna Anti-Replacement Construction

An embedded-in antenna design is used.

3.7.3 Antenna Gain

The antenna peak gain of EUT is less than 6 dBi. Therefore, it is not necessary to reduce maximum peak output power limit.



4 List of Measuring Equipment

Instrument	Manufacturer	Model No.	Serial No.	Characteristics	Calibration Date	Test Date	Due Date	Remark
Spectrum Analyzer	R&S	FSV40	101040	10Hz~40GHz	Oct. 11, 2023	May 06, 2024~ May 11, 2024	Oct. 10, 2024	Conducted (TH01-KS)
Pulse Power Sensor	Anritsu	MA2411B	0917070	300MHz~40GHz	Jan. 02, 2024	May 06, 2024~ May 11, 2024	Jan. 01, 2025	Conducted (TH01-KS)
Power Meter	Anritsu	ML2495A	1005002	50MHz Bandwidth	Jan. 02, 2024	May 06, 2024~ May 11, 2024	Jan. 01, 2025	Conducted (TH01-KS)
EMI Test Receiver	Keysight	N9038A	MY56400004	3Hz~8.5GHz; Max 30dBm	Oct. 10, 2023	May 22, 2024	Oct. 09, 2024	Radiation (03CH06-KS)
EXA Spectrum Analyzer	Keysight	N9010B	MY60242126	10Hz~44GHz	Oct. 10, 2023	May 22, 2024	Oct. 09, 2024	Radiation (03CH06-KS)
Loop Antenna	R&S	HFH2-Z2	100321	9kHz~30MHz	Oct. 10, 2023	May 22, 2024	Oct. 09, 2024	Radiation (03CH06-KS)
Bilog Antenna	TeseQ	CBL6111D	59913	30MHz~1GHz	Aug. 19, 2023	May 22, 2024	Aug. 18, 2024	Radiation (03CH06-KS)
Double Ridge Horn Antenna	ETS-Lindgren	3117	00240132	1GHz~18GHz	Jul. 12, 2023	May 22, 2024	Jul. 11, 2024	Radiation (03CH06-KS)
SHF-EHF Horn	Com-power	AH-840	101093	18GHz~40GHz	Jan. 05, 2024	May 22, 2024	Jan. 04, 2025	Radiation (03CH06-KS)
Amplifier	SONOMA	310N	380827	9KHz ~1GHZ	Jul. 06, 2023	May 22, 2024	Jul. 05, 2024	Radiation (03CH06-KS)
Amplifier	MITEQ	EM18G40GGA	060728	18~40GHz	Jan. 04, 2024	May 22, 2024	Jan. 03, 2025	Radiation (03CH06-KS)
high gain Amplifier	MITEQ	AMF-7D-0010 1800-30-10P	2082395	1Ghz-18Ghz	Jan. 04, 2024	May 22, 2024	Jan. 03, 2025	Radiation (03CH06-KS)
Amplifier	Keysight	83017A	MY53270319	500MHz~26.5GHz	Oct. 10, 2023	May 22, 2024	Oct. 09, 2024	Radiation (03CH06-KS)
AC Power Source	Chroma	61601	F104090004	N/A	NCR	May 22, 2024	NCR	Radiation (03CH06-KS)
Turn Table	ChamPro	EM 1000-T	060762-T	0~360 degree	NCR	May 22, 2024	NCR	Radiation (03CH06-KS)
Antenna Mast	ChamPro	EM 1000-A	060762-A	1 m~4 m	NCR	May 22, 2024	NCR	Radiation (03CH06-KS)
EMI Receiver	R&S	ESCI7	100768	9kHz~7GHz;	May 16, 2023	May 08, 2024	May 15, 2024	Conduction (CO01-KS)
AC LISN (for auxiliary equipment)	MessTec	AN3016	060103	9kHz~30MHz	Oct. 11, 2023	May 08, 2024	Oct. 10, 2024	Conduction (CO01-KS)
AC LISN	MessTec	AN3016	060105	9kHz~30MHz	May 16, 2023	May 08, 2024	May 15, 2024	Conduction (CO01-KS)
AC Power Source	Chroma	61602	ABP000000811	AC 0V~300V, 45Hz~1000Hz	Oct. 11, 2023	May 08, 2024	Oct. 10, 2024	Conduction (CO01-KS)

NCR: No Calibration Required

5 Measurement Uncertainty

The measurement uncertainties shown below were calculated in accordance with the requirements of ANSI 63.10-2013. All the measurement uncertainty value were shown with a coverage K=2 to indicate 95% level of confidence. The measurement data show herein meets or exceeds the CISPR measurement uncertainty values specified in CISPR 16-4-2 and can be compared directly to specified limit to determine compliance.

Uncertainty of Conducted Measurement

Conducted Spurious Emission & Bandedge	±2.26 dB
Occupied Channel Bandwidth	±0.1%
Conducted Power	±0.46 dB
Conducted Power Spectral Density	±0.88 dB
Frequency	±0.4 Hz

Uncertainty of AC Conducted Emission Measurement (0.15 MHz ~ 30 MHz)

Measuring Uncertainty for a Level of Confidence of 95% (U = 2Uc(y))	2.84 dB
---	---------

Uncertainty of Radiated Emission Measurement (9 KHz ~ 30 MHz)

Measuring Uncertainty for a Level of Confidence of 95% (U = 2Uc(y))	3.30 dB
---	---------

Uncertainty of Radiated Emission Measurement (30 MHz ~ 1000 MHz)

Measuring Uncertainty for a Level of Confidence of 95% (U = 2Uc(y))	6.06 dB
---	---------

Uncertainty of Radiated Emission Measurement (1 GHz ~ 18 GHz)

Measuring Uncertainty for a Level of Confidence of 95% (U = 2Uc(y))	5.18 dB
---	---------

Uncertainty of Radiated Emission Measurement (18 GHz ~ 40 GHz)

Measuring Uncertainty for a Level of Confidence of 95% (U = 2Uc(y))	5.38 dB
---	---------

----- THE END -----



Appendix A. Conducted Test Results

DTS Bandwidth


Test Result

TestMode	Antenna	Freq(MHz)	DTS BW [MHz]	FL[MHz]	FH[MHz]	Limit[MHz]	Verdict
NRF_2M	Ant1	2402	1.13	2401.43	2402.56	0.5	PASS
	Ant2	2402	1.14	2401.42	2402.56	0.5	PASS
	Ant1	2440	1.15	2439.42	2440.56	0.5	PASS
	Ant2	2440	1.14	2439.42	2440.56	0.5	PASS
	Ant1	2480	1.14	2479.42	2480.56	0.5	PASS
	Ant2	2480	1.14	2479.42	2480.56	0.5	PASS




Test Graphs


NRF_2M_Ant1_2402



NRF_2M_Ant2_2402




NRF_2M_Ant1_2440




Date: 6.MAY.2024 09:25:03

NRF_2M_Ant2_2440




Date: 11.MAY.2024 07:18:06

NRF_2M_Ant1_2480



Date: 6.MAY.2024 09:26:44

NRF_2M_Ant2_2480



Date: 11.MAY.2024 07:19:43

Occupied Channel Bandwidth


Test Result

TestMode	Antenna	Freq(MHz)	OCB [MHz]	FL[MHz]	FH[MHz]	Limit[MHz]	Verdict
NRF_2M	Ant1	2402	2.034	2400.9810	2403.0150	---	---
	Ant2	2402	2.038	2400.9770	2403.0150	---	---
	Ant1	2440	2.038	2438.9810	2441.0190	---	---
	Ant2	2440	2.038	2438.9770	2441.0150	---	---
	Ant1	2480	2.038	2478.9810	2481.0190	---	---
	Ant2	2480	2.038	2478.9810	2481.0190	---	---




Test Graphs


NRF_2M_Ant1_2402



NRF_2M_Ant2_2402




NRF_2M_Ant1_2440




Date: 6.MAY.2024 09:25:09

NRF_2M_Ant2_2440




Date: 11.MAY.2024 07:18:16

NRF_2M_Ant1_2480



Date: 6.MAY.2024 09:26:55

NRF_2M_Ant2_2480



Date: 11.MAY.2024 07:19:54

Maximum conducted output power

Test Result Peak

TestMode	Antenna	CH.	Peak Conducted Power (dBm)	Conducted Power Limit	DG (dBi)	EIRP Power (dBm)	EIRP Power Limit	Pass/Fail
NRF2M	Ant1	0	6.24	30.00	3.77	10.01	36.00	Pass
		19	6.22	30.00	3.77	9.99	36.00	Pass
		39	6.21	30.00	3.77	9.98	36.00	Pass
NRF2M	Ant2	0	6.10	30.00	2.77	8.87	36.00	Pass
		19	6.16	30.00	2.77	8.93	36.00	Pass
		39	6.12	30.00	2.77	8.89	36.00	Pass

Test Result Average (report only)

TestMode	Antenna	CH.	Duty Factor (dB)	Average Conducted Power (dBm)
NRF2M	Ant1	0	4.89	6.10
		19	4.89	6.21
		39	4.89	6.12
NRF2M	Ant2	0	4.89	6.06
		19	4.89	6.13
		39	4.89	6.10

Note: Power setting is 8


Maximum power spectral density

Test Result


TestMode	Antenna	Freq(MHz)	Result[dBm/3kHz]	Limit[dBm/3kHz]	Verdict
NRF_2M	Ant1	2402	-11.66	≤8.00	PASS
	Ant2	2402	-11.81	≤8.00	PASS
	Ant1	2440	-11.76	≤8.00	PASS
	Ant2	2440	-11.95	≤8.00	PASS
	Ant1	2480	-11.44	≤8.00	PASS
	Ant2	2480	-11.49	≤8.00	PASS

Test Graphs


NRF_2M_Ant1_2402



NRF_2M_Ant2_2402




NRF_2M_Ant1_2440




Date: 6.MAY.2024 09:25:25

NRF_2M_Ant2_2440




Date: 11.MAY.2024 07:18:30

NRF_2M_Ant1_2480



Date: 6.MAY.2024 09:27:11

NRF_2M_Ant2_2480



Date: 11.MAY.2024 07:20:10


Reference level measurement

Test Result


TestMode	Antenna	Freq(MHz)	Max.Point[MHz]	Result[dBm/100KHz]
NRF_2M	Ant1	2402	2401.98	6.22
	Ant2	2402	2401.98	6.06
	Ant1	2440	2439.98	5.93
	Ant2	2440	2439.98	5.79
	Ant1	2480	2479.98	6.03
	Ant2	2480	2479.98	5.91

Test Graphs

NRF_2M_Ant1_2402




NRF_2M_Ant2_2402






NRF_2M_Ant1_2440




Date: 6.MAY.2024 09:25:37

NRF_2M_Ant2_2440




Date: 11.MAY.2024 07:18:43

NRF_2M_Ant1_2480



NRF_2M_Ant2_2480




Band edge measurements

Test Result


TestMode	Antenna	ChName	Freq(MHz)	RefLevel[dBm /100KHz]	Result[dBm /100KHz]	Limit[dBm /100KHz]	Verdict
NRF_2M	Ant1	Low	2402	6.22	-28.1	≤-13.78	PASS
	Ant2	Low	2402	6.06	-28.34	≤-13.94	PASS
	Ant1	High	2480	6.03	-42.49	≤-13.97	PASS
	Ant2	High	2480	5.91	-42.57	≤-14.09	PASS

Test Graphs

NRF_2M_Ant1_Low_2402




NRF_2M_Ant2_Low_2402






NRF_2M_Ant1_High_2480



Date: 6.MAY.2024 09:27:41

NRF_2M_Ant2_High_2480



Date: 11.MAY.2024 07:20:41


Conducted Spurious Emission

Test Result


TestMode	Antenna	Freq(MHz)	FreqRange [MHz]	RefLevel [dBm/100KHz]	Result [dBm/100KHz]	Limit [dBm/100KHz]	Verdict
NRF_2M	Ant1	2402	30~1000	6.22	-45.57	≤ -13.78	PASS
			1000~26500	6.22	-35.99	≤ -13.78	PASS
	Ant2	2402	30~1000	6.06	-44.91	≤ -13.94	PASS
			1000~26500	6.06	-36.4	≤ -13.94	PASS
	Ant1	2440	30~1000	5.93	-45.52	≤ -14.07	PASS
			1000~26500	5.93	-37.39	≤ -14.07	PASS
	Ant2	2440	30~1000	5.79	-45.29	≤ -14.21	PASS
			1000~26500	5.79	-36.19	≤ -14.21	PASS
	Ant1	2480	30~1000	6.03	-45.18	≤ -13.97	PASS
			1000~26500	6.03	-35.83	≤ -13.97	PASS
	Ant2	2480	30~1000	5.91	-45.6	≤ -14.09	PASS
			1000~26500	5.91	-36.14	≤ -14.09	PASS

Test Graphs


NRF_2M_Ant1_2402_30~1000




NRF_2M_Ant1_2402_1000~26500




NRF_2M_Ant2_2402_30~1000



NRF_2M_Ant2_2402_1000~26500




NRF_2M_Ant1_2440_30~1000




Date: 6.MAY.2024 09:25:48

NRF_2M_Ant1_2440_1000~26500




Date: 6.MAY.2024 09:26:04

NRF_2M_Ant2_2440_30~1000




Date: 11.MAY.2024 07:18:53

NRF_2M_Ant2_2440_1000~26500




Date: 11.MAY.2024 07:19:09


NRF_2M_Ant1_2480_30~1000



NRF_2M_Ant1_2480_1000~26500




NRF_2M_Ant2_2480_30~1000



Date: 11.MAY.2024 07:20:53

NRF_2M_Ant2_2480_1000~26500




Date: 11.MAY.2024 07:21:08



Appendix B. AC Conducted Emission Test Results

Test Engineer :	Amos Zhang	Temperature :	25.3~26.2°C
		Relative Humidity :	38~40%
Test Voltage :	120Vac / 60Hz	Phase :	Line
Remark :	All emissions not reported here are more than 10 dB below the prescribed limit.		




Site : CO01-KS

Condition : 15C RSS247-QP LISN-060105-L 2023 LINE

	Freq	Level	Over	Limit	Read	LISN	Cable	
	MHz	dBuV	Limit	Line	Level	Factor	Loss	Remark
			dB	dBuV	dBuV	dB	dB	
1 *	0.186	45.95	-18.25	64.20	35.51	0.03	10.41	QP
2	0.186	28.75	-25.45	54.20	18.31	0.03	10.41	Average
3	0.197	44.04	-19.72	63.76	33.60	0.03	10.41	QP
4	0.197	27.64	-26.12	53.76	17.20	0.03	10.41	Average
5	0.270	37.19	-23.93	61.12	26.80	0.04	10.35	QP
6	0.270	23.89	-27.23	51.12	13.50	0.04	10.35	Average
7	0.320	34.85	-24.86	59.71	24.50	0.03	10.32	QP
8	0.320	21.95	-27.76	49.71	11.60	0.03	10.32	Average
9	0.454	31.53	-25.27	56.80	21.30	-0.02	10.25	QP
10	0.454	22.43	-24.37	46.80	12.20	-0.02	10.25	Average
11	13.057	24.24	-35.76	60.00	13.30	-0.13	11.07	QP
12	13.057	18.24	-31.76	50.00	7.30	-0.13	11.07	Average



Test Engineer :	Amos Zhang	Temperature :	25.3~26.2°C
		Relative Humidity :	38~40%
Test Voltage :	120Vac / 60Hz	Phase :	Neutral
Remark :	All emissions not reported here are more than 10 dB below the prescribed limit.		



Site : CO01-KS
Condition : 15C RSS247-QP LISN-060105-N 2023 NEUTRAL

	Freq	Level	Over	Limit	Read	LISN	Cable	Remark
	MHz	dBuV	Limit	Line	Level	Factor	Loss	
			dB	dBuV	dBuV	dB	dB	
1	0.159	41.96	-23.56	65.52	31.50	0.04	10.42	QP
2	0.159	23.76	-31.76	55.52	13.30	0.04	10.42	Average
3 *	0.182	43.96	-20.46	64.42	33.50	0.05	10.41	QP
4	0.182	28.66	-25.76	54.42	18.20	0.05	10.41	Average
5	0.198	38.26	-25.45	63.71	27.80	0.05	10.41	QP
6	0.198	23.06	-30.65	53.71	12.60	0.05	10.41	Average
7	0.267	35.54	-25.66	61.20	25.19	-0.01	10.36	QP
8	0.267	20.94	-30.26	51.20	10.59	-0.01	10.36	Average
9	0.474	31.77	-24.68	56.45	21.61	-0.07	10.23	QP
10	0.474	23.47	-22.98	46.45	13.31	-0.07	10.23	Average
11	13.841	31.61	-28.39	60.00	20.60	-0.12	11.13	QP
12	13.841	25.91	-24.09	50.00	14.90	-0.12	11.13	Average

Note:

- Level(dBμV) = Read Level(dBμV) + LISN Factor(dB) + Cable Loss(dB)
- Over Limit(dB) = Level(dBμV) – Limit Line(dBμV)

Appendix C. Radiated Spurious Emission

Test Engineer :	Koi Ji	Relative Humidity :	41 ~ 42 %
		Temperature :	22 ~ 23 °C





Radiated Spurious Emission Test Modes

Mode	Band (MHz)	Antenna	Modulation	Channel	Frequency	Data Rate	RU	Remark
Mode 1	2400-2483.5	1	NRF	0	2402	2Mbps	-	-
Mode 2	2400-2483.5	1	NRF	19	2440	2Mbps	-	-
Mode 3	2400-2483.5	1	NRF	39	2480	2Mbps	-	-
Mode 4	2400-2483.5	2	NRF	0	2402	2Mbps	-	-
Mode 5	2400-2483.5	2	NRF	19	2440	2Mbps	-	-
Mode 6	2400-2483.5	2	NRF	39	2480	2Mbps	-	-





Summary of each worse mode

Mode	Modulation	Ch.	Freq. (MHz)	Level (dBuV/m)	Limit (dBuV/m)	Margin (dB)	Pol.	Peak Avg.	Result	Remark
1	NRF	0	2369.80	45.83	54.00	-8.17	H	AVERAGE	Pass	Band Edge
1	NRF	0	4804.00	44.06	74.00	-29.94	H	PEAK	Pass	Harmonic
2	NRF	19	-	-	-	-	-	-	-	Band Edge
2	NRF	19	4880.00	42.27	54.00	-11.73	H	AVERAGE	Pass	Harmonic
3	NRF	39	2483.50	50.93	54.00	-3.07	H	AVERAGE	Pass	Band Edge
3	NRF	39	7440.00	44.59	74.00	-29.41	H	PEAK	Pass	Harmonic
4	NRF	0	2372.14	45.37	54.00	-8.63	V	AVERAGE	Pass	Band Edge
4	NRF	0	4804.00	47.95	74.00	-26.05	H	PEAK	Pass	Harmonic
5	NRF	19	-	-	-	-	-	-	-	Band Edge
5	NRF	19	4880.00	40.86	54.00	-13.14	H	AVERAGE	Pass	Harmonic
6	NRF	39	2483.50	50.03	54.00	-3.97	H	AVERAGE	Pass	Band Edge
6	NRF	39	4960.00	45.26	74.00	-28.74	H	PEAK	Pass	Harmonic





Mode	1																																																						
	Band Edge																																																						
	2400-2483.5_NRF_CH0_2402MHz																																																						
ANT	1																																																						
Pol.	Horizontal																																																						
Peak	 Level (dBuV/m) Frequency (MHz) FCC PART 15C <table><thead><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2385.40</td><td>55.64</td><td>74.00</td><td>-18.36</td><td>43.46</td><td>31.77</td><td>6.60</td><td>32.19</td><td>6.00</td><td>128 125 PEAK</td></tr></tbody></table>												Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg	1	2385.40	55.64	74.00	-18.36	43.46	31.77	6.60	32.19	6.00	128 125 PEAK
		Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																													
	Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																												
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg																																													
1	2385.40	55.64	74.00	-18.36	43.46	31.77	6.60	32.19	6.00	128 125 PEAK																																													
Fundamental	 Level (dBuV/m) Frequency (MHz) FCC PART 15C <table><thead><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2402.00</td><td>105.56</td><td>-----</td><td>-----</td><td>93.32</td><td>31.80</td><td>6.62</td><td>32.18</td><td>6.00</td><td>128 125 PEAK</td></tr></tbody></table>												Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg	1	2402.00	105.56	-----	-----	93.32	31.80	6.62	32.18	6.00	128 125 PEAK
		Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																													
	Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																												
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg																																													
1	2402.00	105.56	-----	-----	93.32	31.80	6.62	32.18	6.00	128 125 PEAK																																													
Avg	 Level (dBuV/m) Frequency (MHz) FCC PART 15C (AVG) <table><thead><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2369.80</td><td>45.83</td><td>54.00</td><td>-8.17</td><td>33.71</td><td>31.74</td><td>6.57</td><td>32.19</td><td>6.00</td><td>128 125 AVERAGE</td></tr></tbody></table>												Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg	1	2369.80	45.83	54.00	-8.17	33.71	31.74	6.57	32.19	6.00	128 125 AVERAGE
		Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																													
	Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																												
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg																																													
1	2369.80	45.83	54.00	-8.17	33.71	31.74	6.57	32.19	6.00	128 125 AVERAGE																																													
Avg	 Level (dBuV/m) Frequency (MHz) FCC PART 15C (AVG) <table><thead><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2402.00</td><td>103.41</td><td>-----</td><td>-----</td><td>91.17</td><td>31.80</td><td>6.62</td><td>32.18</td><td>6.00</td><td>128 125 AVERAGE</td></tr></tbody></table>												Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg	1	2402.00	103.41	-----	-----	91.17	31.80	6.62	32.18	6.00	128 125 AVERAGE
		Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																													
	Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																												
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg																																													
1	2402.00	103.41	-----	-----	91.17	31.80	6.62	32.18	6.00	128 125 AVERAGE																																													



Mode	1																																																																																																	
	Band Edge																																																																																																	
	2400-2483.5_NRF_CH0_2402MHz																																																																																																	
ANT	1																																																																																																	
Pol.	Vertical						Fundamental																																																																																											
Peak																																																																																																		
	<table><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2378.64</td><td>55.46</td><td>74.00</td><td>-18.54</td><td>43.30</td><td>31.76</td><td>6.59</td><td>32.19</td><td>6.00</td><td>126 110 PEAK</td></tr></table>							Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2378.64	55.46	74.00	-18.54	43.30	31.76	6.59	32.19	6.00	126 110 PEAK	<table><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2402.00</td><td>103.05</td><td>-----</td><td>-----</td><td>90.81</td><td>31.80</td><td>6.62</td><td>32.18</td><td>6.00</td><td>126 110 PEAK</td></tr></table>						Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2402.00	103.05	-----	-----	90.81	31.80	6.62	32.18	6.00
	Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																									
Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																																																																								
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																								
1	2378.64	55.46	74.00	-18.54	43.30	31.76	6.59	32.19	6.00	126 110 PEAK																																																																																								
	Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																									
Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																																																																								
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																								
1	2402.00	103.05	-----	-----	90.81	31.80	6.62	32.18	6.00	126 110 PEAK																																																																																								
Avg																																																																																																		
	<table><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2371.75</td><td>45.22</td><td>54.00</td><td>-8.78</td><td>33.09</td><td>31.74</td><td>6.58</td><td>32.19</td><td>6.00</td><td>126 110 AVERAGE</td></tr></table>							Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2371.75	45.22	54.00	-8.78	33.09	31.74	6.58	32.19	6.00	126 110 AVERAGE	<table><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2402.00</td><td>100.94</td><td>-----</td><td>-----</td><td>88.70</td><td>31.80</td><td>6.62</td><td>32.18</td><td>6.00</td><td>126 110 AVERAGE</td></tr></table>						Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2402.00	100.94	-----	-----	88.70	31.80	6.62	32.18	6.00
	Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																									
Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																																																																								
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																								
1	2371.75	45.22	54.00	-8.78	33.09	31.74	6.58	32.19	6.00	126 110 AVERAGE																																																																																								
	Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																									
Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																																																																								
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																								
1	2402.00	100.94	-----	-----	88.70	31.80	6.62	32.18	6.00	126 110 AVERAGE																																																																																								







Mode	1																																																																																																	
	Harmonic																																																																																																	
	2400-2483.5_NRF_CH0_2402MHz																																																																																																	
ANT	1																																																																																																	
Pol.	Horizontal						Vertical																																																																																											
Peak Avg																																																																																																		
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>4804.00</td><td>44.06</td><td>74.00</td><td>-29.94</td><td>61.59</td><td>34.31</td><td>9.44</td><td>61.28</td><td>0.00</td><td>--</td><td>PEAK</td></tr></table>							Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	4804.00	44.06	74.00	-29.94	61.59	34.31	9.44	61.28	0.00	--	PEAK	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>4804.00</td><td>43.04</td><td>74.00</td><td>-30.96</td><td>60.57</td><td>34.31</td><td>9.44</td><td>61.28</td><td>0.00</td><td>--</td><td>PEAK</td></tr></table>							Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	4804.00	43.04	74.00	-30.96	60.57	34.31	9.44	61.28	0.00	--	PEAK
		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																									
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark																																																																																									
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																								
1	4804.00	44.06	74.00	-29.94	61.59	34.31	9.44	61.28	0.00	--	PEAK																																																																																							
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																										
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark																																																																																									
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																								
1	4804.00	43.04	74.00	-30.96	60.57	34.31	9.44	61.28	0.00	--	PEAK																																																																																							







Mode	2																																																																																	
	Harmonic																																																																																	
	2400-2483.5_NRF_CH19_2440MHz																																																																																	
ANT	1																																																																																	
Pol.	Horizontal						Vertical																																																																											
Peak Avg																																																																																		
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th>Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>4880.00</td><td>52.45</td><td>74.00</td><td>-21.55</td><td>69.80</td><td>34.34</td><td>9.53</td><td>61.22</td><td>0.00</td><td>100</td><td>85</td><td>PEAK</td></tr><tr><td>2</td><td>4880.00</td><td>42.27</td><td>54.00</td><td>-11.73</td><td>59.62</td><td>34.34</td><td>9.53</td><td>61.22</td><td>0.00</td><td>100</td><td>85</td><td>AVERAGE</td></tr><tr><td>3</td><td>7320.00</td><td>45.67</td><td>74.00</td><td>-28.33</td><td>58.93</td><td>35.80</td><td>11.69</td><td>60.75</td><td>0.00</td><td>--</td><td>--</td><td>PEAK</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg	1	4880.00	52.45	74.00	-21.55	69.80	34.34	9.53	61.22	0.00	100	85	PEAK	2	4880.00	42.27	54.00	-11.73	59.62	34.34	9.53	61.22	0.00	100	85	AVERAGE	3	7320.00	45.67	74.00	-28.33	58.93	35.80	11.69	60.75	0.00	--	--	PEAK
		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																									
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark																																																																									
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg																																																																								
1	4880.00	52.45	74.00	-21.55	69.80	34.34	9.53	61.22	0.00	100	85	PEAK																																																																						
2	4880.00	42.27	54.00	-11.73	59.62	34.34	9.53	61.22	0.00	100	85	AVERAGE																																																																						
3	7320.00	45.67	74.00	-28.33	58.93	35.80	11.69	60.75	0.00	--	--	PEAK																																																																						
<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th>Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>4880.00</td><td>43.34</td><td>74.00</td><td>-30.66</td><td>60.69</td><td>34.34</td><td>9.53</td><td>61.22</td><td>0.00</td><td>--</td><td>--</td><td>PEAK</td></tr><tr><td>2</td><td>7320.00</td><td>44.78</td><td>74.00</td><td>-29.22</td><td>58.04</td><td>35.80</td><td>11.69</td><td>60.75</td><td>0.00</td><td>--</td><td>--</td><td>PEAK</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg	1	4880.00	43.34	74.00	-30.66	60.69	34.34	9.53	61.22	0.00	--	--	PEAK	2	7320.00	44.78	74.00	-29.22	58.04	35.80	11.69	60.75	0.00	--	--	PEAK														
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																										
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark																																																																									
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg																																																																								
1	4880.00	43.34	74.00	-30.66	60.69	34.34	9.53	61.22	0.00	--	--	PEAK																																																																						
2	7320.00	44.78	74.00	-29.22	58.04	35.80	11.69	60.75	0.00	--	--	PEAK																																																																						





Mode	3																																																																																																					
	Band Edge																																																																																																					
	2400-2483.5_NRF_CH39_2480MHz																																																																																																					
ANT	1																																																																																																					
Pol.	Horizontal						Fundamental																																																																																															
Peak																																																																																																						
	<table><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2483.50</td><td>60.51</td><td>74.00</td><td>-13.49</td><td>48.04</td><td>31.97</td><td>6.73</td><td>32.23</td><td>6.00</td><td>127</td><td>121 PEAK</td></tr></table>							Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2483.50	60.51	74.00	-13.49	48.04	31.97	6.73	32.23	6.00	127	121 PEAK	<table><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2480.00</td><td>105.12</td><td>-----</td><td>-----</td><td>92.66</td><td>31.96</td><td>6.73</td><td>32.23</td><td>6.00</td><td>127</td><td>121 PEAK</td></tr></table>							Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2480.00	105.12	-----	-----	92.66	31.96	6.73	32.23	6.00	127	121 PEAK
		Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																												
Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																																																																												
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																												
1	2483.50	60.51	74.00	-13.49	48.04	31.97	6.73	32.23	6.00	127	121 PEAK																																																																																											
	Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																													
Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																																																																												
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																												
1	2480.00	105.12	-----	-----	92.66	31.96	6.73	32.23	6.00	127	121 PEAK																																																																																											
Avg																																																																																																						
	<table><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2483.50</td><td>50.93</td><td>54.00</td><td>-3.07</td><td>38.46</td><td>31.97</td><td>6.73</td><td>32.23</td><td>6.00</td><td>127</td><td>121 AVERAGE</td></tr></table>							Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2483.50	50.93	54.00	-3.07	38.46	31.97	6.73	32.23	6.00	127	121 AVERAGE	<table><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2480.00</td><td>103.01</td><td>-----</td><td>-----</td><td>90.55</td><td>31.96</td><td>6.73</td><td>32.23</td><td>6.00</td><td>127</td><td>121 AVERAGE</td></tr></table>							Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2480.00	103.01	-----	-----	90.55	31.96	6.73	32.23	6.00	127	121 AVERAGE
		Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																												
Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																																																																												
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																												
1	2483.50	50.93	54.00	-3.07	38.46	31.97	6.73	32.23	6.00	127	121 AVERAGE																																																																																											
	Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																													
Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																																																																												
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																												
1	2480.00	103.01	-----	-----	90.55	31.96	6.73	32.23	6.00	127	121 AVERAGE																																																																																											







Mode	3																																																																																																				
	Band Edge																																																																																																				
	2400-2483.5_NRF_CH39_2480MHz																																																																																																				
ANT	1																																																																																																				
Pol.	Vertical						Fundamental																																																																																														
Peak																																																																																																					
	<table><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2483.50</td><td>59.23</td><td>74.00</td><td>-14.77</td><td>46.76</td><td>31.97</td><td>6.73</td><td>32.23</td><td>6.00</td><td>158</td><td>114 PEAK</td></tr></table>							Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2483.50	59.23	74.00	-14.77	46.76	31.97	6.73	32.23	6.00	158	114 PEAK	<table><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2480.00</td><td>104.07</td><td>-----</td><td>-----</td><td>91.61</td><td>31.96</td><td>6.73</td><td>32.23</td><td>6.00</td><td>158</td><td>114 PEAK</td></tr></table>						Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2480.00	104.07	-----	-----	91.61	31.96	6.73	32.23	6.00	158	114 PEAK
		Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																											
Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																																																																											
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																											
1	2483.50	59.23	74.00	-14.77	46.76	31.97	6.73	32.23	6.00	158	114 PEAK																																																																																										
	Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																												
Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																																																																											
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																											
1	2480.00	104.07	-----	-----	91.61	31.96	6.73	32.23	6.00	158	114 PEAK																																																																																										
Avg																																																																																																					
	<table><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2483.56</td><td>50.07</td><td>54.00</td><td>-3.93</td><td>37.60</td><td>31.97</td><td>6.73</td><td>32.23</td><td>6.00</td><td>158</td><td>114 AVERAGE</td></tr></table>							Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2483.56	50.07	54.00	-3.93	37.60	31.97	6.73	32.23	6.00	158	114 AVERAGE	<table><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2480.00</td><td>101.94</td><td>-----</td><td>-----</td><td>89.48</td><td>31.96</td><td>6.73</td><td>32.23</td><td>6.00</td><td>158</td><td>114 AVERAGE</td></tr></table>						Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2480.00	101.94	-----	-----	89.48	31.96	6.73	32.23	6.00	158	114 AVERAGE
		Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																											
Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																																																																											
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																											
1	2483.56	50.07	54.00	-3.93	37.60	31.97	6.73	32.23	6.00	158	114 AVERAGE																																																																																										
	Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																												
Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																																																																											
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																											
1	2480.00	101.94	-----	-----	89.48	31.96	6.73	32.23	6.00	158	114 AVERAGE																																																																																										







Mode	3																																																																													
	Harmonic																																																																													
	2400-2483.5_NRF_CH39_2480MHz																																																																													
ANT	1																																																																													
Pol.	Horizontal											Vertical																																																																		
Peak Avg																																																																														
	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th colspan="4"></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th colspan="4">Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th colspan="2"></th></tr></thead><tbody><tr><td>1</td><td>4960.00</td><td>43.39</td><td>74.00</td><td>-30.61</td><td>60.68</td><td>34.26</td><td>9.61</td><td>61.16</td><td>0.00</td><td>--</td><td>--</td><td>PEAK</td></tr><tr><td>2</td><td>7440.00</td><td>44.59</td><td>74.00</td><td>-29.41</td><td>58.22</td><td>35.62</td><td>11.77</td><td>61.02</td><td>0.00</td><td>--</td><td>--</td><td>PEAK</td></tr></tbody></table>														Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos					Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg			1	4960.00	43.39	74.00	-30.61	60.68	34.26	9.61	61.16	0.00	--	--	PEAK	2	7440.00	44.59	74.00	-29.41	58.22	35.62	11.77	61.02	0.00	--	--	PEAK
		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																					
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark																																																																					
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg																																																																				
1	4960.00	43.39	74.00	-30.61	60.68	34.26	9.61	61.16	0.00	--	--	PEAK																																																																		
2	7440.00	44.59	74.00	-29.41	58.22	35.62	11.77	61.02	0.00	--	--	PEAK																																																																		
<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th colspan="4"></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th colspan="4">Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th colspan="2"></th></tr></thead><tbody><tr><td>1</td><td>4960.00</td><td>42.49</td><td>74.00</td><td>-31.51</td><td>59.78</td><td>34.26</td><td>9.61</td><td>61.16</td><td>0.00</td><td>--</td><td>--</td><td>PEAK</td></tr><tr><td>2</td><td>7440.00</td><td>44.09</td><td>74.00</td><td>-29.91</td><td>57.72</td><td>35.62</td><td>11.77</td><td>61.02</td><td>0.00</td><td>--</td><td>--</td><td>PEAK</td></tr></tbody></table>														Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos					Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg			1	4960.00	42.49	74.00	-31.51	59.78	34.26	9.61	61.16	0.00	--	--	PEAK	2	7440.00	44.09	74.00	-29.91	57.72	35.62	11.77	61.02	0.00	--	--	PEAK	
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																						
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark																																																																					
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg																																																																				
1	4960.00	42.49	74.00	-31.51	59.78	34.26	9.61	61.16	0.00	--	--	PEAK																																																																		
2	7440.00	44.09	74.00	-29.91	57.72	35.62	11.77	61.02	0.00	--	--	PEAK																																																																		





Mode	4																																																																																																						
	Band Edge																																																																																																						
	2400-2483.5_NRF_CH0_2402MHz																																																																																																						
ANT	2																																																																																																						
Pol.	Horizontal						Fundamental																																																																																																
Peak																																																																																																							
	<table><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2377.34</td><td>55.12</td><td>74.00</td><td>-18.88</td><td>42.98</td><td>31.75</td><td>6.58</td><td>32.19</td><td>6.00</td><td>122</td><td>343</td><td>PEAK</td></tr></table>							Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2377.34	55.12	74.00	-18.88	42.98	31.75	6.58	32.19	6.00	122	343	PEAK	<table><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2402.00</td><td>103.75</td><td>-----</td><td>-----</td><td>91.51</td><td>31.80</td><td>6.62</td><td>32.18</td><td>6.00</td><td>122</td><td>343</td><td>PEAK</td></tr></table>							Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2402.00	103.75	-----	-----	91.51	31.80	6.62	32.18	6.00	122	343
	Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																														
Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																																																																													
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																													
1	2377.34	55.12	74.00	-18.88	42.98	31.75	6.58	32.19	6.00	122	343	PEAK																																																																																											
	Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																														
Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																																																																													
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																													
1	2402.00	103.75	-----	-----	91.51	31.80	6.62	32.18	6.00	122	343	PEAK																																																																																											
Avg																																																																																																							
	<table><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2388.91</td><td>45.24</td><td>54.00</td><td>-8.76</td><td>33.04</td><td>31.78</td><td>6.60</td><td>32.18</td><td>6.00</td><td>122</td><td>343</td><td>AVERAGE</td></tr></table>							Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2388.91	45.24	54.00	-8.76	33.04	31.78	6.60	32.18	6.00	122	343	AVERAGE	<table><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2402.00</td><td>101.63</td><td>-----</td><td>-----</td><td>89.39</td><td>31.80</td><td>6.62</td><td>32.18</td><td>6.00</td><td>122</td><td>343</td><td>AVERAGE</td></tr></table>							Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2402.00	101.63	-----	-----	89.39	31.80	6.62	32.18	6.00	122	343
	Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																														
Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																																																																													
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																													
1	2388.91	45.24	54.00	-8.76	33.04	31.78	6.60	32.18	6.00	122	343	AVERAGE																																																																																											
	Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																														
Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																																																																													
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																													
1	2402.00	101.63	-----	-----	89.39	31.80	6.62	32.18	6.00	122	343	AVERAGE																																																																																											





Mode	4																																																																																																			
	Band Edge																																																																																																			
	2400-2483.5_NRF_CH0_2402MHz																																																																																																			
ANT	2																																																																																																			
Pol.	Vertical						Fundamental																																																																																													
Peak																																																																																																				
	<table><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2354.85</td><td>55.48</td><td>74.00</td><td>-18.52</td><td>43.42</td><td>31.71</td><td>6.55</td><td>32.20</td><td>6.00</td><td>100</td><td>48 PEAK</td></tr></table>							Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2354.85	55.48	74.00	-18.52	43.42	31.71	6.55	32.20	6.00	100	48 PEAK	<table><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2402.00</td><td>103.03</td><td>-----</td><td>-----</td><td>90.79</td><td>31.80</td><td>6.62</td><td>32.18</td><td>6.00</td><td>100</td><td>48 PEAK</td></tr></table>						Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2402.00	103.03	-----	-----	90.79	31.80	6.62	32.18	6.00	100
	Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																											
Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																																																																										
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																										
1	2354.85	55.48	74.00	-18.52	43.42	31.71	6.55	32.20	6.00	100	48 PEAK																																																																																									
	Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																											
Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																																																																										
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																										
1	2402.00	103.03	-----	-----	90.79	31.80	6.62	32.18	6.00	100	48 PEAK																																																																																									
Avg																																																																																																				
	<table><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2372.14</td><td>45.37</td><td>54.00</td><td>-8.63</td><td>33.24</td><td>31.74</td><td>6.58</td><td>32.19</td><td>6.00</td><td>100</td><td>48 AVERAGE</td></tr></table>							Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2372.14	45.37	54.00	-8.63	33.24	31.74	6.58	32.19	6.00	100	48 AVERAGE	<table><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2402.00</td><td>100.91</td><td>-----</td><td>-----</td><td>88.67</td><td>31.80</td><td>6.62</td><td>32.18</td><td>6.00</td><td>100</td><td>48 AVERAGE</td></tr></table>						Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2402.00	100.91	-----	-----	88.67	31.80	6.62	32.18	6.00	100
	Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																											
Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																																																																										
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																										
1	2372.14	45.37	54.00	-8.63	33.24	31.74	6.58	32.19	6.00	100	48 AVERAGE																																																																																									
	Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																											
Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																																																																										
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																										
1	2402.00	100.91	-----	-----	88.67	31.80	6.62	32.18	6.00	100	48 AVERAGE																																																																																									







Mode	4																																																																																																	
	Harmonic																																																																																																	
	2400-2483.5_NRF_CH0_2402MHz																																																																																																	
ANT	2																																																																																																	
Pol.	Horizontal						Vertical																																																																																											
Peak Avg																																																																																																		
	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>4804.00</td><td>47.95</td><td>74.00</td><td>-26.05</td><td>65.48</td><td>34.31</td><td>9.44</td><td>61.28</td><td>0.00</td><td>--</td><td>PEAK</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	4804.00	47.95	74.00	-26.05	65.48	34.31	9.44	61.28	0.00	--	PEAK	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>4804.00</td><td>44.74</td><td>74.00</td><td>-29.26</td><td>62.27</td><td>34.31</td><td>9.44</td><td>61.28</td><td>0.00</td><td>--</td><td>PEAK</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	4804.00	44.74	74.00	-29.26	62.27	34.31	9.44	61.28	0.00	--	PEAK
		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																									
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark																																																																																									
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																								
1	4804.00	47.95	74.00	-26.05	65.48	34.31	9.44	61.28	0.00	--	PEAK																																																																																							
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																										
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark																																																																																									
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																								
1	4804.00	44.74	74.00	-29.26	62.27	34.31	9.44	61.28	0.00	--	PEAK																																																																																							







Mode	5																																																																																
	Harmonic																																																																																
	2400-2483.5_NRF_CH19_2440MHz																																																																																
ANT	2																																																																																
Pol.	Horizontal						Vertical																																																																										
Peak Avg																																																																																	
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th>Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th></th></tr><tr><td>1</td><td>4880.00</td><td>50.87</td><td>74.00</td><td>-23.13</td><td>68.22</td><td>34.34</td><td>9.53</td><td>61.22</td><td>0.00</td><td>128</td><td>65</td><td>PEAK</td></tr><tr><td>2</td><td>4880.00</td><td>40.86</td><td>54.00</td><td>-13.14</td><td>58.21</td><td>34.34</td><td>9.53</td><td>61.22</td><td>0.00</td><td>128</td><td>65</td><td>AVERAGE</td></tr><tr><td>3</td><td>7320.00</td><td>45.82</td><td>74.00</td><td>-28.18</td><td>59.08</td><td>35.00</td><td>11.69</td><td>60.75</td><td>0.00</td><td>--</td><td>--</td><td>PEAK</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB		1	4880.00	50.87	74.00	-23.13	68.22	34.34	9.53	61.22	0.00	128	65	PEAK	2	4880.00	40.86	54.00	-13.14	58.21	34.34	9.53	61.22	0.00	128	65	AVERAGE	3	7320.00	45.82	74.00	-28.18	59.08	35.00	11.69	60.75	0.00	--	--	PEAK
		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																								
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark																																																																								
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB																																																																									
1	4880.00	50.87	74.00	-23.13	68.22	34.34	9.53	61.22	0.00	128	65	PEAK																																																																					
2	4880.00	40.86	54.00	-13.14	58.21	34.34	9.53	61.22	0.00	128	65	AVERAGE																																																																					
3	7320.00	45.82	74.00	-28.18	59.08	35.00	11.69	60.75	0.00	--	--	PEAK																																																																					
<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th>Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th></th></tr><tr><td>1</td><td>4880.00</td><td>45.44</td><td>74.00</td><td>-28.56</td><td>62.79</td><td>34.34</td><td>9.53</td><td>61.22</td><td>0.00</td><td>--</td><td>--</td><td>PEAK</td></tr><tr><td>2</td><td>7320.00</td><td>45.89</td><td>74.00</td><td>-28.11</td><td>59.15</td><td>35.00</td><td>11.69</td><td>60.75</td><td>0.00</td><td>--</td><td>--</td><td>PEAK</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB		1	4880.00	45.44	74.00	-28.56	62.79	34.34	9.53	61.22	0.00	--	--	PEAK	2	7320.00	45.89	74.00	-28.11	59.15	35.00	11.69	60.75	0.00	--	--	PEAK														
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																									
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark																																																																								
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB																																																																									
1	4880.00	45.44	74.00	-28.56	62.79	34.34	9.53	61.22	0.00	--	--	PEAK																																																																					
2	7320.00	45.89	74.00	-28.11	59.15	35.00	11.69	60.75	0.00	--	--	PEAK																																																																					





Mode	6																																																																																																				
	Band Edge																																																																																																				
	2400-2483.5_NRF_CH39_2480MHz																																																																																																				
ANT	2																																																																																																				
Pol.	Horizontal						Fundamental																																																																																														
Peak																																																																																																					
	<table><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2483.56</td><td>60.50</td><td>74.00</td><td>-13.50</td><td>48.03</td><td>31.97</td><td>6.73</td><td>32.23</td><td>6.00</td><td>133</td><td>342 PEAK</td></tr></table>							Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2483.56	60.50	74.00	-13.50	48.03	31.97	6.73	32.23	6.00	133	342 PEAK	<table><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2480.00</td><td>103.97</td><td>-----</td><td>-----</td><td>91.51</td><td>31.96</td><td>6.73</td><td>32.23</td><td>6.00</td><td>133</td><td>342 PEAK</td></tr></table>						Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2480.00	103.97	-----	-----	91.51	31.96	6.73	32.23	6.00	133	342 PEAK
		Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																											
Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																																																																											
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																											
1	2483.56	60.50	74.00	-13.50	48.03	31.97	6.73	32.23	6.00	133	342 PEAK																																																																																										
	Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																												
Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																																																																											
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																											
1	2480.00	103.97	-----	-----	91.51	31.96	6.73	32.23	6.00	133	342 PEAK																																																																																										
Avg																																																																																																					
	<table><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2483.50</td><td>50.03</td><td>54.00</td><td>-3.97</td><td>37.56</td><td>31.97</td><td>6.73</td><td>32.23</td><td>6.00</td><td>133</td><td>342 AVERAGE</td></tr></table>							Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2483.50	50.03	54.00	-3.97	37.56	31.97	6.73	32.23	6.00	133	342 AVERAGE	<table><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2480.00</td><td>101.83</td><td>-----</td><td>-----</td><td>89.37</td><td>31.96</td><td>6.73</td><td>32.23</td><td>6.00</td><td>133</td><td>342 AVERAGE</td></tr></table>						Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2480.00	101.83	-----	-----	89.37	31.96	6.73	32.23	6.00	133	342 AVERAGE
		Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																											
Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																																																																											
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																											
1	2483.50	50.03	54.00	-3.97	37.56	31.97	6.73	32.23	6.00	133	342 AVERAGE																																																																																										
	Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																												
Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																																																																											
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																											
1	2480.00	101.83	-----	-----	89.37	31.96	6.73	32.23	6.00	133	342 AVERAGE																																																																																										







Mode	6																																																																																																			
	Band Edge																																																																																																			
	2400-2483.5_NRF_CH39_2480MHz																																																																																																			
ANT	2																																																																																																			
Pol.	Vertical						Fundamental																																																																																													
Peak																																																																																																				
	<table><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2483.50</td><td>58.33</td><td>74.00</td><td>-15.67</td><td>45.86</td><td>31.97</td><td>6.73</td><td>32.23</td><td>6.00</td><td>100</td><td>46 PEAK</td></tr></table>							Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2483.50	58.33	74.00	-15.67	45.86	31.97	6.73	32.23	6.00	100	46 PEAK	<table><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2480.00</td><td>102.88</td><td>-----</td><td>-----</td><td>90.42</td><td>31.96</td><td>6.73</td><td>32.23</td><td>6.00</td><td>100</td><td>46 PEAK</td></tr></table>						Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2480.00	102.88	-----	-----	90.42	31.96	6.73	32.23	6.00	100
	Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																											
Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																																																																										
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																										
1	2483.50	58.33	74.00	-15.67	45.86	31.97	6.73	32.23	6.00	100	46 PEAK																																																																																									
	Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																											
Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																																																																										
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																										
1	2480.00	102.88	-----	-----	90.42	31.96	6.73	32.23	6.00	100	46 PEAK																																																																																									
Avg																																																																																																				
	<table><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2483.56</td><td>49.09</td><td>54.00</td><td>-4.91</td><td>36.62</td><td>31.97</td><td>6.73</td><td>32.23</td><td>6.00</td><td>100</td><td>46 AVERAGE</td></tr></table>							Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2483.56	49.09	54.00	-4.91	36.62	31.97	6.73	32.23	6.00	100	46 AVERAGE	<table><tr><th></th><th>Limit</th><th>Over</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Limit</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2480.00</td><td>100.79</td><td>-----</td><td>-----</td><td>88.33</td><td>31.96</td><td>6.73</td><td>32.23</td><td>6.00</td><td>100</td><td>46 AVERAGE</td></tr></table>						Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2480.00	100.79	-----	-----	88.33	31.96	6.73	32.23	6.00	100
	Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																											
Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																																																																										
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																										
1	2483.56	49.09	54.00	-4.91	36.62	31.97	6.73	32.23	6.00	100	46 AVERAGE																																																																																									
	Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																											
Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor		Remark																																																																																										
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																										
1	2480.00	100.79	-----	-----	88.33	31.96	6.73	32.23	6.00	100	46 AVERAGE																																																																																									



Mode	6																																																																							
	Harmonic																																																																							
	2400-2483.5_NRF_CH39_2480MHz																																																																							
ANT	2																																																																							
Pol.	Horizontal						Vertical																																																																	
Peak Avg																																																																								
	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th colspan="3"></th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th>Factor</th><th></th><th></th><th>Remark</th><th></th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>4960.00</td><td>45.26</td><td>74.00</td><td>-28.74</td><td>62.55</td><td>34.26</td><td>9.61</td><td>61.16</td><td>0.00</td><td>--</td><td>-- PEAK</td></tr><tr><td>2</td><td>7440.00</td><td>44.22</td><td>74.00</td><td>-29.78</td><td>57.85</td><td>35.62</td><td>11.77</td><td>61.02</td><td>0.00</td><td>--</td><td>-- PEAK</td></tr></tbody></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos				Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg	1	4960.00	45.26	74.00	-28.74	62.55	34.26	9.61	61.16	0.00	--	-- PEAK	2	7440.00	44.22	74.00	-29.78	57.85	35.62	11.77	61.02	0.00	--	-- PEAK
		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																															
	Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark																																																														
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg																																																													
1	4960.00	45.26	74.00	-28.74	62.55	34.26	9.61	61.16	0.00	--	-- PEAK																																																													
2	7440.00	44.22	74.00	-29.78	57.85	35.62	11.77	61.02	0.00	--	-- PEAK																																																													
<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th colspan="3"></th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th>Factor</th><th></th><th></th><th>Remark</th><th></th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>4960.00</td><td>44.53</td><td>74.00</td><td>-29.47</td><td>61.82</td><td>34.26</td><td>9.61</td><td>61.16</td><td>0.00</td><td>--</td><td>-- PEAK</td></tr><tr><td>2</td><td>7440.00</td><td>44.11</td><td>74.00</td><td>-29.89</td><td>57.74</td><td>35.62</td><td>11.77</td><td>61.02</td><td>0.00</td><td>--</td><td>-- PEAK</td></tr></tbody></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos				Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg	1	4960.00	44.53	74.00	-29.47	61.82	34.26	9.61	61.16	0.00	--	-- PEAK	2	7440.00	44.11	74.00	-29.89	57.74	35.62	11.77	61.02	0.00	--	-- PEAK	
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark																																																															
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg																																																													
1	4960.00	44.53	74.00	-29.47	61.82	34.26	9.61	61.16	0.00	--	-- PEAK																																																													
2	7440.00	44.11	74.00	-29.89	57.74	35.62	11.77	61.02	0.00	--	-- PEAK																																																													



Mode	3																																																																																																																																																	
	LF																																																																																																																																																	
	2400-2483.5_NRF_CH39_2480MHz																																																																																																																																																	
ANT	1																																																																																																																																																	
Pol.	Horizontal	Vertical																																																																																																																																																
QP	<table><tr><th></th><th>Over</th><th>Limit</th><th>ReadAntenna</th><th>Cable Preamp</th><th>A/Pos</th><th>T/Pos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Limit</th><th>Line</th><th>Level Factor</th><th>Loss Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dB</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>deg</th></tr><tr><td>1</td><td>55.22</td><td>22.89</td><td>-17.11</td><td>40.00</td><td>42.05</td><td>12.57</td><td>1.03 32.76 --- --- Peak</td></tr><tr><td>2</td><td>177.44</td><td>24.63</td><td>-18.87</td><td>43.50</td><td>40.48</td><td>14.98</td><td>1.94 32.77 --- --- Peak</td></tr><tr><td>3</td><td>324.88</td><td>19.63</td><td>-26.37</td><td>46.00</td><td>30.42</td><td>19.47</td><td>2.65 32.91 --- --- Peak</td></tr><tr><td>4</td><td>456.80</td><td>23.56</td><td>-22.44</td><td>46.00</td><td>30.59</td><td>22.98</td><td>3.14 33.15 --- --- Peak</td></tr><tr><td>5</td><td>604.24</td><td>26.39</td><td>-19.61</td><td>46.00</td><td>30.66</td><td>25.60</td><td>3.65 33.52 --- --- Peak</td></tr><tr><td>6</td><td>913.67</td><td>33.65</td><td>-12.35</td><td>46.00</td><td>32.34</td><td>29.24</td><td>4.51 32.44 --- --- Peak</td></tr></table>		Over	Limit	ReadAntenna	Cable Preamp	A/Pos	T/Pos	Remark	Freq	Level	Limit	Line	Level Factor	Loss Factor			MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	deg	1	55.22	22.89	-17.11	40.00	42.05	12.57	1.03 32.76 --- --- Peak	2	177.44	24.63	-18.87	43.50	40.48	14.98	1.94 32.77 --- --- Peak	3	324.88	19.63	-26.37	46.00	30.42	19.47	2.65 32.91 --- --- Peak	4	456.80	23.56	-22.44	46.00	30.59	22.98	3.14 33.15 --- --- Peak	5	604.24	26.39	-19.61	46.00	30.66	25.60	3.65 33.52 --- --- Peak	6	913.67	33.65	-12.35	46.00	32.34	29.24	4.51 32.44 --- --- Peak	<table><tr><th></th><th>Over</th><th>Limit</th><th>ReadAntenna</th><th>Cable Preamp</th><th>A/Pos</th><th>T/Pos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Limit</th><th>Line</th><th>Level Factor</th><th>Loss Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dB</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>deg</th></tr><tr><td>1</td><td>48.43</td><td>33.84</td><td>-6.16</td><td>40.00</td><td>50.68</td><td>15.39</td><td>0.70 32.93 --- --- Peak</td></tr><tr><td>2</td><td>175.50</td><td>25.25</td><td>-18.25</td><td>43.50</td><td>41.09</td><td>15.22</td><td>1.78 32.84 --- --- Peak</td></tr><tr><td>3</td><td>324.88</td><td>19.85</td><td>-26.15</td><td>46.00</td><td>30.63</td><td>19.65</td><td>2.43 32.86 --- --- Peak</td></tr><tr><td>4</td><td>442.25</td><td>23.44</td><td>-22.56</td><td>46.00</td><td>30.70</td><td>22.92</td><td>2.84 33.02 --- --- Peak</td></tr><tr><td>5</td><td>728.40</td><td>27.71</td><td>-18.29</td><td>46.00</td><td>29.36</td><td>27.62</td><td>3.65 32.92 --- --- Peak</td></tr><tr><td>6</td><td>856.44</td><td>29.93</td><td>-16.07</td><td>46.00</td><td>29.21</td><td>29.07</td><td>3.95 32.30 --- --- Peak</td></tr></table>		Over	Limit	ReadAntenna	Cable Preamp	A/Pos	T/Pos	Remark	Freq	Level	Limit	Line	Level Factor	Loss Factor			MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	deg	1	48.43	33.84	-6.16	40.00	50.68	15.39	0.70 32.93 --- --- Peak	2	175.50	25.25	-18.25	43.50	41.09	15.22	1.78 32.84 --- --- Peak	3	324.88	19.85	-26.15	46.00	30.63	19.65	2.43 32.86 --- --- Peak	4	442.25	23.44	-22.56	46.00	30.70	22.92	2.84 33.02 --- --- Peak	5	728.40	27.71	-18.29	46.00	29.36	27.62	3.65 32.92 --- --- Peak	6	856.44	29.93	-16.07	46.00	29.21	29.07	3.95 32.30 --- --- Peak
	Over	Limit	ReadAntenna	Cable Preamp	A/Pos	T/Pos	Remark																																																																																																																																											
Freq	Level	Limit	Line	Level Factor	Loss Factor																																																																																																																																													
MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	deg																																																																																																																																											
1	55.22	22.89	-17.11	40.00	42.05	12.57	1.03 32.76 --- --- Peak																																																																																																																																											
2	177.44	24.63	-18.87	43.50	40.48	14.98	1.94 32.77 --- --- Peak																																																																																																																																											
3	324.88	19.63	-26.37	46.00	30.42	19.47	2.65 32.91 --- --- Peak																																																																																																																																											
4	456.80	23.56	-22.44	46.00	30.59	22.98	3.14 33.15 --- --- Peak																																																																																																																																											
5	604.24	26.39	-19.61	46.00	30.66	25.60	3.65 33.52 --- --- Peak																																																																																																																																											
6	913.67	33.65	-12.35	46.00	32.34	29.24	4.51 32.44 --- --- Peak																																																																																																																																											
	Over	Limit	ReadAntenna	Cable Preamp	A/Pos	T/Pos	Remark																																																																																																																																											
Freq	Level	Limit	Line	Level Factor	Loss Factor																																																																																																																																													
MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	deg																																																																																																																																											
1	48.43	33.84	-6.16	40.00	50.68	15.39	0.70 32.93 --- --- Peak																																																																																																																																											
2	175.50	25.25	-18.25	43.50	41.09	15.22	1.78 32.84 --- --- Peak																																																																																																																																											
3	324.88	19.85	-26.15	46.00	30.63	19.65	2.43 32.86 --- --- Peak																																																																																																																																											
4	442.25	23.44	-22.56	46.00	30.70	22.92	2.84 33.02 --- --- Peak																																																																																																																																											
5	728.40	27.71	-18.29	46.00	29.36	27.62	3.65 32.92 --- --- Peak																																																																																																																																											
6	856.44	29.93	-16.07	46.00	29.21	29.07	3.95 32.30 --- --- Peak																																																																																																																																											

Mode	3	
	18G-25GHz	
	2400-2483.5_NRF_CH39_2480MHz	
ANT	1	
Pol.	Horizontal	Vertical
Peak Avg	 Level (dBuV/m) Frequency (MHz) FCC PART 15C -60dB FCC PART 15C (AVG) -60dB	 Level (dBuV/m) Frequency (MHz) FCC PART 15C -60dB FCC PART 15C (AVG) -60dB

Note: Only the worst case has assessed 18G ~25GHz to test.

Appendix D. Duty Cycle Plots

Band	Duty Cycle(%)	T(ms)	1/T(kHz)	VBW Setting
nRF	32.41	0.203	4.929	5.1kHz

Ant.1/2
nRF Mode

