



1. Duty Cycle

1.1 Test Result

Ant1							
Mode	TX Type	Frequency (MHz)	T_on (ms)	Period (ms)	Duty Cycle (%)	Duty Cycle Correction Factor (dB)	Max. DC Variation (%)
1M	SISO	2402	0.400	0.625	64.00	1.94	0.00
		2440	0.400	0.625	64.00	1.94	0.00
		2480	0.400	0.625	64.00	1.94	0.03

1.2 Test Graph





2. Bandwidth

2.1 Test Result

2.1.1 OBW


Mode	TX Type	Frequency (MHz)	ANT	99% Occupied Bandwidth (MHz)		Verdict
				Result	Limit	
1M	SISO	2402	1	1.034	/	Pass
		2440	1	1.033	/	Pass
		2480	1	1.031	/	Pass


2.1.2 6dB BW

Mode	TX Type	Frequency (MHz)	ANT	6dB Bandwidth (MHz)		Verdict
				Result	Limit	
1M	SISO	2402	1	0.722	≥ 0.5	Pass
		2440	1	0.719	≥ 0.5	Pass
		2480	1	0.722	≥ 0.5	Pass

2.2 Test Graph


2.2.1 OBW







2.2.2 6dB BW

1M_LCH_2402MHz_Ant1_NTNV



1M_MCH_2440MHz_Ant1_NTNV






3. Maximum Conducted Output Power

3.1 Test Result


Mode	TX Type	Frequency (MHz)	Maximum Peak Conducted Output Power (dBm)		Verdict
			ANT1	Limit	
1M	SISO	2402	0.35	≤ 30	Pass
		2440	0.78	≤ 30	Pass
		2480	0.55	≤ 30	Pass


3.2 Test Graph

1M_LCH_2402MHz_Ant1_NTNV



1M_MCH_2440MHz_Ant1_NTNV






4. Maximum Power Spectral Density

4.1 Test Result


Mode	TX Type	Frequency (MHz)	Maximum PSD (dBm)		Verdict
			ANT1	Limit	
1M	SISO	2402	-14.79	≤ 8	Pass
		2440	-14.37	≤ 8	Pass
		2480	-14.73	≤ 8	Pass


4.2 Test Graph

1M_LCH_2402MHz_Ant1_NTNV



1M_MCH_2440MHz_Ant1_NTNV





5. Unwanted Emissions In Non-restricted Frequency Bands

5.1 Test Result

5.1.1 Ref


Mode	TX Type	Frequency (MHz)	ANT	Level of Reference (dBm)
1M	SISO	2402	1	0.16
		2440	1	0.57
		2480	1	0.35


5.1.2 CSE

Mode	TX Type	Frequency (MHz)	ANT	Level of Reference (dBm)	Limit (dBm)	Verdict
1M	SISO	2402	1	0.16	-19.84	Pass
		2440	1	0.57	-19.43	Pass
		2480	1	0.35	-19.65	Pass


5.2 Test Graph

5.2.1 Ref







5.2.2 CSE




1M_MCH_2440MHz_Ant1_NTNV



1M_HCH_2480MHz_Ant1_NTNV





▶▶▶ END ◀◀◀