

# AVIATOR 200/300/350

## Installation & maintenance manual





# AVIATOR 200/300/350

## Installation & maintenance manual

**Document number:** 98-127093-I

**Release date:** 22 June 2020

## Disclaimer

Information in this document is subject to change without notice.

The information, drawings and wiring diagrams contained in this manual are intended as a reference for engineering planning only. The drawings and wiring diagrams contained herein do not represent any specific Supplemental Type Certificate (STC). It is the installer's responsibility to compose installation drawings specific to the aircraft. This manual and the drawings and wiring diagrams contained herein may not be used as a substitute for an STC package.

The newest versions of Cobham SATCOM user and installation manuals as well as outline drawings can be downloaded from [www.cobham.com/satcom](http://www.cobham.com/satcom), **Cobham SYNC Partner Portal**. Some material and features are for partners only and can only be accessed after login with a password.

Thrane & Thrane A/S is not responsible for the content or accuracy of any translations or reproductions, in whole or in part, of this manual from any other source. In the event of any discrepancies, the English version shall be the governing text.

Thrane & Thrane A/S is trading as Cobham.

## Copyright

© 2020 Thrane & Thrane A/S. All rights reserved. Printed in Denmark.

## Trademark Acknowledgements

- **Inmarsat** is a registered trademark of the International Maritime Satellite Organization (IMSO) and is licensed by IMSO to Inmarsat Limited and Inmarsat Ventures plc.
- Inmarsat's product names are either trademarks or registered trademarks of Inmarsat.
- **Windows** is a registered trademark of Microsoft Corporation in the United States and other countries.
- Other product and company names mentioned in this manual may be trademarks or trade names of their respective owners.

Company web site

[www.cobham.com/satcom](http://www.cobham.com/satcom)

## Disposal

Old electrical and electronic equipment marked with this symbol can contain substances hazardous to human beings and the environment. Never dispose these items together with unsorted municipal waste (household waste). In order to protect the environment and ensure the correct recycling of old equipment as well as the re-utilization of individual components, use either public collection or private collection by the local distributor of old electrical and electronic equipment marked with this symbol.

Contact the local distributor for information about what type of return system to use.



# Record of revisions

| Rev. | Description                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         | Release Date      | Initials |
|------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------|----------|
| A    | Original document                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   | 12 March 2008     | CC       |
| B    | General update to version B.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        | 25 September 2008 | UFO      |
| C    | Configuration of interfaces and network management added. Specifications and DO-160 string of the HLD updated. Editorials.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          | 28 November 2008  | UFO      |
| D    | <p>Page iii: Disposal added</p> <p>The following chapters have been added: 6.7.7</p> <p>The following chapters have been edited: 2.1.1, 2.3.4, 5.1.2, 5.2.2-5.2.4, 5.3.3, 5.3.4, 5.3.6, 5.3.7, 5.3.10, 5.4.3, 5.4.5 - 5.4.7, 6.2.2, 6.5, 6.6.1, 6.6.3 - 6.6.5, 6.6.8 - 6.6.13, 6.7.7, 6.8.7, 7.4.2, 7.5.4, 7.7</p> <p>The following appendices have been added: E, F</p> <p>The following tables have been added: 5-12, 6-3, 6-4</p> <p>The following tables have been edited: 2-1, 2-3, 2-5, 4-3, 5-21, 5-22, 5-28, B-1, B-2, B-3,</p> <p>The following figures have been added: 2-3, 2-4, 3-7, 5-6, 5-9, 7-5</p> <p>The following figures have been edited: 3-10, 3-11, 5-16, 6-2, 6-52</p>                                                                                                                                                                                                                                                                                       | 7 May 2009        | UFO      |
| E    | <p>added. The AVIATOR 300 and AVIATOR 350 replace the earlier Thrane &amp; Thrane Aero-SB Lite system.</p> <p>The following chapters have been added: 5.3.5, 6.5.10, 6.5.15, 6.6.8, 6.7.5, 6.7.10, 6.7.11, 6.7.12, A.2.5, B.2.4, Appendix C, Appendix G.</p> <p>The following chapters have been edited: 2.1.1, 2.1.2, 2.2, 2.3, 4.1.3, 4.4.1, 5.2.4, 5.3.2, 5.3.4, 5.3.7, 5.3.11, 5.4.4, 5.5, 6.2.2, 6.3.4, 6.4, 6.6.1, 6.6.4, 6.5.8, 6.5.12, 6.5.13, 6.5.14, 6.6.6, 6.6.7, 6.7.2, 6.10, 7.2.2, 7.2.3, 7.4 (reorganized), A.1.1 removed, E.1,</p> <p>The following tables have been added: 5-7</p> <p>The following tables have been edited: 2-3, 5-6, 5-28, A-1, F-1, F-2.</p> <p>The following figures have been added: 3-3, 3-5, 3-10, 3-11, 3-13, 3-14, 5-4.</p> <p>The following figures have been edited: 4-3, 5-1, 6-2, 6-4, 6-23, 6-30, 6-33, 6-46, 6-48, 6-49, 6-54, 6-56, 6-58, 7-3, F-2.</p> <p>The section "Using the Call log" has been moved to the user manual.</p> | 29 July 2010      | UFO      |

|   |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          |                  |     |
|---|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|------------------|-----|
| F | <p>The following chapters have been added: 3.13, 6.1.1, 6.5.9, 6.6.9, 6.7.1,</p> <p>The following chapters have been edited: 1.1, 2.1, 2.1.1, 2.2.2, 3.1, 3.10, 5.2.5, 5.3.7, 5.4.6, 6.3.2, 6.5.4, 6.7.2, 7.1.1, 7.3, A-3, B.2.1, B.3, B.3.1, H.1.2.</p> <p>The following tables have been edited: 1-1, 2-3, 2-7, 5-1, 5-6, 5-9, 5-29, 6-3, A-1, A-2, A-3, A-4, A-5, A-6, A-7,</p> <p>The following figures have been edited: 2-1, 3-1, 3-4, 5-1, 6-9, 6-10, 6-28, 6-30, 6-34.</p>                                                                                                                                                                                       | 16 March 2012    | UFO |
| G | <p>The following sections have been added: 6.5.15, 6.7.14, 7.4</p> <p>The following sections have been edited: 2.1.1, 2.1.2, 2.3.1, 2.3.3, 5.2.3, 5.3.4, 5.3.5, 5.3.9, 6.4.2, 6.5.5, 6.5.6, 6.5.8, 6.5.16, 6.72, 6.7.10, 7.3.1</p> <p>The following tables have been edited: 2-1, 2-2, 2-3, 4-3, 5-1, 5-12, 5-13, 6-3, 7-4, A-1, C-1, F-2</p> <p>The following figures have been added: 5-12, 5-5, 6-8, 6-13</p> <p>The following figures have been edited: 2-2, 3-2, 5-4, 5-5, 5-6, 5-7, 5-8, 5-9, 5-10, 5-11, 5-14, 6-32, 6-34, 6-73</p>                                                                                                                               | 27 March 2014    | UFO |
| H | <p>The following sections have been added: 2.1.1 (p. 2-4 +2-5), 5.3.14, 6.5.18, 6.7.13, 7.3</p> <p>The following sections have been edited: 2.1.2, 5.3.1, 4.1.3 (p. 4-5), 5.3. (p. 5-14), 5.3.3 (p. 5-17), 5.3.7, 5.3.8, 5.3.9, 6.5.4, 6.5.5, 6.5.6, 6.5.9, 6.5.11, 6.5.10, 6.5.14 (p. 6-47), 6.5.15, 6.5.16, 6.7, 6.7.15, 7.2.2, 7.6, F.3.1, H.1.2</p> <p>The following tables have been added: 2-3, 2-4, 2-6, F-1</p> <p>The following tables have been edited: 2-5, 2-9, 2-11, 4-2, 4-5, 5-1, 5-19, 5-32, 7-4, A-1, C-1</p> <p>The following figures have been added: 5-10, 6-31</p> <p>The following figures have been edited: 3-2, 3-12, 3-14, 3-15, 6-37, 6-79</p> | 5 September 2017 | UFO |
| I | <p>The following sections have been added: 5.3.0, page 6-1 Important note</p> <p>The following sections have been edited: 2.2.1, 3.13, 4.3, 5.3.1, 5.3.14, 5.3.15, 6.1.1, 6.5.4, 6.5.7, 6.5.13, 6.5.15, 7.1.1, 7.3,,</p> <p>The following tables have been edited: 2-1, 2-4, 2-5, 2-10, 2-11,</p> <p>The following figures have been added: 3-1, 3-2, 3-7, 3-11</p> <p>The following figures have been edited: 3-1, 3-2, 3-3, 3-4, 3-5, 3-8, 3-9, 5-5, 5-10, 7-3,</p>                                                                                                                                                                                                    | 22 June 2020     | UFO |

# Table of contents

---

|                  |                                                                       |      |
|------------------|-----------------------------------------------------------------------|------|
| <b>Chapter 1</b> | <b>About this manual</b>                                              |      |
|                  | 1.1 Purpose .....                                                     | 1-1  |
|                  | 1.2 Organization .....                                                | 1-1  |
|                  | 1.3 Related documentation .....                                       | 1-2  |
|                  | 1.4 Precautions: Warnings, Cautions and Notes .....                   | 1-2  |
| <b>Chapter 2</b> | <b>Introduction</b>                                                   |      |
|                  | 2.1 General description .....                                         | 2-1  |
|                  | 2.1.1 The AVIATOR 200/300/350 system .....                            | 2-1  |
|                  | 2.1.2 AVIATOR 200/300/350 features .....                              | 2-8  |
|                  | 2.2 Application .....                                                 | 2-9  |
|                  | 2.2.1 Minimum system .....                                            | 2-9  |
|                  | 2.2.2 Part numbers .....                                              | 2-10 |
|                  | 2.3 System block diagrams .....                                       | 2-14 |
|                  | 2.3.1 AVIATOR 200 system with LGA-3000 antenna .....                  | 2-14 |
|                  | 2.3.2 AVIATOR 300 system with IGA-5006 antenna .....                  | 2-15 |
|                  | 2.3.3 AVIATOR 350 system with Cobham antennas .....                   | 2-16 |
|                  | 2.3.4 AVIATOR 350 system with ARINC-741/781 antennas .....            | 2-17 |
|                  | 2.3.5 AVIATOR 350D system with ACARS and ARINC-741/781 antennas ..... | 2-18 |
|                  | 2.3.6 User interfaces .....                                           | 2-19 |
| <b>Chapter 3</b> | <b>Equipment drawings</b>                                             |      |
|                  | 3.1 Introduction .....                                                | 3-1  |
|                  | 3.2 TT-5040A SBU .....                                                | 3-2  |
|                  | 3.2.1 TT-5040A-001/TT-5040A-8xy CM (inserted in the SBU) .....        | 3-3  |
|                  | 3.3 TT-5038A-003 Rx Power Splitter .....                              | 3-4  |
|                  | 3.4 TT-5016A HLD .....                                                | 3-5  |
|                  | 3.5 LGA-3002 .....                                                    | 3-6  |
|                  | 3.6 IGA-5001 .....                                                    | 3-7  |
|                  | 3.7 HGA-7001 .....                                                    | 3-8  |
|                  | 3.8 TT-5621B 2-Wire Handset .....                                     | 3-10 |
|                  | 3.9 TT-5622B 2-Wire Cradle .....                                      | 3-11 |
|                  | 3.10 SBU trays .....                                                  | 3-12 |
|                  | 3.11 SBU tray connector .....                                         | 3-16 |
|                  | 3.12 Contact Assembly: Quadrax Pin size 5 special .....               | 3-17 |

|      |                                 |      |
|------|---------------------------------|------|
| 3.13 | TT-5040A-004 WLAN antenna ..... | 3-19 |
| 3.14 | Switch Annunciator Panel .....  | 3-20 |

## Chapter 4

### Connectors and pin-out

|       |                                      |      |
|-------|--------------------------------------|------|
| 4.1   | TT-5040A SBU .....                   | 4-1  |
| 4.1.1 | Connectors on SBU .....              | 4-1  |
| 4.1.2 | SBU Maintenance connector .....      | 4-1  |
| 4.1.3 | SBU rear receptacle .....            | 4-3  |
| 4.2   | TT-5016A HLD .....                   | 4-9  |
| 4.2.1 | Connectors on HLD .....              | 4-9  |
| 4.3   | Cradle connectors for handsets ..... | 4-10 |
| 4.3.1 | Connectors on 2-Wire Cradle .....    | 4-10 |
| 4.3.2 | 2-Wire Cradle connector to SBU ..... | 4-11 |
| 4.4   | Mating connectors in aircraft .....  | 4-12 |
| 4.4.1 | Connection with SBU .....            | 4-12 |

## Chapter 5

### Installation

|        |                                                                 |      |
|--------|-----------------------------------------------------------------|------|
| 5.1    | General installation information .....                          | 5-1  |
| 5.1.1  | Overview .....                                                  | 5-1  |
| 5.1.2  | Minimum system components .....                                 | 5-2  |
| 5.2    | Mounting considerations .....                                   | 5-3  |
| 5.2.1  | Overview .....                                                  | 5-3  |
| 5.2.2  | TT-5040A SBU .....                                              | 5-3  |
| 5.2.3  | TT-5016A HLD .....                                              | 5-3  |
| 5.2.4  | Satcom antenna .....                                            | 5-4  |
| 5.2.5  | TT-5040A-004 WLAN antennas .....                                | 5-7  |
| 5.3    | Electrical installation and wiring .....                        | 5-8  |
| 5.3.1  | Wiring symbols .....                                            | 5-8  |
| 5.3.2  | Wiring the power supply .....                                   | 5-9  |
| 5.3.3  | Wiring the satcom antenna .....                                 | 5-11 |
| 5.3.4  | Wiring ARINC 429 interfaces .....                               | 5-24 |
| 5.3.5  | Wiring GPS interface .....                                      | 5-28 |
| 5.3.6  | Wiring Ethernet .....                                           | 5-30 |
| 5.3.7  | Wiring WLAN antenna interface .....                             | 5-33 |
| 5.3.8  | Wiring ISDN .....                                               | 5-35 |
| 5.3.9  | Wiring telephone systems .....                                  | 5-37 |
| 5.3.10 | Wiring AVIATOR Wireless Handsets .....                          | 5-39 |
| 5.3.11 | Wiring Sigma <sup>7</sup> (2-wire) handsets .....               | 5-40 |
| 5.3.12 | Wiring ICG DECT Cordless Handset (2-wire) phone .....           | 5-40 |
| 5.3.13 | Wiring discretes .....                                          | 5-41 |
| 5.3.14 | Wiring the Switch Annunciator Panel (no longer available) ..... | 5-43 |

|            |                                                   |             |
|------------|---------------------------------------------------|-------------|
| 5.3.15     | Wiring an SB-Safety Voice Annunciator Panel ..... | 5-44        |
| 5.3.16     | Wiring the maintenance interface .....            | 5-44        |
| <b>5.4</b> | <b>Recommended cables .....</b>                   | <b>5-46</b> |
| 5.4.1      | Introduction .....                                | 5-46        |
| 5.4.2      | Power cables, allowed cable lengths .....         | 5-46        |
| 5.4.3      | Recommended Power cables .....                    | 5-47        |
| 5.4.4      | Recommended RF cables .....                       | 5-47        |
| 5.4.5      | Recommended cables for ARINC 429 .....            | 5-48        |
| 5.4.6      | Recommended cables for Ethernet .....             | 5-48        |
| 5.4.7      | Cables for Discrete Signals .....                 | 5-49        |
| <b>5.5</b> | <b>Activation of airtime services .....</b>       | <b>5-49</b> |

## **Chapter 6 Configuration of the AVIATOR 200/300/350 system**

|            |                                                             |             |
|------------|-------------------------------------------------------------|-------------|
| <b>6.1</b> | <b>Configuration tasks .....</b>                            | <b>6-2</b>  |
| 6.1.1      | Basic configuration of the SBU .....                        | 6-2         |
| <b>6.2</b> | <b>Tool for setup and use: Built-in web interface .....</b> | <b>6-6</b>  |
| 6.2.1      | Topics in the web interface .....                           | 6-7         |
| 6.2.2      | Check of the connection to the web interface .....          | 6-7         |
| <b>6.3</b> | <b>The Dashboard .....</b>                                  | <b>6-12</b> |
| 6.3.1      | Overview .....                                              | 6-12        |
| 6.3.2      | Properties .....                                            | 6-12        |
| 6.3.3      | View information on calls and data sessions .....           | 6-13        |
| 6.3.4      | Profiles on the dashboard .....                             | 6-14        |
| <b>6.4</b> | <b>The phone book .....</b>                                 | <b>6-15</b> |
| 6.4.1      | General usage .....                                         | 6-15        |
| 6.4.2      | View and edit the mobile and additional numbers .....       | 6-15        |
| <b>6.5</b> | <b>To set up the interfaces .....</b>                       | <b>6-17</b> |
| 6.5.1      | The SETTINGS page .....                                     | 6-17        |
| 6.5.2      | Select the preferred BGAN satellite .....                   | 6-18        |
| 6.5.3      | Configure the LAN interface .....                           | 6-19        |
| 6.5.4      | WLAN interface (option) .....                               | 6-22        |
| 6.5.5      | Configure the Phone/Fax interface (2-Wire) .....            | 6-24        |
| 6.5.6      | Configure the ISDN interface .....                          | 6-25        |
| 6.5.7      | Set the common interface settings .....                     | 6-27        |
| 6.5.8      | Set up call services .....                                  | 6-28        |
| 6.5.9      | Manage AVIATOR Wireless Handsets .....                      | 6-34        |
| 6.5.10     | Configure the discrete I/O interfaces .....                 | 6-37        |
| 6.5.11     | Set the system type .....                                   | 6-39        |
| 6.5.12     | Configure RF settings .....                                 | 6-43        |
| 6.5.13     | Set up the navigational input and select the antenna .....  | 6-44        |
| 6.5.14     | Calibrate the NRS magnetometer in the IGA-5006 .....        | 6-46        |

|             |                                                          |             |
|-------------|----------------------------------------------------------|-------------|
| 6.5.15      | Set up CMU/ACARS (option)                                | 6-51        |
| 6.5.16      | Enable system options with FLEX keys                     | 6-53        |
| 6.5.17      | Tracking                                                 | 6-54        |
| 6.5.18      | SB-Safety Voice (option)                                 | 6-55        |
| <b>6.6</b>  | <b>LAN/WLAN network users</b>                            | <b>6-57</b> |
| 6.6.1       | Introduction                                             | 6-57        |
| 6.6.2       | Set up the network user groups                           | 6-59        |
| 6.6.3       | Manage network devices                                   | 6-62        |
| 6.6.4       | The network classification table                         | 6-63        |
| 6.6.5       | Definitions for network terms                            | 6-65        |
| 6.6.6       | <b>NAT</b> (Network Address Translation)                 | 6-66        |
| 6.6.7       | Start and stop any data session                          | 6-66        |
| 6.6.8       | Establish a PPPoE connection                             | 6-67        |
| 6.6.9       | To set up static routing                                 | 6-70        |
| 6.6.10      | SNMP interface                                           | 6-71        |
| <b>6.7</b>  | <b>Administration</b>                                    | <b>6-71</b> |
| 6.7.1       | Protect the SBU against unintended configuration changes | 6-71        |
| 6.7.2       | Access the administration settings                       | 6-72        |
| 6.7.3       | Save and load a configuration                            | 6-75        |
| 6.7.4       | Call charges                                             | 6-77        |
| 6.7.5       | Log handling                                             | 6-78        |
| 6.7.6       | Data limits                                              | 6-78        |
| 6.7.7       | To use profiles                                          | 6-78        |
| 6.7.8       | To use traffic flow filters                              | 6-82        |
| 6.7.9       | SIM card access protection: SIM PIN and SIM Lock         | 6-85        |
| 6.7.10      | Set up user permissions                                  | 6-87        |
| 6.7.11      | Remote management                                        | 6-88        |
| 6.7.12      | Remote activation of a connection using SMS              | 6-89        |
| 6.7.13      | Link monitoring (SwiftBroadband only)                    | 6-90        |
| 6.7.14      | Restricted dialing                                       | 6-90        |
| 6.7.15      | Multi-voice (option)                                     | 6-91        |
| <b>6.8</b>  | <b>Site map</b>                                          | <b>6-97</b> |
| <b>6.9</b>  | <b>Configuration of 3rd party phone systems</b>          | <b>6-98</b> |
| 6.9.1       | Sigma <sup>7</sup> setup                                 | 6-98        |
| 6.9.2       | ICG DECT Cordless Handset setup                          | 6-98        |
| <b>6.10</b> | <b>AVIATOR 200/300/350 system ready for use</b>          | <b>6-99</b> |

## **Chapter 7      Maintenance and troubleshooting**

|            |                                |            |
|------------|--------------------------------|------------|
| <b>7.1</b> | <b>Continued Airworthiness</b> | <b>7-1</b> |
| 7.1.1      | General                        | 7-1        |

|                   |                                                                   |             |
|-------------------|-------------------------------------------------------------------|-------------|
| 7.1.2             | Instructions .....                                                | 7-1         |
| <b>7.2</b>        | <b>Get support: HELPDESK .....</b>                                | <b>7-2</b>  |
| 7.2.1             | Airtime support .....                                             | 7-2         |
| 7.2.2             | System support .....                                              | 7-2         |
| 7.2.3             | Help desk and diagnostic report .....                             | 7-2         |
| <b>7.3</b>        | <b>Software update .....</b>                                      | <b>7-3</b>  |
| 7.3.1             | SBU software update .....                                         | 7-4         |
| 7.3.2             | Verify the software update .....                                  | 7-6         |
| <b>7.4</b>        | <b>To exchange LRUs .....</b>                                     | <b>7-7</b>  |
| 7.4.1             | Time consumption .....                                            | 7-7         |
| 7.4.2             | Tools .....                                                       | 7-7         |
| 7.4.3             | Removal and re-installation of the SBU .....                      | 7-7         |
| <b>7.5</b>        | <b>Troubleshooting .....</b>                                      | <b>7-9</b>  |
| 7.5.1             | Status signalling .....                                           | 7-9         |
| 7.5.2             | Status signalling with LEDs .....                                 | 7-10        |
| 7.5.3             | IP Reset (Default) button .....                                   | 7-11        |
| 7.5.4             | View the Event list, Event log and extended status .....          | 7-13        |
| 7.5.5             | Self test .....                                                   | 7-14        |
| 7.5.6             | Initial troubleshooting .....                                     | 7-15        |
| <b>7.6</b>        | <b>Return units for repair .....</b>                              | <b>7-16</b> |
| <b>7.7</b>        | <b>Disposal of electrical and electronic equipment .....</b>      | <b>7-17</b> |
| <br>              |                                                                   |             |
| <b>Appendix A</b> | <b>Equipment specifications</b>                                   |             |
| <b>A.1</b>        | <b>Introduction .....</b>                                         | <b>A-1</b>  |
| <b>A.2</b>        | <b>AVIATOR 200/300/350 system components .....</b>                | <b>A-2</b>  |
| A.2.1             | TT-5040A SwiftBroadband Unit (SBU) .....                          | A-2         |
| A.2.2             | TT-5040A-001 Configuration Module (CM) for SBU .....              | A-3         |
| A.2.3             | TT-5016A High Power Amp./Low Noise Amplifier/Diplexer (HLD) ..... | A-4         |
| A.2.4             | TT-5040A-004 WLAN antenna .....                                   | A-5         |
| A.2.5             | TT-5038A-003 Rx Power Splitter .....                              | A-5         |
| <b>A.3</b>        | <b>AVIATOR 200/300/350 handsets and cradles .....</b>             | <b>A-6</b>  |
| A.3.1             | TT-5621B 2-Wire Handset .....                                     | A-6         |
| A.3.2             | TT-5622B 2-Wire Cradle .....                                      | A-6         |
| <br>              |                                                                   |             |
| <b>Appendix B</b> | <b>DO-160 specifications</b>                                      |             |
| <b>B.1</b>        | <b>General .....</b>                                              | <b>B-1</b>  |
| B.1.1             | Certifying agency .....                                           | B-1         |
| B.1.2             | Environmental Qualification Forms .....                           | B-1         |
| <b>B.2</b>        | <b>AVIATOR 200/300/350 system components .....</b>                | <b>B-2</b>  |
| B.2.1             | SwiftBroadband unit (SBU) .....                                   | B-2         |
| B.2.2             | Configuration Module (CM) for SBU .....                           | B-4         |

|                   |            |                                                         |            |
|-------------------|------------|---------------------------------------------------------|------------|
|                   | B.2.3      | High Power Amplifier/Low Noise Amplifier/Diplexer (HLD) | B-4        |
|                   | B.2.4      | Rx Power Splitter                                       | B-6        |
|                   | <b>B.3</b> | <b>AVIATOR 200/300/350 handsets and cradles</b>         | <b>B-8</b> |
|                   | B.3.1      | 2-Wire Handset and 2-Wire Cradle                        | B-8        |
| <b>Appendix C</b> |            | <b>System messages</b>                                  |            |
|                   | C.1        | Types of messages                                       | C-1        |
|                   | C.2        | List of events                                          | C-2        |
| <b>Appendix D</b> |            | <b>WLAN country codes</b>                               |            |
|                   | D.1        | Restrictions in WLAN use                                | D-1        |
|                   | D.2        | Countries where the “US” country code applies           | D-2        |
| <b>Appendix E</b> |            | <b>References</b>                                       |            |
|                   | E.1        | Applicable standards                                    | E-1        |
| <b>Appendix F</b> |            | <b>TT-5019A Iridium Band Reject Filter</b>              |            |
|                   | F.1        | Introduction                                            | F-1        |
|                   | F.2        | Equipment drawing                                       | F-2        |
|                   | F.3        | Installation                                            | F-3        |
|                   | F.3.1      | Mounting considerations                                 | F-3        |
|                   | F.3.2      | Electrical installation and wiring                      | F-3        |
|                   | F.4        | Configuration                                           | F-4        |
|                   | F.5        | Specifications                                          | F-4        |
|                   | F.6        | DO-160 specifications                                   | F-5        |
| <b>Appendix G</b> |            | <b>Terminal commands</b>                                |            |
|                   | G.1        | Get started                                             | G-1        |
|                   | G.1.1      | Connect to the SBU                                      | G-1        |
|                   | G.2        | Commands for troubleshooting the SBU                    | G-2        |
|                   | G.2.1      | Monitor the ARINC interfaces on the SBU                 | G-2        |
|                   | G.2.2      | Description of the status report                        | G-3        |
| <b>Appendix H</b> |            | <b>SIP setup for Wifi-enabled phones</b>                |            |
|                   | H.1        | Introduction                                            | H-1        |
|                   | H.1.1      | Connect to the WLAN interface                           | H-1        |
|                   | H.1.2      | Set up a SIP profile                                    | H-1        |

# About this manual

## 1.1 Purpose

The purpose of this manual is to provide information for installation, maintenance and troubleshooting of the AVIATOR 200/300/350 system. This manual covers AVIATOR 200/300/350 and AVIATOR 200D/300D/350D.

**Important**

The information, drawings and wiring diagrams contained in this manual are intended as a reference for engineering planning only. The drawings and wiring diagrams contained herein do not represent any specific Supplemental Type Certificate (STC). It is the installer's responsibility to compose installation drawings specific to the aircraft. This manual and the drawings and wiring diagrams contained herein may not be used as a substitute for an STC package.

## 1.2 Organization

The chapters of this Installation Manual provide the following information:

- **Introduction.** A short overview of the AVIATOR 200/300/350 system and services.
- **Equipment Drawings**  
Outline drawings of the units and connectors of the AVIATOR 200/300/350 system.
- **Connectors**  
Drawings and pin-out for the connectors, and a description of the required mating connectors.
- **Installation**  
Wiring drawings and detailed installation and wiring requirements.
- **Configuration**  
An introduction to the SwiftBroadband Unit's web interface, and a description of how to configure the AVIATOR 200/300/350 system. A procedure how to calibrate the Satcom antenna and a short description of how to configure some of the 3rd party handsets.
- **Maintenance and Troubleshooting**  
Descriptions of Airworthiness, help desk, software update, LEDs, BITE test and how to return units for repair.
- **Appendices**  
Equipment specifications, DO-160 Forms, installation of an Iridium Band Reject Filter, WLAN country codes, SIP setup for Wifi enabled phones and a list of applicable standards.

## 1.3 Related documentation

| Part number | Description                                                           |
|-------------|-----------------------------------------------------------------------|
| 98-127719   | AVIATOR 200/300/350 User Manual                                       |
| 98-127720   | AVIATOR 200/300/350 Quick Guide                                       |
| 98-129599   | AVIATOR Wireless Handset and Cradle User Manual                       |
| 98-129600   | AVIATOR Wireless Handset and Cradle Installation & Maintenance Manual |
| 98-128279   | Intermediate Gain Antenna Installation Manual                         |

Table 1-1: List of Related Documentation

## 1.4 Precautions: Warnings, Cautions and Notes

Text marked with “Warning”, “Caution”, “Note” or “Important” show the following type of data:

- **Warning:** A Warning is an operation or maintenance procedure that, if not obeyed, can cause injury or death, or jeopardize the flight safety on the aircraft.
- **Caution:** A Caution is an operation or maintenance procedure that, if not obeyed, can cause damage to the equipment.
- **Note:** A Note gives information to help the reader.
- **Important:** A text marked Important gives information that is important to the user, e.g. to make the system work properly. This text does **not** concern damage on equipment, flight safety nor personal safety.

### General precautions

All personnel who operate equipment or do maintenance as specified in this manual must know and follow the safety precautions. The warnings and cautions that follow apply to all parts of this manual.



**WARNING!** Before using any material, refer to the manufacturers' material safety data sheets for safety information. Some materials can be dangerous.



**CAUTION!** The AVIATOR 200/300/350 system contains items that are electrostatic discharge sensitive. Use approved industry precautions to keep the risk of damage to a minimum when you touch, remove or insert parts or assemblies.

# Introduction

This chapter has the following sections:

- *General description*
- *Application*
- *System block diagrams*

## 2.1 General description

This manual describes the administrative and technical aspects, features, functions and components of the AVIATOR 200/300/350 system. All comments or recommendations regarding the installation, acceptance or operation of the system or its accessories and components should be directed to Cobham.

### Note

The AVIATOR 200/300/350 system is available in two versions:

- AVIATOR 200/300/350 approved to RTCA specification DO-178B level E and DO-254 level E
- AVIATOR 200D/300D/350D approved to RTCA specification DO-178B level D and DO-254 level D.

In general descriptions the nomenclature AVIATOR 200/300/350 covers both versions. Where necessary, the Level D system is specified as AVIATOR 200D/300D/350D.

### 2.1.1 The AVIATOR 200/300/350 system

#### Overview

The AVIATOR 200/300/350 system is a compact, light-weight aeronautical satcom system that uses Inmarsat's SwiftBroadband services.

The AVIATOR system consists of the following units:

- TT-5040A SBU SwiftBroadband Unit
- TT-5040A-001 or TT-4050A-8xy CM Configuration Module, inserted in the SBU. The CM also holds the SIM card, which provides access to the SwiftBroadband services. The SIM card is included in the delivery.
- TT-5016A HLD High Power Amplifier, Low Noise Amplifier and Diplexer in one unit.

These units must be connected to a satcom antenna. See section *Satcom antenna systems* on page 2-5 for supported antenna types and model numbers.

The following drawing shows the AVIATOR 200/300/350 cabin installation with connected communication devices and available options:




Figure 2-1: Communication devices (example for a Level E system)

## Services

The SwiftBroadband services available depend on the type of antenna installed and the current elevation angle to the satellite. The following table shows the services available for the supported antenna types.

| SwiftBroadband service                        | Satcom antenna                          |                                 |                                           |
|-----------------------------------------------|-----------------------------------------|---------------------------------|-------------------------------------------|
|                                               | AVIATOR 200 LGA (Class 15) <sup>a</sup> | AVIATOR 300 IGA (Class 7)       | AVIATOR 350 HGA (Class 6)                 |
| Standard IP background                        | Up to 200 kbps                          | Up to 332 kbps                  | Up to 432 kbps                            |
| IP streaming classes                          | 8/16                                    | 8/16/32/64/128 kbps             | 8/16/32/64/128 kbps/X-Stream <sup>b</sup> |
| Circuit-switched standard voice               | Yes                                     | Yes                             | Yes                                       |
| ISDN service or 3.1 kHz audio (Premium voice) | No                                      | Elevation > 45°                 | Yes                                       |
| Multi-voice: Number of voice calls            | 1+1 (best effort quality)               | 1+Up to 8 (best effort quality) | 1+Up to 8 (best effort quality)           |

Table 2-1: SwiftBroadband services for supported antenna types

- a. The elevation needed for services with this antenna type is > 20°.
- b. Data rates are up to 432 kbps. Check with your service provider for activation.

For current support of Inmarsat services check at

[www.inmarsat.com/aviation/complete-aviation-connectivity/swiftbroadband](http://www.inmarsat.com/aviation/complete-aviation-connectivity/swiftbroadband).

The current elevation angle is shown in the web interface of the AVIATOR 200/300/350.

For ISDN service or 3.1 kHz audio and IGA the elevation angle must be larger than 45 degrees. Note that the ISDN service cannot be used by the AVIATOR 200 or the AVIATOR 200D.

The following map shows the SwiftBroadband coverage.

### Inmarsat's I4 satellite coverage (AMER, Alphasat, MEAS, APAC)




Figure 2-2: SwiftBroadband and classic aeronautical services coverage on I4 satellite

### PBX telephone exchange

The built-in PBX telephone exchange unit of the SBU connects two direct 2-wire POTS interfaces for faxes, auxiliary phones, headset interface boxes etc., as well as an ISDN interface for ISDN phones, fax machines or Secure communication. The built-in PBX of the SBU can route VoIP calls that are terminated in the SIP server of the SBU.

### Configuration Module (CM)

The Configuration Module (CM) for the SBU is inserted in the SBU and holds system and user settings. It is designed as a plug-in module for the SBU, so the SBU can be replaced while retaining all SBU and user settings. The SBU CM contains a permanently built-in SIM card for access to the SwiftBroadband services.

### Web interface for configuration

Via the built-in web interface of the SBU you can access the SBU configuration settings in the CM. A subset of the configuration settings are stored in a write-protected area of the CM. This subset contains the physical settings for the antenna, cabling and other external input.

To set up or change the settings of the write-protected area you must connect a PC to the connector marked **Maintenance** on the SBU front plate. You can view all settings from any LAN or WLAN interface. For further information on the web interface, see *Configuration tasks* on page 6-2.

## Satcom antenna systems

The AVIATOR 200/300/350 system can be used with a wide range of satcom antennas. The following table shows the Cobham SATCOM antennas that are compatible with the AVIATOR 200/300/350.

| System type              | Antenna type      |
|--------------------------|-------------------|
| AVIATOR 200              | LGA-3002/LGA-3000 |
| AVIATOR 300              | IGA-5006          |
|                          | IGA-5001          |
| AVIATOR 350 <sup>a</sup> | HGA-6000/HGA-6500 |
|                          | HGA-7000/HGA-7001 |
|                          | HGA-8000          |

Table 2-2: Satcom antenna types for the AVIATOR 200/300/350 system

- a. For backwards compatibility with previous Aero-SB Lite systems, the AVIATOR 350 can also be used with IGA-5006 or IGA 5001, then the system is an AVIATOR 300.

An AVIATOR 200/300/350 system must only be used with satcom antennas that have received type approval by Inmarsat.

## Built-in router and Wireless (WLAN) option

The AVIATOR 200/300/350 system offers a built-in router as an option. With this option multiple users and applications can use the system simultaneously. Without this option only the first device that connects to the SBU will be allowed on the Internet.

The system also offers a built-in WLAN option for wireless communication devices and a WLAN antenna approved for aeronautical use. This includes full WLAN routing functionality.

If ordered, this option is enabled in the AVIATOR 200/300/350 from the factory. If these options are not included from the start, the system can be upgraded at a later stage. Then you receive the FLEX key for the purchased options and enter it in the AVIATOR 200/300/350 web interface.

## Built-in Multi-voice option

The AVIATOR 200/300/350 system offers a built-in Multi-voice option. With this option multiple calls can be made to and from the system simultaneously. Normally, the BGAN system only supports one call at a time. With the built-in, optional Multi-voice service enabled in your system, you can make multiple calls. The maximum number of concurrent calls depends on your system, see Table 2-1 on page 2-3. If ordered, this option is enabled in the AVIATOR 200/300/350 from the factory. If this option is not included from the start,

the system can be upgraded at a later stage. Then you receive the FLEX key for the purchased options and enter it in the AVIATOR 200/300/350 web interface.

**Note**

You must have Multi-voice in your airtime subscription, AVIATOR Wireless Handset software version minimum 1.03 and SBU software version minimum AVIATOR 200/300/350 (Level E): 1.07, AVIATOR 200D/300D/350D (Level D): 2.01, in order to support the Multi-voice function.

For information on how to set up Multi-voice, see *Multi-voice (option)* on page 6-91.

## Built-in CMU/ACARS option<sup>1</sup>

The AVIATOR 200/300/350 system offers a built-in CMU/ACARS option. With this option it is possible to connect a CMU or equivalent equipment to the SBU via A429 and send and receive ACARS messages over SwiftBroadband. If ordered, this option is enabled in the AVIATOR 200/300/350 from the factory. If this option is not included from the start, the system can be upgraded at a later stage. Then you receive the FLEX key for the purchased option(s) and enter it in the AVIATOR 200/300/350 web interface. For information on how to set up CMU/ACARS, see *Set up CMU/ACARS (option)* on page 6-51.

## SB-Safety Voice option<sup>2</sup>

With the SB-Safety (ICAO) Voice option you can make priority calls (priority level 1, 2 or 3) to and from the cockpit. The 2-wire POTS connection is used for an external dialer and a headset. The SB-Safety Voice service includes:

- Selecting the priority level before placing outgoing calls
- External pre-programmed speed dial numbers with embedded priority (optional)
- Handling priority level for active call
- Handling priority level for incoming call
- Annunciate the call status and SB-Safety Voice service availability via discrete outputs

To be able to use the SB-Safety Voice you must disable the WLAN access point and Multi-Voice in the web interface. ISDN and the second 2-wire POTS interface are disabled when using SB-Safety Voice. If this option is not included from the start, the system can be upgraded at a later stage. Then you receive the FLEX key for the purchased option(s) and enter it in the AVIATOR 200/300/350 web interface.

Note that SB-Safety Voice option may be restricted by regulation and may require Level D.

---

1. Supported from software version 1.07 for AVIATOR 200/300/350 (Level E) and 2.01 for AVIATOR 200/300/350D (Level D).  
2. Supported from software version 3.01 for AVIATOR 200/300/350 (Level E) and 4.00 for AVIATOR 200/300/350 (Level D).

### Priority levels with an external dialer

If an external dialer is connected to the SBU, you can specify the priority level of outgoing calls when entering phone numbers in the dialer's directory.

| Priority Level                                             | Application Category                                      | SATVOICE Call Examples                                                         |
|------------------------------------------------------------|-----------------------------------------------------------|--------------------------------------------------------------------------------|
| 1<br>(highest) Safety of Flight                            | Distress and Urgency                                      | Inflight Emergency, Rapid<br>Emergency Descent, Urgent<br>Sidestep for Weather |
| 2<br>Operational High (second<br>highest) Safety of Flight | Flight Safety                                             | Altitude Request, ATC Clearance/<br>Instruction                                |
| 3<br>Operational Low (third<br>highest) Safety of Flight   | Regularity of Flight,<br>Meteorological<br>Administrative | Air Traffic Information Service,<br>AOC, Redispatch, Maintenance               |

Table 2-3: Priorities for SATVOICE calls (SB-Safety Voice)<sup>a</sup>

- a. Advisory Circular AC No.20-150B of U.S. Department of Transportation Federal Aviation Administration

The priority level of a call can be part of the phone number. When dialing numbers, the international call prefix can be changed to state the priority level: 01 for priority level 1, 02 for priority level 2 and 03 for priority level 3. Then the phone numbers look as follows (example with 45 country code for Denmark):

- Priority level 1: 01 45 XX XX XX XX
- Priority level 2: 02 45 XX XX XX XX (or 00 45 XX XX XX XX)
- Priority level 3: 03 45 XX XX XX XX

No matter which priority level an outgoing phone call has, the phone number transferred to the PBX is converted to the standard phone number using 00 as international call prefix. The priority can be displayed on a connected annunciator panel.

### Coexistence with IRIDIUM satellite phones

An AVIATOR 200/300/350 system can be installed on aircrafts already equipped with IRIDIUM satellite systems. As Inmarsat satcom systems and Iridium satcom systems are using adjacent frequency bands, there is a potential risk of interference when the Iridium system is used at the same time as the Inmarsat system. To avoid this, two filters are needed:

- An Iridium Band Reject Filter, TT-5019A, must be inserted between the SBU and the HLD.
- An INMARSAT Dual RF Filter, Aircell P/N P13167, must be inserted in the antenna coax of the Iridium system.

For further information on installing the Iridium Band Reject Filter see *TT-5019A Iridium Band Reject Filter* on page F-1.

## 2.1.2 AVIATOR 200/300/350 features

The AVIATOR 200/300/350 system has the following features:

- SwiftBroadband channel providing an 'always on' data connection of up to 432 kbps.
- Full duplex, single or multi-user.
- Automatic satellite selection.
- Built-in PBX in the SBU interfacing to two 2-wire connections, one ISDN interface and WLAN in the SBU, and integrated SIP server for VOIP telephony.
- Standard voice.
- 3.1 kHz audio for modems, G3 fax, 14.4 kbps high quality voice etc.
- ISDN voice for Secure communication, G4 fax etc.
- ISDN data for video conferences etc.
- Built-in Router option with DHCP, NAT for six Ethernet interfaces.
- Built-in Wireless option (WLAN) IEEE 802.11 b/g.
- Built-in Multi-voice option, up to 1+8 concurrent calls
- Access to built-in web interface for daily use using LAN and WLAN.
- Built-in CMU/ACARS option
- Built-in web interface for configuration using the Maintenance connector on the SBU front plate.
- Does not affect the operation of an Iridium system.
- SB-Safety Voice (cockpit voice) option (from software 4.00)

**Note**

The availability of some services depends on the satcom antenna type of the system. Check the section *Services* on page 2-3 for an overview of services available for LGA, IGA and HGA.

## Software versions

The AVIATOR 200/300/350 is shipped with software version 4.01. Software versions 2.02 and 4.00 are also available. The following table shows the features that are supported for each software version.

| Software version | Router | Wifi             | CMU/ACARS | Multi-voice      | A429 via RS422 | SB-Safety Voice |
|------------------|--------|------------------|-----------|------------------|----------------|-----------------|
| 4.01             | Yes    | Yes <sup>a</sup> | Yes       | Yes <sup>a</sup> | Yes            | Yes             |
| 4.00             | Yes    | Yes <sup>a</sup> | Yes       | Yes <sup>a</sup> | Yes            | Yes             |
| 2.03             | Yes    | Yes              | Yes       | Yes              | Yes            | -               |
| 2.02             | Yes    | Yes              | Yes       | Yes              | -              | -               |

Table 2-4: Available features for software versions (Level D)

a. Not together with SB-Safety voice and/or ACARS.

Naming of software versions: Level D: 2.xx and 4.xx, Level E: 1.xx and 3.xx.

For Level E, the latest software version covered by this manual is version 3.01.

## 2.2 Application

### 2.2.1 Minimum system

A minimum working system has at least:

- one TT-5040A SBU
- one TT-5040A-001 CM
- one TT-5016A HLD
- one satcom antenna: LGA, IGA or HGA

The minimum wiring required for an AVIATOR 200/300/350 system is described in the section *Minimum system drawing* on page 5-2. The CM, HLD and some satcom antennas are powered by the SBU.

## 2.2.2 Part numbers

### Applicable part numbers

This installation manual is for the AVIATOR 200/300/350 system and is applicable to the part numbers in the following tables.

| Part number | Unit description                                                                                       |
|-------------|--------------------------------------------------------------------------------------------------------|
| 405040A     | SwiftBroadband Unit (SBU) [without CM] for AVIATOR 200/300/350                                         |
| 405040A-THD | SwiftBroadband Unit (SBU) [without CM] for AVIATOR 200D/300D/350D                                      |
| 405040A-001 | Configuration Module (CM) for SBU (no key and no options)                                              |
| 405040A-002 | Built-in Router option                                                                                 |
| 405040A-003 | Built-in Wireless option                                                                               |
| 405040A-004 | WLAN Antenna, optional (2 pieces recommended)                                                          |
| 405040A-009 | Built-in ACARS+SB-Safety (ICAO) voice option                                                           |
| 405040A-010 | Built-in Multi-voice option                                                                            |
| 405040A-006 | AVIATOR 350 Key (HGA/IGA)                                                                              |
| 405040A-007 | AVIATOR 300 Key (IGA)                                                                                  |
| 405040A-008 | AVIATOR 200 Key (LGA)                                                                                  |
| 405016A     | High Power Amplifier/Low Noise Amplifier/Diplexer (HLD)<br>AVIATOR 200/300/350                         |
| 405016A-THD | High Power Amplifier/Low Noise Amplifier/Diplexer (HLD)<br>AVIATOR 200D/300D/350D                      |
| 403002-001  | Low Gain Antenna (LGA). Original Manufacturer Sensor Systems P/N: S65-8282-101 (listed on FAA 8130-3). |
| 405003A-PMA | LGA-3000 Low Gain Antenna (obsolete)                                                                   |
| 405001A-PMA | IGA-5001 Intermediate Gain Antenna                                                                     |
|             | HGA-6000 High Gain Antenna                                                                             |
|             | HGA-6500 High Gain Antenna                                                                             |
|             | HGA-7000 High Gain Antenna                                                                             |
| 405017A     | HGA-7001 High Gain Antenna                                                                             |

Table 2-5: Part numbers

| Part number   | Unit description                                         |
|---------------|----------------------------------------------------------|
| 677-A0163     | HGA-8000 High Gain Antenna (obsolete)                    |
| 405621B-THW   | 2-Wire Handset (white)                                   |
| 405621B-THR   | 2-Wire Handset (black)                                   |
| 405622B-THW   | 2-Wire Cradle (white)                                    |
| 405622B-THR   | 2-Wire Cradle (black)                                    |
| 405612A-100   | PTA-12, Airborne Telephone Adaptor, black                |
| 405612A-104   | PTA-12, Airborne Telephone Adaptor, gray                 |
| 403670B-00500 | Thrane IP Handset incl. Cradle, Wireless                 |
| 405624B-THR   | AVIATOR Wireless Handset Black                           |
| 405624B-THW   | AVIATOR Wireless Handset White                           |
| 405626B-THR   | AVIATOR Wireless Cradle Black                            |
| 405626B-THW   | AVIATOR Wireless Cradle White                            |
| 405017A-801   | Converter RS-422 to A429 (Serial to A-429 Adapter (SAA)) |
| 405019A       | Iridium Band Reject Filter                               |

Table 2-5: Part numbers (Continued)

| Part number | Configuration module description                 |
|-------------|--------------------------------------------------|
| 405040A-838 | CM for SBU with A200 key                         |
| 405040A-828 | CM for SBU with A200 key, Router option(s)       |
| 405040A-818 | CM for SBU with A200 key, WiFi option(s)         |
| 405040A-808 | CM for SBU with A200 key, Router, WiFi option(s) |
| 405040A-837 | CM for SBU with A300 key                         |
| 405040A-827 | CM for SBU with A300 key, Router option(s)       |
| 405040A-817 | CM for SBU with A300 key, WiFi option(s)         |
| 405040A-807 | CM for SBU with A300 key, Router, WiFi option(s) |
| 405040A-836 | CM for SBU with A350 key                         |
| 405040A-826 | CM for SBU with A350 key, Router option(s)       |

Table 2-6: Part numbers for configuration modules and options

| Part number | Configuration module description                                                            |
|-------------|---------------------------------------------------------------------------------------------|
| 405040A-816 | CM for SBU with A350 key, WiFi option(s)                                                    |
| 405040A-806 | CM for SBU with A350 key, Router, WiFi option(s)                                            |
| 405040A-878 | CM for SBU with A200 key, Multi voice option(s)                                             |
| 405040A-868 | CM for SBU with A200 key, Router, Multi voice option(s)                                     |
| 405040A-858 | CM for SBU with A200 key, WiFi, Multi voice option(s)                                       |
| 405040A-848 | CM for SBU with A200 key, Router, WiFi, Multi voice option(s)                               |
| 405040A-876 | CM for SBU with A350 key, Multi voice option(s)                                             |
| 405040A-866 | CM for SBU with A350 key, Router, Multi voice option(s)                                     |
| 405040A-856 | CM for SBU with A350 key, WiFi, Multi voice option(s)                                       |
| 405040A-846 | CM for SBU with A350 key, Router, WiFi, Multi voice option(s)                               |
| 405040A-8B6 | CM for SBU with A350 key, ACARS/SB Safety (ICAO) voice option(s)                            |
| 405040A-8A6 | CM for SBU with A350 key, Router, ACARS/SB Safety (ICAO) voice option(s)                    |
| 405040A-896 | CM for SBU with A350 key, WiFi, ACARS/SB Safety (ICAO) voice option(s)                      |
| 405040A-886 | CM for SBU with A350 key, Router, WiFi, ACARS/SB Safety (ICAO) voice option(s)              |
| 405040A-8F6 | CM for SBU with A350 key, Multi voice, ACARS/SB Safety (ICAO) voice option(s)               |
| 405040A-8E6 | CM for SBU with A350 key, Router, Multi voice, ACARS/SB Safety (ICAO) voice option(s)       |
| 405040A-8D6 | CM for SBU with A350 key, WiFi, Multi voice, ACARS/SB Safety (ICAO) voice option(s)         |
| 405040A-8C6 | CM for SBU with A350 key, Router, WiFi, Multi voice, ACARS/SB Safety (ICAO) voice option(s) |

Table 2-6: Part numbers for configuration modules and options (Continued)

The flex keys for A350 can also be used in A300 systems.

The SwiftBroadband Unit (SBU) and the High Power Amplifier, Low Noise Amplifier and Diplexer (HLD) must all be level E or level D approved. **No mismatch is allowed.**

## Circuit breaker

| Part number | Recommended aircraft circuit breakers                       |
|-------------|-------------------------------------------------------------|
| 2TC2-7.5    | Klixon 2TC series, 7.5 A current rating (SBU <sup>a</sup> ) |

Table 2-7: Part numbers for Klixon circuit breaker

- a. The CM, HLD and some satcom antennas are powered by the SBU.

## Trays and connectors

| Part number                                                 | Approved tray                                                                                                      |
|-------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------|
| PO299-101                                                   | ECS Tray Assembly 1/4-size ATR (for SBU)                                                                           |
| MT4-2346-101                                                | EMTEQ Tray Assembly 1/4-size ATR (for SBU)                                                                         |
| DPX2NA-67322-606<br>(alternate number:<br>DPX2NA-67322-500) | Required Connector Kit for SBU tray: ITT Cannon Connector, Dual Plug, contact arrangement top: 33C4, bottom: 33C4. |

Table 2-8: Part number for connector

## Installation kits

For installation kits for the AVIATOR 200/300/350 system contact:

|                                                                                                                                                                                                                                                                         |                                                                                                                                                                          |
|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>ECS, a Carlisle IT company, USA</b><br>Phone (Franklin, WI): +1 800-327-9473<br>Phone (Kent, WA): +1 800-227-5953<br>E-mail: <a href="mailto:sales@CarlisleIT.com">sales@CarlisleIT.com</a><br>Home page: <a href="http://www.CarlisleIT.com">www.CarlisleIT.com</a> | Emteq (Collins Aerospace)<br>5349 S Emmer Drive<br>New Berlin WI 53151<br>Phone 262-679-6170<br><a href="mailto:LIS_Sales@beaerospace.com">LIS_Sales@beaerospace.com</a> |
|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------|

Table 2-9: Installation kits, contact information

ECS offers installation kits for the SBU.

| Item in installation kit                              |
|-------------------------------------------------------|
| 1 ARINC connector, SBU (DPX2NA-67322-500)             |
| 1 Tray Assembly, SBU, 1/4-size ATR W/DPX2 (P0299-101) |

Table 2-10: ECS installation kit 102-20027-102

| Item in installation kit                              |
|-------------------------------------------------------|
| 1 ARINC connector, SBU (DPX2NA-67322-606)             |
| 1 Tray Assembly, SBU, 1/4-size ATR W/DPX2 (P0299-101) |

Table 2-11: ECS installation kit 120-200027-103

## 2.3 System block diagrams

The following block diagrams and the wiring diagrams in section 5.3.3 show examples of satcom antennas that can be connected to the AVIATOR 200/300/350 systems.

In order to use the satcom antenna with the AVIATOR 200/300/350 systems, the specific antenna type and the AVIATOR 200/300/350 system must be *Type Approved* by Inmarsat as a combined system. The satcom antenna types supported are listed in *Satcom antenna systems* on page 2-5. AVIATOR 200/300/350 systems will be Inmarsat Type Approved with more antennas as requested by market requirements. Contact your Cobham sales/support representative for the latest status on Inmarsat Type Approvals for satcom antennas for the AVIATOR 200/300/350 system.

The following block diagrams show the basic system component interconnection and the user interfaces.

### 2.3.1 AVIATOR 200 system with LGA-3000 antenna

The drawing below shows the AVIATOR 200 system with an LGA antenna.




Figure 2-3: System configuration with LGA-3000 antenna

### 2.3.2 AVIATOR 300 system with IGA-5006 antenna

The drawing below shows the AVIATOR 300 system with an IGA antenna.




Figure 2-4: System configuration with IGA-5006 antenna

### 2.3.3 AVIATOR 350 system with Cobham antennas

The drawing below shows the AVIATOR 350 system with Cobham antennas.




Figure 2-5: System configuration with Cobham antennas

### 2.3.4 AVIATOR 350 system with ARINC-741/781 antennas

The drawing below shows the AVIATOR 350 system with an ARINC-741/781 HGA.




Figure 2-6: System configuration ARINC 429 antennas

For detailed description of the connection of each antenna type, see *Wiring the satcom antenna* on page 5-11.

### 2.3.5 AVIATOR 350D system with ACARS and ARINC-741/781 antennas

The drawing below shows the AVIATOR 350 system with the HGA-6000/6500 or AMT-50 and ACARS/SB Safety (ICAO) voice.




Figure 2-7: System configuration ARINC 429 antennas

For detailed description of the connection of each antenna type, see *Wiring the satcom antenna* on page 5-11.

### 2.3.6 User interfaces

The AVIATOR 200/300/350 system has the following user interfaces:

| Interfaces                                                                                                                                                                                                                                                                 | Number            |
|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------|
| 2-wire POTS interface<br>This interface can be used for the TT-5621B 2-Wire Handset and TT-5622B 2-Wire Cradle or other POTS handsets. The TT-5622B 2-Wire Cradle has an RJ11 connector to which additional 2-wire terminals can be connected, e.g. for fax or modem data. | 2                 |
| 10/100BaseT Ethernet interfaces for connecting IP equipment.<br>Note that the SBU has a Built-in Router option. The SBU has an additional Ethernet interface for system configuration (Maintenance connector on the SBU front plate, not shown in the following figure).   | 6                 |
| Built-in Wireless Option with two WLAN antenna interfaces for diversity operation to connect WiFi-enabled equipment like lap tops, PDAs or VOIP handsets.                                                                                                                  | 1<br>(32 devices) |
| Euro ISDN S-bus interface for PC, Fax or STE (without DC power support) <sup>a</sup>                                                                                                                                                                                       | 1                 |
| Discrete outputs for annunciators                                                                                                                                                                                                                                          | 4                 |

Table 2-7:

- a. Note that the ISDN data service (UDI/RDI) and 3.1 kHz premium voice service cannot be used by the AVIATOR 200 nor the AVIATOR 200D.

The following figure shows most of the possible user interfaces.




Figure 2-8: AVIATOR 200/300/350 interfaces

