


SETTINGS OF DD7-MINI AND ZELLO APP

iOS Android

Please create Zello account for the first use.

Turn on the Bluetooth on your mobile phone (Android must turn on GPS) » Open the Zello APP » Main menu/Options » Push-to-talk buttons » Add New Device » Press the DD7-MINI key once » Click new device (CHILOKI-PTT) » Back to previous menu » Finish.


PTT Test: Select Zello APP Contact/Echo » press the DD7-MINI button » the Screen button change to red » The button is working.




Please read this user manual carefully before using the DD7-MINI wireless PTT button.

DD7-MINI WIRELESS PTT BUTTON TECH SPECS


Function Description:



PTT Key
(waterproof level : IP66)



Indicator light



Magnetic charging port

INSTRUCTIONS:

Battery charging

1. in paired mode, press and hold DD7-MINI button, the red-light breathing, indicate the battery level low.
2. When charging the battery, the indicator light shows green and light off when charging completed.

Note: The battery provides approximately:

- *Cumulative PTT time: 450 min
- *Connection standby time: 500 hours
- *Unconnected standby time: 8 months



Please do not use non-original charging cables for charging!

Pairing DD7-MINI

Press DD7-MINI button, the red-light flashes quickly indicate in pairing mode, or after 40 sec will automatic into sleep mode.

Wake up DD7-MINI

When the DD7-MINI is in the deep sleep state, short press the PTT button once. When the red light of the status indicator flashes quickly, it indicates that is has been awakened and entered the pairing connection state.

Deep Sleep Mode

When the DD7-MINI is unconnected, it will automatically enter the deep sleep state after 40 secs.

FUNCTION OPERATION AND STATUS LIST:

Function	Key	Status light indication
Pairing mode	Press once	Red-light flash quicky
Push-to-talk	Press and hold	Show red light
Battery low	Press and hold	Red-light breathing
Charing battery	—	Show green light

DD7-MINI PRODUCT SPEC

- Model: Bluetooth Button
- Bluetooth specifications: V5.0
- Frequency range: 2402-2480MHz
- Effective use range: Within 10 meters
- Battery capacity: 50mA
- Charging voltage: 5V 100mA
- Charging time: 1-1.5 hours
- Cumulative PTT time: 450 min
- Connected standby time: 500 hours
- Unconnected standby time: 8 months
- Working temperature: -20°C~60°C
- Warranty period: 1 year

※The above time may be changed due to your settings or personal usage habits.



Scan QR Code for more information



掃描QR Code 獲取更多相關資訊

FCC Warning

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment .