



Appendix B

RF Test Data for BT LE (Conducted Measurement)

Product Name: Speaker

Test Model: L-601

Environmental Conditions

Temperature:	23.8 ° C
Relative Humidity:	52.1%
ATM Pressure:	100.0 kPa
Test Engineer:	 Nick Peng
Supervised by:	 Li Huan





B.1 6dB Bandwidth


Condition	Mode	Frequency (MHz)	Antenna	6 dB Bandwidth (MHz)	Limit 6 dB Bandwidth (MHz)	Verdict
NVNT	BLE 1M	2402	Ant1	0.672	≥ 0.5	Pass
NVNT	BLE 1M	2440	Ant1	0.658	≥ 0.5	Pass
NVNT	BLE 1M	2480	Ant1	0.695	≥ 0.5	Pass
NVNT	BLE 2M	2402	Ant1	1.366	≥ 0.5	Pass
NVNT	BLE 2M	2440	Ant1	1.222	≥ 0.5	Pass
NVNT	BLE 2M	2480	Ant1	1.42	≥ 0.5	Pass








Test Graphs

6dB Bandwidth NVNT BLE 1M 2402MHz Ant1



6dB Bandwidth NVNT BLE 1M 2440MHz Ant1







Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity





B.2 Maximum Conducted Output Power


Condition	Mode	Frequency (MHz)	Antenna	Total Power (dBm)	Limit (dBm)	Verdict
NVNT	BLE 1M	2402	Ant1	1.19	30	Pass
NVNT	BLE 1M	2440	Ant1	1.27	30	Pass
NVNT	BLE 1M	2480	Ant1	1.42	30	Pass
NVNT	BLE 2M	2402	Ant1	1.18	30	Pass
NVNT	BLE 2M	2440	Ant1	1.25	30	Pass
NVNT	BLE 2M	2480	Ant1	1.4	30	Pass






Test Graphs

Power NVNT BLE 1M 2402MHz Ant1



Power NVNT BLE 1M 2440MHz Ant1







Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity







B.3 Maximum Power Spectral Density Level


Condition	Mode	Frequency (MHz)	Antenna	Conducted PSD (dBm/3kHz)	Duty Factor (dB)	Total PSD (dBm/3kHz)	Limit (dBm/3kHz)	Verdict
NVNT	BLE 1M	2402	Ant1	-9.89	0	-9.89	8	Pass
NVNT	BLE 1M	2440	Ant1	-9.64	0	-9.64	8	Pass
NVNT	BLE 1M	2480	Ant1	-9.24	0	-9.24	8	Pass
NVNT	BLE 2M	2402	Ant1	-12.01	0	-12.01	8	Pass
NVNT	BLE 2M	2440	Ant1	-12.28	0	-12.28	8	Pass
NVNT	BLE 2M	2480	Ant1	-13.07	0	-13.07	8	Pass






Test Graphs

PSD NVNT BLE 1M 2402MHz Ant1



PSD NVNT BLE 1M 2440MHz Ant1







Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity







B.4 Band Edge


Condition	Mode	Frequency (MHz)	Antenna	Max Value (dBc)	Limit (dBc)	Verdict
NVNT	BLE 1M	2402	Ant1	-57.3	-20	Pass
NVNT	BLE 1M	2480	Ant1	-56.97	-20	Pass
NVNT	BLE 2M	2402	Ant1	-32.73	-20	Pass
NVNT	BLE 2M	2480	Ant1	-56.98	-20	Pass






Test Graphs

Band Edge NVNT BLE 1M 2402MHz Ant1 Ref



Band Edge NVNT BLE 1M 2402MHz Ant1 Emission



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity





Band Edge NVNT BLE 1M 2480MHz Ant1 Ref




Band Edge NVNT BLE 1M 2480MHz Ant1 Emission








Band Edge NVNT BLE 2M 2480MHz Ant1 Ref



Band Edge NVNT BLE 2M 2480MHz Ant1 Emission





B.5 Conducted RF Spurious Emission


Condition	Mode	Frequency (MHz)	Antenna	Max Value (dBc)	Limit (dBc)	Verdict
NVNT	BLE 1M	2402	Ant1	-56.4	-20	Pass
NVNT	BLE 1M	2440	Ant1	-56.25	-20	Pass
NVNT	BLE 1M	2480	Ant1	-55.66	-20	Pass
NVNT	BLE 2M	2402	Ant1	-54.91	-20	Pass
NVNT	BLE 2M	2440	Ant1	-54.35	-20	Pass
NVNT	BLE 2M	2480	Ant1	-55.16	-20	Pass






Test Graphs

Tx: Spurious NVNT BLE 1M 2402MHz Ant1 Ref



Tx: Spurious NVNT BLE 1M 2402MHz Ant1 Emission



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Tx. Spurious NVNT BLE 1M 2440MHz Ant1 Ref




Tx. Spurious NVNT BLE 1M 2440MHz Ant1 Emission






Tx. Spurious NVNT BLE 1M 2480MHz Ant1 Ref



Tx. Spurious NVNT BLE 1M 2480MHz Ant1 Emission



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Tx. Spurious NVNT BLE 2M 2402MHz Ant1 Ref



Tx. Spurious NVNT BLE 2M 2402MHz Ant1 Emission



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Tx. Spurious NVNT BLE 2M 2440MHz Ant1 Ref



Tx. Spurious NVNT BLE 2M 2440MHz Ant1 Emission



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Tx. Spurious NVNT BLE 2M 2480MHz Ant1 Ref



Tx. Spurious NVNT BLE 2M 2480MHz Ant1 Emission





B.6 Duty Cycle


Condition	Mode	Frequency (MHz)	Antenna	Duty Cycle (%)	Correction Factor (dB)	1/T (kHz)
NVNT	BLE 1M	2402	Ant1	100	0	0
NVNT	BLE 1M	2440	Ant1	100	0	0
NVNT	BLE 1M	2480	Ant1	100	0	0
NVNT	BLE 2M	2402	Ant1	100	0	0
NVNT	BLE 2M	2440	Ant1	100	0	0
NVNT	BLE 2M	2480	Ant1	100	0	0






Test Graphs

Duty Cycle NVNT BLE 1M 2402MHz Ant1



Duty Cycle NVNT BLE 1M 2440MHz Ant1







Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity







B.7 Restrict Band


Condition	Mode	Frequency (MHz)	Antenna	Spur Freq (MHz)	Power (dBm)	Gain (dBi)	E (dBUV/m)	Detector	Limit (dBUV/m)	Verdict
NVNT	BLE 1M	2402	Ant1	2310	-49.99	2	47.27	Peak	74	Pass
NVNT	BLE 1M	2402	Ant1	2310	-59.85	2	37.41	Average	54	Pass
NVNT	BLE 1M	2402	Ant1	2339.856	-47.6	2	49.66	Peak	74	Pass
NVNT	BLE 1M	2402	Ant1	2372.496	-58.96	2	38.3	Average	54	Pass
NVNT	BLE 1M	2402	Ant1	2390	-50.1	2	47.16	Peak	74	Pass
NVNT	BLE 1M	2402	Ant1	2390	-59.67	2	37.59	Average	54	Pass
NVNT	BLE 1M	2480	Ant1	2483.5	-49.27	2	47.99	Peak	74	Pass
NVNT	BLE 1M	2480	Ant1	2483.5	-59.07	2	38.19	Average	54	Pass
NVNT	BLE 1M	2480	Ant1	2494.168	-46.58	2	50.68	Peak	74	Pass
NVNT	BLE 1M	2480	Ant1	2494.528	-58.59	2	38.67	Average	54	Pass
NVNT	BLE 1M	2480	Ant1	2500	-49.6	2	47.66	Peak	74	Pass
NVNT	BLE 1M	2480	Ant1	2500	-59.32	2	37.94	Average	54	Pass
NVNT	BLE 2M	2402	Ant1	2310	-51.72	2	45.54	Peak	74	Pass
NVNT	BLE 2M	2402	Ant1	2310	-59.19	2	38.07	Average	54	Pass
NVNT	BLE 2M	2402	Ant1	2319.12	-47.11	2	50.15	Peak	74	Pass
NVNT	BLE 2M	2402	Ant1	2350.992	-58.51	2	38.75	Average	54	Pass
NVNT	BLE 2M	2402	Ant1	2390	-51.02	2	46.24	Peak	74	Pass
NVNT	BLE 2M	2402	Ant1	2390	-59.38	2	37.88	Average	54	Pass
NVNT	BLE 2M	2480	Ant1	2483.5	-47.41	2	49.85	Peak	74	Pass
NVNT	BLE 2M	2480	Ant1	2483.5	-55.25	2	42.01	Average	54	Pass
NVNT	BLE 2M	2480	Ant1	2491.744	-46.7	2	50.56	Peak	74	Pass
NVNT	BLE 2M	2480	Ant1	2483.512	-55.25	2	42.01	Average	54	Pass
NVNT	BLE 2M	2480	Ant1	2500	-50.42	2	46.84	Peak	74	Pass
NVNT	BLE 2M	2480	Ant1	2500	-59.18	2	38.08	Average	54	Pass






Test Graphs

Restrict Band NVNT BLE 1M 2402MHz Ant1 Peak



Restrict Band NVNT BLE 1M 2402MHz Ant1 Average





Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Restrict Band NVNT BLE 2M 2402MHz Ant1 Peak



Restrict Band NVNT BLE 2M 2402MHz Ant1 Average



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Restrict Band NVNT BLE 2M 2480MHz Ant1 Peak



Restrict Band NVNT BLE 2M 2480MHz Ant1 Average



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity