

105G书写纸，黑色
风琴折，成品95*133mm



Holosonic T1w Manual



Tri-Mode Wireless Professional & Gaming Headset

EN

Thank you for purchasing your new Holosonic T1w Wireless Pro & Gaming Headset. We recommend that you spend some time reading this instruction manual in order that you fully understand all the features it offers and keep this instruction manual for future reference.



1

EN

Specifications

Speaker diameter	53mm
Sensitivity	120dB±3dB
Frequency response	20Hz~20K Hz
Rated output power	20mW
Maximum output power	30mW
Speaker impedance	32±15%Ω
Microphone dimension	Ø6.0*5.0mm
Microphone sensitivity	-38±2dB
Directivity	Omnidirectional
Microphone impedance	< 2.2KΩ(1MΩ)
Charging voltage	DC 5V
Battery capacity & working voltage	800mAh DC 3.7V
Charging port	Type-C
Charging current	<400mA
Effective distance	10 meters
Delayed	< 20mS
Continuous working time	15 hours

Power ON/OFF
ON: long press 3 sec on power switch
OFF: long press 3 sec on the power switch

2

EN

2.4G mode connecting

1. Turn on the headset.
2. Plug the USB dongle into your computer's USB port.
3. When the indicator light on USB dongle always on (not flashing) and the headset has been switched into 2.4G mode, that means 2.4G mode has been successfully connected.

Bluetooth Mode

1. To switch to Bluetooth mode, long press "M Button" for 3 seconds and wait for 3 seconds.
2. Open your Bluetooth device, search and connect to "Holosonic T1w" broadcasting ID, pair and connect it accordingly.
3. When pairing, the indicator is flashing and is always on if successfully connected.
4. To disconnect, three click "Power Button".

Wired Mode

1. To use wired mode, use Type-C to 3.5mm Jack audio cable connect the headset and computer. No need pressing power button on the ear shell.
2. Note that when using the headset in 2.4G mode or Bluetooth mode, if we attach the 3.5mm Jack audio cable, the headset will automatically shut down and not able to power on.

Note

- Check your sound/audio settings so that you have the "output" set to wireless audio.
- Keep the distance between headset and dongle less than 10 meters, whenever it will be disconnected.
- When using the headset with the 3.5mm Jack audio cable, the headset will be the last mode-2.4G or Bluetooth which you used before power off.

Microphone

The headset comes with detachable microphone. Just plug the microphone into 3.5mm Jack on headset to use microphone function.

3

EN

Charging

1. Fully charge the headset before first use.
2. Connect the Type-C to USB2.0 charging cable into a USB port device or a USB2.0 adapter, plug us to fully charged the headset. When the headset is charging, the LED indicator is red. LED automatically turns off when fully charged.

Power

When the battery is around 10% of power capacity, you'll hear the voice prompt "Battery Low" reminding you to charge the headset. When the headset has not been paired for 3 minutes, the headset will automatically shut down unless the headset is out of power.

Package Contents

- 1 x Gaming Headset
- 1 x USB Type-C to 3.5mm Jack Audio Cable
- 1 x USB Wireless Receiver
- 1 x Type-C to 3.5mm Jack Audio Cable
- 1 x Type-C to USB Type-C Charging Cable
- 1 x User Manual

Operating Systems

Compatible with PS4-5, Mac, PC, Mobile.

Share to Win Swag

Share your Disk Keyboard experience on social media for a chance to win awesome swag. End of Win of your contest to enter the monthly raffle:

iwantgoodies@deskayboard.com

facebook.com/deskayboard

twitter.com/deskayboard

4

EN

Precautions

- Do not disassemble the product or attempt to fix it.
- Do not crush, dispose of in fire, or expose the product to water or other liquids.
- Do not use the product in a high-temperature environment, including intense sunlight or heat.
- Avoid drops, vibrations, abrasions and impacts.
- If you find that the product is too hot, is emitting an odor, is deformed, or exhibits any suspicious or abnormal behavior, discontinue use immediately.

FCC Warning

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1) This device may not cause harmful interference, and
(2) this device must accept any interference received, including interference that may cause undesired operation.

This device has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules, which limits the radio frequency energy that it can emit. This device does not cause harmful interference in a residential installation. This device generates, uses and can radiate radio frequency energy and, if not time and used in accordance with the instructions, may cause interference to radio communications.

However, any changes to the default settings may cause interference to radio or television reception, which can be determined by turning the device on or more of the following measures:
-Reorient or relocate the receiving antenna
-Increase the distance between the device and the receiver
-Connect the device into an outlet on a circuit different from that to which the receiver is connected

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

20231024-1

5