

IQ SIREN 8 QUICK INSTALL GUIDE



FEATURES & OVERVIEW

The IQ Siren 8 is a wireless Z-Wave Plus 800 series device that allows you to have additional sirens placed throughout the home.

It plugs into any standard outlet, acts as a repeater in the Z-Wave network (when paired as Z-Wave Plus), has a rechargeable back up battery and LED lights that strobe when the siren is triggered.

Mounting Locations:

- Kitchen
- Living Room
- Basement
- Bedrooms
- Garage

Pair up to 3 IQ Sirens with the IQ Panel.

SPECIFICATIONS

Built-in Lithium Battery: 450 mAh

Alarm Power: 1.7W

Max Standby Power: 0.7W

Max Volume: 105dB


Operating Temperature: 0°C to 40°C

Operating Distance:

- Z-Wave Plus: Up to 550 feet outdoors

- Z-Wave Long Range: 1400 feet outdoors*

Frequency Type : Z-Wave Plus & Z-Wave Long Range



* Refer to data from the Z-Wave Alliance

This is a quick guide for experienced installers only. Refer to <http://dealers.qolsys.com> (login required).

Replacing a battery with an incorrect type can defeat the device safeguards. Disposing a battery into fire or a hot oven or mechanically crushing or cutting a battery can result in an explosion.

Leaving a battery in an extremely high temperature environment can result in an explosion or leakage of flammable liquid or gas.

A battery subjected to extremely low air pressure may result in an explosion or leakage of flammable liquid or gas.

STEP 1

DETERMINE
INSTALLATION
LOCATION



Plug in the
IQ Siren 8
at desired
location

STEP 2

PREPARE THE IQ PANEL TO
ENROLL THE IQ SIREN



Select "Add Device"
from Z-Wave menu

INCLUDE

Press the
"Include" button

STEP 3

PAIRING WITH
THE IQ PANEL



Press the button on
the bottom of the IQ
Siren **twice** to enroll
with the IQ Panel.
(LED will flash)

Id	19
Type	External Siren
Name	Basement Siren
Add	

Customize name

Add

Complete pairing process
by touching **Add**



Test device to ensure
proper function

Document#: IQSIREN8-QG
Revision#: 11/18/25
SKU#: IQZWSRN



Qolsys Inc. proprietary.
Reproduction without permission is not permitted.
FCC ID: 2AAJXIQZWSRN
IC: 11205A-IQZWSRN

GOT QUESTIONS?
CONTACT TECH SUPPORT
intrusion-support@jci.com

FCC

Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.
This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy, and if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

*RF warning for Mobile device:

This device complies with FCC radiation exposure limits set forth for an uncontrolled environment. This device should be installed and operated with minimum distance 20cm between the radiator & your body.

ISED

This device contains licence-exempt transmitter(s)/receiver(s) that comply with Innovation, Science and Economic Development Canada's licence-exempt RSS(s).

Operation is subject to the following two conditions:

- (1) This device may not cause interference.
- (2) This device must accept any interference, including interference that may cause undesired operation of the device.

L'émetteur/récepteur exempt de licence contenu dans le présent appareil est conforme aux

CNR d'Innovation, Sciences et Développement économique Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes :

- 1) L'appareil ne doit pas produire de brouillage;
- 2) L'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

Cet émetteur ne doit pas être colocalisé ou fonctionner en conjonction avec une autre antenne ou un autre émetteur.

The device meets the exemption from the routine evaluation limits in section 2.5 of RSS-102 and compliance with RSS-102 RF exposure, users can obtain Canadian information on RF exposure and compliance.

Le dispositif rencontre l'exemption des limites courantes d'évaluation dans la section 2.5 de RSS 102 et la conformité à l'exposition de RSS-102 rf, utilisateurs peut obtenir l'information canadienne sur l'exposition et la conformité de rf.

This equipment should be installed and operated with a minimum distance of 20 centimeters between the radiator and your body.

Cet émetteur ne doit pas être Co-placé ou ne fonctionnant en même temps qu'aucune autre antenne ou émetteur. Cet équipement devrait être installé et actionné avec une distance minimum de 20 centimètres entre le radiateur et votre corps.